AD-763 564

COMPUTER SIMULATION OF HARD ROCK TUNNELING. VOLUME II. SUPPORTING INFOR-MATION

R. R. Hibbard, et al

General Research Corporation

Prepared for:

Advanced Research Projects Agency Bureau of Mines

November 1972

DISTRIBUTED BY:



U. S. DEPARTMENT OF COMMERCE 5285 Port Royal Road, Springfield Va. 22151

DISCLAIMER NOTICE

THIS DOCUMENT IS THE BEST QUALITY AVAILABLE.

COPY FURNISHED CONTAINED A SIGNIFICANT NUMBER OF PAGES WHICH DO NOT REPRODUCE LEGIBLY.



WGRC 72-2852 Copy ___ of __125_ Copies

CR-2-190

COMPUTER SIMULATION OF HARD ROCK TUNNELING

0763564

Final Technical Report

Volume II - Supporting Information

November 1972

Sponsored by

Advanced Research Projects Agency
ARPA Order No. 1578
Admendment 2

Company has

JUL 8. 1915

GENERAL RESEARCH

CORPORATION

WASHINGTON OPERATIONS
1501 WILSON BLVD, SUITE 700, ARLINGTON, VA. 22209

The views and conclusions contained in this document are those of the authors and should not be interpreted as necessarily representing the official policies, either expressed or implied, of the Advanced Research Projects Agency or the U.S. Government

Reproduced by
NATIONAL TECHNICAL
INFORMATION SERVICE
U S Department of Commerce
Springfield VA 22151

Sc AT 7350

DOCUMENT CONT	ROL DATA - R	& D	
(Security classification of title, body of abstract and indexing a	ennotation must be	Da. REPORT SE	CURITY CLASSIFICATION
General Research Corp., Washington Operations,		Unclassified	
		2b GROUP	
1501 Wilson Blvd., Arlington, Va. 22209			
I HEPORT TITLE			
CONTRACTOR OF HADD BOOK THANK!	NC		
COMPUTER SIMULATION OF HARD ROCK TUNNEL	LING		
Volume II - Supporting Information			
4 DESCRIPTIVE NOTES (Typs of report sod inclusive detail)			
Final Technical Report			
5 AUTHOR(5) (Firet name, middle (little), last name)			
R. R. Hibbard, L. M. Pietrzak			
6 HEPORT DATE	TZE. TOTAL NO C	F PAGES	I/b. NO OF REFS
November 1972	iii + 3		12
NO CONTRACT OR GRANT NO	DE. ORIGINATOR	S REPORT NUME	DER(S)
но110238			
b. PROJECT NO			
ARPA Order 1578	CR-2-19	0	
	95. OTHER REPO	RT NOISI (Any of	ber numbers that may be assigned
	,		
d Amendment 2			
10 DISTRIBUTION STATEMENT			
Distribution of this document is	unlimited.		
11 SUPPLEMENTARY NOTES	12. SPONSORING	MILITARY ACTI	VITY
Reproduced from best available copy.	Advanced Research Projects Agency,		
Washington, I.C.			
11 ABSTRACT	-		

4

This volume contains supporting information and further programming guides to the excavation simulation described in Volume I.

The model is implemented in FORTRAN 4 for CDC 6000 Series Computers. A computer source tape is available from NTIS.

Unclassified
Security Classification

4		LIN	K A	LIN	к В	LIN	кс
K	EY WORDS	ROLE	WT	ROLE	w T	ROLE	wr
		ŀ					!
Mining		}					
Excavation							
Tunneling				İ			
Computer Simulation	n						
						}	
		}					
				!			
			l I				
		}					
		ĺ					
						1	
		1	Ì				
				ì			
		i .					
		ļ .					
						1	
						Ì	

Unclassified
Security Classification

CR-2-190

1

COMPUTER SIMULATION OF HARD ROCK TUNNELING

Final Technical Report

Volume II - Supporting Information

November 1972

ARPA order No. 1578, Amendment 2

Program Code No. 1F10

Contract No.

H0110238

Effective Date of Contract

26 October 1970

Contract Expiration Date

Phase I:

30 September 1971

Phase II:

30 April 1972

Amount of Contract

Phase I:

\$124,182

Phase II:

\$ 66,288

Principal Investigators

R. R. Hibbard L. M. Pietrzak

(703) 524-7206

This research was supported by the Advanced Research Projects Agency of the Department of Defense and was monitored by the Bureau of Mines

GENERAL RESEARCH CORPORATION
Washington Operations
1501 Wilson Boulevard
Arlington, Virginia 22209

FOREWORD

This volume contains supporting information and further programming guides to the excavation simulation described in Volume I.

The coordination of the material in Volume II was done by R. R. Hibbard and L. M. Pietrzak. The author credits are as follows:

Appendix I: D. S. Hyman (Geological Surveying and Prediction)

Appendix II: F. H. Murphy (Geology Model)

Appendix III: P. K. Parish (Programs TUNNEL and GENTNL)

Appendix IV: M. McJunkin

F. H. Murphy (Excavation Model)

B. H. Lieu

Appendix V: L. M. Pietrzak (Layout Tunnel Data)
W. R. Thomson (

INDEX OF SUBROUTINES

NOTE: For any subroutine, a subroutine name in parentheses <u>beside</u> it indicates the routines are identical. A subroutine name in parentheses <u>below</u> it indicates the subroutine's normal entry point if it has both a normal and initialization entry point.

ADDTRN ASSMBL	Vol. I, 177 Vol. II, IV-10 IV-21 IV-25 IV-70 VI-91 Vol. I, 77	CVMNT (CVRPR)	Vol. I, 237 Vol. II, IV-10 IV-18 IV-19 IV-52 IV-97 IV-106 VI-76
	Vol. II, IV-96	CUBIC	Vol. II, IV-24
BELT	Vol. I, 223 Vol. II, IV-10	DIAMTR	Vol. I, 98
	IV-27 IV-28 IV-77	DISASM	Vol. I, 98 Vol. II, IV-96
	VI-153	DREPAR (XXXMNT)	Vol. I, 74
BENDER BORE	Vol. II, II-24 Vol. I, 80 Vol. II, IV-10 IV-12 IV-39	ENVIR (ENVIRC)	Vol. II, IV-10 IV-35 IV-80 IV-106 VI-114
	IV-96 IV-106 VI-68	EXTNSN	Vol. I, 215 Vol. II, IV-10 IV-27 IV-28
CUTTER	Vol. I, 89 Vol. II, IV-10 IV-12 IV-40	GETLYR	IV-75 VI-149 Vol. II, III-11
	IV-95 IV-96 VI-70	GRNSUP (GROUN)	Vol. II, IV-10 IV-11 IV-29-34
CVLOAD (LOADCV)	Vol. I, 234 Vol. II, IV-10 IV-11 IV-18 IV-19 IV-51 IV-95 IV-97 IV-101 VI-73	GSMAIN (GSMNT)	IV-78 IV-97 IV-106 VI-103 Vol. II, IV-10 IV-29-34 IV-79 IV-106 VI-111

INDEX OF SUBROUTINES (Cont.)

HOLBRN	Vol. I, 62 Vol. II, IV-10 IV-16 IV-17 IV-49 VI-125	MOVOUT	Vol. I, 74 Vol. II, IV-10 IV-16 IV-18 IV-48 VI-127
INPUT (INPUT2)	Vol. II, IV-10 IV-30 IV-36 IV-81 IV-86 IV-102 VI-60	MUKLOD	Vol. I, 232 Vol. II, IV-10 IV-20 IV-54 VI-138 Vol. I, 228
JETAGN (JETPOS)	Vol. I, 125 Vol. II, IV-10 IV-13 IV-14 IV-15	(LODMUK)	Vol. II, IV-10 IV-20 IV-21 IV-53 VI-136
JETIMP	Vol. I, 119 Vol. II, IV-10	MUKMT (CVMNT) MUKOUT (OUTMUK)	Vol. I, 232 Vol. I, 232 Vol. II, IV-10 IV-20
(JET)	IV-13 IV-14 IV-42 VI-129	NEWPNT OUTPUT	IV-55 VI-139 Vol. II, III-15 Vol. II, IV-10
JETMNT (JETRPR)	Vol. I, 125 Vol. II, IV-10 IV-13 IV-14 IV-15 IV-43		IV-37 IV-82 IV-86 IV-101 IV-104 VI-65
MAXADV (MAXADW)	VI-132 Vol. II, IV-10 IV-37 IV-38 IV-85 IV-101 IV-104 VI-118	PRJAGN (JETAGN) (PRJPOS) PRJBR (PRJBRL)	Vol. I, 138 Vol. II, IV-15 Vol. I, 138 Vol. II, IV-10 IV-15 IV-16 IV-46 VI-135
MOVEIN	Vol. I, 59 Vol. II, IV-10 IV-16 IV-18 IV-47 VI-126	PRJMNT (JETMNT) (PRJRPR)	Vol. I, 138 Vol. II, IV-15

INDEX OF SUBROUTINES (Cont.)

PROJTL (PRJIMP) RAILDS	Vol. I, 137 Vol. II, IV-10 IV-15 IV-46 VI-135 Vol. I, 176	REPORC (REPORD)	Vol. II, IV-10 IV-37 IV-38 IV-84 IV-101 IV-108 VI-122
	Vol. II, IV-10 IV-21 IV-25 IV-29 IV-71 IV-97 VI-94	REPORR (REPORS)	Vol. II, IV-10 IV-37 IV-38 IV-83 IV-101 IV-108 VI-119
RAILEX (RAILXT)	Vol. I, 168 Vol. II, IV-10 IV-21 IV-29 IV-72 IV-97 IV-101 VI-96	SETCHG	Vol. I, 70 Vol. II, IV-10 IV-16 IV-17 IV050 VI-128
RAILHL (RAILTR)	Vol. I, 151 Vol. II, IV-10 IV-21 IV-24 IV-56ff IV-96 IV-101 IV-106	SURGE	Vol. I, 223 Vol. II, IV-10 IV-27 IV-29 IV-76 VI-152 Vol. I, 200 Vol. II, IV-10 IV-27
RAILMT	VI-79 Vol. I, 176 Vol. II, IV-10 IV-21 IV-26 IV-29 IV-73 VI-100	TRUKDS (RAILDS) TRUKEX (RAILEX) (TRUKXT)	Vol. I, 194 Vol. II, IV-29 Vol. II, IV-29 Vol. II, IV-29
RDGEOL REPAIR	Vol. II, III-17 Vol. I, 98 Vol. II, IV-10 IV-12 IV-13 IV-41	TRUKHL (MAILHL) TRUKMT (RAILMT)	Vol. I, 184 Vol. II, IV-10 IV-29 VI-140 Vol. I, 195 Vol. II, IV-29
	IV-96 VI-72	XXXMNT	Vol. II, IV-10 IV-16 VI-154

APPENDIX I

GEOLOGICAL SURVEYING AND PREDICTION

by

D. S. Hyman

SUMMARY

I

This study discusses the significance of the knowledge of geological conditions to a tune ling project and briefly describes those measurement techniques and procedures that are in general use for geological surveying and prediction.

CONTENTS

SECTION		PAGE
I	INTRODUCTION	I-5
II	SURVEY AND PREDICTION TECHNIQUES	I-8
	A. Literature Review	1-8
	B. Surface Exploration	1-9
	C. Subsurface Investigations	1-10
	D. Laboratory Tests	I -1 3
	E. Cost Considerations	I-13
	DEFEDENCES AND NOTES	1-15

I. INTRODUCTION

It is generally recognized that the geological (and hydrological) conditions more than any other factor determine the degree of difficulty and the cost of a given tunnel project. This is easy to see, since the tunneling system, support and liner design, and total system performance are a direct and strong function of the geologic medium to be tunneled through. In essence, the latter is truly a key variable in the total economic picture of a project. As a result, geologic exploration and prediction techniques have a very important influence on the planning, design, and performance of an excavation system. Although it is not yet possible to identify a return-on-investment relationship for geological exploration it is clear that a more accurate knowledge of geological conditions will permit considerable savings from the improved planning and design of a project.

At present, less than 2% of the total project cost is generally allocated to pre-excavation geological investigations. 1,2 This probably reflects the fact that the scope and extent of the geological survey is a compromise between technical desirability and economic feasibility. Moreover, the point of compromise may not be reached objectively in many instances. Budgetary considerations of sponsoring agencies, political considerations, etc., may also play a role in the decision process. In addition, no comparative estimates for total project cost versus the geological investigation investment has ever been made, and even if they had, considerable doubt about the validity of the comparison would remain since it is never possible to "excavate again, this time with more geological information." However, some indications of the significant and perhaps unnecessary costs which may be incurred because of poor or limited geological data can be drawn from isolated case histories. As an example, there were only two bore holes made prior to the excavation of the massive underground defense complex in Cheyenne Mountain for the

North American Air Defense Command (NORAD). Further geological exploration was scheduled but never funded because of a controversy about the project itself. When funding for continuation of the project was eventually released it was allocated for excavation alone, not geological exploration, and partly as a result, poor geology was encountered unexpectedly at a critical intersection of two project chambers. Eventually new plans had to be drawn up, rotating the original design in an attempt to avoid bad ground. Even then extensive and costly reinforcement was necessary at the worst intersection. 3

Traditionally, geological surveying, measurements, and prediction are accomplished before any detailed designs and cost estimates are attempted. Although geophysical measurements are sometimes made during the course of the excavation process, the current practice is to rely heavily on the geological work prior to excavation. As improved techniques for in situ measurement of geological conditions are developed it is likely that greater emphasis will be placed on evaluating the information provided by these techniques to improve the safety and performance of excavating.

Depending upon the extent of the geological survey and measurement program, the information and data that it evokes might be used in site selection and feasibility determination, preliminary design and cost estimates, or detailed construction planning. However, as a result of both the coarse nature of geological measurements and the cost of detailed exploration programs, such decisions and studies are almost always based on incomplete information. Consequently, engineering judgment tempered by previous experience plays a significant role in the decision processes. We shall have more to say about this in the following pages, but given that the site, geometry, and orientation of a tunnel project have been chosen, we can focus attention on the fundamental data requirements imposed upon the engineering geologist.

The results of a geological exploration program should consist of sufficient amounts of data concerning lithological, hydrological, and rock-mass properties to enable a designer and contractor to plan a construction project with confidence. This includes both the quantitative aspects of engineering and excavation system design, and scheduling plans and cost estimates. In other words, the contractor wants answers to the following key questions:

- 1. What would be the most suitable excavation method?
- 2. What are the ground support and tunnel liner requirements along the length of a proposed tunnel?
- 3. How much ground-water inflow can be expected along the tunnel length?
- 4. What is the location of potential geologic hazards?

The extent to which such questions can be answered with precision and reliability determines to a large extent the ultimate cost-performance success of the construction project.

II. SURVEY AND PREDICTION TECHNIQUES

We shall present next a brief survey of those measurement techniques and procedures that are now in general use for geological surveying and prediction. Since comprehensive discussions along these lines are readily available in the literature, 4-9 we shall focus our attention primarily on the extent to which these various techniques are able to delineate geological discontinuities and inhomogeneities such as faults, joints, bedding planes, rock-soil interfaces, and ground-water concentrations. In addition, we shall present relevant cost data, and discuss the technical and economic factors which influence the scope of a typical geological exploration program.

A comprehensive geological exploration program typically involves the following kinds of activities:

- Review of available data (literature research)
- Surface exploration and mapping
- Subsurface studies
- Laboratory analysis of field samples

The degree to which efforts are directed in each area depends not only on technical and engineering considerations but also on economic factors and judgment. This will be elaborated below.

A. LITERATURE REVIEW

An exploration program generally begins with a survey of available literature dealing with geological and engineering geological information pertaining to the area of interest. The objective is not only to save time and expense but also to utilize the information to plan the remaining elements of the exploration program more efficiently and effectively. Of particular interest is information relating to the spatial distributions of rock formations along the tunnel route, the physical properties and quality of the rock types that might be encountered at depth, and expected or possible ground-water conditions during excavation. If underground construction data for previous projects in the general area are

available, they would most likely be used to assess the structural characteristics of the geological strata, and possible problem areas. The sum total of such sources of information would be expected to aid the geologist in interpreting conditions with respect to possible problem areas, tunnel support requirements, and ground-water conditions. Of course, the amount of useful data that can be gathered depends on the extent of previous surface and underground construction in the general vicinity of the proposed tunnel.

B. SURFACE EXPLORATION

Surface investigations comprise the second step in the sequence of progressively refined studies and measurements. With the exception of built-up urban areas, most geographical settings are suitable for surface geological exploration. The objective of this phase of the program is to survey and map in detail the exposed rock formations in a wide area covering the contemplated excavation. The usefulness of this procedure depends on the degree to which geological formations and structures of interest are exposed at the surface. In some cases, aerial and surface reconnaissance is aided where necessary by bulldozer stripping of surface soil to expose underlying rock formations. This is usually an inexpensive way to implement the surface work.

The results of this phase of geological exploration are recorded on a topographical map of the type made available by the U.S. Geological Survey. The map scale may vary between 1200:1 and 4800:1 and the following geological features are usually displayed:

- General geology (location and classification of generic rock types)
- Strike and dip of surface outcrops
- Location of fault zones and veins
- Description of foliation and joints
- Fracture densities as a function of location
- Degree of weathering

When the information is displayed in this form, it is useful to the geologist in connection with two main tasks: it serves as the basis for making a preliminary extrapolation of rock conditions to tunnel depth, and it aids in the planning of subsequent geological and geophysical measurements, such as core drillings and seismic surveys. It is worthwhile to emphasize that at this point the geologist cannot predict with a high degree of certainty what geological factors will be encountered at depth. The information, when evaluated and interpreted by an experienced geologist (and we must emphasize interpret) serves as a basis for perhaps semiquantitative estimates of expected conditions. Conditions are rarely predicted easily since much of the earth's outer crust consists of highly variable geological structures and conditions. Therefore, to increase the information usable for design purposes, additional measurements and tests are often planned, as a result of questions raised by the results of the surface geological mapping. Occasionally, field samples are collected during the surface survey for laboratory analyses and identification.

C. SUBSURFACE INVESTIGATIONS

As discussed in the previous sections, the geologist's chief goal is to measure and/or predict the geological conditions at the depth of interest. It is usually necessary to refine the data obtained from surface mapping by detailed investigations of areas of known faults, areas of potential geological problems, and ground-water conditions. Toward this end, a number of procedures and measurements are currently in use:

- Core drilling
- Pilot bore
- Field geophysical measurements

1. Core Drilling

Information concerning subsurface conditions is obtainable by drilling small vertical (or nearly vertical) holes down to tunnel depth, with the concommitant examination and testing of the removed material (core samples). Holes drilled in rock are usually about 3 in. in diameter, and the amount of core recovered is a function of the quality of the rock and the skill of the drillers. Data on rock properties and geological conditions as a function of depth are obtained through core logging, water testing, and laboratory measurements of core samples.

2. Core Logging

This is essentially the systematic recording of observations of rock properties for successive core samples. In particular, parameters such as rock type, fracture and joint spacing and orientation, density, and hardness are of immediate interest. Since heavy ground-water conditions are particularly influential in a tunneling operation, data on changes in the water level encountered, as well as porosity and permeability measurements and pumping tests, are of value.

Pilot Bore

In view of the inherent deficiencies in the techniques discussed above, the need for exploratory drilling ahead of a working face has been widely recognized. Current geological investigation techniques do not provide enough information for design purposes, nor are they capable of being applied simultaneously with the excavation process. As a result, it would be desirable to obtain in situ geological information in advance of a working face. Either a pilot bore prior to main tunnel excavation or a pilot bore sufficiently ahead of the main tunnel advance may supply the needed information.

The Straight Creek Tunnel Pilot Bore is an example of excavating a complete pilot tunnel in the immediate vicinity of the intended tunnel. A small pilot tunnel was excavated and subsequently surveyed by geophysical techniques. The resulting data indicated potential trouble spots,

and some correlation of rock properties with construction parameters was made. If such a procedure could be made more economical, it would represent a very effective geological measurement tool.

The Japanese Seikan Tunnel across the Tsugaru Strait is an example of excavating a pilot tunnel simultaneously with the main tunnel, far enough ahead to guide the main tunnel operations. This project, in addition to the pilot tunnel, relies on information provided by the drilling of a small probe hole up to 1000 ft ahead of the excavation to locate potentially bad ground conditions.

4. Field Coophysical Measurements

In addition to the techniques mentioned above, surface measurements are occasionally made using seismic velocities as indicators of incomplete rock properties and changing geological conditions. However, its effectiveness is frequently limited by insensitivities of the techniques used and by an inability to distinguish clearly between certain kinds of rock. Surface measurements of DC electrical resistivity have also been used to detect changing rock and ground-water conditions, but with modest success. However, data from the Straight Creek Tunnel Pilot Bore 8,9 indicate that such measurements may be of definite value in conjunction with other in situ techniques.

Some use has been made of borehole photography to provide direct observation of geological conditions inside the borehole.

Geophysical measurements of seismic velocities in boreholes are also made. Depending on the physical differences among the rock types encountered, such data can be used to correlate other surface geophysical measurements. Unfortunately, unless the boreholes are spaced close enough along a proposed tunnel route to reveal all geological changes bearing on engineering design and construction, the resulting information is only generally indicative of conditions to be expected. Core logs

are often incapable of indicating the extent of geological discontinuities. As a result, the data yield only an incomplete picture of geological and hydrological conditions at tunnel depth. However, in mining operations core-boring techniques may provide all the useful information that is needed. 10

D. LABORATORY TESTS

In addition to the logging and measurement techniques used in conjunction with core boring, the intact core samples are usually tested in the laboratory. The object of such tests is to determine those rock propert es which influence the excavation method, support and liner design, and probable ground-water conditions. In particular, such parameters as unconfined compressive strength, hardness, fracture and joint spacing, and degree of weathering are of immediate interest. Prospective bidders and/or tunnel machine designers might perform additional tests of their own choosing to enable them to evaluate the relative advantage of drill and blast versus machine tunneling, but such tests are performed after the initial geologic investigation is made. In recent years, the rock quality designation (RQD) 7,11,12 has come into use as a simply measured indicator of overall rock quality. It is defined as the fraction of the recovered core pieces with a length greater than or equal to 4 in. Thus, it is an approximate measure of the influence of discontinuities on the rock mass encountered. This will be discussed in more detail in a subsequent section, but it suffices to say at this point that the RQD can be correlated at least partially with engineering and construction aspects of tunneling. At the present time, laboratory measurements of intrinsic rock properties are useful only in furnishing guidelines for support design purposes. The measurements are useful, but enough uncertainty remains to require the inclusion of large safety factors in design and construction.

E. COST CONSIDERATIONS

In general, one cannot readily provide rules which determine the optimum allocation of resources to geological exploration. The amount

can vary significantly from one project to another and one geology to another. However, Table I-1 summarizes typical costs associated with current geological surveying and measurement procedures. They can be used to estimate the total cost of postulated exploration programs.

It should be mentioned that the cost per foot of core drilling depends somewhat on the diameter and ultimate depth of the hole. Thus it can be seen that drill holes of 500-foot depth might typically cost \$5,000 or more each. This explains why their locations are chosen with care. Finally, it should be mentioned that in situ engineering tests for design purposes are usually more costly and time consuming than laboratory tests. This includes, in particular, radial jacking tests to measure the deformation of tunnel wall rock under various loading conditions.

TABLE I-1 COST ELEMENT OF GEOLOGICAL SURVEYING

1.	Core drilling into bedrock (3-in. diameter) with boxing of cores	\$5-\$25/ft
2.	Water pressure tests	\$75/test
3.	Mobilization/demobilization (per drill rig and crew)	Variable (several hundred to several thousand dollars)
4.	Observation well (1 $1/2$ in. diameter)	\$4/ft
5.	Surface mapping	\$100/(day-geologist)
6.	Literature research	\$2100/man-mo. (office)
7.	Laboratory tests	\$25-\$100/sample
8.	Seismic tests (surface)	< \$1/lin. ft

REFERENCES AND NOTES

- 1. Dr. C. S. Robinson, C. S. Robinson & Associates, Inc., personal communication.
- 2. Mr. L. Herlin, Metropolitan Area Transit Authority, personal communication.
- 3. Mr. K. Fox, Corps of Engineers, personal communication.
- 4. S. D. Woodruff, Methods of Working Coal and Metal Mines, Vol. I, Pergamon Press, Oxford, 1966.
- 5. <u>Subsurface Investigations</u>, Vol. 1-4, Washington Metropolitan Area Rapid Transit Authorized Basic System (Clearinghouse PBL185757), 1967.
- 6. K. Szechy, <u>The Art of Tunneling</u>, (Hungarian Academy of Sciences, 1966), Chapter 2.
- 7. D. V. Deere et al., <u>Design of Tunnel Liners and Support Systems</u>, (Clearinghouse for Federal Science and Technical Information, PB183799), 1969.
- 8. C. S. Robinson and F. T. Lee, <u>Results of Geologic Research at the Straight Creek Tunnel Pilot Bore</u>, Highway Research Record No. 185, 1967.
- 9. J. H. Scott and R. D. Carroll, <u>Surface and Underground Geophysical</u>
 <u>Studies at Straight Creek Tunnel Site</u>, Highway Research Record
 No. 185, 1967.
- 10. W. Peters, <u>Cost and Value of Drill Hole Information</u>, Mining Congress 53 (1), p. 56, 1967.
- 11. D. Deere et al., Engineering Classification of In-Situ Rock, AFWL-TR-67-144, January 1969.
- 12. R. Peck et al., <u>Some Design Considerations in the Selection of Underground Support Systems</u>, (Clearinghouse PB190443), 1969.

APPENDIX II

GEOLOGY MODEL

by

F. H. Murphy

SUMMARY

This appendix describes the concept, code structure and user operation of the geology model which is a tool for building a file of data which represents the geological conditions found within a given three-dimensional model of a region of rock.

1

CONTENTS

SECTION			PAGE
I	OVERVIEW		11-5
II	OUTPUT FILE STRUCT	TURE	11-6
III	GEOLOGY MODEL STRU		11-1
IV	INPUT DATA CARDS		11-1
	A. Geology Card		11-1
	B. Surface Card		11-1
	C. Plane Card		111
	D. Raise Card		11-1
	E. Lower Card		11-1
	F. Scale Card		11-1
	G. Sum Card		11-1
	H. Differ Card		11-1
	I. Tilt Card		TI-1
	J. Relax Card		11-1
	K. Bend Card		11-2
	L. Graph Card		11-2
	M. Layer Card		11-2
	N. Property Care	đ	11-2
	O. Makefile Card	đ	11-2
v	SUBROUTINE BENDER		11-2

I. OVERVIEW

The geology model is a part of the excavation simulation model.

One of the requirements established for the simulation model by the Bureau of Mines was that it provide a realistic modeling of the geological conditions encountered during the process of tunneling; specifically, it was established that the rock which was encountered was not to be modeled as a homogeneous medium. It was also established that the excavation model was intended to be used as a research tool which would aid in evaluating the relative cost and performance characteristics of various techniques which might be used for tunneling through hard rock in the near future. This latter consideration led to a decision to design the overall model in such a way that the portion which was concerned with modeling geological conditions was a separate entity.

The geology model is intended to be a convenient tool for building a file of data which represents the geological conditions found within a given three-dimensional region of rock. The representation of the geology is meant to be exemplary. By this it is meant that the geology model is primarily intended for use in building files which represent hypothetical geologies which might be of interest in research. Even so, enough flexibility is provided so that reasonable representation of existing geological regions could be rather easily constructed, if desired. The sizes of the geological regions which are simulated, as well as the spacings of data points within the regions, are under the control of the user.

This appendix is intended to document the inputs, the methods of operation, and the outputs of the geology model. In doing this, it is convenient to discuss first the structure of the geology file which is generated; this gives some insight as to why the model is as it is. The structure of the model is then discussed in some detail. A discussion of the specific formats and uses of the various control cards follows. Finally, a detailed description of the subroutine named BENDER, which is used to simulate the tectonic warping of layers of rock, is given.

II. OUTPUT FILE STRUCTURE

The geology file produced by the geology model is a simple sequential (i.e., tape-like) file. This file consists of four parts, in order:

- 1. Dimensional Information
- 2. Rock Layer Information
- 3. Rock Property Information
- 4. Layer Position Information

Each of these four parts will be discussed in turn. It should be noted that there are no end-of-file marks between the parts of the geology file; the only end-of-file mark is located at the end of the file.

The dimensional information specifies the size of the region to be modeled and the horizontal spacing between data points. Implicitly, it also specifies the number of entries which will be found in the fourth part of the geology file—the layer position information. In order to see how this is done, imagine for a moment that you are well up in the air, looking down at a rectangular region of the earth's surface. This region is described, throughout the model, by means of the following directional notation conventions:

Y, NORTH, J, OR N DIRECTION

X, EAST, I, OR M DIRECTION

The compass-like notation is used for input convenience. The X and Y notation is used when it is convenient to refer to points within the region by means of floating-point coordinates; either the I and J or the M and N notation is used when it is convenient to refer to selected points within the region by means of integer coordinates. Vertical levels are

always referred to by floating-point numbers; the variable name Z is most commonly used for this purpose. The positive vertical direction is upward.

Within the model, this region is divided up into an integral number of grid squares. There are NX grid lines from right to left and NY grid lines from top to bottom. NX need not equal NY. These grid squares need not, in truth, be square. A scale factor can be associated with each of them. Thus, each square is SCALEX wide and SCALEY high. SCALEX need not equal SCALEY. The geology file contains geological layer position information for each point at which the grid lines cross.

Going back for a moment, then, the first part of the geology file contains four entries of dimensional information which specify the size of the region to be modeled and the horizontal spacing of the data points. In order, these four entries contain:

Position	Contents	Format
1	NX	15
2	NY	15
3	SCALEX	1PE18.10
4	SCALEY	1PE18.10

At the present time, the model can accommodate regions in which NX and NY are each less than or equal to 30. If these limits are exceeded, the array SURF in the geology model's main program should be redimensioned to $SURF(NX_m, NY_m, 7)$ where NX_m and NY_m are the maximum desired values of NX and NY; no other changes are required. There values of SCALEX and SCALEY are not subject to any practical limitations.

The present version of the geology model allows the user to specify up to 25 different layers of rock, which may correspond to between 2 and 25 kinds of rock. If these limits are exceeded, the array INDEX should be redefined as INDEX(ILAYR_m), where ILAYR_m is the maximum number of layers desired. Depending upon the computer used, it may be necessary to change the PROGRAM card of the geology model to allow for the files

TAPE1, TAPE2, ..., through TAPE(ILAYR $_{\rm m}$). The array BUFF should also be redefined as BUFF(ILAYR $_{\rm m}$ + 2). Additional rock types are accommodated by redefining the array PROP as PROP(6, IROCK $_{\rm m}$), where IROCK is the maximum number of rock types desired.

The geology model allows the user to easily generate surfaces, which are interpreted as the upper boundaries of layers of specified kinds of rocks. The user is required to number these layers, for identification purposes, as he generates them. There is no requirement that the relative vertical positions of layers be in any way related to the identification numbers assigned to them.

The second part of the geology file is simply a copy of the values which the user placed in the array named INDEX. The value of INDEX(ILAYR) is the number of the rock type which the user specified as being found directly beneath the surface to which he gave the identification number ILAYR. Let us suppose that INDEX(ILAYR) = IROCK. Then, PROP (1 through 6, IROCK) contains the six parameters which the user specified as defining the kind of rock which he gave the rock identification number IROCK. The third part of the geology file is simply a copy of the values which the user placed in the array named PROP.

Explicitly, the second part of the geology file consists of rock layer information in the form:

Position	Contents	Format	
29	INDEX (1) INDEX (25)	12	Rock types for layers 1 through 25.

and the third part of the geology file consists of rock property information in the form:

Position	Contents	Format
30	PROP (1,1)	1PE18.10
31	PROP (2,1)	1PE18.10
32	PROP (3,1)	1PE18.10 Parameters for
33	PROP (4,1)	1PE18.10 rock type 1
34	PROP (5,1)	1PE18.10
35	PROP (6,1)	1PE18.10
36	PROP (1,2)	1PE18.10
į.	Ţ	↓
179	PROP (6,25)	1PE18.10

The fourth part of the geology file consists of NX times NY entries, in sequence, each entry being of the following form:

Entry Position	Contents	Format
1	I	1PE18.10
2	J	1PE18.10
3	z_1	1PE18.10
ILAYR _m + 2	Z _{1LAYR}	1PE18.10 1PE18.10

Each entry is for a single point at which the grid lines cross; the coordinates of that point are the integers (I,J). The Z_L for L=1 to $ILAYR_m$ are the vertical positions of the layers which the user has given the identification numbers 1 through $ILAYR_m$ respectively; Z values for layers which he has not specified are set to the value $Z=-10^{51}$. In interpreting the entries at a given (I,J) location, it is understood that, in case of overlap, an arbitrary rule determines which layer numbers take precedence.


For example, suppose that at location (I,J) we were given the values Z_{I} for L=1 through 25. We would receive them in the order given above:

<u>L</u>	<u>z</u>
1	z_1
2	z_2
3 25	z ₂ z ₃ 3 v z ₂ z ₃

Our first step might be to sort the entries into increasing order $\underline{by}\ Z$, and then use L as a precedence number:

<u>L</u>	<u>z</u>
1	z_1
25	z ₂₅
2	^z ₂
3	Z ₃
24	ž ₂₄

This might correspond to the condition:



The above illustration of how layer precedence relationships can be used is meant to be illustrative rather than definitive. No dcubt the reader can imagine other geological conditions in which other precedence

relationships would be useful; e.g., perhaps specific layer numbers might always be interpreted as representing the surface of the earth and the water table.

III. GEOLOGY MODEL STRUCTURE

There are two major phases of the geology model. During the first phase, the user is aided in manipulating surfaces on an NX by NY grid. These working surfaces may then be given layer number and rock type identification numbers, and be stored on auxiliary storage (usually disk storage) one surface at a time. The user is allowed to have up to seve working surfaces in existence at any one time. As was previously stated, the model as presently implemented will accommodate up to 25 layer surfaces.

The result of the 11rst phase of operation is a collection of individual files, each corresponding to the Z values of a single layer surface; each such file of Z values is in the customary FORTRAN ordering by I and J. What is desired is of course a single file, ordered by I and J, which contains the Z values for every surface at each value of I and J. This phase, which begins upon the receipt of a MAKEFILE card, is essentially a reordering phase. During this phase, the values of NX, NY, SCALEX and SCALEY, as well as the contents of the arrays named INDEX and PROP, are written out onto the new geology file. The rest of the file is constructed by stepping through all values of I and J and, for each data point so defined, reading the corresponding Z value from each of the layer-surface files, consolidating these values into one entry, and writing this information onto the new geology file. When this process is completed, the operation of the geology model is terminated.

Figure II-1 illustrates the two-phase nature of the geology model.




Figure II-1. The Two Phases of Operation of the Geology Model

IV. INPUT DATA CARDS

Sixteen different kinds of input data cards are used to control the operation of the geology model. Each kind is identified by a label which is punched into columns 1 to 10 of each card (left justified). The remaining space on each kind of card is divided up into seven equally sized data fields, each field being ten columns wide. All data entered into any of these data fields must be numerical and must include a decimal point. The formats of the sixteen kinds of input data cards are given in Table II-1. The purpose of each kind of cards and its associated data parameters is discussed in this section.

A. GEOLOGY CARD

There must be only one geology card per input data deck. Violation of either of these restrictions will cause a diagnostic message to be printed and the current run of the model to be terminated. The meanings of the variables NX, SCALEX, NY, and SCALEY are as given in Sec. II of this appendix.

B. SURFACE CARD

A SURFACE card provides a method of inputting a completely arbitrary surface. The main disadvantage to this is that many point-data cards (blanks in columns 1 through 10) may be required if NX times NY is large. In specifying an arbitrary surface, the SURFACE card must come first. SURFNO is the number by which the working surface which is to be created will be known; SURFNO can be any integer from 1 to 7, inclusive (but remember that decimal point!). The other data fields on the SURFACE card are ignored—unless they contain non-numeric data, which can cause a fatal error in the FORTRAN input-output routines.

The SURFACE card must be immediately followed by enough point-data cards to define the desired points on the surface. Two points can be defined per card; the problem which arises when it is necessary to define

TABLE II-1 INPUT CARD FORMATS

\$ 13.00 A

A Altred

\$ ---- A

71-80										PTZ			SURFNO		PARAM6			
61-70			SURF(I,J)							PTY			SURFNO		PARAM5			
51-60			r,							PTX		INFLUN	SURFNO		PARAM4			
41-50	SCALEY		н							AXIS		N.W MEDIAN	SURFNO		PARAM3			
31-40	MY		SURF(I,J)				FACTOR	SURFNO(C)	SURFNO(C)	DEGREE		OLD MEDIAN	SURFNO	LAYERNO	PARAM2			
21-30	SCALEX		J	рертн	DISTANCE	DISTANCE	SURFNO(B)	SURFNO(B)	SURFNO(B)	SURFNO(B)	TOLER	NEW SURF	SURFNO	ROCKNO	PARAMI	MAXLAYER		
11-20	NX	SURFNO	I	SURFNO	SURFNO	SURFNO	SURFNO(A)	SURFNO(A)	SURFNO(A)	SURFNO(A)	SURFNO	OLD SURF	SURFNO	SURFINO	ROCKNO	MAXROCK		
1-10	GEOLOGY	SJRFACE	ŧ	PLANE	RAISE	LOWER	SCALE	SUM	DIFFER	TILT	RELAX	BEND	GRAPH	LAYER	PROPERTY	MAKEFILE		

an odd number of points is avoided by checking the value I times J before storing the value SURF(I,J). If I times J is zero (or blank) SURF(I,J) is ignored. The number of point-data cards is not checked. They need not be in any order, as long as all desired cards for the surface to be defined are together and immediately follow the appropriate SURFACE card.

C. PLANE CARD

As was noted above, the definition of large numbers of surface points can require large numbers of point-data cards and, therefore, large amounts of keypunching. This kind of effort is clearly unjustifiable when only very simple surfaces are required. Through the use of the PLANE card, one can establish a working surface with working surface identification number SULFNO, all of whose points are set to the value DEPTH, in one simple operation.

D. RAISE CARD

Geologies having layers whose layer surfaces are virtually identical, except for a vertical separation between layers, are not uncommon. The RAISE card was provided to ease the task of defining such a geological region. The use of the RAISE card simply adds the constant named DISTANCE to every data point of the working surface having the surface identification number SURFNC.

E. LOWER CARD

The same comments made in conjunction with the RAISE card are appropriate here. The use of the LOWER card simply subtracts the constant named DISTANCE from every data point of the working surface having the surface identification number SURFNO.

F. SCALE CARD

The use of the SCALE card is similar in nature to the uses of the RAISE and LOWER cards. In this case, each data point of the working

surface named SURFNO(A) is multiplied by the scale factor named FACTOR, the result being stored in the corresponding location of the working surface named SURFNO(B). SURFNO(A) may equal SURFNO(B), if desired.

G. SUM CARD

The use of the SUM card causes the Z value for each I,J location of working surface number SURFNO(A) to be added to the Z value for the corresponding I,J location of working surface number SURFNO(B); the resulting value is placed in the corresponding I,J location of working surface number SURFNO(C). The Z values for the working surfaces numbered SURFNO(A) and SURFNO(B) remain unchanged unless one or the other or both of the working surfaces have the same number as working surface SURFNO(C). The numbers SURFNO(A), SURFNO(B) and SURFNO(C) may be equal to each other in any combination, if desired.

H. DIFFER CARD

The operation of the DIFFER card is identical to that of the SUM card, except that the corresponding I,J data points of working surface number SURFNO(B) are subtracted from those of working surface number SURFNO(A) in order to obtain the data point values for SURFNO(C). In short, surface A minus surface B equals surface C.

I. TILT CARD

Up until this point, all of the operations performed upon working surfaces have been vertical. It has also been considered desirable to provide some simple method of tilting surfaces, so that it would not be necessary to resort to the definition of surfaces through the use of SURFACE cards whenever the layer structure in a particular geological region happened not to be horizontal. The TILT card provides a simple method of tilting arbitrary surfaces.

The arbitrary surface which is to be tilted is that working surface having the surface identification number SURFNO(A). The data point values

which result when this surface is tilted DEGREE degrees, in a right-handed fashion, around a horizontal vector through the point having the coordinates (PTX, PTY, PYZ) and pointing in a direction AXIS which is measured in degrees, in a compass-like fashion from north (or equivalently, the Y axis), are placed in the appropriate locations of the working surface having the surface identification number SURFNO(B).

This all sounds very complicated at first, but in practice, it is easy. The formulas used are well known. The only difficult part of the operation stems from the fact that originally our working surface number SURFNO(A) has its Z values recorded at integer values of X and Y; after the tilting operation takes place, this is no longer true, in general. Yet this has to be true before we can store the Z values for working surface number SURFNO(B). It is therefore necessary to use a surface-fitting subroutine SRFIT in order to determine the second-degree equation which best fits that set of data points which is closest to each integer valued I,J pair for which we want a Z value for working surface number SURFNO(B). We then use the equation to interpolate in order to find the desired Z value. This must be done for every I,J pair where $1 \le I \le NX$. $1 \le J \le NY$.

Normally, the six closest data points should suffice for such a fit. It has been found desirable to use the closest eight in most cases. This results in a small amount of "smoothing" which is helpful at boundaries or at parts of the surface which have sharp bends. If it has trouble in fitting the surface with the eight closest points, the program will next try ten, then twelve points. If the trouble persists, diagnostic information is provided.

See, for example, pp. A-255 of the Handbook of Chemistry and Physics.

There is no restriction as to how surfaces can be tilted. They can be tilted in a positive or negative direction, in small amounts or in barrel rolls. The only real constraint is that the resulting surface must be singly-defined at each integral value of I and J where $1 \le I \le NX$, $1 \le J \le NY$; otherwise, trouble will be encountered with SRFIT, as noted above.

J. RELAX CARD

We have discussed the use of completely arbitrary surfaces, specified through the use of the SURFACE card, and the use of planes specified through the use of the PLANE card. The RELAX card provides a means of achieving a middle ground between the relative advantages of realism and simplicity achieved through these two approaches.

Many geological surfaces may be adequately represented by "minimum energy" surfaces. That is, given the boundary points through which the surface would have to pass at the edges of the geological region which we serrodeling, this type of surface is the smoothest which could be constructed which would still pass through the boundary points. An infinitely flexible membrane, such as a soap bubble, could be expected to provide the same kind of surface.

Mathematically, this kind of surface is called a harmonic surface; it satisfies LaPlace's equation in two dimensions:

$$\frac{\partial^2 \mathbf{F}}{\partial \mathbf{x}^2} + \frac{\partial^2 \mathbf{F}}{\partial \mathbf{y}^2} = 0$$

Given the boundary points for such a surface, there is a straightforward algorithm known as the relaxation algorithm which can be used in order to find the interior points which satisfy the above equation. This algorithm is iterative; its values converge to those of the desired surface. In general, this convergence is quite rapid at first, then more and more gradual as the computation continues.

The RELAX card allows us to use this algorithm. A typical approach would be to first use the SURFACE card method to specify only all of the boundary points for working surface number SURFNO. The RELAX card would then be used to find all of the interior points for this surface; these would have the property of representing the smoothest possible surface through the boundary points given.

The parameter TOLER allows the user to control the accuracy with which the surface is determined. The relaxation process will stop when, during one iteration of the algorithm, the value of no data point on the working surface changes by no more than TOLER. Note that TOLER measures the amount of change, not the amount of error as compared to the final, exact surface. Given reasonable surfaces, TOLER should probably be at least an order of magnitude smaller than the maximum error desired; when NX and NY are large, two orders of magnitude might be appropriate. If the user specifies that TOLER = 0 or leaves the specification of TOLER blank, the following automatic definition of TOLER takes place, in order to conserve computer time:


$$TOLER = \frac{SCALEX + SCALEY}{200}$$

Note that the RELAX card can be used in conjunction with any working surface whose boundary points are defined. The user is not restricted to using it in conjunction with the SURFACE card as outlined above.

K. BEND CARD

The subroutine (BENDER) used to implement the operation of the BEND card is the most complex subroutine of the geology model. It is discussed in detail in Sec. V, but an overview of its operation is provided here.

When something is bent, there is a median surface which is neither stretched nor compressed—only displaced. For example, consider a simple beam:



As we can see above, the stretched and compressed sides of the beam are not related to each other by a simple vertical distance relationship. While this is a two-dimensional example, the same kind of thing happens in three dimensions, except that there is a median surface which need not necessarily be a plane or cyliner.

The question which the bending subroutine attempts to answer is, "Given two working surfaces which represent the locations of the old and new median surfaces, prior to and after the bending of the rock, what is the new surface which resulted from the deformation of the old surface during this bending process?"

The exact analytical solution of this question would involve great data processing expense. We have provided an approximate solution, which seems to give reasonable answers, but even then involves significant

expense when NX and NY are large, since the processing time is related to (NX times NY) 2 . Much of this expense is unnecessary since, when NX and NY are large, it is not usual for the displacement of the median surface at one I,J location on the grid to have much effect on surface deformations for I,J locations which are many grid points distant. The INFLUN parameter allows us to take advantage of that fact. Through its use, the consideration of the effect on deformation by causes more than INFLUN grid spacings distant can be eliminated. This makes the running time proportional to (NX times NY) times $(1 + 2 \text{ times INFLUN})^2$ —a significant saving when NX and NY are large. If INFLUN is not specified, it is automatically set equal to three.

L. GRAPH CARD

From time to time, one may become curious as to the current Z values of a given working surface--especially after using a BEND card. The GRAPH card allows the user to print out X-Y plots of the surfaces, with X and Y coordinates labeled, and the appropriate Z values displayed. Plots that are too wide are automatically printed out in vertical strips which, when laid side by side, depict the entire surface. There is therefore no problem in producing plots, regardless of how large NX and NY become. Plots for several working surfaces can be produced with the same GRAPH card by placing their working surface identification numbers in sequential data fields on the card, beginning in the leftmost data field. The first blank data field encountered will terminate the process of producing plots. The process of producing plots does not alter any surface in any way.

M. LAYER CARD

The LAYER card is used in changing the status of a working surface to that of a geological surface. In doing this, the working surface is left unchanged; it is merely copied onto a disk file, and given a new number—a <u>layer</u> number as opposed to a working surface number. In addition, an entry is made in the array INDEX. This entry specifies the kind of rock properties which the user wants to have associated with this

geological layer. In effect, in using the LAYER card, the user is saying, "Use working surface number SURFNO, associated with rock type ROCKNO, as geological layer LAYERNO."

N. PROPERTY

The PROPERTY card allows the user to specify the properties which are to be associated with rock type ROCKNO. The meanings of these parameters are not specified at the present time and are not relevant to this discussion.

O. MAKEFILE

The MAKEFILE card is the card which causes the consolidation of geological information into the geology file. In making the geology file, the geology model will assume that the user has specified properties for all types of rock having the numbers 1 through MAXROCK, inclusive. Likewise, it will assume that geological layer information is stored for all layers having layer numbers 1 through MAXLAYER, inclusive.

P. SUMMARY

Except for the first ten columns of any input data card, which must be alphabetic and left justified, all data entered on input data cards must be numeric and must contain decimal points.

The reader is cautioned to be thorough and consistent in redefining arrays within the geology model. For example, if the array SURF were redefined as SURF (27, 53, 7) in the main program GEOMOD, then the arrays named A, B, C, D, BX, and BY in the subroutine BENDER would have to be dimensioned as (27, 53), the array POINT in BENDER would have to be redefined as POINT(3, 1431), and the array GRID in the subroutine GRAPH would have to be redefined as GRID(27, 53). Failure to redefine these arrays outside of the main program GEOMOD would lead to incorrect indexing of these arrays and would cause erroneous results.

V. SUBROUTINE BENDER

The motivation in developing the BENDER program (Fig. II-2) was to create a subroutine which would geometrically alter geological layers in a reasonable and consistent way, and with a reasonable expenditure of computer time. The approach taken was geometrical rather than physical, on the basis of simplicity, available geological knowledge, and programming priorities.

When one begins to think about geometrical approaches to the warping of geological surfaces, some concepts seem to quickly come to mind and persist:

- 1. Any reasonable way of defining the three-dimensional deformation of a layered geological region seems to involve a description of what happened to the surface which, after deformation is the "median" surface in the sense that it was neither stretched nor compressed, but merely displaced.
- 2. It is true that, in a given pattern of deformation, there might be a large volume which might be neither stretched nor compressed and therefore, in the above sense, there can be no reasonable definition of any single "median" surface on the basis of its being neither stretched or compressed. While this is true, it is also true that, in this region, any surface would form an acceptable "median" surface, in the above sense.
- In fact, when one begins to think about the time spans involved, the stresses and strains involved are probably not that well defined or understood; they may be dissipated by slippage, plastic flow, changes in the chemical makeup of the rock, etc. It is probably more realistic to think about deformations rather than stresses and strains, although the concept of a median surface is still an aid to understanding.





Figure II-2. Flow Chart of Logic of BENDER Subroutine

It is immediately obvious, after glancing at Fig. II-2, that the basic logic of the BENDER is exceedingly simple; it is also obvious, after looking at the 350 lines of FORTRAN in its listing, that its implementation may be straightforward, but it is not simple. For example, computing the normal vectors for the new median surface involves computing the partial derivatives in the X and Y directions at each grid line crossing point and storing them in the BX and BY arrays, respectively. These partial derivatives are then converted to the direction cosines of the desired normal vectors, the results of this computation again being placed in the BX and BY arrays. About 25 lines of FORTRAN code are involved.

Likewise, finding all of these normal vectors which pass through each grid line crossing point on the old surface is no simple task. First of all, this implies that the direction cosines for each grid line crossing point on the new median surface have to be examined in order to determine whether a normal vector from that point on the new median surface could go through each of the grid line crossing points on the old surface which is to be distorted. The mechanics of this operation infer that this processing step would have to be performed (NX times NY) times (NX times NY) times. This problem, whose solution was discussed in the preceding section, is compounded by the fact that the normal vectors from the new median surface will generally not originate at grid line crossing points, if they pass through grid line crossing points on the old surface which is to be distorted; some method of interpolation is therefore needed. The problem is further compounded by the fact that an iterative procedure is used to find the origination point of the normal vectors; there seems to be no better alternative to this procedure.

Although the iterative procedure could not be avoided, a quick, reasonable method of interpolation was found. If a function has a stated

value at the four corners of a square grid, and if its value at some interior point is desired:



then if F(I + DX, J + DY) is computed as follows:

$$F(I + DX, J + DY) = (1 - DX) (1 - DY) F(I,J)$$

+ DX (1 - DY) F(I + 1, J)
+ DY (1 - DX) F(I, J + 1)
+ DX (DY) F(I + 1, J + 1)

The value of F(I + DX, J + DY) obtained is the same as if F(X,Y) were a harmonic function whose boundary values varied linearly along the boundaries between the four points in question. This interpolation scheme is used several times in the BENDER subroutine.

Having found a normal vector (suitably interpolated) from the new median surface which passes through a given grid crossing point on the old surface to be displaced, the next task is to extend the vector—in one direction or the other—until it intersects the old median surface, so that the displacement of the median surface can be calculated; this displacement will contribute to the displacement of point on the old surface to be displaced into the new, displaced surface. Again, it seems

that the only way to do this is by an iterative procedure. The method used is similar to that used with the normal vectors, above. Basically, one makes a guess as to where the desired vector might originate or terminate, as the case may be. One then determines what correction is necessary to make the vector collinear (not necessarily in the same direction) with a previously determined vector. This procedure is repeated until either the computation drives the guesses out of bounds or the process converges to a solution, within a reasonable tolerance.

Finally one encounters the same problems with surface fitting that were discussed in conjunction with the TILT card (previous section). In fact, the same code is used, since the TILT routine is part of the BENDER subroutine. The same comments apply.

APPENDIX III

PROGRAMS TUNNEL AND GENTNL

by

P. K. Parish

SUMMARY

The two programs, TUNNEL and GENTNL, are alternative means of creating the geology file, TUNNEL, required by the excavation model. Program TUNNEL uses as input the GEOLOGY file generated by the geology model; program GENTNL allows direct creation of the TUNNEL file using only card input.

CONTENTS

CH/MTAN			
SECTION			PAGE
I	PROC	GRAM TUNNEL	111-5
	A.	Purpose	111-5
	В.	General Technique	III-5
	C.	Input	111-5
	D.	Output	111-10
	E.	Program Logic	111-11
II	PROGRAM GENTNL		111-18
	A.	Purpose	111-18
	В.	General Technique	111-18
	С.	Input	111-18
	D.	Output	111-18
	Ε.	Program Logic	TTT_18

I. PROGRAM TUNNEL

A. PURPOSE

Program TUNNEL creates, from the GEOLOGY file written by the geology model, a TUNNEL file for input to the excavation model. The TUNNEL file describes the properties of the rock encountered in a specific tunnel through the three-dimensional area defined by the geology model. Execution and information flow is shown schematically in Fig. III-1.

B. GENERAL TECHNIQUE

The geology information is read from the GEOLOGY file and stored internally. The user, meanwhile, inputs (X,Y,Z) coordinates of the end points of any number of straight-line segments which describe the tunnel midline through the given geological area. The program advances along the midline of this tunnel at intervals of DELTA feet (see "OPTION" card), determining what geological layer contains each point. Whenever a new layer is entered (or the end of a segment is reached), a record is written for the TUNNEL file.

C. INPUT

- The GEOLOGY file, generated by the geology model, containing three-dimensional layer and rock property information
- 2. User parameter cards

There are four types of input cards (see Table III-1): OPTION, START, NEWLEG, and END. Each card is considered to have up to 6 fields of 10 columns each. The first field contains the alphabetic keyword, beginning in column 1. Values entered in succeeding fields must contain decimal points, but may appear anywhere in the assigned 10 columns. A description of each card type follows.

Preceding page blank




Figure III-1. TUNNEL File Creation by Program TUNNEL

TABLE III-1
INPUT CARD FORMATS FOR PROGRAM TUNNEL

1-10	11-20	21-30	31-40	41-50	51-60	
OPTION	DIAM	XORIG	YORIG	UNIT	DELTA	(Optional)
START	х	Y	Z			(Required)
NEWLEG	х	Y	Z			(Optional)
•						
•						
•						
NEWLEG	х	Y	Z			(Optional)
END	х	Y	Z			(Required)

OPTION Input Card

This card is used to override default values for certain program parameters. If default values are acceptable, this card is not required; if present, however, it must be entered first. For each parameter except XORIG and YORIG (for which zero may be the desired value), a blank or zero entry will cause the default to be in effect. None of these parameters is written to the TUNNEL file.

Field	Description	<u>Default</u>	Comments
DIAM	Tunnel diameter, in feet	10 ft	Currently not used by the TUNNEL program
XORIG	X location (feet) coin- cident with I=1 in geology model grid. This is the reference point used for X entries on succeeding cards.	1 ft	If OPTION card is present, this field must be filled in.
YORIG	Y location (feet) coin- cident with J=1 in geology model grid. This is the reference point used for Y entries on succeeding cards.	1 ft	If OPTION card is present, this field must be filled in.
UNIT	Number of feet represented by each SCALEX, SCALEY unit in geology model grid.	1 ft	
DELTA	The number of feet to be used by the program be- tween test points along the tunnel midline.	20 ft	A smaller number here yields greater accuracy and longer processing time.

START Input Card

The X,Y,Z entries define the start of the tunnel midline through the area described in the geology model. The X and Y coordinates refer to the I,J axes of the geology model grid after application of XORIG, YORIG, UNIT, SCALEX, and SCALEY. The Z coordinate corresponds directly to those of the geology model, without transformation.

Hence, the X entered here will be transformed to the position $\mathbf{X}_{\widetilde{\mathbf{I}}}$ on the geology model grid by:

$$X_{I} = 1 + \frac{(X - XORIG)}{SCALEX \times UNIT}$$

and similarly for Y.

NEWLEG Input Card

If the tunnel is one straight-line segment, this card is not used. If the tunnel is composed of $N_{\rm S} > 1$ segments, however, there will be $N_{\rm S} - 1$ "NEWLEG" cards entered sequentially, each one containing the coordinates of the start of each new segment (except for the first segment, the coordinates of which are entered on the START card). There is no practical upper limit for $N_{\rm S}$. X, Y, Z are interpreted as for the START card.

END Input Card

The last card entered must be an END card. It contains the position of the end of the tunnel midline. X, Y, Z are interpreted as for the START card.

D. OUTPUT

- 1. A printed report, showing the OPTIONs in effect, and a copy of the information written to the TUNNEL file.
- The TUNNEL file, which will be input to the excavation model.
 Each logical record on the file contains the following fields:
 - a. POSITION: The distance, in feet, from the beginning of the tunnel (X = 0) at which the following properties cease to apply. That is, the properties are applicable through the interval from the POSITION given on the preceding record (or from X = 0 for the first record) up to, but not including, this POSITION.
 - b. PROPERTY 1: Unconfined compressive strength, psi
 - c. PROPERTY 2: Abrasiveness
 - d. PROPERTY 3: RQD, rock quality designation
 - e. PROPERTY 4: In situ density, 1b/ft³
 - f. PROPERTY 5: Ambient temperature, °F
 - g. PROPERTY 6: Water inflow rate, gal/min
 - h. IFLAG: Not used at present. May be utilized later to indicate mixed geology situations.

The FORMAT statement used to write each record is "FORMAT (7(1PE18.10), I2)." End-of-file is indicated by a dummy record containing a POSITION < 0.

For the logic of the TUNNEL program, as well as for the geology model, the entity assigned to any PROPERTY is completely arbitrary. The definitions shown here are those currently expected by the excavation model.

E. PROGRAM LOGIC

1. Main Program

Program TUNNEL reads the GEOLOGY file, processes the user input cards, and creates the TUNNEL file. The program technique is described in Sec. III-B, "General Technique." A flow chart is shown in Fig. III-2.

2. Subroutine GETLYR

This subroutine is used to determine which geological layer (LL) contains the point (XX,YY,ZZ).

Layer information is given in the GEOLOGY file only at the integral (I,J) grid points, hence interpolation may be required when seeking layer information at (XX,YY). Throughout the following discussion, $Z_{(I,J,L)}$ = vertical position in feet of the upper boundary of layer L at grid point (I,J).

First, (XX,YY) is translated to the geology model's (I,J) grid by:

$$XCOOR = 1 + \frac{(XX - XORIG)}{SCALEX \times UNIT}$$

$$YCOOR = 1 + \frac{(YY - YORIG)}{SCALEY \times UNIT}$$

The integers bounding (XCOOR, YCOOR), then, are given by:

The four grid points surrounding (XCOOR, YCOOR), therefore, are (ILOW, JLOW), (ILOW, JHI), (IHI, JLOW), and (IHI, JHI).




Figure III-2. Program TUNNEL Flow Chart




Figure III-2. Program TUNNEL Flow Chart (Cont.)

If (XCOOR, YCOOR) falls within the (I,J) grid (i.e., if $1 \le ILOW \le NX - 1$ and $1 \le JLOW \le NY - 1$), the processing is as follows

- The layer information for the four surrounding grid points is examined. If ZZ is contained in the same layer at each point, that layer number is stored in LL, and the subroutine returns.
- 2. Otherwise, interpolation is required. To do this, the upper boundary of layer L in this grid square is assumed to coincide with the plane defined by the three points:
 - · ILOW, JLOW, Z(ILOW, JLOW, L)
 - · IHI, JLOW, Z (IHI, JLOW, L)
 - (XCOOR, JHI, ZC), where ZC is calculated by finding the equation of the line (2-point form) in the (X,Z) plane connecting the points (ILOW, JHI, Z (ILOW, JHI, L)) and (IHI, JHI, Z (IHI, JHI, L)), substituting XCOOR and solving for ZC.
- 3. The subroutine, then, cycles through for each layer L defined in the geology file, derives the equation of the plane (3-point form) defined by the above three points, substitutes XCOOR and YCOOR in this equation, and solves for Z. This value Z is stored in ZHOLD(L), and represents Z (XCOOR, YCOOR, L)
- 4. When ZHOLD(L) has been calculated for all L, the routine finds the lowest ZHOLD(L) such that ZHOLD(L) \geq ZZ. This L is stored in LL as the layer containing (XX,YY,ZZ).

Special cases exist if (XX,YY) falls outside the geology model grid. Here, each boundary grid line is assumed to define the area beyond it; e.g., the layer information for I=NX is taken to be true for all I>NX. Hence, if the given point (XX,YY,ZZ) is N,S,E, or W of the grid, only two (I,J) grid points need be examined, and interpolation, when necessary

is done in two dimensions. For a point NE, NW, SE, or SW of grid, only one (I,J) gridpoint must be examined, and no interpolation is required.

3. Subroutine NEWPNT

Given the end points of a straight-line segment, (X1,Y1,Z1) and (X2,Y2,Z2), subroutine NEWPNT determines the coordinates (XM,YM,ZM) of the point on the line segment which is DL ft from (X1,Y1,Z1). It is used by program TUNNEL to retrieve each successive point along the tunnel midline, at intervals of DELTA feet, which is to be tested for layer information.

In the normal case, $X1 \neq X2$, $Y1 \neq Y2$, and $Z1 \neq Z2$. The derivation of the calculations performed when this is the situation is as follows:

a. The formula which is to be solved for (XM,YM,ZM) is that for the distance, DL, between the points (X1,Y1,Z1) and (XM,YM,ZM):

$$DL = \sqrt{(XM - X1)^2 + (YM - Y1)^2 + (ZM - Z1)^2}$$

b. In order to reduce the problem in (a) to one unknown, YM and ZM are expressed as functions of XM using the 2-point form of the straight-line equation:

$$YM = Y1 + \frac{(Y2 - Y1)XM}{(X2 - X1)} - \frac{(Y2 - Y1)X1}{(X2 - X1)}$$

$$ZM = Z1 + \frac{(Z2 - Z1)XM}{(X2 - X1)} - \frac{(Z2 - Z1)X1}{(X2 - X1)}$$

c. Substituting the expression for YM and ZM from (b) into the equation in (a) yields:

$$DL^{2} = [XM - X1]^{2} \left[1 + \frac{(Y2 - Y1)^{2}}{(X2 - X1)^{2}} + \frac{(Z2 - Z1)^{2}}{(X2 - X1)^{2}} \right]$$

d. This is then solved for XM as follows: Let

$$A = 1 + \frac{(Y2 - Y1)^2}{(X2 - X1)^2} + \frac{(Z2 - Z1)^2}{(X2 - X1)^2}, \text{ a constant.}$$

a constant. Then

$$A(XM)^2 - 2A(X1)(XM) + A(X1)^2 - DL^2 = 0$$

from (c). Let

$$B = -2A(X1)$$
 and $C = A(X1)^2 - DL^2$

both constants. Then we have

$$A(XM)^{2} + B(XM) + C = 0.$$

XM can now be found by computing

$$\frac{-B \pm \sqrt{B - 4AC}}{2A}$$

(Note that B^2 - 4AC simplifies to $4A(DL)^2$) and selecting the root which is between X1 and X2.

e. Once the required XM is found, the corresponding YM and ZM can be determined by substituting the value for XM in the expressions of (b).

Special cases exist if X1 = X2, Y1 = Y2, or Z1 = Z2. If only one of these conditions is true, then the same procedure is followed as in the normal case except that the problem is reduced to two dimensions. If two of the conditions exist, then the problem is one-dimensional, and the proper coordinate of (X1,Y1,Z1) is simply incremented (or decremented) by DL.

4. Subroutine RDGEOL

Entry RDGEOL reads the entire GEOLOGY file and stores the information internally for retrieval during program execution. The variables stored as they are on the file are NX, NY, SCALEX, SCALEY, INDEX(25), and PROP(6,25). Layer information is stored in ZSTOR(30,30,25), where ZSTOR(I,J,L) contains the depth in feet of layer L at grid point (I,J). A flag array, LFLAG(25), is set during reading such that LFLAG(L) = 1 if the GEOLOGY file contains data for layer L; it is zero otherwise.

Given II, JJ, and ZZ, where II and JJ are integers, entry FINDL examines ZSTOR(II,JJ,L) for all L to determine what geological layer (LL) contains ZZ. It is used by subroutine GETLYR.

II. PROGRAM GENTNL

A. PURPOSE

Program GENTNL, using card input only, creates a TUNNEL file for input to the excavation model, thereby bypassing the geology model. Execution and information flow is shown schematically in Fig. III-3.

B. GENERAL TECHNIQUE

The input cards are read, checked for ascending sequence by POSITION, and the values written to the TUNNEL file and to the printer. There are no practical restrictions to the number of cards or the number of PROPERTY combinations input.

C. INPUT

User data cards, containing the values which are to be written to the TUNNEL file, are the only input. The card format is shown in Table III-2. Any number of cards may be submitted, but the last card must contain a negative number in the first word (POSITION) to indicate the end-of-input. Each card is considered to have 8 fields of 10 columns each; each number entered must contain a decimal point, but may appear anywhere within its assigned 10 columns.

D. OUTPUT

- 1. A TUNNEL file for input to the excavation model. For a file description, see OUTPUT under program TUNNEL.
- 2. A printed copy of the contents of the TUNNEL file.

E. PROGRAM LOGIC

The program is basically a card-to-tape-and-printer utility which includes a sequence check on the POSITION field.




Figure III-3. TUNNEL File Creation by Program GENTNL

TABLE III-2 INPUT CARD FORMAT FOR PROGRAM GENTNL

71-80	IFLAG	
0/ 19	PROPERTY 6	
51-60	4 PROPERTY 5	
41-50	PROPERTY 4	
31-40	PROPERTY 3	
21–30	PROPERTY 2	
11-20	PROPERTY 1	
1-10	POSITION	

See description of TUNNEL file record for meaning of entries. Notes:

All numbers entered must contain decimal points.

Cards must be entered in ascending sequence by POSITION.

A card containing a negative POSITION must be placed at the end of the

input deck; the remainder of this card may be blank.

APPENDIX IV

EXCAVATION MODEL

by

M. McJunkin F. H. Murphy B. H. Lieu

SUMMARY

This appendix reviews the programming details of the excavation model and gives a short description of its conceptual basis. The sub-routines simulating the tunneling activities are then described in detail, followed by a description of steps that need to be taken to incorporate the routines described into a control program which will coordinate the tunneling activities. Finally, the control logic required to coordinate any simulation is described, and the construction of a sample control program with its associated input and output routines is discussed.

CONTENTS

SECTION		FAGE
I	NOTES ON EXCAVATION MODEL DESIGN	IV-5
II	DESCRIPTION AND FLOW CHARTS OF SUBROUTINES IN EXCAVATION MODEL	IV-8
	A. Introduction	8-VI
	B. Element: Rock Fragmentation	IV-11
	C. Element: Materials Handling (Short Haul)	IV-17
	D. Element: Materials Handling (Long Haul)	IV-20
	E. Element: Ground Support	IV-29
	F. Element: Environmental Control	IV-34
	G. Input Routine	IV-35
	H. Output Routines	IV-36
III	NOTES ON INCORPORATING SUBROUTINES INTO A CONTROL PROGRAM	IV-84
IV	GENERAL REQUIREMENTS FOR THE CONTROL PROGRAM LOGIC	IV-88
V	CREATING A CONTROL PROGRAM FOR THE LAYOUT TUNNEL	IV-92
	A. Subroutines	IV-92
	B. Subroutine Usage	IV-93
	C. Control Logic	IV-93
	D. Initialization of Data	IV-100
	P Output	TV-102

Preceding page blank

FIGURES

NO.		PAGE
I -1	Information Flow for Individual Tunneling Model Subroutines	IV-6
IV-2	Subroutines of the Excavation Model	IV-10
IV-3	Example, Ground Support Input Cards	IV-33
IV-4	Overall Logic of a Control Program for the Tunneling Model	IV-91
IV-5	Logic of the Control Program for the Layout Tunnel	IV-99
IV-6	Initialization Sequence for Layout Tunnel	IV-103
IV-7	Printout of Working Storage	IV-105
IV-8	Interim Performance Report	IV-107
IV-9	Interim Cost Report	IV-109

SUBROUTINE FLOW CHARTS

BORE	IV-39
CUTTER	IV-40
REPAIR	IV-41
JETIMP	IV-42
JETMNT	IV-43
JETAGN	IV-44
PROJTL	IV-45
PRJBR	IV-46
MOVEIN	IV-47
MOVOUT	IV-48
HOLBRN	IV-49
SETCHG	IV-50
CVLOAD	IV-51
CVMNT	IV-52
MUKLOD	IV-53
MUKIN	IV-54
MUKOUT	IV-55
	T\$1 /.

IV-4

SUBROUTINES (Cont.)

RAILHL	IV-56ff
ADDTRN	IV-70
RAILDS	IV-71
RAILEX	IV-72
RAILMT	IV-73
TRNPRT	IV-74
EXTNSN	IV-75
SURGE	IV-76
BELT	IV-77
GRNSUP	IV-78
GSMAIN	IV-79
ENVIR	IV-80
INPUT	IV-81
OUTPUT	IV-82
REPORR	IV-83
REPORC	I V- 84
MAXADV	IV-85

1. NOTES ON EXCAVATION MODEL DESIGN

The tunneling model is designed as a time-step simulation program. Each step in the simulation is considered to occur between one well-defined time and state of existence and another. The data required to so proceed is processed by subroutines that correspond to the various activities in the tunneling process being simulated. The subroutines simulate the whole excavation process. A control program must be provided by the user to coordinate the activities of the subroutines, initialize data, and print output reports.

The concept of the simulation proceeding from one well-defined time and state to another is implemented through the use of "old" and "new" working parameter common areas (OLDCOM, NEWCOM). During any given time step, the contents of OLDCOM describes the state of the tunneling system at the beginning of the time step; the NEWCOM contents describes the state of the tunneling system at the end of the current time step. Each subroutine receives its input information from OLDCOM and places its output information in NEWCOM. Each subroutine, therefore, determines the state of the system at the beginning of the new time step according to information received at the beginning of the current time step.

by any given subroutine. Some of the information paths for some subroutines may be absent, but no subroutine has any information path not depicted in Fig. IV-1. It is emphasized that all information transfer to and from subroutines is through common areas; the control program is not in any way involved in information transfer to and from subroutines. From time to time, as the tunnel advances, the control program transfers new geology information to the common area of an old working parameter, but it never transfers information directly to or from a subroutine.

Parameter information for the use of the subroutines is read by the control program and is placed in the common areas. After cards are read




Figure IV-1. Information Flow for Individual Tunneling Model Subroutines

in, each subroutine which has an initialization entry point is called at that entry. The subroutines contain default values for the various parameters. If no card input information has been provided for one or any of them, the model uses the default values. This approach was taken in order to avoid the need to specify large numbers of parameters. Parameter information for one execution of the model need contain specifications only for those subroutine parameters which are of interest.

The time stepping and the approach creating two working common areas leads to a simplification of reality, forcing the simulation model to operate in a discontinuous fashion (in reality, some tunneling processes are continuous). This is not considered to be a significant problem as long as the time steps are kept relatively short—perhaps about 1 to 10 minutes.

As the subroutines are executed, cost, availability, and utilization information is generated and cumulated. This information is placed in common areas by the abroutines involved. These common areas are used to compute values for printing reports.

II. DESCRIPTION AND FLOW CHARTS OF SUBROUTINES IN EXCAVATION MODEL

A. INTRODUCTION

The subroutine descriptions are grouped by the element of excavation and subgrouped by the type of tunneling they represent. For example, the first group of subroutines (Sec. IV-B) covers rock fragmentation, each type of fragmentation (boring machine, water jet, etc.) being described separately. Also discussed are the input and output routines written for the Layout Tunnel (see Vol. I of this report), which may be modified for use in other simulations. Figure IV-2 is a chart of subroutines related to the operations they simulate.

The text of this section of Appendix IV is organized as follows:

- A short description of the process being simulated.
- A list of the common blocks that need to be included in any control program written to simulate an excavation using a given process. Note that, in addition to the common blocks, any TYPE, EQUIVALENCE, and/or DATA statement involving a variable in the common blocks listed must be included in the model.
- A list of input variables, principally a NAMELIST (and its variables).
- A list of status variables through which the subroutines change the status of the process or of another process.

 Almost all of the status variables exist in two forms: present and future. They belong to the two common areas (of parameters) described in Sec. I of this appendix. The future form is that shown in the descriptions of routines. These variables are used to turn on and off the excavation in the sample control program. However, they can also be used to turn off other processes or change subroutine calls, thus giving the user more flexibility in simulating the tunneling process.




Figure IV-2. Subroutines of the Excavation Model

Input variables and status variables are defined in Appendix VI, and should be studied in conjunction with the listings and definitions in Appendix VI.

Several general statements that apply to the subroutines follow.

- 1. All subroutines have a normal entry point, used when the routine is called during the run for each time step. A few subroutines have two normal entry points (e.g., SURGE), and these are called by other subroutines, not by the control program.
- 2. Most subroutines also have an initialization entry point. Unless otherwise stated, the initialization entry should be called only once, at the start of the run immediately following the reading in of cards.
- 3. As mentioned above, status variables have two forms. future form of the variable is usually the present form preceded by an F or L. For example, the status variable in CVMNT which indicates whether the loader is being maintained has a present form MCV and a future form LMCV. Each subroutine uses the present form to indicate the present status of the process described, and changes the future form as a result of computations. The subroutine never changes the present form. At the beginning of each time step the control program sets the present status variables equal to the future variables and thus updates the status of processes. For example, in the sample control program, LIEXCA is set equal to 1 in GRNSUP to indicate that ground support is falling too far behind the excavator and as a result the excavator must be turned off in the next cycle to allow ground support to catch up. At the start of the next cycle IEXCA (the present variable) is set equal to LIEXCA in the control program. When the checks are made to determine the status (MBORE) of the boring machine, IEXCA is found to be 1 and MBORE is set equal to 7, indicating that the boring machine is idle.

B. ELEMENT: ROCK FRAGMENTATION

Type: Boring Machine

The set of subroutines BORE, CUTTER, and REPAIR simulate rock fragmentation using a boring machine. These routines are currently set up so that their status variables are not in the two parameter common areas (OLDCOM, NEWCOM) but are single variables which have only a present form. This could be changed by having the user insert another form in the routines and put the two forms in COMMON/OLDCOM/, COMMON/NEWCOM/.

Common blocks: COMMON/ALL/

COMMON/BORE/

COMMON/PERFRM/

COMMON/MONEY/

Input variables: NAMELIST/BORE/

CL, CPC, DTA, DTC, DTCD, DTD, DTM, KK, PBM, R,

RC, RPM, TR, XCPC, EBOREQ, ETRANSL, DJMBMM, BOMEN, BOCST

Status variables: MBM

MBORE

LNCUTR

BORE - Rock Fragmenting

Operating time, plant and equipment costs, and labor costs for the boring machine for each time slice are computed and cumulated. If the boring machine is operating it computes the distance traveled by the boring machine and the job material cost of operating the machine.

CUTTER - Changing Cutters

Cutter wear is computed if the boring machine is operating and cutters are not being replaced. Cutter wear is checked and cutters are scheduled for replacement by setting LNCUTR = 1 if necessary. If cutters are in the process of being replaced, then one time step (DT) is added

to the time already spent in replacement. If time spent in replacement is greater than or equal to the replacement time input by the user, then replacement of cutters is scheduled to end in the next cycle by setting LNCUTR = 0.

REPAIR - Repairing Boring Machine

The subroutine cumulates time until the user input time for scheduling maintenance is reached. At that point, maintenance is scheduled for the machine to start in the next time cycle by setting MBM = 1 and cost of the maintenance is computed. If maintenance is in progress, then time is added to the user input maintenance period. When the user input maintenance period has elapsed, maintenance is scheduled to end in the next cycle by setting MBM = 0.

2. Type: Water Jet

The set of subroutines JETDP. JETMNT, and JETAGN simulate rock fragmentation using water jet impact, continuous and intermittent pulses.

Common blocks:

COMMON/ALL/

COMMON/NJETS/

COMMON/PERFRM/

COMMON/MONEY/

COMMON/OLDCOM/

COMMON/NEWCCM/

Input parameters:

NAMELIST/JETS/PNOZZ, DNOZZ, NJETS, MODEJ,

PPM, PULSED, ETAJ, ETAIMP, ENERGJ, DTCJET,

DTMJET, DJMWJM, DTRJET, XRJET

Status variables:

LMWJ

LMWJR

LMWJM

FHEA: J

FQWATR

JETIMP - Jet Impact

In a normal entry a check is made to determine if the water jet is operating (MWJ = 0); if not the routine is exited. If it is operating, the subroutine computes the amount of rock disintegrated, the amount of heat and water added to the tunnel by the jet, and the cost for one time step.

JETMNT - Maintenance

A normal entry checks first to find whether maintenance is in progress. If not, then one time step is subtracted from the time left until the next maintenance period (time between maintenance periods input by user). If the remaining time is then 0, and if repositioning is not being done (MWJR \neq 0), the jet is scheduled for maintenance in the next time step by setting LMWJM = 0 and set LMWJ = LMWJ + 1 to indicate jet not operating.

If maintenance is in progress at entry to the routine, the time elapsed for maintenance is increased by one time step. If the user impact time for maintenance (DTMJET) has been reached or exceeded, the jet is scheduled for removal from maintenance in the next time step by setting LMWJMC = 1 and subtracting 1 from LMWJ, and the cost is increased by the cost of a maintenance period.

JETAGN - Repositioning in Progress

The first check in a normal entry determines whether the jet is operating; if not, then if maintenance is in progress the routine is exited. If maintenance is not in progress, if the jet is not operating, and if repositioning is being done, one time step is added to the elapsed repositioning time and a check is made for repositioning completed. If it is completed, then its completion is scheduled for the next time step (LMWJR = 1 and LMWJ = LMWJ - 1).

If the water jet is operating at normal entry to the routine, then the distance traveled by the jet since the last repositioning is checked.

If it is greater than the user input maximum allowed distance, repositioning is scheduled for the next cycle (LMWJR = 0, LMWJ = LMWJ + 1).

3. Type: Projectile Fragmentation

The set of subroutines PROJTL, PRJBR, JETAGN, and JETMNT simulate rock fragmentation using projectile impact. The routine to simulate repositioning of the guns is the same as for the water jet, as is the maintenance routine. The initialization and normal entry points are different, however (PRJAGN and PRJPOS for the repositioning routine, PRJMNT and PRJRPR for the maintenance routine).

Commor blocks:

COMMON/ALL/

COMMON/NJETS/

COMMON/PERFRM/

COMMON/MONEY/

COMMON/OLDCOM/

COMMON/NEWCOM/

Input parameters: NAMELIST/PELLET/DTCJET, DTMJET, ETAGN, ETAIPT,

WPRJ, VELPRJ, VOLPRJ, NGUNS, CSTPRJ, PRJPM,

CPBRL, TRBRL, BLT, XRJET, DJMWJM, DTRJET

Status variables: LMPI

LNBARL

LMWJR

FHEATJ

PROJTL - Rock Fragmentation

In a normal entry a check is made to determine if projectile guns are operating. If yes, rock fragmented, advance of face, power costs, and heat generated are calculated for one time step. Total job materials cost for rock fragmentation is incremented. If no, the subroutine is exited.

PRJBR - Barrel Replacement

In a normal entry a check is made for barrel replacement in progress; if it is not, time elapsed since replacement is increased by one time step. Time elapsed against user input time between replacements is checked. If it is time for replacement, repositioning of barrel in progress is checked. (MWJR = 0). If it is not, barrel replacement is scheduled for next time step (LNBARL = 0, LMP1 = LMP1 + 1).

If on the first check in a normal entry barrel replacement is in progress, then time elapsed since barrel replacement began is incremented by one time step. A check is made for replacement completed. If completed, end of replacement is scheduled for next time step (LNBARL = 1, LMPI = LMPI - 1). Job material cost (DJMRD) is incremented by cost of replacement.

4. Type: Drill and Blast

This set of four subroutines simulates rock fragmentation by drilling and blasting. The four subroutines provided are: MOVEIN, MOVEOUT, HOLEBRN, SETCHG. A maintenance routine which can be patterned after the general maintenance routine XXXMNT shown in Appendix VI must be provided by the user. Note that variables chosen for maintenance times and costs must be added to NAMELIST below and to COMMON/BLAST/.

Common blocks: COMMON/ALL/

COMMON/MONEY/

COMMON/PERFRM/

COMMON/BLAST/

COMMON/OLDCOM/

COMMON/NEWCOM/

Input variables: NAMELIST/BLAST/PF, TYPEPF, TCHG, MEN, NH, CCAP

WPL, CPL, CEX, CM, ND, LD, NHB, NDB, LDB, POD,

ADH, SE, POB, LBIT, LSTEEL, LBURN, TIN, TOUT,

CSTEEL, CBIT, CBURN, ADH, ADB

Status variables: LNDRLB

LNCHRG

LJUMOT

LJUMIN

LNDRIL

HOLBRN - Drilling

The subroutine simulates the drilling of holes of a burn pattern with drifter drills and burn-cut drills. In a normal entry one time step is subtracted from both time to drill holes with percussion drills and time to drill with burn-cut drills. If the result for percussion drills is positive, then the result for burn drills is checked; if both are positive, then drilling is not finished and the subroutine is exited. If one or both of the results are negative, drilling for one or both is scheduled to end in the next cycle (LNDRIL = 1 and/or LNDRLB = 1) and costs of drilling are calculated before the main program is resumed.

Note: Initialization must be redone for each drilling period.

Therefore, the control program must reset to ICYCLE = 1

when drilling is to be done.

SETCHG - Setting Charges

The subroutine simulates setting the blast charge. In a normal entry, one time step is subtracted from the time remaining to set a charge. If time still remains, the main program is executed. If no time remains, the finish of setting charge for the next cycle is indicated (LNCHRG = 1). Job materials costs for setting charges are computed and a return main program is executed.

Note: This routine, like HOLBRN, must be initialized for each drilling period.

MOVOUT - Moving Out Drilling Equipment

This subroutine simulates moving out drilling equipment. In a normal entry the time to move out is decreased by one time step. A check is made to determine whether moving out is completed. If it is, then end of moving is scheduled for the next time cycle by setting LJUMOT = 1.

Note: This routine must be reinitialized each time moving is done by setting ICYCLE = 1.

MOVEIN - Moving Drills In

This subroutine simulates moving drills in. A normal entry first decreases moving time remaining by one time step. Then, if no time remains, the end of moving is scheduled by setting LJUMIN = 1. Also, the number of feet that the tunnel will be advanced (DX) and the volume of muck created (DV) for this drilling and blasting cycle is computed here.

Note: This routine must be reinitialized each time moving is done by setting ICYCLE = 1.

C. ELEMENT: MATERIALS HANDLING (SHORT HAUL)

1. Type: Integrated Conveyor Loader

This set of subroutines simulates moving muck from the face area. It must be used with another set of subroutines for long haul (e.g., rails). Together the two sets simulate removal of the muck to the discharge area. The integrated conveyor loader is simulated by two subroutines CVLOAD and CVMN1.

Common Blocks: CC

COMMON/ALL/

COMMON/OLDCOM/

COMMON/NEWCOM/

COMMON/WHEELS/

COMMON/CONVEY/

COMMON/PERFRM/

COMMON/MONEY/

Input parameters: NAMELIST/LOADER/AB, VBI, SM, TCCV, TMCV, WMR,

MLTYP, ECONEQ, ECONESS, JMCV, CVMEN, CVCST

Status variables: LMCV

LLOADR

LMFLAC

Note: Operating time for the total muck hauling (short haul and long haul is computed in the long-haul subroutines. Long haul and short haul each compute down time.

CVLOAD - Loading Muck

One time step is added to labor time used for the loader, operating time for materials handling is updated, plant and equipment costs are updated for the time period advance. If the loader was unable to handle all the muck on the last cycle, or no train was available for loading the excess muck remaining is computed, then the total muck to be moved is computed. The muck is then either loaded onto vehicles (MLTYP = 1), or carried away by a conveyor (MLTYP = 2). (A check is made to determine if the long-haul system will take it all. If not LLOADR is set to 1 to indicate that it is overloaded.) If rails or trucks are the long-haul system and none is available for loading, LLOADR is set to 1. After loading the vehicle is sent to the discharge area if it is full.

CVMNT - Maintenance

One time step is added to the time elapsed since the last maintenance period. If the user input time between maintenance periods has been exceeded, maintenance is scheduled for the next time step by setting LMCV = 1.

If maintenance is in progress, then one time step is added to the time already accumulated for this maintenance period. If the time accumulated is greater an or equal to the user input maintenance period, the loader is schedu as go back into operation in the next time step by setting LMCV = 0.

2. Type: Machine Loaders and Shovels

This set of subroutines simulates removing of muck from the face area and is interchangeable with the integrated conveyor loader set. It is to be used with one of the sets of subroutines for long haul. Together they form the simulation of materials handling in the model. It consists of three subroutines, MUKLOD, MUKIN, MUKOUT; and a fourth routine, CVMNT, is used for simulating maintenance. (The same routine, CVMNT, is used by the integrated conveyor loader.) Note that MUKIN and MUKOUT status variables must be set = 0 in the control program to initialize each move in and out, respectively, from the face.

Common blocks: COMMON/ALL/

COMMON/COMOLD/

COMMON/COMNEW/

COMMON/WHEELS/

COMMON/CONVEY/

COMMON/PERFRM/

COMMON/MONEY/

Input variables NAMELIST/SHOVL/

STIME, QDMR, DTMO,

DTMI, TMCV, TCCV,

MLTYP, JMCV

Status variables: LMKIN, LMUKOT,

LLODR, FQL

MUKIN - Moving In Shovels

In a normal entry, the routine determines whether muckers are in the process of being moved to the face. If not, nothing is done. If they are being moved in then their moving time is decreased and a check is made to determine if the move has been completed. If it has, LMKIN is set to 1 to indicate completion.

MUKOUT - Moving Out Shovels

This routine handles the moving of muckers away from the face in exactly the same way MUKIN handles their moving to the face.

MUKLOD - Loading Muck

In a normal entry, the routine first determines whether a continuous main-line system (long-haul system is a conveyor belt) is being used. If it is, then the mucking rate is computed and compared with the muck to be moved. If the mucking rate is not adequate, LLODR = 0 is set to indicate mucking still in progress, load as much as possible. If the mucking rate is adequate, muck is loaded. If a unitized main-line system is being used instead of a continuous system, then a first check is made to determine if units (e.g., trains) are being switched. If yes, the time used for switching has one time step added to it. Time used for switching is compared with time needed to complete switching. If still more time is needed, no loading is done. If switching is finished and time is left, then the mucking rate is computed for time remaining. The number of units per vehicle is checked (e.g., muck cars per train). If there exists only one unit per vehicle, the full vehicle just switched with the empty one is released. If there is more than one unit per vehicle, a check determines if all units are filled; if so, the vehicle is released. Whether a vehicle is released or not, the computation for loading muck described below is done for whatever time remains.

If no vehicles are being switched, the calculation of the mucking rate is made. If it is adequate for the muck to be loaded, LLODR is set to 1 to indicate loading is complete. If unit is full after loading, switching time is set (TIMEL) and the check for switching time is made as described above. If the unit is not filled, the routine is exited.

D. ELEMENT: MATERIALS HANDLING (LONG HAUL)

1. Type: Rails

The set of subroutines simulates a long-haul rail system to carry the muck to the discharge area. This set in conjunction with a set of short-haul subroutines from the materials handling element of tunneling. The routines in the set are RAILHL, CUBIC, ADDTRN(I), RAILDS, RAILEX, and RAILMT.

Common blocks:

COMMON/WHEELS/ COMMON/OLDCOM/ COMMON/NEWCOM/ COMMON/MONEY/ COMMON/PERFRM/

Note: The routine CUBIC does not need any common blocks.

Input variables:

NAMELIST/RAILTS/ AE, AF, AMAX, AMAXL, AMINL, BSL, CARCAP, CP, DE, DF, DTAS, DTMA, DTU, NSWCIF, NGEO, NEXON, XDE, AB, VBI, SM, EL, FC, FR, FT, HPA, HPEV, HPEA, HPFA, HPFV, HPV, LOCO, MC, ML, NCARS, NPOINT, NTD, NTM, NTMAX, XP, NTMILP, NTMLPP, NTRACK, SL, TCURVX, TCURVY, TMAINT, TWE, VD, VE, VF, VS, VMAX, WC, WL, XDX, MAXLD, NVEHCL, NUMSWT, SWITCH, ISTA, TPOS, TSPD, TMAIN, KSTOP, MLTYP, WMR, ELOCO, EMUCKC, ETRACK, ESWITC, EUNLOA, ERMAIN, JMMHM, NUMLD, ISW, RAMEN, RACST.

General status variables:

LLUHCL LNBYBY LNSWCH LIFILD LKUNLO LLSTOP LNTRADA LNVHCL LNMSWT NUMLD

Status Variables for Each Train:

FTSTAT (J, I), J Jth Train/Truck

- I = 1 Status (see below)
 - = 2 Position, feet from discharge area
 - = 3 Speed, mph
 - = 4 Days since last maintenance, days

FTSTAT (J, 1)

- = 0 Train/truck is stopped, EMPTY reason given
- = 1 Train/truck is stopped, FULL by JSTOP(J)
- = 2 Train/truck is excelerating, E

- = 3 Train/truck is excelerating, F
- = 4 Train/truck is going at full speed, E
- = 5 Train/truck is going at full speed, F
- = 6 Train/truck is decelerating, E
- = 7 Train/truck is decelerating, F
- = 8 Train/truck is in switch, E
- = 9 Train/truck is in switch, F
- = 10 Train/truck is in discharge area
- = 11 Train/truck is in maintenance area

ISTOP

- = 0 Continue train/truck system
- = 1 Shut down train/truck system
- = 2 Bring up train/truck system

LKSTOP(J)

- = 0 Not stopped
- = 1 At face, loading
- = 2 In switch, train stopped ahead
- = 3 In switch, train approaching
- = 4 External reasons
- = 5 In switch, waiting to enter discharge area
- = 6 In switch, waiting to enter load area
- = 101, 102 ... At face, in queue

FUTIME(J) = Time to unload train J

FTOP (J) = Cumulative operating time of train J

FTFC(J) = Cumulative cost of train J

Status variables for each switch K: Kth switch

FSWTCH(K) = Distance in feet of centroid of switch K from discharge area.

RAILHL - Handling Muck by Train

The subroutine first adds DT to the labor time for rails. It also computes plant and equipment costs and down time for the rail system. Then it sets into local varia is the (see Table IV-2 for status codes):

Status of each train	(ITSTAT(J, 1))
Position of each train	(TSTAT(J, 2))
Speed of each train	(TSTAT(J, 3))
Maintenance factor	(TSTAT(J, 4))
Reasons train stopped	(KSTOP(J))
Cumulative cost for train	(TFC(J))
Operating time of train	(TOP(J))

It then divides DT into smaller time cycles, and if the system is operating puts each train through the smaller time cycles until DT is reached, changing the train's status as indicated by its status at the beginning of the cycle and what is happening to other trains. For example, if train 1 is waiting to move toward the discharge area, and train 2 is moving back from unloading to loading area, train 2's progress will be calculated and monitored by train 1. When train 2 is back to the loading area then train 1 will be allowed to start for the discharge area.

If the system must be brought up or shut down, this is done first and then each train is put through the small time cycles. After all small time cycles are finished, the global status variables JSTAT (J, 1, etc.) are reset to the updated values of the local variables and the subroutine is exited.

CUBIC

This routine is a function which finds the first real root of a cubic equation.

RAILDS - Unloading Muck at Discharge Area

This subroutine accounts for unloading much from trains. If unloading has been stopped (KUNIO = 1), the routine does nothing; otherwise, it determines whether any train is unloading. If train J is unloading (ITSTAT(J, 1) = 10), the time remaining before it completes unloading is computed. If it will be finished before the end of the current time cycle, train J is added back into the system (if system is 2 track) or (if system is 1 track) subroutine ALOTKN is called and adds the train back into the system if it is possible. If the train has been added, the count of trains in the discharge area is reduced by 1. After all trains have been dealt with, the number of trains left in the loading area at the next cycle is compared to the allowed number. If the number is greater than allowed, the run is stopped. If it is equal to the number allowed, the discharge area is indicated filled for the next cycle by setting LIFILLD = 1. If it is less than number allowed, the discharge area is indicated ready for a train by setting LTFILLD = 0.

RAILEX - Extend Track

This routine handles extension of the track for the trains. If rail extension is stopped (NEXON = 1), the routine does nothing. Otherwise, NSWTCH is checked to determine whether the switch is already being moved. If not, the track extension needed is computed using either cyclic operations geometry (NGEO = 1) or continuous operations geometry (NGEO = 1) which has been input by the user. If the computed advance of the track is not enough to allow the excavator to continue operating, then the excavator is turned off for the next cycle by setting LNBYBY = 1. Then there is a check to determine if a new switch needs to be added and/or the last switch needs to be pushed forward. If either of these need to be done, computations described below are done.

If at normal entry a switch was being moved or added, then time to move the switch and/or add a switch is decreased (computed if just beginning move or add) and the completion is scheduled when finished. In

pushing the last switch torward, it is not marked as pushed forward until after the time to push it is finished. It is pushed either a distance equal to the excavator's progress in the cycle (DX) or by a distance preset by the user (AMAXL - AMINL). The latter distance will be used unless AMAXL = AMIND. If a switch is to be added, again it is not indicated as having been added until the time to add it is over. Then, the number of switches is updated and the position of the new switch is put just behind the position of the moveable switch which is always closest to the face.

Finally, a check is made to determine if a train should be added to the system since the rails have been extended. Distance from the portal in miles is computed and compared against user inputs which give NTMILP trains allowed before XP miles and NTMLPP trains allowed after XP miles. If the number of trains in the system is already equal to the number allowed, no train is added. Otherwise, ADDTRN is called if the discharge area is not filled. The new train, if ADDTRN allows it, is entered into the discharge area.

RAILMT

DT is added to the time since last maintenance TSTAT(I, 4) for each train I which is not unloading or already in maintenance. If for any train I, TSTAT(I, 4) is greater than the user input time between maintenance, the train is put into maintenance (if maintenance area is not full).

If a train I is already in maintenance, then its time in maintenance is decreased by DT. If this time has reached 0, the train is returned to the discharge area from the maintenance area and cost of maintenance is computed.

Finally, the number of trains in maintenance, NTMA, is compared to the user input maximum allowed trains. If too many trains are in maintenance an error message is printed and the run is stopped.

2. Type: Conveyor Belt

A set of four routines: TRNPRT, EXTNSN, SURGE, and BELT, simulates hauling muck to the discharge area by the conveyor. Each routine need be initialized only once at the start of the run. Initialization is done by setting ICYCLE to 1 before calling each routine. SURGE need never be initialized.

Common blocks:

COMMON/ALL/

COMMON/MONEY/

COMMON/PERFRM/

COMMON/NEWCOM/

COMMON/OLDCOM/

COMMON/CONVEY/

Input variables:

NAMELIST/BELTS/VBI, WP, AB, ACM, NGEO, SM, DTBS,

QC, FL, XE, NSURGE, DWM, DTC, DTMB, EE, HP, FLM,

SMIN, XLF, WBI, DMAINT

Status variables:

LMCAPC

LNSURG

LMACON

LNSPLC

LNBYBY

FQL

FSM

TRNPRT

Subroutine simulates the long haul of muck by conveyor belt to the discharge area. In a normal entry, loader capacity required for this time step is calculated. If this capacity WR is less than the available capacity WPCOMP, then muck is loaded and excess muck in the surge bin is taken out and loaded onto a belt. If WR is equal to WPCOMP, then muck is loaded. If capacity WR > WPCOMP, then it is determined if a surge bin has been provided. If not, the excavator is scheduled to be stopped on the next cycle (LMCAPC = 1). If a surge bin exists, the excess is loaded into it; then the surge bin is checked for overload. If it is overloaded, an excavation stop is scheduled on the next cycle (LMCAPC = 1).

In any case horsepower used is determined and job material cost DJMMH is incremented. Then the control program is executed.

EXTNSN - Extension of Conveyor Belt and/or Structure

This routine simulates extension of the conveyor belt (either extension of the structure and/or extension by a belt splice). In a normal entry, first a check is made to determine whether the extension is shut down (NEXON = 1). If it is, then a return to the control program is executed. If the extension is not shut down, a check determines if a structural extension is needed. If yes, the extension is carried out for whichever of the three geometries (NGEO = 1, 2, 3) (cyclic or one of two continuous) is being used; if it will be completed at the end of the time step, the end is scheduled by setting LNBYBY = 0; Julierwise LNBYBY is set to 1. Another check is made to determine if a belt splice is also needed, and LNSPLC set to 1 if it is needed. Then the belt splice as described below is computed for the time remaining in time step.

If at normal entry a conveyor belt splice is going on, a check is made to determine if a surge bin has been provided. If a bin does not exist, the belt splice is simulated and the excavator is turned off if the splice is not complete at end of the time step (LMSPLC = 1). If a bin does exist, the excavator is turned off only if the surge bin becomes overloaded (LNSURG = 1).

BELT - Maintenance

This subroutine simulates maintenance of the conveyor belt. In a normal entry a check is made to determine whether maintenance is in progress (MACON = 1). If no maintenance is in progress then a check is made for which criterion is being used for maintenance, time (DTCB) or volume of muck loaded (DWM). For whichever criterion is being used a calculation is made to determine if maintenance is required. If maintenance is needed then it is scheduled for the next time cycle by setting LMACON = 1 and the subroutine does calculations for maintenance. If at

entry maintenance was in progress, or if the belt has been put into maintenance, one time step is subtracted from maintenance time left and a check made to determine if maintenance is complete. If so, it is scheduled to end in the next cycle (LMACON = 0) and the cost of maintenance is added to the job materials costs DJMMH.

SURGE

This subroutine handled adding muck to and subtracting muck from the surge bin. It is called by the other conveyor belt routines if a surge bin exists (NSURGE = 1). It has one entry point SURGE for adding to the bin and one for subtracting, SURGE 2. When adding muck, a flag will be set to indicate overloading of the bin if this occurs (LNSURG = 1).

Type: Trucks

This set of routines simulates long haul of muck to the discharge area by trucks. The routines in the set are TRUKHL, RAILEX, TRUKDS, TRUKMT. TRUKHL is almost identical to RAILHL described in Sec. II-D-1 (see Vol. I of this report for exceptions). The routines TRUKEX, TRUKDS, and TRUKMT are actually the routines RAILEX and RAILDS described in Sec. II-D-1 with different entry points. Subroutine TRUKHL is identical to RAILHL with the exception of some coding to ensure that the truck stops before it hits the face. This coding is identified in the listing by comment cards. TRUKHL is the initialization entry point and TAUKTR is the normal entry point into the routine.

Common blocks: Identical to those for rails

Input parameters: NAMELIST/TRUCKS/parameters are identical to those

for rails

Status variables: Identical to rails

E. ELEMENT: GROUND SUPPORT

1. Type: Rock Bolts, Shotcrete, Steel Sets, and Combinations of These
Unlike other elements which have a different set of routines for
each type, all ground-support types are handled in one set of subroutines
(GRNSUP, GSMAIN). Ground support frequently uses combinations of support

types, making it more efficient to put all types in one set of subroutines. The decisions about type of ground support to be used for each geology during the simulation are made with the aid of a primary ground-support table (stored in array PSST). This table may be input by the user, or the default table (Table IV-1) will be used. Any primary ground-support table gives the major and minor support types and their spacing (or thickness) for different rock fragmentation methods (JMETH), and for ranges of rock densities (RDQ). For instructions on inputting the default table, see below.

Common blocks:

COMMON/ALL

COMMON/PERFR 11/

COMMON/MONEY/

COMMON/OLDCOM/

COMMON/NEWCOM/

COMMON/GRND/

Status variables:

LMGS(5)

LIEXCA

Input variables:

NAMELIST/GROUND/USC, UCSC, RATERB, RATESC, GSETDO

RATESS, MAXPSS, ERBDRI, GDOW, ESCPLA, DJMGS,

GMEN, GCST

A set of cards must be input for the ground support if MAXPSS # 0 in the set of cards described above. In this case the user is indicating that he wishes to input his own primary ground-support table in preference to the default table (Table IV-1). See INPUT routine written for the Layout Tunnel for an example of one method of reading in these cards. A sample set of cards is shown in Fig. IV-3. The value of MAXPSS in the set of cards above should be equal to the number of these cards. The columns on the cards correspond to the columns in Table IV-1. These data cards are the last set of input cards for the model, and cards should be ordered such that the RQD column is decreasing on successive cards. The cards give the type of support that will be used for various ranges of

TABLE IV-1
PRIMARY GROUND SUPPORT
(Default Values Are Shown)

SUPPORT	1.00	1.00	1.00	1.00	1.00	1.00	1.00	1.00	1.00	2.00	2.00	1.09	1.00	1.00	1.00	
CROWN AND/ OR STORS	0.00	0.00	00.0	00.0	. 00°0	00.0	0.00	0.0	0.00	1.00	00.00	0.00	00.00	00.0	0.00	
THICKNESS	0.00	0.00	5.00	1.00	1.00	0.00	3.00	0.00	0.00	5.00	0.00	00.0	00.0	0.00	00.00	IN TABLE
SPACING	00.0	00.0	00.0	00.0	00.0	2.00	0.00	3.00	4.00	00.0	3.00	3.00	2.00	2.00	2.00	THAN THOSE
SUPPORT	1.00	1.00	3.00	3.00	3.00	2.00	3.00	4.00	4.00	3.00	00.4	4.00	4.00	4.00	4.00	OTHER
INTERFERENCE LENGTH FT	00.0	00.0	00.0	0.00	00**	00.0	00.0	4.00	00.0	00.0	4.00	00.0	00.0	4.00	00.0	ICATES ANY PROCESS
UNSUPPORTED	06.666666	06.666666	10.00	8.00	8.00	5.00	6.00	6.00	4.00	2.00	5.00	3.00	2.00	2.00	2.00	PROCESS =5 INDIC
EXCAVATION PROCESS	5.00	5.00	2.00	5.00	1.00	2.00	2.00	1.00	2.00	2.00	1.00	2.00	5.00	1.00	2.00	EXCAVATION PA
RODE	95.00	99.00	90.00	75.00	75.00	75.00	50.00	50.00	50.00	25.00	25.00	25.00	00.0	00.0	00.0	MOTE. E

rock RQD and type of rock fragmentation. Each card input gives a major and additional support type to be used for one rock excavation process, and any rock RQD greater than or equal to the one on the card but less than the one on the previous card.

The codes for the rock excavation type to be put on the card are as follows:

Rock Excavation Type	Code
Boring machine	1
Drill and blast	2
Water jet	3
Projectile	4
To be used if actual	
type is not in table	5

The codes for support types and additional support types are as follows:

Support Type	Code
None	1
Rock bolts	2
Shotcrete	3
Steel sets	4
Lagging	5

The other parameters on each card are as follows:

- 1. Unsupported Length Maximum Feet This is the maximum number of feet from the heading that ground support can be before the excavator must be turned off to allow ground support to catch up.
- Interference Length Feet
 Number of feet that must separate ground support and the heading. Ground support will not be allowed closer to the face.

1911 19 terestate the terestate .00 1.00 1.00 1.00 0.00 0.00 0.00 0.00 0.00 1.00 1.60 1.00 0.00 2.00 1.60 1.00 S. 00 5, 60 6.00 3.00 1.00 3.00 0.00 02.0 5.00 0.00 0.00 3.00 1.00 0.00 1.60 00.0 0.00 0.00 00.0 3.00 3,68 4.00 3.00 0.00 3,00 0.00 6.00 0.00 3.00 0.00 3,00 0.00 4.00 0.00 0.00 3.00 3.00 6.66 3.00 5. 0059599, 00 76.06 1.60 20.00 15.00 4.00 2.00 . 20.00 2.00 0.00 5.00 20.00 3,00 5,00 20,00 5.00 4.00 00.0 5.00 70.00 2.00 20.00 4.60 0.00 1.00 20.00 5.00 10.00 00.3 90.00 96.00 10.00 4.00 80.00 10.00 26.60 7.00 6.06 1.00 2.00 50.00 E. P.C 50,00 5,0 50.00 33.88 10.00

Figure IV-3. Example, Ground-Support Input Cards

- 3. Spacing Feet
 This will be \$\neq 0\$ only if rock bolts or steel sets are being used as support or additional support. It gives the spacing between rock bolts or steel sets.
- 4. Thickness Inches
 This is the thickness of the shotcrete to be installed and is #0 only if shotcrete is being used.
- 5. Crown and/or Sides

 This is #0 if shotcrete not being used or if only crown is to be covered. If crown and sides are to be covered it is =1.

GRNSUP - Ground-Support Installation

In a normal entry (ENTRY GROUN), ground support, using the rock density (RQD) and the rock fragmentation method, computes the ground-support parameters for this time step from the primary ground-support table (PSST). Checks are made to determine the ground-support status and position with respect to the face of the tunnel. Labor time used is incremented. For each type of support being used the amount of material needed is computed. The cost and advance of ground support is calculated (either actual or lost due to idleness or maintenance). Finally, operating time and plant and equipment costs are incremented.

GSMAIN - Ground-Support Maintenance

A normal entry to this routine (ENTRY GSMNT) first determines if a combination of types is being used. If yes, then the time step is divided by 2. Then for each of the five ground-support types it asks if the type is being used. It then asks if the type (in use or not) is in maintenance.

If the type is in maintenance, the maintenance time remaining for the type is reduced by one time step and if no time remains it is marked to be removed from maintenance in the next time step.

If the type is not in maintenance and not in use the next type is looked at. If it is not in maintenance and in use, then one time step is subtracted from the time remaining before maintenance. If the time remaining is ≤ 0 , the ground-support type is marked to be put into maintenance for the next time step.

F. ELEMENT: ENVIRONMENTAL CONTROL

Type: Ventilation, Cooling Plant, and Water Removal

One subroutine (ENVIR) simulates the environmental control. The environmental element is assumed to need no maintenance and to always be operating. It is assumed also to not interfere with other elements in the tunneling process and therefore has no status variables.

Common blocks:

COMMON/ALL/

COMMON/PERFRM/

COMMON/MONEY/

COMMON/ENVC/

Input variables:

NAMELIST/ENVIRC/EVENTP, MAXMEN, TDTHP, QM, QD,

VAMIN, VAMAX, TA, TD, WA, FKD, FKT, CPA, CKA,

REFRAT, PR, AMC(10), CAVMP

ENVIR

In a normal entry (ENTRY ENVIRC) labor time used, plant and equipment costs, and operating time are incremented. Next the cost of pumping water is computed. Then the amount of heat added to the air from various sources is computed; then the velocity of air is checked if more cooling is needed. Finally, the amount of cooling and ventilation needed in this time step are calculated. Cost of cooling and ventilation are added to job materials costs for environmental control DJMEC.

G. INPUT ROUTINE

This subroutine was written for the Layout Tunnel (see Vol. I). It is described here as a sample of possible way of initializing data in the model. It can easily be modified and used with any control program written to model other excavation systems. The routine is called at the beginning of a run and will read in the input cards for the subroutines and initialize the geology parameters by reading in the first geology record. It has two entry points, INPUT AND INPUT 2.

Common blocks: All common blocks that the control program contains.

ENTRY INPUT Reads in cards and starts geology file.

First cards are read and their images written onto tape (LOGICAL unit 5 in present control program; see listing of INPUT in Appendix II), card images being printed out. When an end-of-file is encountered, tape 5 is rewound.

After the rock fragmentation and materials handling methods have been read in from the first card image, tape 5 is read by the various NAMELISTs. Note that the card sequence of NAMELISTs must be the same as the reading sequence because the READ statement will search through the NAMELIST images on tapes for the first one to be read and then search subsequent ones for the next, and so on. Therefore if NAMELIST BORE appears on the cards before GENERL, BORE will never be read because in INPUT, BORE is read after GENERL.

After all MAMELISTs which were found on tape 5 have been read and printed out, the first record on the geology file is read. This is not necessarily the starting point in the tunnel for the model but merely starts the geology file. (This file is described in Appendices II and III.) Then the cross section of the tunnel is computed and the local variables used to read in train status, position, speed, and maintenance times are set into a global array TSTAT(J, K) (equivalent to ITSTAT (J, K)). From train status it is also determined which, if any train is available for loading. Finally, if a primary ground-support table is to

be read in (MAXPSS \neq 0), it is read from cards in fixed format (see listing of INPUT in Appendix VI).

ENTRY INPUT 2

This routine is entered at this entry point after all subroutines included in the run have been initialized. Variables which can be initialized (those on NAMELISTs) are again printed. Those that were undefined by the user will have been given default values by the individual routines. See Appendix VI for a sample printout of the routine.

H. OUTPUT ROUTINES

These four routines, OUTPUT, REPORR, REPORC, and MAXADV, were written for the Layout Tunnel. Two of the routines produce the interim reports using variables which are computed in the element subroutines. A third prints out the working storage common variables necessary for restarting the model at an intermediate point in the tunnel. Finally, a fourth routine computes the advance each day and retains the maximum daily advance. These routines may be easily modified and used with another control program to produce output. The last three routines, REPORR, REPORC, and MAXADV, may be used without modification if the notes in Sec. III of this appendix are followed.

Common blocks: (for OUTPUT) All common blocks in control program

(for REPORR, REPORC, MAXADV) COMMON/ALL/

COMMON/MONEY

COMMON/PERFRM/

COMMON/LABOR/

COMMON/TEST/

Input variables: Contained in NAMELIST/GENERAL

REPORT, DTPRNT

OUTPUT

This routine must be modified by the user if he is simulating tunneling with different methods than those in the sample program.

It is essentially a printout of selected variables in various common blocks which give the user a picture of the status of the tanneling elements at intervals during a simulation and at the end of a run. It should contain the variables needed to restart the model.

At present it prints, besides general variables, status variables for the boring machine, integrated conveyor loader, rails, and ground support. These are the processes being used in the sample tunnel, and the variables needed to restart the tunneling at any time or heading.

MAXADV

The advance per operating hour is computed for the past 24 hours elapsed time. If it is greater than the maximum advance already saved, then it becomes the maximum advance and is retained as such.


REPORR

This routine prints out the interim performance reports giving cumulative time, advance, (since beginning of this run) and heading position, maximum daily advance values, (since beginning of run) and utilization and availability figures for each general process.


REPORC

Routine prints out cumulative costs since beginning of run. Total costs and costs for each general process are printed out.


Subroutine BORE




Subroutine CUTTER




Subroutine REPAIR




Subroutine JETIMP




Subroutine JETMNT







Subroutine PROJTL




Subroutine PRJBR




Subroutine MOVEIN




Subroutine MOVOUT



Total State







Total said

IV-50


Subroutine CVLOAD




Subroutine CVMNT




Subroutine MUKLOD



Subroutine MUKIN





Subroutine MUKOUT




Subroutine RAILHL MORMAL ENTRY INITIALIZATION ENTRY HINTRY ENTRY RAILTS RAILHL SET DEFAULT OCOMOTIVE DIESEL YES INITIALIZATION VALUES FOR DONE CP AND FC LOCO=2 YES NO SET DEFAULT COMPUTE NO. OF ITERATIONS TO BE VALUES FOR POWER COST CP & FUEL MADE IN TIME CONSUMPTION FC STEP COMPUTE DOWN COMPUTE VELOCITIES TIME, UPTIME, PERFORMANCE READ IN VE. UMHTIME, DMHTIME **FACTORS** VF>0 NO COMPUTE INCREMENT LABOR VELOCITIES AND TIME USED PERFORMANCE HTIME(1) FACTORS FOR TRAIN COMPUTE LOCAL COMPUTE PLANT **VARIABLES** & EQUIPMENT USED IN COSTS ROUTINE RETRIEVE COMPUTE CAPACITY OF VARIABLES FROM LAST TRAINS QUC, WUC TIME CYCLE INITIALIZATION ONLYTRETSW

IV-56







RAILTE 3A ISTATE(I,1) = 0 TRAIN IS STOPPED, ENTRY. AS FACE, LOADING.





(RAILTR 3B ISTATE(1,1) = 0 TRAIN IS STOPPED, EMPTY.

JSTOP(1) = 6 WAITING TO ENTER LOAD ANLA.











RAILTR 6


 $\begin{array}{ll}
ISTATE(I,1) &= 1 \\
JSTOP(I) &= 5
\end{array}$

TRAIN IS STOPPED, FULL. WAITING IN DISCHARGE AREA.




RAILTR 7 ISTATE(1,1) = 2 -- TRAIN IS EMPTY AND ACCELERATING







RAILTR 9 ISTATE(1,1) = 4 -- TRAIN IS COING FULL SPEED, EMPTY





(RAILTR 10) ISTATE(1,1) = 5 -- TRAIN IS GOING FULL SPEED, FULL







. .






RAILTR 15 END OF LOOP







Subroutine RAILDS




Subroutine RAILEX



Subroutine RAILMT




Subroutine TRNPRT




portion on 1

IV-74


Subroutine EXTNSN




IV-75




Name of Street




Subroutine GRNSUP




Subroutine GSMAIN





Subroutine ENVIR




Subroutine INPUT









Subroutine REPORR





Subroutine MAXADV



III. NOTES ON INCORPORATING SUBROUTINES INTO A CONTROL PROGRAM

In writing a control program to incorporate any routines described in Sec. II which are not now in the sample control program, several things must be kept in mind.

- A. Status variables which exist in a new and old form must be placed in NEWCOM and OLDCOM.
- B. Common blocks which are needed but not at present in the routines' decks must be put into the decks. Also any common block in any routine must be put into the control program.
- C. The NAMELIST which is to read in the input variables for the routines must be put into INPUT if the INPUT routine is going to be used to initialize. Both the definition of the NAMELIST and the calls to read it, write it on tape, and print it must be in INPUT.
- D. OUTPUT must be changed to print the common variables associated with the processes being simulated.
- E. Job material costs computations are already in the routine sets. However, computations for labor costs, plant and equipment costs, and utilization values are not in the suproutines. Procedure to add these three is as follows:
 - 1. Labor costs add the following to the NAMELIST which is associated with routine set:
 - a. Number of men needed in each of 1 to 10 labor categories
 - b. Hourly cost of one man in each category

 The variables representing these parameters are
 dependent on the element the set simulates:

Rock Fragmentation

a. BOMEN(10) b. BOCST(10)

Materials Handling (Short Haul)

a. RAMEN(10) b. RACST(10)

Ground Support

a. GMEN(10) b. GCST(10)

Environmental Control

a. VCMEN(10) b. VCCST(10)

Next, in one routine of the set accumulate labor time used for each time cycle by one of the following statements depending again upon the element being simulated by the routine set.

- a. Rock disintegration
 RDTIME = RDTIME + DT
- b. Materials handling (short haul)
 HTIME(2) = HTIME(2) + DT
- c. Materials handling (long haul)
 HTIME(1) = HTIME(1) + DT
- d. Ground support
 GSTIME = GSTIME + DT
- e. Environmental control

 ECTIME = ECTIME + DT

These may be bypassed by checking status variables as desired, so labor costs are not always incremented. The computation of cumulative labor costs is then done in the report routines.

Plant and equipment costs - first add to the routine set's NAMELIST and common block, variables for costs for plant various types of plant and equipment. Each cost should be either hourly cost or cost per foot. Next add a statement to one routine in the set which computes the cost for either a time step (DT) or for a foot advance (DX) and cumulates the cost in one of the following variables depending on the element being simulated:

- a. Rock disintegration RDPLAN
- b. Materials handling (long or short haul) HPLANT
- c. Ground support
 GSPLAN
- d. Environmental control ECPLAN

Again, as with labor costs, the computing of cost in any time step can be bypassed by a check of status variables.

Utilization times:

To determine utilization values, it is necessary to compute operating time and down time. Then knowing shift time, the utilization of each element can be computed in the report subroutines according to the formulas:

Availability = Shift time - down time
Shift Time

Utilization = Operating time
Shift time

Operating time and down time must be cumulated in each time cycle. Status variables should be used to determine which, if either, should be added to in each time cycle. The cumulating is done in routines of the set for each process being simulated. The variables used for cumulating the time are:

Operating Tir	ne	Down Time
Rock Fragmentation	RDUTIM	RDDTIM
Materials Handling (long & short haul)	UMHTIM	DMHT IM
Ground Support	GSUTIM	GSDTIM
Environmental Control	ECUTIM	ECDTIM

NOTE: Since there are two sets of routines for materials handling, care must be taken in computing the operating time for materials handling as a whole to avoid double counting.

IV. GENERAL REQUIREMENTS FOR THE CONTROL PROGRAM LOGIC

Figure IV-4 represents the logic for a control program to coordinate the tunneling processes simulated by the subroutines. That figure and this discussion are given to assist a user in writing a control program and not necessarily to be rigidly adhered to.

The first step in the operation of the control program is to read the input parameters into common areas and read the first geology parameters. The control program then calls each subroutine which has an initialization entry (see the flow charts) for initialization of parameters not read in, and initializes the old working parameter common (OLDCOM) area so it portrays the proper initial state for start of processing.

For each time step in the simulation, a check is first made as to whether the tunnel has progressed to the point where new geology information is needed. If this is the case, new geology information is read into common overlaying the old information.

Each subroutine is called for its normal entry point. Note that subroutines for one element (e.g., rock disintegration) may be order-dependent and should be ordered as they are listed in Fig. IV-4. The order in which the elements are called does not matter.

After all routines have been called, the resulting information in the new working parameter common area is then copied into the old working parameter common area. Also, heading position and time are updated. The control program then interrogates the flags in the old-working-parameter common area and determines the status of the rock disintegration process in the next cycle. This is done in the control program for flexibility.

^{*} Previously called status variables.




Figure IV-4. Overall Logic of a Control Program for the Tunneling Model

THE RESERVE TO SERVE THE PARTY OF THE PARTY

The rock disintegration process is the lead process; it determines the heading advance and the muck created. Other elements follow it automatically, given its progress. The rock fragmentation process, however, must be informed through flags set by the other elements what state it should be in (with the exception of its own maintenance). Looking at these flags in the control program gives the user more flexibility in determining how the excavator reacts to other elements.

The control program also handles the queuing of the long-haul materials-handling element if it requires queuing. The queuing is handled here to retain the order independence of the elements.

The control program's next step is to determine whether output reports are desired at this point and to call routines to produce them. Note that these reports can be spaced in any desired manner with respect to time, length along the tunnel, or whatever. There is no restriction as to how reports are generated.

After output report checking is performed, a check is made to determine if the model should be ended; this would usually be equivalent to asking if the time or distance limits input have been exceeded. If this is the case, the simulation is ended with a printout of working common variables needed to restart the model at the heading position reached. If the simulation is not to be ended, another time step is started by checking to determine if new geology parameters are needed.

The tunneling activities which are being coordinated by the control program are, as previously stated, embodied in subroutines; one or more

of these routines made up a process such as boring machine rock fragmentation. In any simulation one and only one process for each of the following tunneling elements should be included:

- 1. Rock fragmentation
- 2. Materials handling (long haul)
- 3. Materials handling (short haul)
- 4. Ground support
- 5. Environmental control

Descriptions of the sets of routines representing the processes available for each element are given in Sec. II.

The user should use the preceding discussion of the control program as a guide in writing his own program. The control program written for the Layout Tunnel which actually consists of several subroutines and a control program is described in the next section and should be studied for further information on writing a control program.

V. CREATING A CONTROL PROGRAM FOR THE LAYOUT TUNNEL

As mentioned in Sec. I, the various tunneling activities are simulated by modular subroutines. The simulation of an entire excavation project can therefore be made by using a building-block technique. Ideally, the program that analyzes a given project would consist of all the subroutines that are pertinent to the simulation and a driver (main) program that ties them together. The subroutines are ideally independent of each other in function and in logic, so that they are not order-dependent in their usage by the main program. This section is concerned with the construction of a control program and secondary input and output routines to initialize data and report results, and discussion will be restricted to a sample control program that simulates the excavation of the Strawberry Aqueduct Layout Tunnel.

A. SUBROUTINES

The tunneling subroutines needed for the Layout Tunnel simulation are as follows:

Element and General Process	Activity	Subroutine Entry Initialization/Normal
Rock fragmentation, boring machine	Bore Cutter change Maintenance	BORE/BORER CUTTER/CUTCHG REPAIR/MAINT
Materials handling, conventional rail system	Train logistics Track laying Discharge Train maintenance Loading Loader maintenance	RAILHL/RAILTR RAILEX/RAILXT RAILDS/RAILDS RAILMT/RAILMT CVLOAD/LOADCV CVMNT/CVRPR
Ground support	Rock bolts, etc. Equipment maintenance	GRNSUP/GROUN GSMAIN/GSMNT
Environmental control	Ventilation and cooling	ENVIR/ENVIRC

B. SUBROUTINE USAGE

After proper initialization of data (see Sec. V-D below), each excavation subroutine is called once for each time station T. The time stations are equally spaced at DT, which is input. Each subroutine calculates the progress made in the time DT and sets a flag indicating the status of the progress. For example, CUTTER calculates the incremental cutter wear for the time DT and the cumulative cutter wear up to time T. If one or more cutters have exceeded the maximum-wear criterion (an input), a flag LNCUTR is set to 1. Otherwise, LNCUTR is set to 0. The boring machine is then turned on or off depending on whether LNCUTR is zero or nonzero. As another example, CVLOAD simulates the muck loading activity. The volume of muck created in DT depends on the hardness of the rock and the boring machine operating characteristics. At the end of DT, the muck is assumed loaded onto the trains via the loader. If the train is full, it is sent on its way to the discharge area, and another train (if one is available in the load queue) is moved into the loading area. A flag LOADR is set to 0 in this case. If, however, there is no train available for loading, LOADR is set to 1 which indicates that the boring machine should be turned off until a train becomes available for loading. A control program that simulates the excavation process as a whole must interrogate all the flags (see Table IV-2) set by all the subroutines and then decide on what status the boring machine should have.

C. CONTROL LOGIC

The essential features of the control logic for the sample control program are shown schematically in Fig. IV-5. Note that the rock fragmentation activity BORE/BORER is controlled by the flag MBORE. In general, the boring machine is turned off any time any of the support activities cannot keep up with the rate of advance of the boring machine or if any

TABLE IV-2
DEFINITION OF FLAGS SET IN EXCAVATION MODEL

SUBROUTINE	FLAG		OPTIONS
BORE	MBORE	MBORE = 0	normal operation - boring machine going full speed
		= 1	boring machine in maintenance
		= 2	boring machine cutters being changed
		= 3	mil extension rate exceeded
		= 4	new switch being added
		= 5	switch being moved up
		= 6	no train available for loading
		= 7	ground support construction rate exceeded
		= 8	loader in maintenance
CUTTER	LNCUTR	= 0	normal operationno cutter change needed
	= 1	cutter change started	
		= 2	cutter change still in progress
REPAIR	МВМ	= 0	normal operationno maintenance needed on
			boring machine
		= 1.	boring machine due for maintenance
ASSMBL	MASSEM	= 0	normal operationboring machine assembly
			completed
		= 1	boring machine assembly in progress
DISASM	MDISAS	= 0	normal operationboring machine disassembly
			completed
		= 1	boring machine disassembly in progress
			IV-96

TABLE IV-2 (cont.)
DEFINITION OF FLAGS SET IN EXCAVATION MODEL

SUBROUTINE	FLAG		OPTIONS
RAILTR	LSTOP	= 0	normal operationcontinue system
		= 1	shut down system external reasons
		= 2	bring up systemexternal reasons
RAILDS	IFILD	= 0	normal operation
		- 1	discharge area filled
CVLOAD	LOADR	- 0	normal operation
		- 1	no train available for loading
CVMNT	LMCV	= 0	normal operation
		- 1	loader maintenance in progress
CVMNT	LMFLAC	- 0	normal operation
		- 1	loader turned off for external reasons
GRNSUP	IEXCA	= 0	normal operation
		= 1	ground support construction rate exceeded
RATLEX	NBYBY	= 0	normal operation
		- 1	rail extension rate exceeded
RAILEX	NSWCH	- 0	normal operation
		- 1	new switch to be added
		= 2	switch to be pushed forward
CVLOAD	IEXCAV	= 0	normal operation
		= 1	boring machine turned off, loader in maintenance

TABLE IV-2 (cont.) DEFINITION OF FLAGS SET IN EXCAVATION MODEL

SUBROUTINES RAILTR, RAILDS, RAILEX

LTSTAT = 0	stopped, empty
= 1	stopped, full
= 2	accelerating, empty
= 3	accelerating, full
= 4	going full speed, empty
= 5	going full speed, full
= 6	decelerating, empty
= 7	decelerating, full
= 8	in switch, empty
= 9	in switch, full
= 10	in discharge area
= 13	in maintenance area
LKSTOP = (not stopped
= :	at face, being loaded
= 2	in switch, train ahead
= (in switch, train approaching
= -	external reasons
# .	in switch, waiting to enter discharge area
	in switch, waiting to enter load queue
= 10	in load queue, 1st in line
= 1	on load queue, 2nd in line
= 1	in load queue, (n-100)th in line
	• •
LLVHCL =	no train in load area
	train #n is in load area




Figure IV-5. Logic of the Control Program for the Layout Tunnel

and the season of the season o

of the equipment becomes unavailable because of maintenance requirements. Note also that the boring activity is not resumed unless all of the support activities have caught up with the rock fragmentation process. In other words, boring is the pivotal activity that is affected by all the other activities. The flag MBORE is therefore set according to the table shown below.

MBORE	CONDITION
0	normal operation: boring machine is going full speed
1	no advance: boring machine is in general maintenance
2	no advance: boring machine cutters are being replaced
3	shut-down boring machine: rail extension rate has been exceeded
4	shut-down boring machine: a new switch is being added
5	shut-down boring machine: switch needs to be moved up
6	shut-down boring machine: there is no train available for muck loading
7	shut-down boring machine: ground support activity has fallen behind
8	shut-down boring machine: muck loader is in maintenance

One of the tasks required of the control program is to make certain that the boring machine is not turned on unless the flags from all the subroutines indicate that boring activity should be turned on. This means a series of tests must be made of the flags from all the subroutines and that the boring machine flag MBORE must be set and reset in accordance with these flags.

Another task required of the control program is to move the trains up in the load queue when it is time to do so. The reason that this task is given to the control program is that several conditions have to be satisfied before a train can be moved up. First of all, the train that is currently being loaded must be full. This is tested in subroutine CVLOAD. Then the rail extension activity must be able to keep up with the boring activity. This is tested in subroutine RAILEX. Then the installation of a new switch must be complete if one is needed before a train can move up the load queue. This is also tested in subroutine RAILEX.

A third task required of the control program is to insure that RAILTR is called before any of the other rail subroutines which include CVLOAD and RAILEX. The reason for this requirement is that RAILTR is the subroutine that controls the dynamics of the trains. Since the speed of the trains is on the average several orders of magnitude greater than the rate of excavation, a time interval DT compatible with the excavation activity would be too great for the rail activity. Therefore, RAILTR divides the time interval DT into many subintervals such that no train would have moved more than 50 feet in any one subinterval. The position and the speed of the trains can thus be simulated more realistically. But since different trains would be doing different things at different subintervals, the only way to keep the logic tractable is to update the status of all the trains at the end of DT: i.e., the status flags of all the trains are reset at the end of DT. Now if another rail subroutine is called before RAILTR and if that subroutine resets the flag of one of the trains, that result would be nullified by RAILTR.

A last task of the control program is to produce reports by calling output routines written for the Layout Tunnel (REPORC, REPORS, and OUTPUT) at intervals specified by the user, and to call MAXADV once each day to determine the daily advance (see Sec. V-E below).

D. INITIALIZATION OF DATA

The initialization of data for the simulation is handled by the control program and a subroutine INPUT written to accompany the control program. Figure IV-6 shows the initialization sequence.

Two types of data need to be initialized:

- 1. Geology parameters which give the geology characteristics along the tunnel. These parameters are on a tape (logical unit 40; see listings in Appendix II). See Appendixes II and III for a description of the creation of this tape. The routine INPUT reads the first parameters from the tape. Then the control program tests at the start of each time interval to determine if a new set of parameters is needed. When one is needed the control program reads a new set.
- 2. Parameters for each general process and a set of parameters which apply to all processes, such as initial reading, initial time, and time step length. These parameters are read in at the start of each run by INPUT. The FORTRAN NAMELIST data reader capability is used by INPUT for reading in the cards. A special provision is made for reading in a primary ground support table (described in Sec. II-E above). This table is read in on cards in fixed format (9F8.2; see listing in Appendix II) if the user wishes to input his own table.

After INPUT has read in all parameter cards, the control program calls each general process subroutine by its initialization entry. In each routine parameters for the general process will be compared to 0; if found equal to 0, they are then given a default value. Parameters not dealt with in this way will have a default value of 0 if not read in. INPUT then prints out a list of all parameters with the value read in or the default value.




Figure IV-6. Initialization Sequence for Layout Tunnel

Finally, the control program initializes the working common area (OLDCOM) for the first time step.

E. OUTPUT

The output for the Layout Tunnel is of two kinds: (1) a printout of common variables, and (2) interim cost and performance reports. It is handled by subroutines which are called by the control program.

- 1. OUTPUT prints out common variables from the various subroutines and from OLDCOM. These parameters show the status of the different general processes at an instant in time. A sample of this printout is shown in Fig. IV-7. The routine is called by the control program at time intervals (DTPRNT) input by the user. It is also called at the end of a run to print out variables to be used for restarting the model at that point.
- 2. MAXADV The routine computes each day's advance and saves values for the maximum advance.
- 3. REPORR rints cumulative performance figures for each element (subsystem). The performance figures are computed as follows:

Subsystem availability = (shift time - down time)/shift time

Subsystem utilization = operating time/shift time

Shift time = 24 hours in Layout Tunnel. Can be input by user (TSHFT)

INCUTA 0	NAYHY= 0	- 5.400E+01	00E+01	C	RORE= 2	STR	IA= 2 STR= 1.200E+01 DX= MRORE= 0 LUADR= 0 NUMSWT=	E+01 NU	EXG MSWT=	-	0. 1 IEXCA=	N C	MAY == 0 MCV=	0	0	0 MFLAGC=
TEXCAV= 0.		MGS(2)= 0.		MGS	MGS(3)= 0 MGS(4)= 0.	MGS	• 0 = (+)				•					
CUTTER JEAR.	!		ı			,	. ·									
0.	•	•			•		•0	•		0	•0					
.0	•0	0		•	•		•	•		•	0					
٥.	•	0		•	•		•	•		•						
TRAIN VO. 1	STOPPED.	. EMPTY	AT	FACE.	LOADING		5.3100E+02	1	11 >	,	MPH	DSM =	0.000	0	c	-
TAMIN NO. 2	TAAIN VO. 2 STOPPED. EMPTY	, EMPTY	AT	FACE .	IN QUEUE		3.3100F+02	1-1	× 0 ×		T d	DSM =	0.00	0	0	101
TPAIN NO. 3	STOPPED.	, EMPTY	AT	FACE.	AT FACE. IN QUEUE		X =-5.3100E+02 FT	FT	v = 0.		A D	DSM =	DSM = 0.0000	0)	102
GROUND SUPPORT AT	ORT AT 54	54.000														
ENVIRONMENT	ENVIRONMENTAL CONTROL	=800	0000													

Figure IV-7. Printout of Working Storage

Down time and operating time are computed in subroutines for each general process and cumulated in the following variables:

Element - Subroutine	Operating Time	Down Time
Rock disintegration (BORE)	RDUTIM	RDDTIM
Materials handling (CVMNT, RAILHL)	UMHTIM	DMHTIM
Ground support (GRNSUP, GSMAIN)	GSUTIM	GSDTIM
Environmental control (ENVIR)	ECUTIM	ECDTIM

The status variables in Table IV-2 are used to determine in each time step whether the element is operating, down, or neither (idle) for the time interval (DT) in the following manner:

Element Boring machine	Down MBORE > 0	Action Taken RDDTIM = RDDTIM + DT	Operating MBORE = 0	Action Taken RDUTIM = RDUTIM + DT
Materials handling rails, conveyor loader	and MBORE < 3 NUMLD = 0 or MCV = 1	DMHTIM = DMHTIM + DT	NUMLD ≠ 0 & MCV = 0	UMHTIM = UMHTIM + DT
Ground support	<pre>MGS(I) = 1 where I is support type using</pre>	GSDTIM = GSDTIM + DT	MGS(I) = 0 and ground support can proceed (not too close to face	GSUTIM = GSUTIM + DT
Environmental control	Never		Always	ECUTIM = ECUTIM + DT

See Sec. III of this appendix for further information on handling availability and utilization values for simulation. In Fig. IV-8 a sample of this report is shown.

2.000
207.172
352,686
AVERAGE RATE FOR THAT DAY (FEET/OPERATING HOUR) 12.754
~

	SUBSYSTEM	UTILIZATION++
PERFORMANCE.	OPERATIONAL	AVAILABILITY+
CUMULATIVE SUBSYSTEM PERFORMANCE.	ELEMENT/MEASURE	

.488	.488	1.000	1.000
• 500	266.	1.000	1.000
ROCK FRAGMENTATION	WATERIALS HANDLING	GROUND SUPPORT	ENVIRONMENTAL CONTROL

+OPERATIONAL AVAILABILITY=(TOTAL SHIFT TIME-DOWN TIME)/TOTAL SHIFT TIME

++SUBSYSTEM UTILIZATION=(TOTAL SHIFT TIME-DOWN TIME-IDLE TIME)/TOTAL SHIFT TIME

Figure IV-8. Interim Performance Report

IV-107

4. REPORC - prints out cumulative cost values. The cost values are computed for each general process in one of its subroutines (see Sec. III above for a description of variables used). They are cumulated in parameters in COMMON/MONEY/. Totals and overhead costs are recalculated each time REPORD is called. See Fig. IV-9 for a sample of the cost report.

Both REPORS and REPORD (normal entry points for REPORR, REPORC) are called at time intervals specified by the user with input parameter REPORT.

DAYS	DAYS SINCE COMME	ENCED EXCAVATING	ING	Ž	5.000	
AVERA	AVERAGE COST PER	R IN SITU CUE	IN SITU CUBIC YARD EXCAVATED		19.82	
AVERA	AVERAGE COST PER	R FOOT OF TUN	TUNNEL	36	96.19	
CHAIN ATTVF COST SUMMARY TO DATE. (DOLLARS)	RY TO DATE.	(DOLLARS)				
ELEMENT/CATEGORY	DIRECT	PLANT + EQUIPMENT	JOB MATERIALS	PERMANENT MATERIALS	OVER- HEAD	FLEWENT
ROCK FRAGMENTATION	2153.76	11350.08	809.48	აც•0	1431,33	15744.65
MATERIALS HANDLING	4673.76	1899.08	153.03	0.00	672,59	7398.46
GAOUND SUPPORT	3379.20	00.0	00.0	0.00	337.92	3717.12
ENVIRONMENTAL CONTROL	1398.24	298.69	2.80	0.00	169.97	1869.70
CATEGORY TOTAL	11604.96	13547.85	965.31	00.0	2611.81	24729.93

1

Figure IV-9. Interim Cost Report

APPENDIX V

LAYOUT TUNNEL DATA

by

L. M. Pietrzak and W. R. Thomson

SUMMARY

This appendix contains data acquired from the Bureau of Reclamation and other sources concerning the first 5,038 feet of the Layout Tunnel, a part of the Strawberry Aqueduct Project. The tunnel was driven between June 25 and September 22, 1971. Geological reports, machinery specifications, and progress records are included.

ACKNOWLEDGMENTS

The information found in this appendix was kindly supplied by
Mr. Booneymixon of the S. A. Healy Co., Project Engineer for the Layout
Tunnel; A. S. D'Alessandro, Contruction Engineer in the central Utah
Projects Office for the Bureau of Reclamation; Ray Moran of Moran
Engineering Co. which fabricated the muck cars and the loading and unloading equipment; and Don Shaver of Plymouth Locomotive Works which
fabricated the train locomotives. H. F. Haller of Holmes and Narver
supplied data on rock properties and muck characteristics.

CONTENTS

SECTION		PAGE
I	EQUIPMENT AND SYSTEM DESCRIPTION	V-5
II	GEOLOGY	V-11
	A. Geology Reports	V-11
	B. Rock Properties and Muck Characteristics	V-17
III	PROGRESS REPORTS	V-21
IV	WAGE RATE SPECIFICATIONS: CENTRAL UTAH, 1970-1971	V-42

I. EQUIPMENT AND SYSTEM DESCRIPTION

The Layout Tunnel is a part of the Strawberr, Aqueduct Project and was driven in the summer of 1971 near Heber City. Utah. S. A. Healy Company is excavating Layout and Currant Tunnels with a Robbins Co., Model No. 141-127-1, excavating machine ("the male") previously used to excavate a tunnel in the Chicago, Illinois, area. The machine was rebuilt and modified by Robbins Company, 651 S. Orcas, Seattle, Washington. The first section arrived at the work site May 24, and the mole was assembled during the rest of May and June near the outlet portal of Layout Tunnel. Approximately 1,670 man-hours were used to assemble the machine, which is 45 ft long and weighs approximately 200,000 lb. The last shipment of the integrated conveyor loader was delivered to the site at the end of July 1971.

The mole cuts a 12 ft 11 in. diameter tunnel. The rotating head consists of a center tri-disc cutter with a series of 29 disc cutters. The tri-disc center cutter is a cluster of three disc mounted on one shaft. The cutters are numbered from the center out. The cutters are spaced radial as follows: cutters No. 1 through 8, 2-7/8 in.; cutters No. 9 through 21, 2-3/4 in.; cutter No. 22 is 2-11/16 in. from No. 21; cutter No. 23 is 2-1/2 in. from 22; cutters No. 24 through 27 are spaced at 2-1/8 in.; cutter No. 29 is spaced at 1-1/4 in. from No. 27 and gage cutter No. 29 is 1-1/4 in. from No. 28.

The maximum thrust on the head is 892,000 lb with a propel pressure of 3,500 psi. The thrust rating for each of the four drive arms is 223,000 lb at 3,500 psi. The contractor has operated with propel pressure between 1,800 and 2,600 psi.

The mole is powered by six 100 hp, CJ5NB Pacemaker, 440 volt electric motors. These motors create a rated torque of 630,240 ft·1b. Electricity is delivered to the mole at 7,200 volts and transformed to 440 volts through a transformer located at the rear of the mole. Electricity to operate the mole is obtained from commercial supplier, Moon

Lake Electric. The mole is held in place while excavating by two hydraulic powered side grippers, immediately behind the cutter head.


The excavated material was hauled from the tunnel to an 800 ft long dump site located 12,000 ft from the outlet portal. Three trains of ten, 6 2/3 yd³ (struck) side dump cars, pulled by two 10-ton diesel powered Plymouth Mine-o-motive, GA-24, Model DMD-24 locomotives were used. The track gauge was 24 in., and rail weight 65 lb per linear yard.

The mucking equipment included an integrated 24 in. troughed belt conveyor, and a California switch for train switching that extended 765 ft behind the boring machine. This configuration is shown schematically in Fig. V-1.

The normal sequence for loading and muck removal starts with three trains in the loading area, i.e., one in the loading position, and the others waiting in the California switch. Once loaded the first train departs for the discharge area, and an empty train moves into the loading position. Thereafter, at any given time one train would typically be loading while one is waiting to be loaded and the third is on its way to the discharge area for dumping. The cars returning from the discharge area carry men and materials to the face as needed.

Other than the California switch at the face, there are no switches between the discharge area and the near face zone. Only one train can occupy the track between the loading and discharge area at any given time. This situation applies for the first 8650 ft of tunnel which includes the entire segment being considered for computer simulation at this time.

In the discharge area, each muck car is dumped individually using side dump equipment that rung on a track parallel to the main line track, dumping each car as it proceeds.



Muck Loading Equipment Configuration Used in Layout Tunnel (Courtesy of Moran Engineering Co.) Figure V-1.




Figure V-1. Muck Loading Equipment Configuration Used in Layout Tunnel (Cont.)




Figure V-1. Muck Loading Equipment Configuration Used in Layout Tunnel (Cont.)

Dust removal and ventilation is accomplished by drawing air from the near-face loading and working area (17,000 cfm at 2405 fpm) through a 36 in. diameter fan line. The equipment includes an Elbair scrubber in the near-face zone and a 100-hp fan motor that supplements a portal fan.

Ground support includes steel ring sets, rock bolts, cribbing and lagging, and shotcrete as required. Actual support installation for the 5038 ft segment is described in the June 29 progress reports summarized in Sec. III of this appendix.

II. GEOLOGY

A. GEOLOGY REPORTS

Date	Station	Geology
6/25/71	1786+26 - 1786+20	Layout Tunnel: Rock is a firm, medium hard, brown sandstone. Dip = 2-3° downstream. Rock is tight and impermeable.
6/28/71	1786+20 - 1785+93	Browr sandstone (medium hard) is periodically cut by lenses of soft, gray, porous sandstone.
6/29/71	1785+93 - 1785+61	Three vertical joints (cracks) at springline at Station 1785+00, LW (left wall) 1 to 2 ft long.
6/30/71	1785+61 - 1785+26	Periodic short vertical joints continue upstream.
7/1/71	1785+26 - 1784+55	Normal entry of formations into tunnel bore is at invert and rising upstream into roof. However, conglomerate enters from roof and trends upstream erratically.
7/2/71	1784+55 - 1783+93	At Station 1784+40 a very hard, well-cemented conglomerate starts in roof. It contains a 3 in. maximum quartzite rock.
		Conglomerate is lightly fractured and is dripping water.
7/3/71	1783+93 - 1783+41	Vertical joints at Stations 1783+25, 1783+50, 1783+45, all dripping water.
		No support steel thus far.
7/6/71	1783+41 - 1782+91	

Date	Station	Geology
7/7/71	1782+91 - 1/8i+33	Hard conglomerate is now a 4 ft bed at springline with the previously mentioned brown sandstone (medium hard) above and below.
7/8/71	1781+33 - 1780+04	Brown sandstone is interbedded with thin (1-2 in.) brown shales that push out when wet and dried. Mole gripper pads leave small chips and fractures
		near springline.
7/9/71	1780+04 - 1778+43	Beds dipping downstream 2-3°. Conglomerate (very hard) is now in middle of tunnel near springline.
7/10/71	1778+43 - 1777+89	Brown, silty sandstone (medium hard) is above and below conglomerate and has thin brown shales.
7/12/71	1777+89 - 1777+19	Formations dip 2-3° down-stream.
7/13/71	1777+19 - 1776+23	Hard conglomerate is grading upstream into a gray, medium hard sandstone.
		Gray sandstone contains lenses and thin beds of pebble conglomerates.
7/14/71	1776+23 - 1775+17	Medium hard, brown sand- stone becoming fractured with short, closely-spaced joints.
7/15/71	1775+17 - 1774+32	
7/16/71	1774+32 - 1774+01	Loose, channel-fill zone, Stations 1771+30 to 1775+00, a very loose, soft section containing poorly-cemented sandstones with gravel streaks.

Date	Station	<u>Geology</u>
7/17/71	1774+01 - 1773+87	Above mentioned zone is wet and contains many joints and fractures due to close proximity to fault west of tunnel.
7/19/71	1773+87 - 1773+73	
7/20/71	1773+73 - 1773+59	
7/21/71	1773+59 - 1773+13	
7/22/71	1773+59 - 1772+82	Same conditions as above
7/26/71	1772+82 - 1772+39	Many seeps.
7/27/71	1772+39 - 1771+86	
8/3/71	1771+86 - 1770+56	Joint, filled with white calcite RW: 1770+90, LW: 1770+80.
		Rock is half hard sandstone and half soft poorly-cemented tan sandstone.
8/4/71	1770+56 - 1769+38	Soft tan sandstone has drips and many fractures.
8/5/71	1769+38 - 1768+56	Whole tunnel is soft, tan sandstone.
		Rock is firm, medium-hard sandstone at Station 1769+00.
8/6/71	1768+56 - 1767+50	
8/7/71	1767+50 - 1767+50	
8/9/71	1767+50 - 1765+95	Top half of tunnel is medium- hard brown sandstone; bottom half is soft, wet tan sand- stone, containing thin shale.
		Light fallout along thin shales near springline.

Date	Station	Geology
8/10/71	1765+95 - 1765+70	Fault Zone - Station 1763+42 to 1766+10
8/11/71	1765+70 - 1765+34	Fault is considered to be a side fracture off larger fault located west of tunnel and bearing nearly parallel.
8/12/71	1765+34 - 1764+87	Fault Zone: Stations 1763+42 to 1766+10
		Rock is broken mass of soft sandstone and conglomerate.
		Broken rock is mixed in with a wet mixture of sand and clay.
8/13/71	1764+87 - 1764+01	
8/14/71	1764+01 - 1764+01	4 in. circular steel H-beam supports were installed throughout fault zone because of loose, unstable condition of tunnel walls.
8/16/71	1764+01 - 1763+04	
8/17/71	1763+04 - 1762+05	Rock is medium-hard, brown sandstone containing thin shales.
8/18/71	1762+05 - 1759+96	Vertical joint at 1761+90, with many small fractures.
8/19/71	175 9+ 96 - 1758+02	At Station 1759+00 sandstone grades into hard conglomer- ate top half of tunnel. Bottom half is soft, tan sandstone containing thin shales.
8/20/71	1758+02 - 1757+43	Conglomerate and sandstone has many small fractures that are dripping water.
8/21/71	1757+43 - 1757+43	Conglomerate pinches out in roof at Station 1757+95.
		Occasional vertical joints and many small fractures.

<u>Date</u>	Station	Geology
8/23/71	1757+43 - 1756+57	Top half is medium-hard brown sandstone with thin shalesbottom half is a soft sandstone.
		Conglomerate enters in roof.
8/24/71	1756+57 - 1755+07	Tunnel bore all hard con- glomerate with lenses of soft sandstones.
8/25/71	1755+07 - 1753+35	
8/26/71	1753+35 - 1752+7 5	Rock is mostly hard conglom- erate with lenses of soft sandstone.
8/27/71	1752+75 - 1751+68	Conglomerate has few lumps of shale.
8/28/71	1751+68 - 1751+68	Conglomerate has many fractures and joints from Station 1756+50 to 1756+00.
8/30/71	1751+68 - 1750+68	
8/31/71	1750+68 - 1749+55	Top half of tunnel is medium hard, sandstone; soft, tan sandstone in bottom.
		Many small fractures and a few vertical joints.
9/1/71	1749+55 - 1748+69	
9/2/71	1748+69 - 1747+46	Tunnel rock is all a soft brown sandstone with thin shales.
		Small amount of fallout in thin shales.
9/3/71	1747+46 - 1746+20	
9/7/71	1746+20 - 1745+49	Soft, brown, poorly-cemented sandstone.

<u>Date</u>	Station	Geology
9/8/71	1745+49 - 1744+56	Many joints, and fractures with 5 gal/min water in joint at Station 1745+20 RW.
9/9/71	1744+56 - 1743+90	Fallout in soft, fractured sandstone.
9/10/71	1743+90 - 1743+30	
9/13/71	1743+30 - 1742+38	Gray and tan, soft sandstone with thin brown shales.
		Many small vertical fractures throughout.
9/14/71	1742+38 - 1741+34	Fallout along shales near springline.
9/15/71	1741+34 - 1740+65	
9/16/71	1740+65 - 1739+86	
9/17/71	1739+86 - 173 9+ 02	Tunnel rock is harder. Sandstone is better cemented.
9/20/71	1739+02 - 1738+17	Fewer joints and fractures than downstream.
9/21/71	1738+17 - 1736+77	Note: Because of nearby fault paralleling tunnel to west, tunnel throughout has many joints and fractures.
		There are short sections of tunnel supported with steel.
9/22/71	1736+77 - 1736+60	Longer supported sections include soft, channel-fill from Station 1771+30 to 1775+00, the fault zone from Station 1763+42 to 1766+10.
		The last 1700 ft of tunnel (Stations 1736+60 to 1752+60) is fractured and jointed and is 60% steel supported.

B. ROCK PROPERTIES AND MUCK CHARACTERISTICS

The following information was acquired by Holmes and Narver Inc. as part of the Muck Designation Study under Contract No. HO210013 of the ARPA program. The rock properties cited are for a rock sample taken 4,100 ft from the tunnel portal.

PROJECT & LOCATION	OWNER OR AGENCY	SIZE	LENGTH	CONTRACTOR
Currant & Layout Tunnels Strawberry Aqueduct, Heber City, Utah	U.S. Bureau of Reclamation Denver, Colorado	10'-4" Dia.	Combined Length 4.9 mi	S.A. Healy

A Robbins boring machine has been operating in sandstone. Existing logs of 13 drill holes show lithology. Compressive strength test results, varying from 5,000 psi for a shale to over 38,000 psi in the conglomerate, have been provided by the Bureau of Reclamation. This tunneling was stopped in September 1971 pending provision of additional funds but has since been resumed.

Rock Data:

Lithology: Sedimentary, sandstone, medium grained, light brown to red, massive, porous, poorly cemented.

Uniaxial Compressive Strength: 10 kpsi

RQD: (Estimated) 84%

Dry Unit Weight: 150 lb/ft3

Ground Water: Generally dry.

Hardness: NA 1/11/72

Tunnel Data:

Size: 12 ft, 11 in. diameter. Grade: (+) .125%

Ventilation System: 15-17 kcfm exhaust, 36 in. dia. pipe, 100 hp

at 4100 ft

Utility System: 3 1/2 in. water line, 6 in. air line, 8 in. pump

line.

Water Inflow: 20-100 gpm Power System: 7300/480 V

Haulage System: Muck, supplies, personnel, 10 ton locomotives,

6 2/3 CY cars, 24 in. gauge, 65 lb rail.

Support System: 4 in. H full rings, 4 ft centers: 35%; 13 in. ×

9 ft pans 3/4 in. \times 7 ft rock bolts: 10%.

Excavation Data:

Machine: Robbins 141-127, total weight: 125 tons

Cutters: 30 Robbins steel disc. Gauge: 6-11 in. Center: 1-11 in.

triple disc. Interior: 23-11 in.

Rotation: Center cutter integral with head, 6 or 3 rpm

Torque: 600 hp

Thrust: 900 K# max., 685 K.# operating. Anchor pressure: 1,000 K#

Muck Collection: Pickup by buckets fixed to head, discharging on

30 in. belt to a 24 in. × 204 ft belt on gantry.

Power System: 6-480/240 V electric motors drive head. Hydraulic

pumps power thrust and gripper cylinders.

Guidance System: Laser

Muck Data (Table V-1; Fig. V-2):

Abrasiveness: N.A. 1/11/72

Pot. Vol. Change, Material Size - 0.056 in.: 0

Spec. Gravity, Material Size -0.75 in.: 2.66

Atterbfrg Limits, Material Size (-)0.056 in.

Liquid Limit 21.20% Plastic Limit 17.06% Shrinkage Limit 15.17% Plasticity Index 3.14% Toughness Index 0.52 Flow Index 6.00

Material Size (-)2.0 in.

Angle/Repose 1 in. Drop @ 3.6% Moisture, 37° Angle Slide Steel Plate @ 3.6% Moisture, 27° Apparent Cohesion 1b/ft³
@ 3.6% Moisture, 210
Bulk Density 1b/ft³
@ 0.0% Moisture, 97.4

Angle/Repose 10 in. Drop @ 3.6% Moisture, 35° Angle Internal Friction @ 3.6% Moisture, 38°

TABLE V-1
LAYOUT TUNNEL MUCK DATA

RET IDENTIFICATION WOCK PROPERTIES 25 LAYOUT SEDIMENTARY: SANDSTONE MEDIUN ORY COMPR RODHARONESS CAAINED. LIGHT BROWN TO RED. WT STRNIH PCI SHORE NOW SCHNIDT SAME NOW SCHNIDT POF KPSI EST PORDUS. PORDUS. PORDUS. POORLY PCF KPSI EST CEMENTED. LAY-I CEMENTED. 150 IO 84 NA NA NA		
MOCK PROPERTIES SEDIMENTERY: SANDSTONE MEDIUM ORY COMPR ROD GRAINED. LIGHT BROWN TO RED. WAS SINE, POHDUS. POORLY PCF KPSI CEMENTED. 150 10 84	ESSON SCHOOL	
MOCK PROPERTIES SEDIMENTERY: SANDSTONE MEDIUM ORY COMPR ROD GRAINED. LIGHT BROWN TO RED. WAS SINE, POHDUS. POORLY PCF KPSI CEMENTED. 150 10 84	NO4 NO4 NA	
ROCK PROPERTIES SEDIMENTARY: SANDSTONE MEDIUM ORY COMPR GRAINED. LIGHT BROWN TO RED. WASSIVE, PORDUS, POORLY PCF KPSI CEMENTED. 150 10 6	SHORE NA	
MOCK PROPERTIES SEDIMENTER: SANDSTONE MEDIUM GRAINED. LIGHT BROWN TO RED. PASSIVE. PORDUS. POORLY CEMENTED.	Rab PC1 EST	
ROCK PROPERTIES SEDIMENTER: SANDSTONE MEDIUM GRAINED. LIGHT BROWN TO RED. PASSIVE. PORDUS. POGRLY CEMENTED.	COMPR STRNIN RPSI	
S NO S D	PKT PKT	
KEY IDENTIFICATION ZS LAYOUT SA"PLE NO LAY-:	MOCK PROPERTIES SEDIMENTER: SANDSTONE MEDIUN GRATIED. LICHT BROWN TO RED. MASSIVE. POMPUS. POORLY CEMENTED.	
	KEY ICENTIFICATION 25 LAYOUT 54"2LE NO LAY-:	

SHAPE OF FRACTIONS BETWEEN SCREEN SIZES A-ANGULAR S-SUBANGULAR R-ROUNDED P-PLATY C-CUBIC I-IRREGULAR E-ELONGATED SP-SPHE2013

P

4

14

Id

7.52

1.0

15.4

1.8

2.7

12.6 4.6

5.7 IZ.0

7.6 7.5

0.0

1.4

105

HUCK DATA
DRY UNIT MOISTURE PCI(+)6
WI PCF PCI IN-SIZE

61N. 31N. 21N. 1/21N. NO4 NOB NOIG NOSO NOSO NOIGO 10200

		ž	
•		SIZE(-)2.0 IN. ANGLE INER FRICTION DEGREES AT 3.6 PCT HOIST	
TOUGHNESS	0.52	SIZE(-) ANGLE FRICTI DEGREE 3.6 PG	38
•		APPARENT BULK COHESION DEUK PSF AT PCF AT 3.6 PCT MOIST 0.0 PCT MOIST	97.4
FLOW	00.9	BULK DENS PCF ST 0.0	
S6IN		PARENT HESION F AI PCT MOI	210
PLAST PLAST INDEX PCT	3.14		
MITS.SIZ	~	E(-)2.0 IN- ANGLE/SLIDE STEEL PLATE DEUREES AT 3.6 PCT MOIST	27
ERBERG LI SHRIN LIMIT	15.17	SIZE(-)2. ANGLE SIEEL 3.6 P	
PLASTIC SHRINKAGE PLASTICITY LIMIT LIMIT PCT PCT	17.06	ANGLE/REPOSE ANGLE/SLIDE ANGLE/REPOSE ANGLE/SLIDE OI DIN UROP STEEL PLATE DEGREES AT DEGREES AT 3.6 PCT MOIST	35
		ANGL 10 10 3.6	-,
LIGUID LIMITS PCT	21.20	ZREPOSE DROP ES AT	
37.1		(-)0.75 IN.SIZE ************************************	37
POT VOL CHANGE (+)0.056 IN.SIZE		75 IN.SI IF ITY	
TC9 0 (-)	•	(-)0. SPEC GRAV	2.66




Figure V-2. Layout Tunnel Muck Characteristics

STREET, S

S Accompanies

Principle of the Section of

III. PROGRESS REPORTS

The following information is taken from the Bureau of Reclamation L-29 progress reports for the Layout Tunnel.

April 1971

Strawberry Aqueduct, Currant and Layout Tunnels, Diversions and Appurtenant Structures - Specifications No. DC-6855. Contract No. 41-06-D-7058. S. A. Healy Company.

At the close of the month, the percentage of work complete was:

	Part 1	Part 2
This month	0%	1%
To date	0%	1%
Time elapsed	47%	12%

Excavation for outlet portal Layout Tunnel was initiated April 27. The portal excavation of $6,414 \text{ yd}^3$ was completed during the month. The contractor plans to excavate 40 ft of tunnel from the outlet portal by conventional methods and the remainder of the tunnel with a mole.

The mole is scheduled for shipping from Robbins Plant in Seattle, Washington, about May 15.

The contractor continued with preparatory work for the camp site completion of developing two culinary water wells and completion of two sediment ponds. One well is located at the contractor's camp site and the other is near the outlet portal of Layout Tunnel. Well water samples were submitted to the State Health Department for tests. The sediment ponds are located downstream from the Water Hollow siphon.

L. G. Everst, Inc., will process sand and aggregate for concrete. Plans are to obtain the aggregate from a deposit owned by Elmer Ray Moon and located in SW1/4, Sec. 1, T.35, R.10W, Uinta Meridian.

All remaining work under Schedule 4 was subcontracted to Jerico-Highland of Murray, Utah. Jerico-Highland plans to excavate the inlet portal and the outlet portal for Layout and Currant Tunnels, respectively, during this summer. The subcontractor also plans to start work on the Water Hollow Diversion works and Layout Creek Access Road about the middle of May.

Contract earnings for the month and earnings to date are \$128,280.00.

May 1971

Currant and Layout Tunnels - S. A. Healy Company excavated, by conventional methods, 54 ft of Layout Tunnel from the outlet portal. The Robbins mole arrived at the work site May 24. Offloading and assembly were started May 25. The access roads and tunnel portals in Layout Creek were cleared.

Strawberry Aqueduct, Currant and Layout Tunnels, Diversions and Appurtenant Structures - Specifications No. DC-6855. Contract No. 14-06-D-7058. S. A. Healy Company.

At the close of the month, the percentage of work complete was:

	Part 1	Part 2
This month	0%	0.3%
To date	0%	1.3%
Time elapsed	56%	14%

S. A. Healy Company excavated 54 ft of Layout Tunnel from the outlet portal by conventional methods in parparation for excavation with a mole. Water and air pipelines were installed to the portal.

The Robbins mole arrived at the work site May 24, and assembly was initiated May 25.

Jerico-Highland, subcontractor, initiated work on a bypass channel at the Water Hollow Diversion Dam.

Hamilton and Skewes, subcontractor for Jerico-Highland, cleared trees and brush from the Layout Creek road, Layout Creek road extension, Layout Tunnel inlet portal, Currant Tunnel outlet portal, Water Hollow Creek road extension, and Water Hollow Diversion Damsite. About half of the Water Hollow feeder pipeline right-of-way was also cleared.

Preparatory work by the prime and subcontractors included fabrication and ventilation of line and laying tracks.

The contractor plans to complete assembling the mole and start tunnel excavation by mole during June.

Jerico-Highland plans to complete the clearing operation and in early June to start building the Layout Creek Access Road and Water Hollow Diversion Dam.

Contract earnings for May were \$14,202.00. Earnings to date are \$142,482.00.

June 1971

Currant and Layout Tunnels - S. A. Healy initiated moling Layout Tunnel June 25 and moled 100 ft during the month. Jerico Construction excavated for Water Hollow Diversion Dam, completed open cut excavation of inlet portals of Currant Tunnel and Layout Tunnel, cleared Water Hollow Feeder Pipeline, and cleared and initiated construction of Layout Creek Access Road and Extension.

Strawberry Aqueduct, Currant and Layout Tunnels, Diversions and Appurtenant Structures - Specifications No. DC-6855. Contract No. 14-06-D-7058. S. A. Healy Company.

At the close of the month, the percentage of work complete was:

	Part 1	Part 2
This month	17%	1.7%
To date	17%	3%
Time elapsed	64%	16%

S. A. Healy Company excavated 100 ft of Layout Tunnel from near the outlet portal with a mechanical mole. Moling was initiated June 25, 1971.

Excavation was in hard sandstone and no support was required.

Daily tunneling operations are as follows:

FOOTAGE

Date	Hours Operated	Day	Accumulated	Remarks
6/24/71				Station 1786+26.
6/25/71	3.9	6	6	Initial exc. by mechanical mole. Had difficulty controlling line and grade caused by grippers against unstable timbers in ribs.
6/28/71	5.3	27	33	Had electrical and gripper trouble.
6/29/71	3.3	32	65	Had an oil leak at the head of the mole and electrical trouble.
6/30/71	3.0	35	100	Moling resumed middle of swing shift without determining cause of oil leak.
Totals	15.5	100		Station 1785+26.

SUMMARY

Item	This Month	Previous	<u>Total</u>
Total operating time in hours	15.5	0	15.5
Total footage	100	0	100
Rate per hour	6.5	0	6.5
Maximum advance per day	35	0	35

Jerico Construction Company, subcontractor, completed excavating a bypass channel and excavated about 80% of the required foundation for Water Hollow Diversion Dam. Work on foundation excavation was slow as the dewatering system was inadequate until the third sump and pump were installed June 24, 1971. Open cut excavation for Layout Tunnel inlet and Currant Tunnel inlet was completed. Pioneering and excavating for Layout Creek Access Road and Layout Creek Access Road extension were initiated.

Hamilton and Skewes, subcontractor for Jerico Construction Company, finished the clearing.

Additional preparatory work by the prime and subcontractors included fabrication of ventilation line and laying tracks.

The contractor plans to excavate by mole on a 3-shift 5-days per week schedule. Plans are to excavate about 40 ft by conventional method from the inlet portal of Layout Tunnel.

Jerico Construction Company plans to work on building the Layout Creek Access Road, Layout Creek Access Road Extension, Water Hollow Diversion Dam earthwork and concrete, and the excavation at the Currant Tunnel outlet portal.

Contract earnings for June were \$202,988.00. Earnings to date are \$345,470.00.

July 1971

Strawberry Aqueduct, Currant and Layout Tunnels, Diversions and Appurtenant Structures - Specifications No. DC-6855. Contract No. 14-06-D-7058. S. A. Healy Company.

At the close of the month, the percentage of work complete was:

	Part 1	Part 2
This month	2%	5%
To date	19%	8%
Time elapsed	73%	18%

S. A. Healy Company excavated 1,329 ft of Layout Tunnel from Station 1785+26 to Station 1771+97 with a mechanical mole. From Station 1774+71 to 1772+40, some fallout and water were encountered. Through this reach, structural steel supports with lagging was installed and timber was used for gripper pads.

Ground formations consisted of hard and softer layers of sandstone with some gravel and conglomerate seams.

Daily tunneling operations are as follows:

FOOTAGE

Date	<u>Hours</u> Operated	Day	<u>Accumulated</u>	Remarks
6/30/71			100	Station 1785+26
7/1/71	5.9	71	171	Electric drive motor for hydraulic pumps that run gantry belt failed. Stopped moling, worked to install fanline, tracks, and maintain catwalk and gantry.

Date	Hours Operated	Day	Accumulated	Remarks
7/2/71	4.1	62	233	Changes two cutters, Nos. 10 and 23. Motor was removed graveyard shift. Replaced with new motor during swing shift. High speed RPM cut out drive motors. Used low speed RPM.
7/3/71	3.8	52	285	Material increasing in hardness.
7/6/71	4.5	50	335	Changed three cutters, Nos. 27, 28, and 29, slight fault, 3 in. by 4 ft in crown section well cemented. (No supports required this day.)
7/7/71	12.8	158	493	Changed two cutters, vos. 1 and 23. Hit small flow of water at left rib, Sta. 1783+76. Belt trouble, shut down from 3:45 p.m. to 4:30 and 30 min during swing shift.
7/8/71	10.6	129	622	(Routine working conditions.) Electrical trouble with 100 hp drive motors. Change three cutters, Nos. 16, 28, and 29.
7/9/71	11.1	161	783	Changed 17 cutters, Nos. 2, 3, 4, 5, 6, 8, 9, 10, 11, 27, 12, 14, 15, 25, 28, and 29. Down because of trouble with trains in disposal area and to check outer seal.
7/10/71	4.4	54	837	Started changing cutters.
7/12/71	5.4	70	907	Changed two cutters, Nos. 12 and 29. Had trouble with pump on scrubber and mole belt. Down to check noisey cutter, and installing spray bar at gantry belt pickup from mole belt.
7/13/71	8.3	96	1003	Changed three cutters, Nos. 17, 22, and 23. Down to revamp spray nozzle bar between mole belt and gantry belt. One train of loaded muck cars derailed at 5:00 a.m. Mole belt plugged and slipped from wet material.

Date	<u>Hours</u> Operated	Day	Accumulated	Remarks
7/14/71	8.8	106	1109	Changed seven cutters, Nos. 13, 23, 25, 26, 27, 28 and 29. Had belt problems. Tried new spray bar. Down with broken hydraulic line to mole conveyor.
7/15/71	7.1	85	1194	Excavated 61 ft on graveyard shift. Hit bad ground, sand and gravel washed out with approximately 15 gpm flow of water. Started rib steel supports and lagging as mole advanced. Cribbing behind grippers was necessary in places.
7/16/71	3.6	31	1225	Had trouble gripping and with chunks falling out from above springline.
7/17/71	0.3	3	1228	Cleaned out invert of tunnel. Advanced mole 3 ft when another large fallout from crown occurred. Placed rib support steel.
7/19/71	1.7	14	1242	Changed cutter No. 27. Installed ribs at 3-ft centers and lagged and moled intermittently.
7/20/71	3.8	14	1256	Had trouble with grippers against unstable lagging.
7/21/71	5.2	46	1302	Had trouble with transformer and left side gripper moving rib steel and lagging.
7/22/71	2.6	31	1333	Day shift 7/22 thru graveyard shift 7/26 were spent on mole, airline maintenance and structural steel supporting of bad ground.
7/26/71	4.1	43	1376	Ran mole enough for one set of support steel at a time until mole was stopped due to dust after waterline to scrubber was broken.
7/27/71	5.3	53	1429	Changed seven cutters, Nos. 23, 13, 16, 12, 15, 29, and 26. Installed gantry.
Month Total	113.4	1329		Station 1771+97

SUMMARY

<u>Item</u>	This Month	<u>Previous</u>	Total
Total operating time in hours	113.4	15.5	128.9
Total footage	1,329	100	1,429
Rate per hour	11.7	6.5 ·	11.1
Maximum advance per day	161	35	

Structural steel tunnel supports consisting of 4" H beam 13#/ft were installed as follows:

Stations:

1774+71 to 1774+63	Partial ring set on 4 ft centers and pinned 2 ft below springline.
1774+59 to 1774+47	Full ring on 4 ft centers.
1774+43 to 1774+23	Partial ring set on 4 ft centers and pinned 2 ft below springline.
1774+19 to 1774+15	Full ring on 4 ft centers.
1774+15 to 1774+08	Full ring on 3 ft centers.
1774+08 to 1773+98	Full ring on 2 ft centers.
1773+98 to 1772+64	Full ring on 4 ft centers.
1772+60 to 1772+40	Partial ring set on 4 ft centers and pinned at springline.

Jerico Contruction Company, subcontractor, excavated the foundation for Water Hollow Diversion Dam and started compacted embankment. Work on foundation excavation and embankment was slow as the contractor had difficulty with dewatering. Initial concrete placement was made for the footing of the upstream cutoff wall for Water Hollow Diversion Dam. Undesirable material was removed and backfill and compacted backfill for structures were placed for the Water Hollow Tunnel intake structure. Open cut excavation for tunnel portals was substantially completed. Excavating for Layout Creek Access Road and Layout Creek Access Road Extension advanced to about 55%.

The contractor plans to excavate by mole on a 3-shift 5-days per week schedule. Plans are to excavate about 40 ft by conventional method from the inlet portal of Layout Tunnel.

Contract earnings for July were \$612,231.00. Earnings to date are \$957,701.00.

August 1971

Strawberry Aqueduct, Currant and Layout Tunnels, Diversions and Appurtenant Structures - Specifications No. DC-6855. Contract No. 14-06-D-7058. S. A. Healy Company.

At the close of the month, the percentage of work complete was:

	Part 1	Part 2
This month	18%	8%
To date	37%	16%
Time elapsed	82%	20%

S. A. Healy Company excavated 2,314 ft of Layout Tunnel from Station 1771+97 to Station 1748+83 with the mechanical mole.

Ground formations consisted of hard and soft layers of sandstone with some siltstone, conglomerate and shale seams. Supports were required in the following areas:

1767+38 to 1761+94 1759+22 to 1759+06 1758+04 to 1756+17 1752+62 to 1748+83

Through these reaches, steel pans with rock bolts or structural steel supports with lagging and cribbing were installed. Timber was used for gripper pads as needed.

Daily tunneling operations are as follows:

FOOTAGE

Date	<u>Hours</u> Operated	Day	Accumulated	<u>Remarks</u>
7/31/71				Station 1771+97
8/2/71	5.2	83	1,512	Hydraulic system repaired, some ground water encountered.
8/3/71	9.6	130	1,642	Changed 16 cutters, Nos. 22, 11, 7, 18, 10, 19, 28, 14, 20, 15, 23, 23, 23, 7, 8, and 9. No. 7 cutter was changed twice, once on day shift and once following graveyard shift; and No. 23 was changed three times on swing shift, when material was hardest.
8/4/71	6.9	118	1,760	Changed 11 cutters, Nos. 24, 25, 26, 28, 6, 3, 16, 21, 15, 28, and 29. Cutter No. 28 changed twice.
8/5/71	6.0	82	1,842	Changed 6 cutters, Nos. 19, 12, 18, 13, 21, and 20. Down day shift waiting on repair parts. No moling 9:30 p.m. to 10:00 p.m. while unsafe conditions were being corrected. Rockbolts with pans were tried as support on left side, between Stations 1769+75 and 1769+90, but 6 ft rockbolts failed to torque.
8/6/71	9.1	106	1,948	Changed 18 cutters, Nos. 23, 14, 27, 11, 17, 5, and 24, 23, 24, 25, 26, 27, 29, 10, 21, 15, 3, and 29. Cutters changed twice at locations No. 23, 27, 24, and 29. Grippers fractured material causing flaking from left side. 10' × 12" × 16 gage pans were anchored with 2 ft rock bolts from Station 1767+04 to 1766+84.
8/7/71	0	0	1,948	Changed center cutter.

<u>Date</u>	Hours Operated	<u>Day</u>	Accumulated	Remarks
8/9/71	12.9	155	2,103	Changed cutter No. 23. Had trouble gripping on sides. Pans and rockbolts used from Stations 1766+84 to 1765+86.
8/10/71	2.4	25	2,128	Hit soft, wet, caving ground; water inflow estimated at 70 to 80 gpm. Placed structural steel supports and lagging intermittently.
8/11/71	3.8	36	2,164	Set structural steel supports and lagging.
8/12/71	5.4	47	2,211	Conditions similar to those encountered 10th and 11th except estimated 100 gpm of water.
8/13/71	7.6	86	2,297	Moled, blocked grippers, placed support steel and lagging intermittently and pumped water. Had trouble with mud building up around support wheels for transformer and scrubber platform.
8/14/71	0	0	2,297	Changed 4 cutters, Nos. 1, 15, 26, and 29.
8/16/71	8.3	97	2,394	Changed 5 cutters, Nos. 26, 11, 28, 18, and 16. Ground became firmer.
8/17/71	7.6	99	2,493	Changed 7 cutters, Nos. 26, 18, 10, 19, 21, 23, and 25. Placed support steel and lagging, heading became dry and supports were discontinued.
8/18/71	15.4	209	2,703	Changed 6 cutters, Nos. 24, 28, 22, 7, 14, and 2. The hydraulic "tugger" system for moving muck cars under the gantry was tried. It was slow and could move only 8 cars at a time when loading. Started supporting with rockbolts and pans at Station 1759+90. Empty muck car derailed at 7:30 p.m.

<u>Date</u>	<u>Hours</u> Operated	Day	Accumulated	Remarks
8/19/71	13.5	194	2,896	Changed 11 cutters, Nos. 29, 6, 16, 21, 22, 2, 11, 17, 23, 19, and 10. Contractor worked to correct cause of derailment from 8 to 10:40 a.m. and started moling at 10:40. Maximum advance was 4½ in. per min with 2100 lb of propel. Water was encountered above invert on left side at Station 1758+01.
8/20/71	4.4	59	2,955	Changed cutter No. 24. Down 3 hr and 10 min on day shift to set transformer at Station 1768+36 and install 1,000 ft of 7200 volt electric cable. At 3:15 p.m., encountered loose conglomerate which required steel rib supports, moled 4 ft at a time then stopped to place support steel and lagging.
8/21/71	0	0	2,955	Changed 6 cutters, Nos. 5, 11, 17, 23, 25, and 28.
8/23/71	9.4	86	3,041	Changed 7 cutters; Nos. 24, 27, 9, 6, 14, 18 and 22. Continued to mole slowly and installed supports for most of day. Down an hour to repair vent line and scrubber. Material got harder and had more stability.
8/24/71	16.4	150	3,191	Changed 16 cutters, Nos. 1, 29, 15, 18, 12, 10, 16, 11, 12, 13, 19, 17, 22, 23, 8 and 3. Cutter at location No. 12 was changed twice. Down twice on swing shift and once on graveyard shift to change cutters because of hard well cemented conglomerate. Advanced 2 in. per min at propel pressure of 2,800 psi.

<u>Date</u>	Hours Operated	<u>Day</u>	Accumulated	Remarks
8/25/71	15.6	172	3,363	Changed 23 cutters, Nos. 15, 16, 20, 18, 14, 22, 19, 25, 24, 26, 28, 27, 29, 22, 21, 7, 17, 23, 13, 24, 21, 11, and 16. Cutters at locations Nos. 16, 21, 22, and 24 were changed twice.
8/26/71	6.5	60	3,423	Water encountered in crown at 3:00 p.m. Started setting pans and rockbolts. Changed water nozzles at throat of the mole for better dust control. At 4:15 p.m. began installing structural steel supports.
8/27/71	11.6	107	3,530	Changed 3 cutters, Nos. 4, 28, 29. Moled and set steel alternately until shut down for hydraulic system repairs.
8/28/71	0	0	3,530	Changed 5 cutters, Nos. 14, 19, 23, 25, and 27, and set some structural steel supports while making hydraulic system repairs.
8/30/71	9.2	100	3,630	Changed 2 cutters, Nos. 12 and 20. Continued repair on hydraulic system and encountered ground that required supports.
8/31/71	7.5	113	3,743	Changed 2 cutters, Nos. 28 and 29. Moled 4 ft and set support steel alternately.
8/31/71				Station 1748+83.

CI	TMM	Δ	Þ	v

Item	This Month	Previous	Total
Total operating time in hours	194.3	128.9	323.2
Total footage	2,314	1,429	3,743
Rate per hour	11.9	11.1	11.6
Maximum advance per day	209	161	

Jerico Construction Company, subcontractor, placed approximately 25% of the compacted embankment and compacted backfill for Water Hollow Diversion Dam. This material came from borrow. Nearly all of the structural excavation in the diversion dam was oversize and rejected.

About 102 yd 3 of concrete was placed for the upstream cutoff wall, cutoff walls under the spillway and sluiceway floors, and the 10' \times 31' \times 4' sluiceway floor section. At the Water Hollow Tunnel inlet structure, 19 yd 3 concrete was placed for the floor and part of the walls.

Excavation and embankments for Layout Creek Access Road, Layout Creek Access Road Extension and Road above the Layout Feeder Pipeline were substantially completed. Earthwork and laying of pipe were initiated for the Layout Feeder Pipeline.

Jerico Construction Company plans to work a 10-hr shift 6 days per week on Water Hollow diversion structures. L. G. Everst plans to process coarse concrete aggregate until winter shutdown about October 1, 1971. Plans are to use a rod-mill next summer to process sand for concrete because current processes have failed to produce sand within the specified gradation.

Contract earnings for August were \$708,358.60. Earnings to date are \$1,666,059.60.

September 1971

Currant and Layout Tunnels - S. A. Healy moled 1,295 ft of Layout Tunnel. On September 22, the contractor discontinued moling because funds were exhausted. About 2,900 ft of pipe was laid for Layout Feeder Pipeline and 235 yd³ of concrete was placed for Water Hollow Diversion Dam and the inlet structure to Water Hollow Tunnel.

Strawberry Aqueduct, Currant and Layout Tunnels, Diversions and Appurtenant Structures - Specifications No. DC-6855. Contract No. 14-06-D-7058. S. A. Healy Company.

At the close of the month, the percentage of work complete was:

	Part 1	Part 2
This month	22%	6%
To date	59%	22%
Time elapsed	91%	22%

S. A. Healy Company excavated 1,295 ft of Layout Tunnel from Station 1748+83 to 1735+88 with the mechanical mole.

On September 22, at noon, the contractor discontinued tunnel excavation because funds were exhausted. Swing and graveyard shifts were discontinued on September 24 and 25 respectively. Py September 30, S. A. Healy had laid off all employees except supervisory personnel.

The material at the heading when work was discontinued is conglomerate in the arch to about 2 ft above springline and shale and sandstone below that.

The contractor has completed the following work to protect the Layout Tunnel and boring machine during the shut down period:

- 1. Applied shotcrete to 90% of the tunnel except for the invert from the end of the California switch to and including the heading.
- 2. Installed 4 in. tunnel support steel on 4 ft centers around the mole.
- 3. Installed a bulkhead at the outlet portal.

- 4. Installed 8 in. drain pipe at the outlet portal. This line connected to the invert of the tunnel to the original 8 in. pump discharge line outside the portal and was buried about 2 ft. The pipe was insulated when buried.
- 5. Cleaned invert of tunnel around mole and backup equipment to facilitate drainage of water. Pumping was discontinued October 1, 1971.
- 6. Performed general cleanup of the mole and backup equipment.
- 7. Blocked up the mole and retracted all hydraulic rams.
- 8. Greased all machine surfaces left exposed.
- Activated internal heaters in the electric drive motors on the mole head.
- 10. Electricians sprayed a moisture proof preservative coating on all internal electrical wiring for motors, transformers, switches, etc.
- 11. Covered mole with a plastic covering.

In addition, the contractor plans to have watchmen on the job site during the entire shut down period. Also, electric power will be left on in the tunnel to activate the motor heaters and keep the transformers in operation to prevent deterioration.

Ground formations excavated during the month consisted of hard and soft layers of sandstone with some siltstone, conglomerate and shale seams. Structural steel supports with cribbing and lagging were installed in the following areas:

1748+83 to 1743+42 1740+64 to 1738+80 1736+32 to 1736+00 Timber was used for gripper pads as needed. A small amount of pans with rock bolts were also installed.

Approximately $170~{\rm yd}^3$ of shotcrete was placed to retard rock deterioration along the tunnel walls and crown between Stations 1784+50 and 1735+88 on an intermittent basis as needed.

Daily tunneling operations were as follows:

FOOTAGE

Date	<u>Hours</u> Operated	<u>Day</u>	Accumulated	Remarks
8/31/71			3,743	Station 1748+83
9/1/71	5.3	86	3,829	Changed 9 cutters, Nos. 25, 29, 18, 24, 27, 26, 21, 15, and 9. Alternately moled 4 ft and stopped to set rib support steel at 4 ft centers. Grippers cause rock to slab off.
9/2/71	8.8	123	3,952	Changed 10 cutters, Nos. 23, 17, 20, 8, 19, 22, 16, 10, 28, and 29. Alternately moled 4 ft and stopped to set rib support steel. Material was getting more stable.
9/3/71	9.4	126	4,078	Changed 7 cutters, Nos. 14, 13, 8, 6, 5, 11, and 23. Alternately moled 4 ft and stopped to set rib support steel. Material was getting softer and falling out from both sides.
9/7/71	5.2	71	4,149	Changed 2 cutters, Nos. 23 and 28. Alternately moled 4 ft and stopped to set rib support steel. Ground was blockey and some slabs fell out.
9/8/71	6.2	93	4,242	Changed 5 cutters, Nos. 27, 21, 18, 15, and 2. Alternately moled 4 ft and stopped to set rib support steel, as grippers were breaking slabs out.

<u>Date</u>	Hours Operated	Day	Accumulated	Remarks
9/9/71	5.6	66	4,308	Changed 13 cutters, Nos. 29, 26, 27, 12, 23, 22, 28, 24, 23, 26, 25, 27, and 29. Cutters at location No. 23, 26, 27, and 29 were changed twice. Alternately moled 4 ft and stopped to set steel until rib support steel was discontinued at Station 1743+42± at stable ground.
9/10/71	6.1	60	4,368	Changed 5 cutters, Nos. 17, 20, 21, 24, and 26. Ground was harder and moling speed was slow.
9/13/71	11.5	92	4,460	Changed 14 cutters, Nos. 14, 15, 16, 23, 11, 9, 4, 8, 13, 19, 20, 21, 10 and 2. Had trouble with high speed gripper valve, dust control equipment and conveyor belts. Stopped from time to time to repair these.
9/14/71	12.1	104	4,564	Changed 14 cutters, Nos. 5, 7, 10, 17, 18, 23, 24, 25, 26, 27, 28, 29, 1, and the center cutter. Hose to spray bar, dust controller, replaced.
9/15/71	5.4	69	4,633	Changed 2 cutters, Nos. 22 and 23. Moled 4 ft and stopped to install full ring steel supports alternately. Also had trouble getting grippers to hold.
9/16/71	8.5	79	4,712	Alternately moled 4 ft and stopped to set full ring support steel. Lagging behind grippers was required.
9/17/71	10.4	84	4,796	Changed 3 cutters, Nos. 23, twice and 24 once. Alternately moled 4 ft and stopped to set full ring support steel. At Station 1738+80, rib support steel was discontinued.

Date	<u>Hours</u> Operated	Day	Accumulated	Remarks
9/20/71	7.0	85	4,881	Changed 14 cutters, Nos. 8, 10, 11, 15, 16, 17, 18, 19, 21, 22, 24, 26, 28, and 29. The lubricating system to the cutter head bearings was repaired.
9/21/71	11.9	140	5,021	Changed 10 cutters, Nos. 14, 20, 23, 24, 25, 27, 3, 6, 8, and 29. Mole was without power for about 7 hr while contractor installed new transformer.
9/22/71	1.6	17	5,038	When softer ground was first encountered at 11:30 a.m., the contractor elected to stop the mole to leave it in stable ground until additional funds are available.
9/30/71				Station 1735+88

SUMMARY

Item	This Month	Previous	Total
Total operating time in hours	115.0	323.2	438.2
Total footage	1,295	3,743	5,038
Rate per hour	11.3	11.6	11.5
Maximum advance per day	140	209	

Jerico Construction Company, subcontractor, is working one 10-hr shift six days per week. About 207 yd 3 of concrete was placed for the upstream middle apron, right and left wing walls, left downstream cutoff wall and the remaining spillway floor for Water Hollow Diversion Dam. At the Water Hollow Tunnel inlet structure, about 28 yd 3 of concrete was placed for the upper parts of the walls and roof sections.

Earthwork and laying of pipe for the Layout Feeder Pipeline were advanced about 2,900 ft.

L. G. Everest, subcontractor, discontinued processing concrete aggregates until after the winter months. Some fine sand was produced and blended with the coarse sand already produced to obtain sand within specified gradations. This sand was used for shotcrete material in Layout Tunnel.

Contract earnings for September were \$695,912.32. Earnings to date are \$2,361,971.92.

IV. WAGE RATE SPECIFICATIONS: CENTRAL UTAH, 1970-1971

This information is taken from the Schedule, General Provisions, Specification, and Drawings, Strawberry Aqueduct, Currant and Layout Tunnels, Specifications No. DC-6855, U.S. Department of Interior, Bureau of Reclamation.

Pursuant to the provisions of the Davis-Bacon Act, 40 U.S.C. 276(a), as amended, the Secretary of Labor has determined that rates of wages and fringe benefits listed in this paragraph are those prevailing for the classifications specified in the locality of the work covered by these specifications and said rates of wages and fringe benefits shall be the minimum rates per hour to be paid for the work covered by the specifications.

Fringe benefit payments include medical and hospital care, compensation for injuries or illness resulting from occupational activity, unemployment benefits, life insurance, disability and sickness insurance, accident insurance (all designated as health and welfare), pensions, vacation and holiday pay, apprenticeship, or other similar programs, and other bona fide fringe benefits.

While the wage rates and fringe benefits shown are the minimum rates required by these specifications to be paid during the life of the contract, it is the responsibility of bidders to inform themselves as to local labor conditions such as the length of workday or workweek, overtime compensation, fringe benefit contributions, labor supply, and prospective changes or adjustments of wage rates or fringe benefits. No increase in the contract price will be allowed or authorized on account of the payment of wage rates or fringe benefits in excess of those listed herein.



Decision No. AK-2,013 (3) dated 8-16-70

	BASIC HOURLY	FRINGE BENEFITS F			PAYMENTS		
	RATES	HAT	PENSIONS	VACATION	APP TR	OTHERS	
ASBESTOS WORKERS	6.81	, 35	.42				
BOLLERMAKERS	6.30	.30	, 55	.40	. 02	•	
SOLLER WATERS' HELPERS	6.00	.30	. 55	.40	.02		
BRICFIATURS	5.86	.21	. 15				
CARPENTERS;	3.00		1		l		
Carpestara:				i	ļ	ł	
Zone 1: (4) miles or less from				i	1	1	
Brigham City-Ceder City-	1		ł	1	1	l	
Kanab-Logan-Dyden-Price-	Ī :	1	1		1	Į.	
Prove-Righfield-Salt Lake			ı	1	ľ		
City-Vernal)	6,30	.15	.20	. 13	.02	l	
	0.30	•••	1	• • • •	. •••	1	
Zone 2: (Eryond 40 thru 50 miles					1	ļ	
Zrou Brigham City-Ceder City-	j			1		l	
Kanab-Logen-Ogden-Price-Prove			i			ł	
Richfield-Selt Lake City-							
Vernal)	7.05	.15	.20	.13	.02		
		•••		'''	•••	ł	
Zone 3: (Seyord 50 thru 60 miles from							
Brigham City-Coder City-			1			1	
E-mab-Logan-Orden-Price-Prove	-		1	1		1	
Richfield-Selt Lake City-]						
Vernal)	7.175	. 15	.20	. 13	.02	j	
	1	-				i	
Zone 4: (Over 60 miles from Brigham	Į l						
City-Coder City-Kenab-Legen-	1		1				
Ogden-Price-Provo-Richfield-			1				
Selt Lake City-Vernal)	7.30	.15	.20	.13	, 02	l	
						i	
Saw Filers, Saw Ops., & Corpenters	1 1					l	
handling cressots material:	6,425	. 15	.20	.13	.02	ł	
Zone 1	7,175	.15	.20	.13	.02	ľ	
Zoma 2			,20	.13	.02	i	
Zone 3	7.30	.15	.20	.13	.02		
Zone 4	7,425	.15	.20		.02]	
Millwrights (All Zones)	6,55	.15	.20	.13	. 02	İ	
	6,30	.15	20	.13	.02	l	
Acoustical Carpenters (All Zones)	0.30				•	ł	
Value							
THERT MASHS:							
Coment Masons							
Zone 1 (The erea less than 45 miles							
from any county seat except	5.87	. 15	.20	.13			
Daggatt County)	7."/	,		•••			
Zone 2 (All of DAGGETT COUNTY and							
the area beyond a distance			ł l				
greater than a radius of			1				
45 miles from the remaining	6.27	.15	.70	.13			
county seats)	6.27	, 17	.,,	'''			
Machine Op.; Mastic Floor Materials;							
Spark Proofing; Scaffold (2) to 40	4.		ļi				
	6.00	.15	.20	.13			
Zone 1	6.40	.15	.20				
Zone 2	1 0,00	,		.13			

Total Second

	BASIC	FRINGE BENEFITS PAYMENTS						
	HOURLY	H & 0	PENNONS	VACATION	APP, TR.	ОТНЕМ		
ATWILL III. In								
Imping, finishing and texturing		.,	.12	1	.02	i		
(man: or machine)	5.05	.16	•**			ļ		
LECTRICIANS:	1 ({					
cache Davie (That portion of Devis Co.								
lying north of the 41st pe ellel)-								
Weber Counties.			15	1	3/10%			
Electricions	6.2C	. 18	15		3/10%			
Ceble Splicers	6.45	.16	•••					
ox Blder-Mccgen-Rich Counties.			15	1	3/10%			
Electricians .	7.20	. 18	15		3/10%			
Ceble Splicers	7,45	, 18	12			ì		
salt Lake County & thet portion of			1					
Davis County lying south of the wist	1 1		4	}	1]		
parellel: and thet portion of Uteh	} 1			1	1			
County lying north of the 40th	1 1		1		1			
serellel.	l 1			ł .	İ			
10 mi. Best or West from Interstate	1 1		1	i '				
they #15;	1 1		1%	ł	8/10%			
Blectriciens	6,20	. 18 . 18	15	•	0/10%			
Cable Splicere	6,45	. 10	1					
Over 10 mi, East or West from	i i					•		
Interstete Hwy #15:	1 1	. 10	15		8/10%			
Blectricians	6.70	.10	15	i	0 /105			
Ceble Splicers	6,95		1					
Remainder of State.		.18	15	İ	8/10%			
Electric lane	7.70	, 16	15	1	0/10%			
Ceble Splicers	7,95	, 10	1					
LEVATOR CONSTRUCTORS	5.56	. 16	.185	25+4]	1		
LEVATOR CONSTRUCTORS' HELPERS	70%JR	. 16	,105	2%+e	1	i i		
LEVATOR CONSTRUCTORS' HELPERS (PEOS.)	50%		Ī					
CLAZ IFRS	4.39	, 16		,	1			
LEONVORKERS:	1 -		i .	1		1		
Ornametel-Reinfercing-Peace Brector-			1		.025			
Structurel	6,475	.25	.25	1				
LABORERS:			.25		1	1		
Brick Tendere .	5.195	.15	.25					
Pleaterers' Tenders			.40		.01			
LATHERS	5,63	.20	5	l e	.01	1		
LEAD BURNERS	5.10	.15		1				
LINE CONSTRUCTION:		.15	15	1	3/45			
Ceble Splicers	6.37	.15	15		3/45	1		
Linemen	5.01	.15	15	1	3/45			
Line Equipment Operator	4.47	115	15		3/45	1		
Heed Groundmen	4.05	.15	15		3/45			
Groundates	03	•••	1		1			

	BASIC	FRINGE BENEFITS PAYMENTS					
	RATES	HAU	PENSIONS	VACATION	APP. TR	OTHER	
PAINTERS:						[
Ares North of 41st Parallel.			i -] _	
Brush	4.30	. 16			.01	1	
Spray; Structural Stael; Swing Stage	4.50	.16	1		.01	l	
Steepls Jack Work	4.50	. 16	1		.01		
Remaini: rort of State, Brush; soller; laperhanger; Sheet Rock Taper	4.87	.16	.12		.01		
Brush (String Stage); Brush (Steel & Bridge); Spray & Sandblaater;		.,			۵,		
Steeple Jack Spray (Swing Stage); Spray (Steel & Bridge); Sandblaster (Swing Stage);	5.07	. 16	.12		.01		
and apecial Coating Applicator	5,27	.16	.12		.01		
ILEDRIVERIUM; Bridge, Wharf, & Dock	7.09	16	.20	. 13	.02		
Cerpenters, Riggers, Boom Men LASTERERS	5,86	. 15 . 20	.20		.01	١.	
LABRERS: Pipelittera & Steenfitters:	3,60	.20	.20		.0.		
Lom 1- 15 mi, radius from centar of			[İ	
each city, namely Salt Lake	t l		•				
City, Orden and Provo	6,15	. 16	.20		.04		
Zone 2- Zona l plus 15 miles	6.45	. 16	.20		.04		
ione 3- Zone 2 plus 15 miles	6.80	.16	.20		.04	İ	
ione 4- All arese beyond Zone 3.	7,65	. 16	.20		.04	1	
SPRIGERATION & AIR COMDITIONING:							
50 tena er cuit:	1 1		1				
Zone 1- 15 mi, radius from center	1 1		1			ľ	
of each city, namely Salt						l	
Lake City, Orden and Provo	6,45	. 16	.20		.02	l	
Zona 2- Zone 1 plus 15 milas	6,80	. 16	.20		.02	ľ	
Zone 3- Zone 2 plus 15 miles	7.15	. 16	.20		.02		
Zome 4- All areas beyond Zone 3.	7.50	. 16	.20	1	.02		
Index 50 tome:				ĺ			
All Louise	5,35	. 16			.02		
007528	5.55	. 10	.10				
GIT NETAL WORKERS	5.70	. 18	.20				
PRINKLER FITTERS	6.20	.20	.30		.05		
FIRAZZO WORKERS	5.00			I			
ile entrais	5.00						
RLDELS: Receive rete prescribed for eraft to which welding is incidentel.							
O)THOTES;	ĺ						
. Employer contributes 4% of basic hot	ITLY FATE	for 5 we	bra' serv	ice and 2	basic h	ourly	
rate for 6 months to 5 years' service A through P.	e as Vac	tion Pay	Credit.	6 Peld H	lidaye:		
. Employee small receive 2 weeks' wac acruice; hmployee who has served cor raceive a third week's vacation. 7	stinuoual's	with on	er complete amployer	for twel	TO YOUTA!	to	
. Fight paid holidays: A through P p providing employee has worked 45 ful holiday, and the regular scheduled the holiday.	Il deye ch	ring tha	120 cald	dar days	prior to	the	
AID BOLIDAYS: -Kew Yerr's Day; B-Memorial Day; C-Ind -Christmas Day.	pendance	Days D-1	aber Day	B-Thenkej	iving De	, ;	

p.C. Johansia

postaliza-

1

That eres in the State of Utah within 45 road miles of the county seats aveluding largett County

excluding laggett County	BASIC		FRINGE B	ENEFITS P	AYMENTS	
LI JOHANS	HOURLY RATES	HAT	PENSIONS	VACATION	APP. TR.	OTHER
CROUP 1						
Boxman, Carpanter tender, Cement finisher helper, Chat boxman, Choker setter, Claring & grading, Clasning of equipment i parts in connection with concrete, Concreta crew, Dockhand & cleaning man, Pence crector & installer (includes installation & arection of fances, guard rails, median rails, reference post, guida post, & right-of-way markers), Flagment Porm atripper, Gardemer helper, General laborer, Grizzlay operator (whether by power or hand), Group pump eperators, Hesters tender, Belpers (all not berein asperataly classified), House mover, Lendscaping helper, Laborers on wrecking & Demolition, Nurseryman helper, Pre-watermen, Riprap man (hand placed), Sloper, Spreader & weighman, Stake jumper, Stripping & clasming of steal & pans, Tool dispatcher & checker (full time), Unloading & packing of rainforcing steal rods & mesh	4.305	.15	.25		.04	
GROUP II				1		
Air track beiper, Asphelt rakers & ironara, Dumpman, Gunita reboundman, Hand à chain saw operator (bucking & felling timber), J. Temper & similar type tampera, Matal form of ther (airport paving & highway) Operator & tenders of pneumatic & alectric tools & compressors & concrete saw, Operators of power-type form cleaner & ofling machines, Pipe wrapper, Put tender & joint mainr, Power type buggisa, Rollers, Scream & cleanup man, Signal & Buspman on concrete construction, Tummel & belt man,	4.43	.15	.25		.04	
CROUP III						
Barko vibratory roller & similar type, Compacing machines, High pressure water nourlemen, Jackhammer & pavemen	t					

	BASIC	PRINGE BENEFITS PAYERNTS						
LABORERS-Cont'd	HOUPLY RATES	HAT	PE NSIONS	VACATION	APP. TR.	OTHERD		
CROUP III- Cont'd								
bracker, Pipelayer, Powderman helper, Pumperete operetors, Refinery tank & vessel clashera, Sand Blastera, Send blaster pot tender, Vibrator operator Work of all type using cutting torches & tools meeded in wrecking		.15	.25		·.04			
GROUP 1V								
Air treck & core diamond drillers, Dril mechanic (on job site), Righ sceler- operating jackhammer or breeker, Hailn vibrators & similar types - 70 lbs., Hultiple side boom driller, Wagon driller	4.68	.15	.25		.04			
GROUP ▼	l i							
Gunite groundman, gunite mosslemen, gun rodman, Fowderman	5.03	.15	.25		.04			
TURNEL AND SHAPT WORK:	1							
CROUP I (Underground) Underground Laborers	4.43	.15	.25		.04			
GROUP 11 (Underground) Breekenen, Chucktender, Dumpman, Powderman belper, Puddler	4.53	,15	.25		.04			
GROUP 111 (Underground) Hipper, Screedwan, Vibretor, Tapman	*4.63	,15	.25		.04			
GROUP IV (Underground) Cutting merbins operator, Drill doctor Finisher, Gunite gunman, Minera, Powder make-up man, Speder & Tuggers, Steel- man, Timberman GROUP V		. 15	.25		.04			
(Underground) Gunite groundman, Gunite novaleman, Gunite rodman	5.03	.15	.25		,,			
GEOUP VI (Underground) Shifter	5.18	.15	.25		.04			

The state of the s

-	200	-	4

POWER EMILIPIENT OPERATORS	BASIC	FRINGE BENEFITS PAYMENTS					
OPEN PERMITTED VICTORIANS	HOURLY	HAT	PENSIONS	VACATION	APP. TR.	OTHERS	
CROUP 1 Chainman; Rodman	4.69	.41	.45	.20	.05		
GROUP II Asphelt Plant Firemen; Brakeman- Locomotive; Elevator Operator; Fireman; Hydraulic Monitor; Material Loader or Conveyor Operator; Partaman - Field; Grade Setter - Repairman Helper - Field		.41	.45	.20	.05		
GROUP III Air Compressor Operator; Concrete Mixer Operator (skip type); Concrete Pump or Pumpcrete Gun Operator; Enginee Dinkey Operator; Generator (100 KW or over); Mixer Box Operator (Concrete or Asphalt plant) (continuous mix or simil Pump Operator; Self-propelled, Auto- matically epplied concrete curing machine (on streets, highweys, eirports end canals); Screedman; Truck Crane	ar);	.41	.45	.20	205		
Other CROUP IV hallast Jack Tamper; Ballast Regulator; Ballast Tamper-Multiple Purpose; Front End Loader up to and including 1 c.y. Struck KZC; Noist Operator - 1 Drum; Line Emeter; Lubrication & Service Engineer (Mobile & Grease Rack); Slip Form Pumps	5.38	.41	.45	.20	.05		
GROUP IV-A Heavy Duty Repairman end Welder Permanent Shop	5.59	.41	.45	.20	.05		
GROUP V Air Compressor Operator (two or more compressore); Batch Operator (Asphalt Plant); Motorman; Pevezent Breaker Operator (Lesco & similar type); Signalman; Cuttlecsr; Sacil Kubber Tired Tractors; Small Self-propelled Pneumatic Rollers; Towermobile Operator Welding Machine (2 or more)	5.59	.41	.45	.20	.05		

POUTR EQUIPMENT CREMATORS	(Cont'd)
Ch was st	

*AREA 1

GH. UP VI	ſ
A-freme trime & tugger hoist; Concrete	l
Saks reif it perief unit on streets,	
highways, sirports and canalsi;	l
Ergineer, we motive; fork Lift	ĺ
(construct) n jot eite.; Eclean Loader	l
(eni similar); Maginnia Internal Fuli	l
Sieb Vitrator (on airporte, hiptesys,	
canels and warehouses; Mixermotile	
Operator; Pipe Sunding Machina Uperator	i
Pipe Cleaning Machine; Pipe wrapping	l
Macrine; Road Mixing Macrine courator;	
Rosa Carrier, or similar type, Small	ı
Rubber Tired Tractor (with attachments,	ĺ
including tackhoe); Small Trector with	ĺ
Boom; Surface Heatar (self-propelled;	l
Loader Operator (over 'c.y. up to end	
including 2 c.y. struck MHJ); rower	
Jumbo Operator (setting alip forms,	
etc. in tunnels); Small Rubber Tired	
Trenching Machine	
COURD HILL	

CROUP VII Bridge Crane; Chip Box Spreadar (fleherty type end similar); Concrete Mixar Operator (paving or betch plant Deck Engineers (Marine); Drilling Machine operator (well or diamond); Dual Drum Mixers; Elevating Gracer Opfuller Kenyon Fump and similer types; Heavy Duty Motery Drill Rigg (euch as quarry master, joy drills or equal; Hniet Operator - 2 drums; Instrument Man; Mechanicel Finisher Operator (Asphelt or concrete); Mine or Smeft Holet; Pevement Breeker (Yevament Breaker with compressor abmination); Pevament Breaker, truck mounted, compressor combination; Refrigeration Plent; Self-Propelled Pipeline, Mrapping Eachine (Perault, CRO, or eimilar types); Slusher Operator; Trector Operator (Misepte foot and enm; acting equipment); Treroing Machine; Tractor-Compressor Drill Comtination; No- Joint Pipe Laying Machine; Lull High-Lift (40 ft. or eimilar); Holler Operator or melf-propelled compactor

BASIC HOURLY RATES		FRINGE BI	ENEFITS P	AYMENTS	
RATES	HAT	PENSIONS	VACATION	APP TR	OTHERS
5.94	.41	.45	.20	.05	



-AREA 1	BASIC		FRINGE B	ENEFITS P	AYMENTS	
POWER EQUIPMENT OPERATORS (Cont'd)	RATES	HAT	PENSIONS	VACATION	APP. TR	OTHERS
Side Boom Operator; Asphelt Plant Engineer; Engineer Grushing Plant; Tractor Operator (bulldosar, scrapar or drag-type snoval or boom attachment) (up to and including 3-7 or similar)	6.09	.41	.45	.20	.05	
GROUP VIII Do-Nor loader and Adams Elegrader; Euclid Loader and similar types; Chicago Boom (Including Stiff lag and chicago Boom (Including Stiff lag and chicago Boom (Including Stiff lag and chicago Boom (Including Stiff lag and combination Simshar and Motor Operaotr; Concreta Batch Flant (Multipla unit); Koebring Skooper (or similar, up to 5c., Struck MRC); Loadar Operator over 2 c., up to and including 5 c.y. Struck MRC; Mucking Machina Operator; Saurman Type Dragline (undar 5 c.y. Struck MRC); Self-Propelled Eleveting Grade Plana; Soil Stabilizar (P & H or equal); Sub- grader (automatic subgrader - fine - gradar); Self-Propelled Boom type lifting davice; Mechanical Tranch Shiele Rubber Tired Scraper (undar 35 c.y. Struck MRC); Tri-Batch Paver; Tunnel (Mole or similar)		.41	.45	.20	.05	
GROUP VIII-A Heavy duty Respirmen or helder; Tractor Operator Bulldoser, Scraper or Drag typ Showel or Boom Attachment larger than D-7 or similar	6.40	.41	.45	.20	.05	
CROUP IX Combination Mixar & Compressor (Gunite) Highlina Cableway Signelman; Motor Patrol; Towar Grana (Linden type or eimilar designs and capacity) (in the erection, dismantling & moving of equipment there shall be additional Operator Enginear) CROUP X Big's Cableway Operator (Signalman required); Lift Slab Machina (Vagborg & eimilar types); Locomotive (ovar 100 tons) (singla or multiple units); Pra- Stress wire Wrapping Machine; Saurman type draglina (5 c.y. Struck MRC and ovar	6.45	.41	.45	.20	.05	

*AREA 1

FUWER EQUIPMENT CPERATERS (Cont'd)	BASIC HOUSELY	FRINGE BENEFITS PAYMENTS					
	HOU'KLY RATES	H & T	PENSIONS	VACATION	APP TR	OTHERS	
GRUIP 1 (Cont'd) Tractor Tan'ez Scrarers; Da 10,20 etc. (Taniem Scraper); Universal Equipment Operator (snoval, tackhoe, dragline, derrick, derrick barge, clamabell crane, gradall, etc. (up to and including 5 c.y., Struck MRC; Loader (over 5 c.y. up to and including 12 c.y. Struck MRC) -		-41	.45	.20	.05		
GROUP II Automatic Concrete Slip Form Paver (Gradesetter, Screedman); Koehring Skooper (or eimilar) (5 cu. yda. & over Struck MRC); Multiple Propulsion Power Unit Earth Movars (up to and including 75 c.y. Struck MRC); Remote Controlled Cranes and Derricks; Power Equipment with shovel-type controls (over 5 cu. yd up to and including 7 cu. yds. Struck MRC; Rubber Tired Scraper (35 cu. yde. and ovar Struck MRC); Self-Fropelled Compactor (with multiple propulsion pwoer units); Slip Form Pavar (concrete or esphelt) (1 operstor and 2 ccreedman	5 .						
when required); Tandem Tractors; Tower Cranes Mobile GROUP XI-A Multi-purpose Earth Moving Machines; (Two (2) or more scrapers (over 75 c.y.	6.90	.41	.45	.20	.05		
Struck MRC); Power Shovels & Draglinee (over 7 c.y. Struck MRC; Loader over 12 c.y. Struck MRC)	7.62	.41	-45	.20	.05		
GROUP XI-B Operator of Helicopter (when used in erection work)	7. 96	.41	.45	,20	.05		

BASIC	FRINGE BENEFITS PAYMENTS				
RATES	HAT	PENSIONS	VACATION	APP. TR.	OTHER
5.89	.41	.45	.20	.05	
,	.41	.45	.20	.05	
) 	n		.20	.05	
6.51	.41	.45	.20	.05	
6.59	.41	.45	.20	.05	
6.59	.41	.45	. 20	.05	
	5.89 6.09 6.38 6.51 6.59	5.89 .41 6.09 .41 6.38 .41 6.51 .41	5.89 .41 .45 6.09 .41 .45 6.38 .41 .45 6.51 .41 .45	FATES HAW PENSIONS VACATION 5.89 .41 .45 .20 6.09 .41 .45 .20 6.38 .41 .45 .20 6.51 .41 .45 .20 6.59 .41 .45 .20	RATES N & V PERSIONS VACATION APP.TR. 5.89 .41 .45 .20 .05 6.09 .41 .45 .20 .05 6.38 .41 .45 .20 .05 6.51 .41 .45 .20 .05 6.59 .41 .45 .20 .05

PC-TR E-VILPMENT OFERATURS (Cont'd)	BASIC							
	RATES	HAV	PENSIONS	VACATION .	APP. TR.	OTHER		
A-frame truck & tunger hoist; Concrete Saws (self Propelled unit on streats, highways, eirports end canels); Engineer, Locomotive; Fork Lift (construction job site); Rolman Loeder (and similer); Maginnis Internal Full Sleb Vibrator (on eirports, highways, canels end warehouses); Mixermobila (perator; Pipe Bending Machine Operator; Pipe Claening Machine; Pipe Wrapping Machine; Roed Nixing Machina Cperator; Ross Carrier, or similer type; Small Rutter Tired Tractor (with ettachments, including tachhoa); Small Trector with Boom; Surface Heater (salf-propelled; Loeder Operator (over 1 c.y. up to and including 2 c.y. struck MRC); Power Jumbo Operator (setting slip forms, etc. in tunnals); Small Rubber Tired Tranching Machine GROUP VII Bridge Grans; Chip Box Spreader (flaherty type end similar); Concrete Mixer Operator (wall or diamond); Duck Engineers (Marine); Drilling Machina Operator (wall or diamond); Duck Engineers (Marine); Drilling Machina Operator (wall or diamond); Duck Drum Mixers; Elsvating Greder Oper- Pullar Kanyon Pump end similar types; Masvy Duty Rotary Drill Rigs (such as quarry mestar, joy drills or equal; Moist Operator - 2 drums; Instrument Man; Machanical Finisher Operator (Asphalt or concrata); Mine or Shaft Moist; Pevement Bracker (Pevement Bracker with compressor combination; Pavement Bracker, truck mounted, compressor combination; Refrigaration Plant; Self-Propelled Pipeline, wroping machina (Pereult, CRC, or similar types); Slusher Operator; Trector Operator (Sheap's foot end eempacting aquipment); Trenching Machina; Tractor-Compressor Drill Combination; No- Joint Pipe Laying Machina; Lull Migh-Lift (40 ft. ar similar); Roller Operator er self- prepelled eempacter	6.94	.41	.45	.20	.05			

Perendicional

Suppress of

**AREA 2	BASIC		FRINGE B	ENEFITS P	AYMENTS	
PUTER EQUIPMENT UPERATORS (Cont'd)	RATES	HAT	PENSIONS	VACATION	APP TR.	OTHERS
GRAVE VIL-A Side Form Uperstor; Asphalt Plant Engineer; Engineer Crushing Plant; Trector (perstor (buildness, screper or dreg-type shovel or boom attachment) (up to end including D-7 or similar)	7.09	.41	.45	.20	.05	
CRUP VIII Do-Mor Loader end Adems Elegreder; Euclid Loader end eixilar types; Chicegn Boom (Including Stiff leg and sheer pole); Chief of Perty; Combination Slusher end Motor Opereotr; Concrete Satch Flent (Multiple unit); Koehring Skooper (nr similer, up to 5c. Struch MRC); Loader Operetor over 2 c.y up to end including 5 c.y. Struck MRC; Mucking Machine Operetor; Saurman Type Dregline (under 5 c.y. Struck MRC; Self-Propelled Eleveting Grade Plene; Soll Stabiliser (P & H or equal); Sub- greder (sutomatic eubgrader - fine - grader); Self-Propelled Boom type lifting device; Mechanicel Trench Shiel Rubber Tired Screper (under 15 c.y. Struck MRC); Tri-Batch Paver; Tannel (Mole or similar)	<i>r</i> -		.45	.20	.05	
GROUP VIII-A Heevy duty Respirms or Helder; Tractor Operator Bulldoser, Screper or Drag typ Shovel or Boom Attachment Larger than D-7 or similar	7.40	.41	.45	.20	.05	
GROUP IX Gosbination Mixer & Compressor (Gunite) Highline Cablevey Signelman; Motor Patrol; Tower Crane (Linden type or similer designs end capacity) (In the erection, dismontling & moving of equipment there shall be edditional Operator Engineer) GROUP 1 High Cablevey Operator (Signalman required); Lift Slab Machine (Vegborg & similar types); Locomotive (over 100 tons) (single or multiple units); Pre- Stress wire Wrapping Fachine; Saurman type draglime (5 e.y. Strack NAC and aver	7.45	.41	.45	.20	.05	

MAREA 2	BASIC		FRINGE B	ENEFITS P	AYLENTS	
POWER ENTIPHENT CHERATURE (Cont'd)	HOURLY RATES	HAT	PENSIONS	VACATION	APP. TR.	ОТНЕЖ
CRUIP I (Cont'd) Tractor Tandez Scrapers; DW 10.20 etc. (Tandem Scraper); Universal Equipment Operator (shove), tackhoe, dragline, derrick, derrick barge, classheli crane, gradall, etc. (up to and including 5 c.y.) Struck MRC; Loader (over 5 c.y. Mg to end including 12 c.y. Struck MRC)		.41	.45	.20∙	.05	
GROUP 41 Automatic Concrete Slip Form Paver (Gredasetter, Scraedman); Koehring Skooper (or similer) (5 cu. yde. & over Struck MRC); Multiple Propulsion Power Unit Earth Movers (up to end including 75 c.y. Struck MRC); Remote Controlled Granes and Derricks; Power Equipment with shovel-type controls (over 5 cu. yd up to and including 7 cu. yde. Struck MRC; Rubber Tired Scraper (35 cu. yde. and over Struck MRC); Self-Propelled Gompactor (with multiple propulation						
pwoer units); Slip Form Paver (coecrete or esphelt) (1 operator end 2 acreedman when required); Tandem Tractore; Tower Granes Hobile	7.90	.41	.45	.20	.05	
GROUP SI-A Muiti-purpose Earth Moving Machinee; (Two (2) or more acrapers (over 75 c.y. Struck NRC); Power Shovels & Draglinee (over 7 c.y. Struck NRC; Loader over 12 c.y. Struck NRC)	8,62	.41	.45	.20	.05	
GROUP 1[-B Operator of Relicopter (whom most in ercetion work)	8.96	.41	.45	.20	.05	
Reproduced from the same available copy.						

	RASIC HOURLY		FRINGE BI	NEFITS P	AYMENTS	
FILEDRIVING	RATES	H & T	PENSIONS	VACATION	APP. TR.	OTHERS
GROTP 1 (a) Assistant to Engineer (Fireman, Oiler, Decthari) (b) Compressor Operator (Electrically, ges or dissal powered, etc.) (c) Truck Crane Oiler	5.60 5.83 5.92	.41 .41 .41	.45 .45 .45	.20 .20 .20	.05 .05	
GROUP 2 (a) Operator of Trager Moist (Moisting materials only) (b) Compressor Operator (2 to 6) (Electrically, gas or diseal powered); Generator op. (electrically, gas or diseal powered); Pump op. (2 to 6); Welding	6.35	.41	.45	.20	.05	
machine op. (2 to 6) (Gas or disse perered)	6.50	.41	-45	.20	.05	
GROUP 3 "A" Frame; Dack Engineer; Fork Lift Operator; Self propelled Boom Type Lift- ing Device	6.69	.41	.45	.20	.05	
GROUP 3-A Heavy Duty Repairmen end/or Welder	6.96	.41	.45	.20	.05	<u> </u>
Operating Engineer in lieu of assistant to engineer tending boiler or compressor attached to crane piledriver; Operator of Filedriving rigs, skid or floating & derrick barges; Operator of dissal or gasoline powered Grane Filedriver (w/o boiler) up to & incl. 1 cu. yd. rating; Truck Grane Op. (up to & incl. 25 tons) (heisting saterial only) (assistant to engineer required) (not driving piles) GROUP 3 Operator of dissal or gasoline powered Grane Filedriver (w/o biler) over 1 cu. yd. rating; Operator of Grane (stached); Op. of steam powered enwiser or Universal Type Driver (Kaymond or similar type); Truck Grane Op. (over 25 tons (Hoisting saterial or performing piledriving work)	7.33	.41	.45	.20	.05	

Steel Erection	BASIC		FRINGE B	ENEFITS P	AYMENTS	
	HOURLY RATES	HAT	PICH SHOPES	VACATIOP	APP. TR.	OTHERS
GROUP 1 Assistant to Engineer (Oiler)	5.90	.41	.45	,20	,05	
GROUP 2 Assistant to Engineer (Truck Crone Oilar); Compressor; Generator, gaselist or dissel driven (100 EW)	6.16	.41	.45	.20	.05	
CROSS 3 Congressors, Generators &/er Welding Machines or Combination (2 to 6); Deck Engineer; Instrument Man; Signslmen (using mechanical equipment); Fork Lift	6.83	.41	.45	.20	.05	
GROUP & Hopairman; Tractor Op.	6.94	.41	.45	.20	.05	
Ghoup had Compination Beavy Duty Repairmen; Welder	7.13	.41	.45	.20	.05	
GROUP 5 "A" Frame or Boom Truck; Boom Cat; Chicago Boom; Crawler Crama a Truck Crames (15 Tona m.r.c. or leas) Salipropelled Boom Type lifting Device; Single Drum Loist; Tugger Hoiat; Chief of Party	7.45	.41	.45	.20	.05	
CROUP 6 Fravier Cremes & Truck Crames (ever 15 tens m.r.c.); Darricks (2 epe. required when cwirg ergine remote from heist); highline Cubissay (Signalman required); Truser Crames Robile; Universel Lieblar & Toser Crames (& similar types) (1s the erection, distantling & moving of equipment, there shall be an addi- tisual Operating Engineer); Two or more Drum Moist	7.73	.41	.45	.20	.05	
CROTP 7	8.77	.41	.45	.20	.05	
Operator of Belicopter	6.77					

10.5 per 10.5

Reproduced from best available copy.

	MASIC	FRINGE IN HILLITS PAYMENTS					
Truck DRIVERS	RATES	H & T	PENSIONS	VACATION	APP. TR	OTHE	
DUMP TRUCKS - Viter Level Capacity (bottom end or adds) (including Dumpiter Trucks, Euclid type trucks, Turnivations, Turnivators & Dumperstr Less than 8 yards 8 yards & less than 14 yards 14 yards & less than 15 yards 35 yards & less than 55 yards 55 yards & less than 75 yards 75 yards & less than 95 yards 75 yards & less than 95 yards 95 yards & less than 95 yards 95 yards & less than 105 yards Over 105 yards	5.30 5.45 5.60 5.50 6.00 6.20 6.40 6.52	.30 .30 .30 .30 .30 .30	.20 .20 .20 .20 .20 .20 .20	.30 .30 .30 .30 .30 .30			
thenever doubles are used, the drivere will be paid under the appropriate yardage schedule es outlined plus 25# per hour.							
When three (3) or more trailers ere put into operation, use the appropriate yardage rate as outlined above plus 25¢ per hour for the third (3rd) and each additional trailer which is pulled by one power unit. Whenever additional power units are used and operated by one driver, he shall receive an additional 50¢ per bour for operating such equipment. PLAT RACK TRUCKS, Bulk Coment Trucks, Transport Trucks, Semi-Trailer (Corry							
ing capacity): Pickup Lees than 10 tons 10 tons & less than 15 tons 15 tons & less than 20 tons 20 tons & over	5.125 5.20 5.35 5.45 5.60	.30 .30 .30 .30	20 ,20 ,20 ,20	.30			
Employee, driving any of the above on Flat Rick Trucks with Minch, Hoist Attachments or "A" Frames shall receis. 125 additional per hour when such winch hoist or "A" Frames are in use. These drivers load end unload sack camer explosives end/or ratificed ties by hitter shall receive \$.15 per hour additional for actual hours worked.	nd,						

JEA 1	PASIC		FRINGE BE	NEFITS P	AYMENTS	
TRUCK DRIVERS - CONT'D	RATES	HAT	PENSIONS	VACATION	APP. TR.	OTHER
RANGIT HIX TRUCKS:		.30	.20	.30		
Al made caractev & 1008	5.325	. 30	•==		1	ł
Over 4' yards capacity to & including		.30	.20	.30	1	1
6 71724	5.425	.30	.20	.30	1	1
Over by yards	5.525	.30	20	.30	1	1
Concrete pumping trucks	5.525	.30	•••		1	1 -
ATER, FUEL & OIL TANK TRUCKS:	. 305	. 30	.20	.30		
O to 1200 galions	5.175	.30	.20	.30	1	1
1200 to 2500 gallons	5.30		,20	.30	1	1
2500 to 4000 gallons	5.45	.30	.20	.30		1
4000 to 6000 gallons	5.75	.30		.30	1	N. Contraction
6000 gallons to lese than 10,000	6.00	. 30	.20		1	l l
6000 gallons to less than 10,000				1	Ł	1
10,000 gallons to lets then 15.000	6.25	.30	.20	.30	1	1
gallone						1
15,000 gallons to less than 20,000 gallons	6.50	.30	,20	.30		1
20,000 gallons to less than 25,000		۱	.20	.30		1
20,000 garrous as rose	6.75	.30	20	.30		4
gellons Over 25,000 gellone	7.00	.30	1 .20			
Whenever two water tanks are pulled,		1	1	· I	1	
addition to the combined unter galloms rates. Oil Spreader Operator (on eingle man operation where boot man is not required)	6.00	.30	.20	.30		
CONSTRUCTION JOB SERVICEDON:		.30	.20	.30	,	ì
managed Manifelt Truck	5.50			1		1
Fork Lift (under 6 tons) & Straddle.		.30	.20	.30		
Truck	5.50		. 20	0 1 .30	ויס	
Truck Driver Halper	5.075		.2	0 .3		1
Chauffeurs	5.075	.30		0 .3	0	
Bunker & Truck Loadere	5.20	.3	• • •		0	1
Marchousemen (Counter Clerk)	5.25	· ·	_	o .3	0	1
Vershousemen	5.125				0	
Machere, Greacers & Tiremen	5.275					1
Gee Station Attendants	5.075	.3		0 .3		1
Fork Lift (Over 6 tone)	5.60	د.			0	
POLE Tive foat a some,	5.42	.3			0	
Material Engineer	6.31			0	10	
Teamster Mechanic	6.06				30	
Tenmster Mechanic Helper					50	
Teamster Walder	5.075		-		50	
Teamster Driving Two Horses		5 .	30	20	~	
Teamster Driving Three or Nore Morse	1					

•AREA 2	BASIC		FRINGE BI	ENEFITS P	AYMENTS	
TRUCK DRIVERS	HOURLY RATES	HAV	PENSIONS	VACATION	APP TR.	OTHERS
DUMP TRUCKS - Water Level Capacity (bottom end or side) (including Dumpster Trucks, Euclid type trucks, Turnavagons, Turnarockers & Jumpcrete Less than 8 yards 8 yards & less than 14 yards 14 yards & less than 35 yards 35 yards & less than 55 yards 55 yards & less than 75 yards 75 yards & less than 95 yards 95 yards & less than 105 yards Over 105 yards	6.30 6.45 6.60 6.80 7.00 7.20 7.40 7.52	.30 .30 .30 .30 .30 .30	.20 .20 .20 .20 .20 .20 .20	.30 .30 .30 .30 .30 .30		
Whenever doubles are used, the drivers will be paid under the appropriate yardage schedule as outlined plus 25¢ per hour.						
When three (3) or more trailers are put into operation, use the appropriate yardage rate as outlined above plus 25¢ per hour for the third (3rd) and each additional trailer which is pulled by one power unit. Whenever additional power units are used and operated by one driver, he shall receive en additional 50¢ per hour for operating such aquipment.	1					
FLAT RACK TRUCKS, Bulk Coment Trucks, Transport Trucks, Semi-Trailer (Carry ing capacity): Pickup Less than 10 tons 10 tons & less than 15 tons 15 tons & less than 20 tons 20 tons & over	6.125 6.20 6.35 6.45 6.60	.30 .30 .30 .30	.20 .20 .20 .20	.30 .30 .30 .30		
Employees driving any of the ebove on Flat Rack Trucks with Winch, Hoist Attachments or "A" Frames shall recei \$.125 additional per hour when such winch hoist or "A" Frames era in use. When drivers load and unload sack cemer explosives and/or railroad ties by he they shall receive \$.15 per hour additional for actual hours worked.	i di					

TRUCK DRIVERS - CONT'D	BASIC		FRINGE B	enefits P	AYMENTS	
TRUCK BRIVERS - CONT B	RATES	HAT	PENSIONS	VACATION	APP. TR.	OTHER
TRANSIT MIX TRUCKS:			1			
4 yards capacity & less	6.325	.30	.20	.30		
Over 42 yards capacity to & including	4 114.					
6- yerds	6.425	.30	.20	.30		
Over 62 yards	6.525	. 30	.20	.30		
Concrete pumping trucks	6.525	.30	.20	. 30		i
MATER, FUEL & OIL TANK TRUCKS:					İ	
O to 1200 gallons	6.175	.30	.20	.30	l	1
1200 to 2500 gallons	6.30	.30	.20	.30	}	
2500 to 4000 gellons	6.45	. 30	.20	.30	ł	
4000 to 6000 gallone	6.75	. 30	.20	.30	ŀ	
6000 gallons to lass than 10,000	7.00	30	.20	.30	İ	
10,000 gallons to less than 15.000 gallons	7.25	.30	.20	.30	<u> </u>	
15,000 gellons to less than 20,000	- 10		.20	.30		
gallons 20,000 gallons to less than 25,000	7.50	.30	.20	.,,0		
gallons	7.75	.30	.20	.30		
Over 25,000 gallons	8.00	.30	.20	.30		į
addition to the combined unter gallonage rates. Oil Spreader Operator (on eingle man						
operation where boot man is not required)	7.00	.30	.20	.30		
CONSTRUCTION JOB SERVICEMEN:						Ì
Telescopic Manlift Truck	6.50	.30	.20	.30	l	
Fork Lift (under 6 tons) & Straddle	4				1	
Truck	6.50	.30	.20	.30	}	
Truck Driver Helper	6.075	.30	.20	.30	I	
Chauffeura	6.075	.30	.20	.30	ł	
Bunkar & Truck Loaders	6.20	.30	.20	.30	· ·	i
Warehousemen (Counter Clerk)	6.25	.30	.20	.30		
darehousesen	6.125	.30	.20	.30	i	Ì
Machers, Gressers & Tiremen	6.075	.30	.20	.30		
Gas Station Attendants	6.60	.30	.20	.30]
Fork Lift (Over 6 tons)	6.42	.30	.20	.30		
Meterial Engineer Teamster Mechanic	7.31	.30	.20	.30		ł
Teamster Mechanic Helper	7.06	.30	.20	.30		1
Teamster Welder	7.31	.30	.20	.30		į.
Teamster Driving Two Horses	6.075	.30	.20	.30		f
Teamstar Driving Three or More Horase	6.175	.30	.20	.30		

UTAH
AREA DEPINITIONS
for

Truck Drivers & Operating Engineers

etarra 2: All areas not included within Area 1 as defined below.

*Area 1: All eress included in the description defined below which is based upon township end range-lines as referenced to the Salt Lake City Base and Maridian:

Commencing at the intersection of the Utah-Nevada border and the Northerly line of Township 36S, thence easterly slong the northerly lines of Township 36S to the Northeast corner of Township 36S, Range 17W.

Theoce Hortherly to the H.W. corner of township 35S, range 16W; Thence Easterly to the N.E. corner of township 355, range 16 W; Thence Northerly to the N.W. corner of township 315, range 15 W; Thence easterly to the N.E. corner of township 315, renge 15 W; Thence Northerly to the N.W. corner of township 265, range 14 W; Thence Easterly to the N.E. corner of township 265, range 14 W; Thence Mortherly to the N.W. corner of township 255, range 13 W; Thence Easterly to the N.S. corner of township 255, range 13 W; Thence Northerly to the N.W. corner of township 245, range 12 W; Thence Easterly to the N.E. corner of township 24 S, range 12 W;
Thence Northerly to the N.W. corner of township 19 S, range 11 W;
Thence Easterly to the N.E. corner of township 19 S, range 11 W;
Thence Easterly to the N.E. corner of township 19 S, range 10 W;
Thence Easterly to the N.S. corner of township 17 S, range 10 W;
Thence Easterly to the N.S. corner of township 17 S, range 10 W; Theore Northerly to the N.W. corner of township 16 S, range 9 W; Thence Easterly to the N.E, corner of township 16 S, range 9 W; Thence Mortherly to the N.W. corner of township 15 S, range 8 W; Thence Easterly to the N.E. corner of township 15 S, range 8 W; Thence Mortherly to the S.W. corner of township 7 S, range 7 W; Thence Westerly to the S.W. corner of township 7 S, range 10 W; Thence Northerly crossing the Selt Lake Base line to the N.W. Thence Northerly crossing the Selt Lete 1888 1216 to the National Corner of township 6 N, range 10 W;
Thence Sasterly to the N.W. corner of township 6 N, range 8 W;
Thence Northerly to the N.W. corner of township 12 N, range 8 W;
Thence Easterly to the N.E. corner of township 12 N, range 8 W;
Thence Northerly elong the Westerly line of range 7 W to the Utah/ Thence Easterly elong the Uteh/Idaho border crossion the Salt Lake Meridien to the Intersection of the Utah/Ideho/Wyoming borders Thence Southerly along the Utah/Myoming Border
Thence Sasterly along the Utah/Myoming border to the Sasterly line of range 11 E; Thence Southerly elong the East line of range 11 8, crossing the Selt Lake Bace line to the N.E. corner of township 4 S, range 11 B; Thence Easterly to the N.W. corner of township 4 S, range 18 E; Thence Northerly to the N.W. corner of township 1 S, range 18 E; Thence Easterly elong the Silt Lake Base line to the N.F. corner of township 1 S, range 24 8; Thence Southerly to the N.E. corner of township 3 S, range 24 E; Thence Easterly elong the Northern line of township 3 S, to the Utah/Colorado border;

UTAH AREA DEPINITIONS for

Truck Drivers & Operating Engineers

Thence Southerly elong the Utah/Coloredo border, to the Southerly line of township 6 S; Thence Westerly to the N.E. corner of township 7 S, renge 23 E1 Thence Southerly to the S.E. corner of township 7 S. range 23 E; Thence Westerly to the S.W. corner of township 7 S. range 20 E; Thence Southerly to the S.E. corner of township 8 S. range 19 E; Thence Westerly to the S.E. corner of township 8 S, range 16 E; Thence Southerly to the S.E. corner of township 11 S, range 16 E; Thence Southerly to the S.E. corner of township 11 S, range 14 E; Thence Southerly to the S.E. corner of township 16 S, range 14 E; Thence Westerly to the S.E. corner of township 16 S, range 12 E; Thence Southerly to the S.E. corner of township 20 S, range 12 E; Thence Westerly to the S.E. corner of township 20 S, range 8 E; Thence Southerly to the S.E. corner of township 21 S, range 8 E; Thence Westerly to the S.Z. corner of township 21 S, range 6 E; Thence Southerly to the S.E. corner of township 23 S, range 6 E; Thence Westerly to the S.E. corner of township 23 S, range 5 E; Thence Southerly to the N.S. corner of township 27 S, range 5 E; Thence Easterly to the N.E. corner of township 27 S, range 7 E; Thence Southerly to the S.E. corner of township 30 S, renge 7 E; Thence Westerly to the S.E. corner of township 30 S, range 4 E; Thence Southerly to the S.E. corner of township 31 S, range 4 E; Thence Westerly to the S.W. corner of township 31 S. range 4 E. Thence Southerly to the S.E. corner of township 35 S, range 3 E. Thence Westerly to the S.W. corner of township 35 S, range 3 K; Thence Southerly to the S.E. corner of township 37 S, range 2 E; Thence Westerly to the S.W. corner of township 37 S, range 2 E; Thence Southerly to the S.E. corner of township 39 S, range 1 E; Thence Westsrly crossing the Salt Lake Meridian to the S.E. corner of township 39 S, range 2 W; Thence Southerly to the S.E. corner of township 41 S, range 2 W; Thence Westsrly to the S.E. corner of township 41 S, range 4 W1 Thence Southerly eiong the Easterly line of range 4 W, to the Utah/ Arisons border; Thence Westerly elong the Utah/Arizona botder to the S.W. corner of Utah: Thence Northerly elong the Utah/Nevede border to the point of beginning;

Commencing at the intersection of the Utah/Coloredo border and the Southstly line of township 34 S.
Thence Westerly to the S.W. corner of township 34 S. range 21 E;
Thence Northerly to the S.W. corner of township 29 S. range 21 E;
Thence Northerly to the S.W. corner of township 29 S. range 19 E;
Thence Northerly to the N.W. corner of township 23 S. range 19 E;
Thence Easterly to the N.W. corner of township 23 S. range 22 E;
Thence Northerly to the N.W. corner of township 23 S. range 22 E;
Thence Easterly to the N.W. corner of township 21 S. range 24 E;
Thence Easterly to the N.E. corner of township 31 S. range 24 E;
Thence Easterly sleng the Northerly line of township 31 S. to the Utah/Colorado border;
Thence Southerly elong the Utah/Colorado border to the point of beginning.

HOTE: Truck Drivers, only - If env part of portion of env job or project falls within Area 2, then the Area 2 rate of pay will apply for all work done on eaid job or project. This means, eli ectual on-site work, such see dams, bridges, roads, etc., including berrow pits which may be located in Area 1.

APPENDIX VI

PROGRAM LISTINGS

SUMMARY

This appendix contains the FORTRAN listing of the computer program developed for simulating the Layout Tunnel and listings of all tunneling subroutines. Definitions of common variables used in these programs are given.

CONTENTS

N	
I (COMMON VARIABLE DEFINITIONS
I :	INPUT FOR LAYOUT TUNNEL
A	A. Card Images
F	Parameter Values Before Initialization by the Subroutines
C	Parameter Values After Initialization by t Subroutines
F	PROGRAMS AND SUBROUTINES
A	A. Program GEOMOD
E	3. Frogram TUNNEL
C	Program GENTNL
D	Program CONTROL
E	Subroutine INPUT
7	. Subroutine OUTPUT
G	Subroutine BORE
Н	Subroutine CUTTER
I	. Subroutine REPAIR
J	Subroutine CVLOAD
K	. Subroutine CVMNT
L	• Subroutine RAILHL
М	. Function CUBIC
N	• Subroutine ADDTRN(I)
0	. Subroutine RAILDS
P	• Subroutine RAILEX
Q	. Subroutine RAILMT
R	• Subroutine GRNSUP
S	Subroutine GSMAIN
T	Subroutine ENVIR
U	Subroutine MAXADV
V	Subroutine REPORR

CONTENTS (Cont.)

SECTION				PAGE
	w.	Subroutine	REPORC	VI-122
	х.	Subroutine	HOLBRN(ICYCLE)	VI-125
	Υ.	Subroutine	MOVEIN(ICYCLE)	VI-126
	z.	Subroutine	MOVEOUT (ICYCLE)	VI-127
	AA.	Subroutine	SETCHG(ICYCLE)	VI-128
	вв.	Subroutine	JETIMP	VI-129
	CC.	Subroutine	JETAGN	VI-131
	DD.	Subroutine	JETMNT	VI-132
	EE.	Subroutine	PROJTL	VI-133
	FF.	Subroutine	PRJBR	VI-135
	GG.	Subroutine	MUKLOD	VI-136
	нн.	Subroutine	MUKIN	VI-138
	II.	Subroutine	MUKOUT	VI-139
	JJ.	Subroutine	TRUKHL	VI-140
	KK.	Subroutine	TRNPRT (ICYCLE)	VI-146
	LL.	Subroutine	EXTNSN(ICYCLE)	VI-149
	MM.	Subroutine	SURGE .	VI-152
	NN.	Subroutine	BELT (ICYCLE)	VI-153
	00.	Subroutine	XXXMNT	VI-154

I. COMMON VARIABLE DEFINITIONS

COMMON VOLDCOMY PARAMETERS/FLAGS THAT CHANGE WITH TIME

NOT USED AT PRESENT HEAT ADDED TO THUSEL FROM WATER JET (OR PROJECTILE) ATU STATUS VARIABLE FOR GRUNNO SUPPORT 1-GROUND SUPPORT FALLEN BEHIND COS) YPMUG HEATJ 1FXCA FLAG TINICATTING DISCHARGE AREA IS FILLED IFILD 1-DISCHARGE AREA FILLED . 0-DISCHARGE AREA NOT FILLED STATUS VARIABLE FOR URILL AND BLAST MOVING OF JUMBO DRILL TO FACE 0-40VING IN PROGRESS. I-40VING COMPLETED
STATUS VARIABLE FOR ORILL AND HLAST MOVING JUMBO ORILL FROM FACE
0-40VING IN PROGRESS.1-MOVING COMPLETED MIMIL TUOMUL REASON FOR TRAINSTRUCK 1 TO HAVE STOPPED (SEE APPENDIX TV-OFSCRIPTION OF RAIL SYSTEM) KSTOP (25) 1-UNLOADING STOPPED. FLAG FOR UNLOADING TH DISCHARGE APEA KUNLO 0- PLOADING CONTINUING
STATUS VAPIABLE FOR INTEGRATED CONVEYOR LOADER 1-LOADER CAPACITY
EXCEEDED 0-LOADER CAPACITY NOT EXCEEDED VARIABLE ALSO USED FOR
MACHINE LOADERS AND SHOVELS 1-LOADING FINISHED+0-LOADING IN LOADR FLAG TO SHUT DOWN OR BRING UP LONG HAUL TRAINS/TRUCKS SYSTEM LSTOP 1-SYSTEM SHIT DOWN C-SYSTEM UP STATUS VARIABLE FOR LONG HAUL THATMS/TRUCKS 0-VEHICLE NOT AVAILABLE FOR LOADING WIFDHAL TO 0- VEHICLE AVAILABLE FOR LOADING I VEHCL EDUTANTERUE IN PROCHESSION MATRIEMANCE COMPLETED THAT INTERNANCE IN PROCHESSION (LONG HAUL) MACON STATUS MAPITABLE FOR CONVEYOR (LONG HAHL) O-CAPACITY OF HELT NOT MCAPC EXCEEDED . 1 - CAPACITY DE HELT EXCEEDED STATUS VARIABLE FOR INTEGRATED CONVEYOR LOADER FOR MACHINE LOADERS AND SHOVELS 1-MAINTENANCE IN PROGRESS.O-MAINTENANCE COMPLETED FLAG TO INSTRACT SHORT HADE MATERIALS HANDLING STOPPED 0-401 STOPPED-1 OF ORESTER THAN 1-STOPPED 1915 STATUS VARIABLE FOR GROUND SUPPORT TYPE I 1-1-40 SUPPORT 1-2-ROCK ROLTS 1-3-SHOTCHETE -1-4-STEEL SETS MELAGO MGS (1) 0- MAINTENANCE COMPLETED-1-MAINTENANCE IN PROGRESS COMPLETED MOVE TO FACE .C-MICKERS MOVE TO FACE IN PROGRESS COMPLETED WOVE FROM FACE IN PROGRESS COMPLETED WOVE FROM FACE IN PROGRESS MKIN MUKOT STATUS VANIABLE FOR PROJECTILE AND MATER JET 0-OPERATING. 441 OF GREATER THAN 1 -STOPPED FOUTVALENCE (MPT+MAJ) STATUS VARIABLE FOR WATER JET (OF PROJECTILE) 0-MAINTENANCE IN PLWN DROGRESS . 1-44 INTENANCE COMPLETED STATUS VARIABLE FOR REPOSITIONING WATER JET (OR PROJECTILE) 0-REPOSITIONING THE PROGRESS. 1-MEPOSITIONING COMPLETED STATUS VARIABLE FOR PROJECTILE 0-RARREL PERLACEMENT IN PROGRESS. MWJR NRARL 1-DVSDET MERTACEAEAL CUADFELLU THE TO THOUGHT FEFDED DOW AWAY TOLERANCE EXCHENED 1-TOLERANCE EXCHENED -0-TOLERANCE NOT EXCHENED VAYAY STATUS VARIABLE FOR DRILL AND BLAST CHARGE SETTING NCHRG



```
I-UNTRUE PRILING CONDERTED OF CHARGE SETTING IN HADOMESS
                              STATIS VARIABLE FOR ORILL AND HEAST O-DRILLING IN PROGRESS.
NORILL
                              1-DPILLING COMPLETED
                              STATIS VARIABLE FOR DRILL AND BLAST O-HURN CUT DRILLING IN PROSPESS
NORTER
                              .1-RURY OUT DRILLING COMPLETED
                              STATUS VARIABLE FOR CONVEYOR (LONG HAUL) 0-SPLICING BELT COMPLETED
NSPL 1C
                              HINESULAL TO A-SPETCING HELT IN PROGRESS STATUS VARIABLE FOR TRAINSZIPHICKS
NSWTCH
                              0-SWITCH MOVE DO AND COMPLETED. I-SWITCH BEING ADDED. 2-SWITCH
                              BEING MOVED
                              EDUTVALENCE (NS OTOHONSWCH)
                              NUMBER OF TRAINS IN DISCHARGE AFFA
NTPDA
                              NUMBER OF TRAILSZIPHICKS ACTIVE
NVEHCL
                              MINNER OF SMITCHES IN TRAINVIBUCK SYSTEM
NUMSWT
                              AVERAGE LOADING VOLUME RATE FOR MACHINE LOADERS AND SHOVELS
01
                              FFFT##3/HOUP
                              VOLUME OF WATER NODED TO TUNNEL FROM WATER JET
                                                                                                                                                  FFET**3
OWATH
                              FEFORE RUN AWAY TOLFRANCE. FT
LOCATION OF SWITCHES FEET FROM DISCHARGE AREA
 SWITCH(20)
                              CHARLINE COST EDS TENTALISMENT OF THEINVIRUCK I CHARLINE TIME IN OBERATION FOR TRAINVIRUCK I CHARLINE STATUS OF TENTALISMENT STATUS OF TENTALISMENT STATUS OF TENTALISMENT OF THE STATUS OF TENTALISMENT OF THE STATUS OF TENTALISMENT OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE STATUS OF THE ST
 TFC(25)
                                                                                                                                              HOURS
 TOP (25)
 TSTAT (25.4)
                                   EDUTVALENCE (ISTAT+ITSTAT)
                               (SEE ADDEMOIX IV-OFSCRIPTION OF PAIL SYSTEM)
TIME PENAINING IN UNLOADING OF TPAIN TRUCK I. HR
 UTIME (25)
                               DISTANCE FROM DISCHARGE AREA TO GROUND SUPPORT POSITION FEET
 XGS
                                              UPDATED VALUES OF THOSE VARIABLES IN JOLDCOM/
 CCMMON /NFWCOM/
                                             GPRATER VALUES OF DUMMY (20)
 FULLWIAY (20)
                               UPNATED VALUE OF HEATS
 FHFAT.
                               UPDATED VALUE OF TEXCA
 LIFXCA
                               HENATED VALUE OF IFILED
 LIFILD
                               UPDATED VALUE OF JUMIN
 LJHMIN
                               UPDATED VALUE OF JUMBIT UPDATED VALUE OF KSTOP (25)
  LJUMOT
  LKSTI)P(25)
                               UPDATED VALUE OF KUNLO
 LKHNLO
                               HPDATED VALUE OF LOADS
 LLOADR
  LESTOP
                                UPDATED VALUE OF LYPHCL
  LLVHCL
                               FO HVALENCE (LEVACE + LETRAN+LETUCK)
UPDATED VALUE OF MACON
UPDATED VALUE OF MCAPC
  LMACON
  LMCA-'C
                                HPDATED VALUE OF MELAGE
  LMCV
  LMFLAC
                                UPDATED VALUE FOR MOS(I)
  LMGS(I)
                                HODATED VALUE OF METH
  LMKIN
                                 HENATED VALUE OF MIKOT
   LMUKOT
                                 UPDATED VALUE OF MWJ
   LMM1
                                 FOITVALFNCF (LMPT+LMHJ)
                                MEMM TO BLILL OF MALME OF MALE
   LMW JM
   LMW JP
                                UPDATED VALUE OF WHARL UPDATED VALUE OF LARYAY UPDATED VALUE OF NORMS
   LNRAYL
   ENHYHY
   LNCHPG
                                 UPNATED VALUE OF MODILE UPNATED VALUE OF NOBILE
   LNOPIL
   INDPLA
                                 UPHATER VALUE OF NEPLIC
   LNSPLC
                                 UPDATED VALUE OF NEWCH
   INSWCH
   LNTRDA
                                     FOUTVALENCE (LATROA-NTOA)
                                 UPDATED VALUE OF NVEHCL
ECUIVALENCE (L'IVHCL .LNTRAN.LNTRUK)
   LNVHCL
                                 UPPATED VALUE OF MUSAT
   LNMSWT
```

```
UPDATED VALUE OF OL
FOI.
                 UPDATED VALUE OF DWATE
FOWATR
                 UPPATED VALUE OF SM
FSM
                 UPDATED VALUE OF SWITCH(20)
UPDATED VALUE OF TEC(25)
UPDATED VALUE OF TOP(25)
FSHTCH(20)
FTFC (25)
FT0P (25)
                UPDATED VALUE OF TSTAT(25.4)
FOUTVALENCE (FTSTAT-LISTAT)
FTSTAT (25.4)
                 UPDATED VALUE OF HITTHE (25)
FUTTME (25)
                 UPDATED VALUE OF XGS
FXGS
                         GENERAL DATA
COMMON /ALL
                 MAXIVIM DISTANCE FROM PORTAL ASSOCIATED WITH THE FOLLOWING SIX
ΧŦ
                 CONDITIONS
                 UNCOVERNED COMPRESSIVE STRENGTH OF POCK. 1.E3 LH/IN**2
STP
                 ROCK ARRASIVE INDEX
TA
                 ROCK QUALITY OFSIGNATION
THE STEEL DENSITY OF ROCKS. LR/FT.**3
900
CS
                 ANATENT TEMPERATURE. DEGREES FARRENEHIT
TAMB
                 WATER THELOW RATE. GPM
FLAG (NOT USED AT PRESENTE
FLOW
IFLAG
                   ENUTVALENCE (G(T) .XT) . (G(A) . TFLAG)
                 CROSS SECTIONAL AMPA OF TUNNEL . FT ...
AT
                 DIAMPTER OF TURNEL . FT
n
                 TIME RETWEEN PUINT OUT OF WORKING COMMON
                                                                        HOURS
DIPRNI
                 TIME INCREMENT. HR VOLUME OF ROCK ROCKEN IN DT. FT. 3
DT
OX
                 ADVANCE OF FACE IN DI. FT.
                 ENERGY REGULATO DED HOCK VOLUMN BROKEN. IN-TBALLES IN-+3
г
                 FLAG TO INDICATE THAT GEOLOGY HAS CHANGED O-GEOLOGY NOT CHANGED
 ICHNG
                  .T-GEOLDGY CHANGED
                 MEADING POSITION OF LAST GEOLOGY PARAMETER CHANGE FT
TIME FROM START OF BUN OF LAST GEOLOGY PARAMETER CHANGE
FLAG TO INDICATE METHOD OF LONG HAUL MATERIALS HANDLING
 X CHNG
                                                                                             HOURS
 TCHNG
 THOVE
                 FLAG TO INDICATE METHOD FOR ROCK FRAGMENTATION
 IMETH
                  T-RORING MACHI LE . P-PLAST . 3-WATER JET . 4-PROJECTILE
                    FOUTVALENCE (JUSTH : 1METH)
                  FRACTION OF TOTAL COST FOR OVERHEAD
 OPPCT
                  POWER RATE, 4/44-HR
FOUTVALENCE (PRAPE)
TIME INTERVALS RETWEEN INTERIM REPORTS (HOURS)
 99
 REPORT
                  ROCK SVELL FACTOR
 SK
                  MAXIMUM TIME FOR CUPRENT SIMULATION RUN. HR
 TMAX
                  INITIAL VALUE OF T HOURS
PRINT DUTPUT WEN TETPRINT. HR
TOTAL SHET TIME PER DAY HOU
 TO
 TPRINT
                                                   HOURS
 TSHFT
                  POSTITION OF FACE FROM DISCHARGE AREA.FT
DISTANCE FROM TUMMEL POWTAL TO DISCHARGE AREA
MAXIMUM DISTANCE FOR CUMPENT SIMULATION RUN. FT
 KOTSCH
 XMAX
                                               CEFT
                  INTITAL VALUE OF X
 X O
                          BORING MACHINE ACTIVITIES
 COMMON /40RING/
                  MINNER OF MEN IN LAHUR CATEGORY T (T=1+10) FOR HORING MACHINE
 ROMEN(I)
                  SYSTEM
                  HOUPLY COST OF MAN IN LABOR CATEGORY : FOR BORING MACHINE SYSTEM
 ROCSTITE
                  LIFE OF CUTTERS FEET OF CUTTER TRAVEL
 CL (3)
                  COST PER CUTTED. $
TIME TO ASSEMBLE CORING MACHINE. HR
 CPC
 DTA
                  TIME SETWEEN RORING MACHINE MAINTENANCE PERIODS. HR
 DTC
```

```
TIME TO CHANGE PORE OTAMETER. HR
DICD
                 TIME TO DISASSEMBLE BORING MACHINE. HR
                DURATION OF ROPING MACHINE MAINTENANCE. HR
DTD
                COST OF BORING MACHINE UNIT/FOOT OF EXCAVATION COST OF TRANSMISSION LINES/FOOT OF EXCAVATION
OTM
FROREG
ETRANS
                NUMBER OF CUTTERS
NUMBER OF CUTTERS CHANGED
KK
LNCHNG
                 FLAG FOR CUTTER CHANGE O-CUTTER CHANGE COMPLETED.
LNCUTR
                 I-CUTTERS BEING CHANGED
                 FLAG TO ASSEMBLE HORING MACHINE FLAG FOR BORING MACHINE MAINTENANCE
MASSEM
                 0-MAINTENANCE COMPLETED . 1-MAINTENANCE IN PROGRESS
MRM
                 FLAG TO INDICATE STATUS OF BORING MACHINE DEUP+UNFQUAL DEDOWN
MAORE
                 (SEE APPENDIX IV-DESCRIPTION OF CONTROL PROGRAM FOR LAYOUT TUNNEL)
                 OR TOLE
                 FLAG FOR CHANGING BORING DIAMFTER FLAG FOR DISASSEMBLY OF BORING MACHINE
MCD
                 NUMBER OF THE CUTTER TO BE CHANGED ON THE I TH CHANGE FOR THIS
MDISAS
NCUT(I)
                 TIME CYCLE I=1.50
ROTATIONAL HP OF BORING MACHINE. HP
PRM
                  PADIAL LOCATIONS OF CUTTERS. IN
R(100)
                  CHITTER REPLACEMENT CRITERION. PERCENT WEAR
 BC.
                  ROTATIONAL SPEED OF BORING HEAD. RPM
 RPM
                  TIME TO REPLACE ONE CUTTER. HR
 18
                  WEAR OF CUTTER I (I=I+100)
CUTTER BEARING COST+ PERCENT CUTTER COST
 WEAR (I)
 XCPC
                           DRILL AND BLAST ACTIVITIES
 COMMON /PLAST /
                  AREA OF BURN CUT RELIEF HOLE. IN. 2
 ADR
                  AREA OF DRIFTER HOLF. IN. 2
 ACH
                  ORIFTER AIT COST. $
 CHIT
                  COST OF BURN BIT. $
 CBURN
                  COST OF FIRING CAPS
                                                S/CAP
 CCAP
                  COST OF EXPLOSIVE
                                               5/LR.
 CEX
                  MISCELLANFOUS COST
                                              $/HOLE
 CM
                                         S/LAS
  CPL
                   COST OF STEFL. 5
                  AVERAGE LIFE OF OPTIL BIT. FT OF TUNNEL DUG
AVERAGE LIFE OF BUPN BIT. FT OF TUNNEL DUG
AVERAGE DEPTH OF ORIFTER HOLFS. FT
AVERAGE DEPTH OF STEFL. FT OF TUNNEL DUG
AVERAGE LIFE OF STEFL. FT OF TUNNEL DUG
  CSTFFL
  LAIT
  LBURN
  LO
  LDA
  LSTEEL
                   NUMBER OF MEN OR AUTOMATED UNITS SETTING CHARGE
  MEN
                                                                               Reproduced from
                   NUMBER OF ORIFTED DEILLS
NUMBER OF BURN CUI ORILLS
  NΠ
  NOB
                   NUMBER OF OFIFTER HOLES
  NH
                   NIMBER OF BURN CUT HOLFS
  NHB
                   POWDER FACTOR. LP/YD**3
                   POWER OUTPUT OF RURN CUT DRILL. HP
  POH
                   POWER OUTPUT OF DRIFTER DRILL
  POD
                   APPARENT SPECIFIC ENERGY IN-LRS/IN**3
TIME TO SET ONE CHARGE. HR
  SF
  TC+G
                   TIME TO MOVE IN JUMBO AND ALIGN. HR
TIME TO MOVE OUT JUMBO. HR
  TIN
```

WATER JET AND PROJECTILE ACTIVITIES COMMON/NJET/

OPTION?-0=0YNAMITE AMOUNT OF PRIMER PER HOLE. LB5/HOLE

BARREL OPERATING LIFETIME HOUSE COST PER BARREL FOR PROJECTILE GUN PROJECTILE COST \$/PROJECTILE CPARL CSTPRJ

TOUT TYPEPF

WPL

INDICATES EXPLOSIVE TO BE USED OPTIONI-3-AMMONIUM NITRATE

```
JOR MATERIAL COST OF MAINTENANCE PERIOD FOR WATER JET (OR PROJECTILE) SYMMINTENANCE PERIOD JET NOZZLE DIAMETER INCHES
D JMM JM
DNOZZ
                   TIME HETWEEN MAINTENANCE PERIODS FOR WATER JET (OR PROJECTILE)
OTCUET
                   HO JPS
                   LENGTH OF MAINTEMANCE PERIOD FOR WATER JET (OR PROJECTILE)
DIMJET
                   TIME DURATION OF REPOSITIONING OPERATION FOR WATER JET
DTRUET
                   (OP PROJECTILE)
                                          HOURS
                   JET ENERGY REQUIRED PER VOLUME DE ROCK BROKEN
ENERGU
                  PROJECTILE GUN FFFICIENCY
FFFICIENCY OF MATER JET DEVICE
FTAGN
FTAJ
                  EFFICIENCY OF TRENSMITTING JET FRERGY FRERGY TO POCK
FTAIMP
                   MODE OF OPERATION O-CONTINUOUS JET-1-INTERMITTANT JET
MODEJ
                  MODE OF DETAILING NUMBER OF PROJECTILE GUMS
NUMBER OF WATER JETS OPERATING
PSI
NGUNS
                   NUMBER OF WATER OFFISHER
WATER OFT NOTTLE POESSURE PST
WATER OFT NOTTLE POESSYMIN
NUETS
PN07Z
                                                           PROJECTILEZMIN
                   PPOJECTILE GIN FT THE MATE
PRJPM
                   PULSE OUPATION FOR WATER JET SECONDS
TIME TO REPLACE MARRIE FOR PROJECTILE GUN
PROJECTILE SPEED FEET/SEC
PHESEO
TRARL
VELPR J
                   PPO ISCTILE VOLUME
AUTBHI
                                                 INCHES**3
                   PROJECTILE WEIGHT LAS.
ADVANCE OF TUNNEL REFORE REPOSTITIONING OF WATER JETTOR PROJECTILE)
MPRJ
KRJET
                   IS PEQUIPED
                        TPAIN/TRUCK AND SHORT HAUL MATERIALS HANDLING ACTIVITIES
COMMON /WHFELS/
                   PEAK ACCELERATION. EMPTY. MPH/H
AF
ΔF
                   PEAK ACCELERATION. FULL. MPH/H
                   MAXIMUM ACCELERATION: MPH/H
MAXIMUM LOADING APEA: FT
MINIMUM LOADING AREA REQUIRED: FT
XAMA
AMAXL
AVINL
                   DISTANCE METHERN SHITCHES. FT
CAPACITY OF CAP OR TRUCK. YOUR
HSI
CAPCAP
                   COST OF FUEL OF PORFR TO ORIVE TRAIN/TRUCK S/HOUR
CP
                   AVERAGE DECELERATION RATE. EMPTY. MPH/H
AVERAGE DECELERATION RATE. FULL. MPH/H
DF
ΩE
                   TIME TO ASSEMBLE CALIFORNIA SWITCH. HP
DTAS
                   DAYS RETHERN MAINTENANCE PEPIDOS. DAYS
TIME TO UNLOAD ONE THAIN. HE
COST OF CONVEYOR FOULPMENT/FOOT OF EXCAVATION
COST OF SUPPORTIME STRUCTURE FOR CONV-LOAD/FOOT OF EXCAVATION
EFFICIENCY OF LOCOMOTIVE OR POWER TRAIN
DTMA
DTIL
FCCNEO
FCONSS
                   COST OF LOCAMOTIVE HALL
FLOCO
                                                                S/HOUR USF
                   COST OF MUCK CAR SCHOOL OF USE COST OF MAINTENANCE SHOP FOR PAILS
EMPICKO
                                                                            S/FOOT OF FXCAVATION
ESALTCH
                   COST OF SWITCH
                                            */FUNT OF EXCAVATION
                   COST OF TRACK MATERIALS SYFOOT OF EXCAVATION COST OF UNLOADING FOUIPMENT FOR PAILS SYFOOT
 FTRACKM
                                                                             S/FOOT OF EXCAVATION
FUNLOAD
                   FUEL CONSUMPTION RATE. GALZHP-HP
FC
FR
                   ROLLING PESISTANCE FACTOR
                   TPACTION COFFEICIENT
PEAK HP AVAILABLE FOR ACCELERATION. HP
FI
 HPA
                   POWER CONSUMPTION PATE PERK ACCEL FMPTY HP
 HPFA
 HPFV
 -PFA
                   POWER CONSUMPTION PATE - PEAK ACCEL - FILL - HP
                   POWER CONSUMPTION RATE. PEAK VEL. FULL. MP
RATED HP FOR CONTINUOUS OPERATION. MP
FLAG TO INDICATE STATUS OF HORING MACHINE
 HPFV
 HPV
 THORE
                   FOUTVALENCE (TIROPE . MHORE)
                   (SEE APPENDIX TV-DESCRIPTION OF CONTROL PROGRAM FOR LAYOUT TUNNEL) INDICATES WHICH SWITCH TRAIN I-IS IN
```

[Sw(25)

```
LOCO
LOUE
MAXLD
                 NUMBER OF AXLES PER MUCK CAP
MC
ML
                 INDICATES UNITIZED(2) OF CONTINUOUS(I) CONVEYOR SYSTEM
MLTYP
                 NUMBER OF CAPS PER TRATH
NUMBER OF POINTS IN TOURVE-TOURVE TARLE
NCARS
NPOINT
                 MAXIMIN NUMBER OF TRAINS IN DISCHARGE AREA INITIAL NUMBER OF TRAINS IN SYSTEM MAXIMIN NUMBER OF TRAINS IN MAINTENANCE AREA
NTD
NTINIT
                 MAXIMUM NUMBER OF TRAINS AVAILABLE
NTMAX
                 DISTANCE CRITERION FOR NIMILE AND NIMILED NIMBER OF TRAINS PER MILE FOR X-LE-XP NIMBER OF TRAINS PER MILE FOR X-GT-XP
10
NTMILP
NTMLPP
                 TRACK OPTION...1=STUGLE. Z=DOUBLE NUMBER OF TRAIN/TRUCK AT FACE
NTRACK
NUMED
                 VOLUME CAPACITY OF THATH. FT .. 3
OUC
                 NUMBER OF MEN IN LABOR CATEGORY I (I=I+IO) FOR RAIL SYSTEM
RAMENCES
                 HOURLY COST OF WAN IN LAHOR CATEGORY I FOR RAIL SYSTEM
PACST(I)
                 LENGTH OF CALTEOPHIA SWITCH. FT
                 TRAIN STATUS (HOLLERITH)
MAINTENANCE PERIOD FOR SHORT HALL MATERIALS MANDLING HOURS
STATUS (34)
 TCCV
                 TIME BETWEEN MAINTENANCE PERIODS FOR SHORT HAUL MATERIALS
TMCV
                 HANDLING HOURS
DURATION OF MAINTENANCE PERIOD FOR TRAINS/TRUCKS
 TMAINT
                 VELOCITY ENTRY 1" VELOCITY-VS-TRACTIVE FORCE TABLE
 TCURVX (20)
                 TRACTIVE FORCE FUTRY IN VELOCITY VS-TRACTIVE FORCE TABLE
 TCURVY(20)
                 WEIGHT OF EMPTY TRUCK. TONS
 TWE
                 VELOCITY IN DISCHARGE APEA. MPH
 Vn
                 VELOCITY IN SWITCH. MPH
 VS
                  PEAK VELOCITY. FYPTY. MPH
 VF
                  PEAK VELOCITY. FILL. MPH
 VF
                  MAXIMUM VELOCITY ALLOWED FOR TRAINS. MPH
WEIGHT OF EMPTY MICK CAPS. TONS
 VMAX
 ₩C.
                 REASON FOR STOPPING (HOLLERITH)
MAXIMUM MUCKING PATE TONS/HOU
WEIGHT CAPACITY OF THAIN. TONS
 WHY (24)
                                              TOUS / HOUR
 WM구
 WUC
                  WEIGHT OF LOCOMOTIVE. TONS
 WL.
                  SPEED OF MOVING CALIFORNIA SWITCH+ FI/HR
 INS
```

COMMON/CONVEY/ CONVEYOR (SHORT AND LONG HAUL) AND MACHINE LOADER ACTIVITIES .

```
MUCK FLOW CROSS SECTION. FT**2
ΔR
                     MAXIMIM CROSS SECTION OF CONVEYOR STRUCTURE. FT... AND CONVEYOR LOADER HOUPLY COST OF MAN IN LARGE CATEGORY I (I=I.10) FOR CONVEYOR LOADER
ACM
CVMEN(I)
CVCST(I)
                     JOR MATERIAL COST FOR LONG HAUL CONVEYOR MAINTENANCE
DMAINT
                     TIME TO DO A HELT SPLICE (LONG HAUL)
NTRS
                     TIME RETWEEN MAINTENANCE PERIODS FOR CONVEYOR (LONG HAUL)
LENGTH OF MAINTENANCE PERIODS FOR CONVEYOR (LONG HAUL)
DTCR
                     TIME TO MOVE MICKERS TO THE FACE LEDR MACHINE LOADERS AND
DIMI
                                          H10175
                     SHOVELS) HOURS TIME TO MOVE MUCKERS AWAY FROM THE FACE (FOR MACHINE LOADERS
DIMO
                     AND SHOVELS

HOURS

TONNAGE HAULED HEFORE MAINTENANCE SCHEDULED FOR CONVEYORILONG

HAUL) (ALTERNATIVE TO MAINTENANCE CRITERIA TO DICH) TONS

MOTOR AND REDUCTION EQUIPMENT EFFICIENCY
                     AND SHOVELS
                                                  HOURS
DWM
                     LENGTH OF FFEDEN FOR CONVEYOR SYSTEM (LONG HAUL) FEET MAXIMUM LENGTH OF FFEDER REFORE BELT SPLICE IS NEEDED (LONG HAUL CONVEYOR) USED IF NGEO (GEOMFTRY INDEX) IS 2 FEFT
EE
FLM
                     TOTAL HENENGTH TO PUN CONVEYOR FLAG FOR BELT SYSTEM LONG HAUL
                                                                          I-SURGE RIN CAPACITY EXCEPDED.
LNSUPG
                      0-5 PROF BIN CAPACITY NOT EXCEEDED
```

```
FLAG FOR RELIZEATE EXTENSION 1-EXTENSION SHUT DOWN GEOMETRY MODEL INDEX FOR CONVEYOR SYSTEM 1-CONTINUOUS EXTENSION ASSUMES FEEDER EXTENDS FULL LENGTH OF
VEXON
NGEO
                                     CONVEYOR
                                     C-CONTINUOUS EXTENSION ASSUMES FEFORE CONVEYOR EXTENSION TS SMALL ( (F1=0) AND EMPTIFS INTO SMAFE DIRECTLY
                                    3-CYCLIC EXTENSION USING MINIMUM AND MAXIMUM ALLOWABLE DISTANCE FROM FACE FOR PELT
                                     GEDWETRY MODEL IMPEX FOR TRAIN/TRUCK SYSTEM
NGEO
                                     1-CONTINUOUS EXTENSION+2-CYCLIC FXIENSION
                                     T-CONTINUOUS EXTENSIONS-CITCLE PATENDARY
STATUS VARIARLE FOR LONG HAUL CONVEYOR SYSTEM
T-SUPGE RIN FXISTS FOR FXCESS MUCK+0-NO SURGE HIN FOR EXCESS
NSURGE
                                    MUCK (LONG HAUL CONVEYOR )
FOUTVALENCE (PR.PC) SEE COMMON/ALL/
PC
                                     AVENAUE MUCKING MAIF CAPABILITY OF MACHINE LOADER FEET**3/HOUR SURGE RIN CAPACITY FEET**3 VOLUME OF MUCK TO BE TAKEN OUT OF DR PUT IN SURGE RIN FEET**3
1211M-4
OC
DE
                                     PEAR VOLUME RATE OF CONVEYOR. FT. 3/HR
QP.
SHIN
                                     DISTANCE HETHERN FACE AND CONVEYOR STRUCTURE. FT.
                                     TIME TO SWITCH WHITS WHEN USING MACHINE LOADERS ANDSHOVELS
STIME
                                      WITH A UNITIZED SYSTEM OF LONG HAUL
                                                                                                                                                                   HOURS
VRI
                                      BELT SPEED. FT/MIN
                                     RELT WINTH. TY
IPW
                                      ESTIMATED PEAK TONNAGE RATE. TONS/HR
WP
                                      RAIL/HELT EXTENSION RATE. FT/HR
XΕ
                                           FOUTVALENCE IXE-XOET
                                     FLIGHT LENGTH. FT
XLF
                                                         GROUND SUPPORT ACTIVITIES
COMMON /GPNO /
                                                                                                                    $/HOUR
                                      COST OF ROCK BOLT ORILLS
 FRANRI
                                     COST OF SHOTCHETE STANDARY THE HETHER GROWN SUPPORT MAINTENANCE PERIODS HOURS
ESCPLA
 GDCW
                                      NUMBER OF MEN IN LAHOR CATEGORY I (1=1+10) FOR GROUND SUPPORT
 GMEN(T)
GCST(1)
                                       HOUSLY COST OF MAIL IN LANGE CATHGORY I FOR GROUND SUPPORT SYSTEM
                                     LENGTH OF GROUND SUPPORT MAINTENANCE PERIDDS HOURS
GROUND SUPPORT FEET LOST DUE TO ROCK DISINTEGRATION STOPPED
MAUGR GROUND SUPPORT TYPE BEING USED 1-NO SUPPORT-1-HOCK BOLTS.
GSFTDO
 SELDS
                                      3-SHOT COFTE . 4-STEEL SETS . 5-LAGGING
                                     SETSOFTHE SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SUPPORT AND IT IN ADDITIONAL GROWN SUPPORT TYPE BEING USED I NO SUPPORT PROCK BOLL TO SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOFTH SETSOF
 145
 MAXPSS
 PSST (60.0)
                                  PHARMETITATION FOR FACH ROD MAXIMUM OF 60
RATE OF INSTALLATION OF ROCK ROLTS(ROCKROLTS/HDURS)
RATE OF INSTALLATION OF SHOTCHETE VARDS*3/HOURS
RATE OF INSTALLATION OF STEEL SETS/HOURS
COST OF STEEL */LB
COST OF SHOTCRETE $/YARO*3
 RATEUR
 PATESC
 RATESS
 UCS
 HOSC
                                                          ENVIRONAENTAL CONTROL ACTIVITIES
 COMMON /FNVC /
                                      MAXIMUM ALLOWARLE CONCENTRATION OF GAS(N) ( PARTS PER 10006 BY VOLUME DEFAULTED
 AMCCION
                                      CONDUCTIVITY OF AIR
                                                                                                 STUZHR FT DEGE OFFAULT=.0147
 CKA
                                     SPECIFIC HEAT OF AIR STUVEN OFF.

SPECIFIC HEAT OF AIR STUVEN OFF.

COST OF VENTILATION PLANT $/FORT OF EXCAVATION

FRICTION FACTOR FOR DUCTING OFFAULT=2.000-9

FRICTION FACTOR FOR TUNNEL OFFAULT=1.500-R

HEAT ADDED TO TUNNEL IN DI FROM MACMINERY RIU

MAXIMUM NO. OF MEN IN TUNNEL AT ANY TIME DEFA
 CPA
 EVENTP
 FKN
 FKT
 HEAT
```



MAXMEN

DEFAULT =0

```
MINIMUM AIR VOLUME PATE PER DIESEL HORSFPOWER PFO.RY LAW(CFM)
QD
                              DEFAULT=106...334*TOTHP
DESIGN REQUIREMENT OF AIR VOLUME RATE (CFM)
VOLUME RATE OF TOXIC GAS(N) ENTERING TUNNEL (CFM) DEFAULT=0
MINIMUM AIR VOLUME RATE PER MAN REQUIRED BY LAW (CFM) DEFAULT=200
COST OF MECHANICAL REFRIGERATION PLANT $/RTU DEFAULT=2.0E-6
AMBIENT TEMPERATURE AT PORTAL OFG.F DEFAULT=0
DESIGED AIR TEMPERATURE AT TUNNEL FACE DEG.F DEFAULT=0.
MAXIMIM TOTAL DIFSEL HOPSEPDMER IN TUNNEL AT ANYTIME DEFAULT=0
                               DEFAULT=106. .. 334 TOTHP
ONR
06(10)
DM
REFRAT
TA
                               ROCK TEMPERATURE DEGREES F
MAXIMUM VELOCITY OF AIR AT TUNNEL FACE (FPM) DEFAULT=1000
MINIMUM VELOCITY DE AIR AT TUNNEL FACE (FPM) DEFAULT=50
NUMBER DE MEN IN LAROR CATEGORY I (I=1.00) FOR VENTILATION AND
CODILING SYSTEM
TOTHP
TROCK
VAMAX
VAMIN
VCMEN(1)
                                HOUPLY COST OF HAM IN LABOR CATEGORY I FOR VENTILATION AND
VCCST(1)
                                COOLING SYSTEM
DENSITY OF AIR
                                                                       LAS/FT ** 3 OFFAULT= . 075
```

COMMON/ PERENMI PERFORMANCE OF SYSTEM

DMHT IM	CUMULATIVE DOWN TIME OF MATERIALS MANDLING ACTIVITIES HOURS
ECOTIM	SUMIN TAIRE DURN LINE OF PHAINCHMAINE COMPACT ACTIVAL
ECUT IM	CUMILATIVE UP TIME OF ENVIRONMENTAL CONTROL ACTIVITIES HOURS AVERAGE ADVANCE DIRING MAXIMUM ADVANCE DAY FFET/OPERATING MOUR
GADV	POCTATON OF EACE FOOM PORTAL AT START OF MAX ADVANCE UNTER
GREG	NIJURER OF DAYS SINCE EXCAVATION STARTED AT END DE MAX ADVANCE DAY
GDAY	HEADING POSITION (FFET) AT END OF MAXIMUM ADVANCE DAY
GEND	HEATING POSITION (PFET) AT END OF PROPET ACTIVITIES HOURS
GSDTIM	CHAIR TIRE DURN TIME OF CHOOMS SUPERIOR RELATION
GSUTIM	CHAIR TIME IS TIME IN CADOMI SOFFORI MOINTAIN
ROOT IM	
ROUT IM	WHICH ATTUE IS TIME IN MOCK DISTRICOMMITTING ACTIVATIONS
UMHT IM	CUMULATIVE UP TIME OF MATERIALS HANDLING ACTIVITIES HOUPS

COMMON /MONEY / COST ITEMS

DJM	JOR WATERIAL COST FOR SETTING CHARGE. \$
DJMRM	CHARLE ATTUE COST FOR MATERIALS HANDLING MAINTENANCE
DJMRMM	JOR MATERIAL COST FOR ROCK FRAGMENTATION MAINTENANCE
DUMEC	CHAIR ATTAK COST OF JOR MATERIALS FOR ENVIRONMENTAL CONTROL
DJMGS	COST FOR GROUND SUPPORT MAINTENANCE S/MAINTENANCE PERIOD
HHMLD	JOR WATERIAL COST FOR MATERIALS HANDLING. & TOTAL
DUMSD	IOD MATERIAL COST FOR ROCK FRAGMENTATIONS & TOTAL
DMAINT	MO MATERIAL COST FOR RELT MAINTENANCE & SMAINTENANCE PENTITO
ROTIME	CHAIR ATER LARGE TIME USED FOR ROCK FRAGMENTATION MINORS
HT IME IT)	CUMULATIVE LARGE TIME USFO FOR MATERIALS MANDLING MOUNS
W. L. C. 117	TETELAROD TIME LISEO FOR LONG LAUL SYSTEM
	TERM AROR TIME USED FOR SHORT HAUL SYSTEM
ECTIME	CINITIATIVE LABOR TIME USED FOR ENVIRONMENTAL CONTROL MOUNS
	CUMULATIVE LABOR TIME USED FOR GROUND SUPPORT SYSTEM HOURS
GSTIME	ADE INDICES
5651 Av.	TOTAL COST OF PLANT AND FOULPMENT FOR ENVIRONMENTAL CONTROLS
ECPLAN	TOTAL COST OF PLANT AND EQUIPMENT FOR GROUND SUPPORT
GSPLANT	TOTAL COST OF OLANT AND FOLITOMENT FOR MAILY INLD PANULING
HPLANT	COST OF MAINTENANCE FOR INTEGRATED CONVEYOR STABILITENANCE PERIOD
JMCA	JOB MATERIAL COST FOR TRAIN/TRUCK MAINTENANCE SAMAINTENANCE PERIOD
JMMHM	PERMANENT MATERIALS COST FOR GROUND SUPPORT & TOTAL
PMGS	PERMANENT MAIEPIALS COST FOR GREAT FOR PROK DISTRIFGRATION \$
ROPLAN	TOTAL COST OF PLANT AND EQUIPMENT FOR ROCK DISINTEGRATION 5

COMMON /LABOR/ LABOR COSTS AND MEN

ROMEN(1.J) INTO LARGE CATEGORIES FOR ROCK FRAGMENTATION INTO MAKE OF HEN IN LARGE CATEGORY T

II. INPUT FOR LAYOUT TUNNEL

A. CARD IMAGES

	5 10 15 20 25 30 35 40 45 50 55 60 45 70 75
CARN	5 10 15 20 25 30 50
1	90PF PATLS
2	SGENEPL PARTIES - TOPE TOPE TO THE TOPE OF
3	#GENEPL NET NE
4	OPPCT=-1-REPORT=1PR=-02.
5	xn15CH=12000
5	SKEI.7
- 7 A	\$RORF 22 25 25 25 25 25 25 25 25 25 25 25 25
10	R(12)= 1436.75.19.5.42.25.4547.75.50.5.53.25.5654.75.61.4375.
• "	
CARD	5 10 15 20 27 30 30 30 30 30 30 30 30 30 30 30 30 30
11	
12	PRM=6002PM=60TC=1.4TR=.5.FR0PF0=34.6.FTPAMS=3.4.,NJMRMM=[00
14	RN=79.01 6=1 75.011 CO-2001 1 7
- 15	HNCST=4.46.5.37.4.07.7.11.
16	CPC=R0.xCPC=3.3R
 7 -	KEND.
18	RPAILS
19	NUMLD=7. NVFHCL=7.NTMAX=4.NTM1LP=0.NTMLPP=1.NCARS=10.CARCAP=7NC=4.05.MC=2.
20	AANHUE SOUTHER SOUTH TENERS OF THE TENERS OF
	E 10 19 20 75 10 35 40 45 48 55 A0 65 76 75
CADO"	7 10 17 17 17 17 17 17 17 17 17 17 17 17 17
51	The second of the second secon
27	
21	2.2. 一点大点:"我没有,我们就说了你们就是是有什么,你是我是是没有到你上来看我的的。我们也是有什么。""我们也是有什么的。""我们也是一个一个一个一个一个
74	
115	THAT COUNTY - TERTIFICATION - TERTIFICATION - THAT COUNTY - TERTIFICATION - TE
. PV.	
27	PAMFN=2.2.1.2.1.2.1.1 RACST=7.70.7.20.7.70.7.20.8.00.5.32.7.11
24	FUNLO4=.50.FRM41N=1.00.CP=.14.JMMHM=50.
- 30 - 30	(FND
30	
	5 10 15 20 25 30 35 40 45 50 55 60 65 76 75
CARD	5 10 15 70 75 30 33 40
31	\$LOADER .
32	CVMFN=1.1
33	/VCST=7.20-7.20 WLTYP=1.WMR=175TCCV=312TMCV=8ECONFQ=4.65.FCONSS =4.00.JMCV=50.
34	
36	
37 37	
38	
70	GCST=7.00.7.20.
40	FSCPLA=10.00 .DJMGS=50RATESS=5.
P-1MAG	SES
	5 10 15 20 25 30 35 40 45 50 55 60 65 70 75
CAPD	5 10 15 20 27 30 72 40 40 40 40 40 40 40 40 40 40 40 40 40
41	\$FND
62	SFNV1PC
12	VCMEN=1 • 1 • 2
44	VCCST=R.02.7.11.7.00 ·

B. PARAMETER VALUES BEFORE INITIALIZATION BY THE SUBROUTINES

SCENEDL"		1. Appropriate (see 10.1. 10.1	
0	E	0.179176+07+	
ਜ	2	0.15.00.	
x	=	0.12054E.05.	
XMAX	=	0.170925.05.	
·	=	0.0.	
THAX		0.25F.02.	
DTPRUT	=	9.15.01.	
ŠK	*	0.176.01.	
PQ	7	0.2F-01.	
OPPCT	=	0.15.00.	
PEPORT	=	0.15.01.	
MESCH	•	6.12F-05-	
	•	0.0+	
CPSPC	-		

FRORE	and the state of t
CL	= 0.1F.07. 0.4E.06. 0.1E.06.
CPC	= 0.AF+02+
DTA	= 0.176F+03+
DTC	= 0.14F.01.
ntcn	= 0.245.02.
חזס	= 0.0.
DT4	= 0.56F+0]+
KK	= 29.
PRM	= 0.6F+03+
R	= 0.2875F+01+ 0.575F+01+ 0.8625F+01+ 0.115F+02+ 0.14375F+02+ 0.1775F+02+ 0.20125 0.2575F+02+ 0.295F+02+ 0.3125F+02+ 0.34F+02+ 0.3675F+02+ 0.495F+02+ 0.4225F+02 0.4775F+02+ 0.505F+02+ 0.5325F+02+ 0.56F+02+ 0.5875F+02+ 0.614375F+02+ 0.63937 0.681875F+02+ 0.703125F+02+ 0.724375F+02+ 0.736875F+02+ 0.749375F+02+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+
RC.	= 0.9F.n0.
RPM	= 0.4F+0].
TR	= 0.5F+00+
XCPC	= 0.338F+01+
EROPEO	3 0.74AF+0?+
FTRANS	= 0.34E.01.
ММВМГИ	= 0.16.03.
ROMEN	= 0.1F+01+ 0.4E+01+ 0.1F+01+ 0.1F+01+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+
ROCST	= 0.845F+01+ 0.532E+01+ 0.802E+01+ 0.711E+01+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+
SEND	

- SPATES	
AF	± 0.00
AF	= n.n.
AMAK	E 0.72F.01%.
AMAYL	± 0,274F+03.
AMTNL	= 0.27AF.91.
ASL	E 0.865F.04.
CARCAP	= 0.7F•n]•
CP	z 0.14F.0A.
	± 0.7>F.03.
	■ 0.72F.03.
	= 0.11F.0Z.
DTHA	3 0.91AF+00.
	= 0.17F.AD.
NEVEN	s 0·
NGEO	7 1
NEKON	= 0·
XOF	= 0.125.02.
AR	= 0.0.
VRI	= 0.0.
<u> </u>	± 0.755.02.
FL	E 0.00
FC	7 0.00
FIE	= 0.0.
	*** 0.0.
HPA	× 0.145.63.
HPFV	= 0.0.
HPET	E 0.0.
HOFV	= 0.0.
нрга	3 0.0.

The second

Autorial I

A Liverieur 4

3 --- Jack 5

Management |

1

1

```
= 0.1E+03.
HPV
    = 1.
LOCO
MC
    = 2.
    = ?•
ML
    = 10.
NCARS
NPOINT = .0+
 NTD = 1.
NTM = 2.
NTMAX = 4.
X,5 = 0.1E+02+
NTMILP = 0.
NYMLPP = 1.
NTPACK = 1.
    * 0. TAF . 0.3.
0.0. 0.0-
 TMAINT = 0.2E.01.
    = 0.0.
TWE
     = 0.1E-01.
VD
    = 0.7F+01+
 75
     = 0.0.
VF
VF"
    = 0.0.
     = 0.178.02.
VHAX
     = 0.405F.0)T.
WC-
     = 0.1F.02.
----
     # 0.2F.+04+
XDS
WAXED # T.
NVEHCL # 1.
NUMSHT *
      SWITCH
```

```
MLTYP = 0.
  = 0.0°
445
FLOCO = 0.18F.01.
FMICKC # 0.17F.00.
FTD4CK = 0.75F+01.
FSWITC # 0.00
FINE DA ... A. AF . BO.
FRMATH = 0.1F.P.
Junua = 0.4F.02.
"NilAFU" = "J.
DANEN = 0.25-01. 0.25-01. 0.15-01. 0.25-01. 0.15-01. 0.35-01. 0.15-01. 0.0. 0.0.
RACST = 0.776.01. 0.726.01. 0.776.01. 0.726.01. 0.86.01. 0.5326.01. 0.7116.01. 0.0.
SENO
```

SLOADER		
AR FA	3	0.0.
VAI	2	0.0.
54	=	0.756.02.
TCCV	=	0.3125.03.
THCV	2	0.AF.01.
AMB	=	0.175F.03.
MLTYP	.E	1.
ECONFO	=	0.4655+01+
FCONSS	=	0.4F-011-
JMCV		0.56.02.
CVMFN		0.15.01. 0.15.01. 0.0. 0.0. 0.0. 0.0. 0.
CVCST		0.725.01. 0.725.01. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0.

Emiliable L

- Participation

h-spellings-proper

Parameter of the last of the l

FUBUIND		BORGONIE I MINIE DE 1900 F ample (1-10 00 CTT) I de 1900 Metro - Matrice Metro Metr
(Irq		0. TF 0.00 .
(म. ५८	•	n. 27F • 11Z •
RATFRA		0.46.01.
RATESC	7	0.1755.07.
PATES	±	0.5F.0].
MÄKPSS		0•
FRANCI		0.755.01.
FSCPLA	-	0.15.0>.
DUMES		1.56.02.
CUUA		0.0.
GSETOO	3	0.0.
GMFN		n. arente n. 2rente n. 3. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0
GCST	-	9.75.01. 0.725.01. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0.
ACNO.		

SENVIRC		
EVENTE		0.16.01.
-		25.
TOTHE	•	n. W-03.
TA		A.AE-82-
эн	•	1.0.
nn	•	n.o.
-		1.0.
VARAV	•	n,6-
10	٠	0.00
WA.	•	0.0.
CPA		M.O.
CYA	٠	0.0.
REFRET		
- Jug	-	3.8. 0.0. 0.0. 8.0. 0.0. 0.0. 0.0. 0.0.
VCHFN	=	0.1F-01- 0.1F-01- 0.2F-01- 0.0- 0.0- 0.0- 0.0- 0.0- 0.0-
VCCST	=	0.902F+01+ 0.711F+01+ 0.7E+01+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+
Chilmb	- 2	0.0•
FRT	3	0.0.

germanand

Signatural Control

THANKL CORS SECTION = 131.042H SO FT HPFV HPFV PATE PADANFTERS -12.000 12.000 742.170 916.050 50.500 145.000 36.642 29.687 TRAIN CAPACITY = 1890.0000 CURIC FFFT AND 94.5000 TONS RAIL FXTENSION - FXT. RATE = 12.00 SWITCH MOVE PATE = 2000.00 DISTANCE RETWEEN SWITCHES = RAIL MAINT. PARAMETERS - TIME TO REPAIR = 2.00 COST OF MATERIALS = 50.00 DAYS RETWEEN MAT דבחפפווף העוורפה צפאיין פפ INTERFERENCE THITEHERS. CHINN ANTIF HAZODOUPLEU TERRORES SPACING BUU FYCAVATION LENATE FF EFNGTH- AVET TYPE TIT HE GLIES TT PANCESC 4:44 1:00 0.00 F.04 0.00 95.99 5.00 949999,00 5.00 Name. 00.00 10.00 0.00 1,00 0.00 5. NA 4.40 2.00 99.00 3.4n 3.4n 1:22 A.00 75.00 0.0* 0.00 5.00 4.00 N. 10 1.00 0.00 Fell W 75.00 7.00 5.07 # ; p# 7.00 -10± 3.00 #. 0= #. 0A 4,44 A.00 50.00 5.00 *** 7.90 9.00 0.00 50.00 1.00 6,00 m.:00 # . nn } . nn 2.00 50.00 B.00 4.00 4.00 A. A.A. 5,46 3,00 25.00 5.09 0.08 3,00 1,00 1,00 H. 114 2.00 25.10 4.00 4.00 W. 0.4 4.00 1,45 4.00 25.00 = Lnn 7, 55 7, 55 2:00 6.06 5.00 1.00 4.00 7,14 0.00 0.00 7,68 4.00 0.00 2.00 7,68 A. 08 *.00 2.6 d. nn G. RA NOTE . FYCAVATION PROCESS =5 INDICATES ANY PROCESS OTHER THAN THOSE IN TAMLE

C. PARAMETER VALUES AFTER INITIALIZATION BY THE SUBROUTINES

SEENERL			
n	=	0.129176.02.	
ΠŢ	=	0.15.00.	
x .	=	0.120546.05.	
XMAX	=	0.170926.05.	
Υ ·	=	0.0.	
THAX	=	0.25F+02+	
DTPRNT	=	0.1F+01+	
SK	-	0.175.01.	
PR	=	0.25-01.	
OPPCT	=	0.1F+00+	
REPORT	=	0.15.01.	
XDISCH	7	0.125.05.	
E	=	0.0.	-
KEND.			

```
SRORF
CL
    = 0.1F+07+ 0.4F+06+ 0.1E+06+
      = 0.9F.07.
DTA
      = 0.174F+03.
      = 0.14F.01.
DTC
DTCD
      = 0.245.02.
DTD
DTM
    = 0.666+01.
KK
      = 29.
PRM "
     = 0.4F+03+
      = 0.9F+00+
RC
      = _0.6F.n].
RPM
TR
      = 0.5F+00+
      = 0.330F.01.
ACPC
FRORFO = 0.344F+02.
FTRAMS = 0.74F+01+
DJMRMM = 0.1F+03+
      = 0.1F+01+ 0.4F+01+ 0.1F+01+ 0.1F+01+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+
      = 0.94KF.0]. 0.532F.0]. 0.P02F.0]. 0.71[F.0]. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0.
ROCST
SEND
```

SRATES		
AF	=	0.0.
AF	=	n.n.
AMAX	=	n.72E+03+
AMAXL	=	0.276F+03·
AMTHL	Ξ	0.276F+03.
ASL	=	0.8K5F+04+
CARCAP	7.	0.7F+01.
CP	=	0.14F.00.
DF	=	0.725.03.
DF	=	0.72F+03+
DTAS	=	
DTMA	#	0.9145.00.
DTU	=	0.17F.00.
NSWCH	- E	0.
NGEO	Ξ	1.
NEXON	=	
XDE	=	n.12F.42.
AR	1	: 0.0.
VAI	7	0.0.
- SM		0.755.02.
EL	-	, 0.AF+00.
FC	•	: 0.455F-01.
FR		× 0.0•
FT		= 0.25f.00·
HPA		≥ 0.14F • 03 •
HPEV		= 0.29KAK7A1909005F+02•
HPFA		± 0.0.
HPEV		* 0.2968A7A1909005F+02•
HPFA		= 0.0•
"HPFV"		- 0.3KK4[94]909005F+02-

```
= 0.1F+03.
    = 1·
LOCO
40
    = 2.
4L
    = .2.
NCARS = 10.
NPOINT = 0.
NTM = 2.
NTMAX = 4.
  = 0.1F+02.
NTMILP = 0.
NTMLPP = 1.
NTRACK = 1.
SL = 0.36F+03.
0.0. 0.0.
TMAINT = 0.2F+01+
--- TWF ------
Vn = 0.1F-01.
   = 0.2F+01.
------ + 0.12F+02+
VF = 0.12F+07.
VWAX = 0.12F+02.
WC = 0.405F.01.
 WL = 0.1F+07.
X75 = 7.25+04+
MAXED ... = 3.
 NVEHCL = 3.
NIMSAY = T.
```

ISTA	-	C. r. n. o. n. a. o. n. n. n. n. n. n. n. n. n. n. n. n. n.
TPOS		0.114605+05+ 0.114605+05+ 0.114605+05+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0
TSPN		1.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0.
		0.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0. 0.0
KSTOP	-	1. 101. 192. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0.
WE TYP	Ŧ	1 to the second
ių vi J	=	0,1755.03.
FLOCO	=	0.155.01.
-	-	0.175+00+
		9.755.01.
ESHITC	= .	n.n.
FHMI OA	÷	ρ _* κε•ρή•
FRMATN	=	7.15.01.
Inner	-	0.55.02.
dimit o	7	3.
154	=	= 1 · 1 · 1 · 1 · 1 · 1 · 1 · 1 · 1 · 1
פאארין	Ŧ	- 0.2F+01+ 0.2F+01+ 0.1F+01+ 0.2F+01+ 0.1F+01+ 0.3F+01+ 0.1F+01+ 0.01F+01+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+ 0.0+
FACST	=	= 0.775.01. 0.725.01. 0.775.01. 0.725.01. 0.85.01. 0.5325.01. 0.7115.01. 0.0. 0
<u> </u>		



| SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND | SEND |

EVENTP = 0.15.01. MAXMEN - 40. TOTHS = 0.3E+03+ TA = 0.6F.02. = 0.2F.03. ηη = η.2η62F.13. VAMIN = 0.55.12. VAMAX = 0.15+04+ TD = 0.8F+02+ = 0.755-01. CPA = 0.24F.00. = ^.147F+01. PFFRAT = 0.2F=05. $A^{14}C = 0.0 \cdot$ CDIIMD = 0.0. FKT = 0.15F-07. SEND "

III. PROGRAMS AND SUBROUTINES

A. PROGRAM GEOMOD

```
PAGGRAM GEUMOD
                             GENERATES GEOLOGY FILE
С
C
       COMMON /10COM/ NLINE . NPAGE
С
       DIMENSION SURF (30.30.7).PROP(6.25).SPEC(7).INDEX(25).BUFF(27)
    10 FORMAT (1H1.//////////25X.86HEEEEEE X
                                                                CCCCCC
              V AAAA TITTITI 1
X X C A A V
                                                                  N./.25X.86HE
                                                000000
      AV
      ь
                                                                   AAAAAAA
                  N N N. /. 25x . BOHEEEE
                                                   X
                                                         C
      C
              Ω
                                                          N N./25X.86HE
              AAAAAAA
                                                  0
              D v
                                                        A
                                                                                    ٥
                                                A
            C
      Ε
                                                  CCCCCC A
                                                    NN . / / / / .
      G
                                 000000
                                             N
                                                                          000000
                                                     45X+40HM
                                                                    М
                                                MM 0
D 0 EL
                                                             0 D
                                                                         0
                  EEEEEE L./.45X.40HMM
       1 00000
                                                                   L+/+45X+40HM
                                                                             Ł
         L DDDDD EEEREE LLLELLL.///////>/27X.14HPREPAREO FOR .59X
M.4HEY 9//.14X.4UHUNITED STATES DEPARTMENT OF THE INTERIOR.34X.28H
NGFREHAL KESEARCH CORPONATION.//.26X.15HBUREAU OF MINES.50X.21HWASH
01.GTON OPERATIONS.//.17X.34HBUILDING 20. DENVER FEDERAL CENTER.35X
P.32M1501 WILSON BUULEVARO. SUITE 700.//22X.24HOENVER. COLORADO 8
UD.255.43A.25HARLINGTON. VIRGINIA 22209.///.53X.30HUNOER CONTRACT N
       RUVEER HOLLOZ331
C
       NI 155 = 999
       NPAGE = 0
       96000H5500
       READ (30.20.EN0=30) TAGI.TAG2. (SPEC(1).1=1.7)
       60 TO 50
       00000
       33384LDC5400
       1- 40 20 . TAG1 . TAG2 . (SPEC(1) . 1=1 . 7)
       1F (EGr +49) 30:50
C
       ....
   20 FORMAT (2A5.7F10.0)
    30 PHINT 40
    -0 F MMAT (1H1.31(1H+).68H AGNORMAL ENDING - END OF INPUT FILE REACHE
      -D - EXECUTION TERMINATED .32(IH*))
    45 PHINT IU
       PHINT 10
   CALL EXIT
       -- 11.7 - 10
    60 1F (TAU1.EQ.SHOEULO) GO TO 60
    PHINT TO TOWART (141-13(144) -104H THE FIRST CAME HAS TO BE A GEOLOGY CARD -
      - PLEASE REFER TO PROGRAM OCCUMENTATION - EXECUTION TERMINATED .
      - 13(1m+1)
       5772
    60 1.1=5-EU(1)
        SCALEX=SPEC(2)
       1,7=5PEC(3)
        SCALEY=SPEC (4)
       90 F , FMAT (//.26x.2A5.7F10.4)
 1 100 MEAU (10.20.END=30) TAGI.TAG2. (SPEC(I).I=I.7)
```

```
*****CDC6400
С
  100 READ 20. TAG1.TAG2.(SPEC(1).1=1.7)
       IF (EOF+49) 30+110
  110 CALL PAGER(2)
       PRINT 90. TAG1.TAG2. (SPEC(1).1=1.7)
       NLINE=NLINE+2
C
       IF (TAGI-NE. SHGEOLO) GO TO 130
  PRINT 120
120 FOPMAT (1H0.38(1H+).58H ERROR - TWO GEOLOGY CAROS PRESENT - EXECUT
-10N TERMINATED .37(1H+))
       GO TO 45
  130 IF (TAG1.NE.SHSURFA) GO TO 160
      K=SPEL(1)
       *****85500
C 140 READ (30.20.ENO=30) TAG1.TAG2. (SPEC(1).1=1.7)
       *****COC6400
  140 READ 20. TAG1.TAG2.(SPEC(1).[=1.7)
IF(EOF.49) 30.145
C
  145 IF (TAG1 .NE. 5H CALL PAGER (2)
                              ) GO TO 110
       PRINT 90. TAG1. TAG2. (SPEC(1), I=1.7)
       NLINE=NLINE+2
       I=SPEC(I)
       J=SPEC(2)
       IF (1*J.LE.0) GO TO 150
SURF(1.J.K)=SPEC(3)
  150 1=SPEC(4)
       J=SPEC(5)
       IF (1+J.LE.0) GO TO 140
       SURF (1.J.K) = SPEC(6)
       GO TO 140
  160 IF (TAG1.NE.SHPLANE) GO TO 190
      K=SPEC(1)
       OEPTH=SPEC (2)
       DO 180 I=I.NX
       DO 170 J=1.NY
 SURF (1.J.K)=0EPTH
  180 CONTINUÉ
      GO TO 100
  190 IF (TAGI.NE. SHRAISE) GO TO 230
  200 K=SPEL(1)
      OIST=SPEC(2)
      00 220 1=1.NX
00 210 J=1.NY
       SURF (I.J.K) = SURF (I.J.K) +DIST
  210 CONTINUE
  220 CONTINUE
GO TO 100
  230 IF (TAGI-NE.5HLOWER) GO TO 240
SPEC(2) = -SPEC(2)
       GO TO 200
  240 IF (TAGI.NE.SHT1LT ) GO TO 250
       IA=SPEC(1)
IR=SPEC(2)
```

DEG=SPEC (3)

```
Anito- stabint
    PTX=5PEG(5)
    PTY=SPEC (6)
    PTZ=SPEC (7)
    CALL TILT (NX.NY.SCALEX.SCALEY.SURF (1.1.1A).
               DEG.AXIS.SURF(1.1.1B).PTX.P1Y.PTZ)
    GO 10 100
250 IF (TAG1.NE. SHUEND ) GO TO 260
    I4=SPEC(1)
     ID=SPEC(2)
     IC=SPEC(3;
     IH=SPEC(4)
     SCOPE=5"EC(5)
     IF (SCOPE.E... 0.0) SCOPE = AMINO (NX.NY.3)
    CALL BENDER (NX.NY.SCALEX.SCALEY.SURF (1.1.1A).SURF (1.1.1B).
                   SURF (I.1.1C) . SURF (1.1.10) . SCOPE . DUMMY . DUMMY)
    GO TO 100
200 IF (TAGI-NE. SHPROPE) GO TO 280
     J=5PEL(I)
     00 270 I=1.6
    PPOP(I+J)=SPEC(I+1)
270 CONTINUE
     GO TO 100
280 IF (TAGI-NE.SHGRAPH) GO TO 290
    CALL EPAGE
     N = 1
203 F=5PEC (11)
     IF (SPECIN) .LE.O.O) GO TO 266
     CALL GRAPH (SURF (I . I . K) . NX . NY . K)
1F (N.LT.8) GO TO 283
286 CALL PAGER(994)
GO TO 100
290 IF (TAGI-NE. SHLAYER) GO TO 310
     ISUMF: SPEC(1)
     140CK=5PEC(2)
     ILAY - SPEC (3)
##ITE (ILAY#.300) ((SURF(1.J.1SURF).1=1.NX).J=1.NY)
300 FORMAT ((IPE18.10))
     INDEX (ILAYR) = IROCK
GU TO 140
310 1F (TAGI.NE.SHRELAX) GO TO 320
     K=SPEC(1)
     TOLER-SPEC(2)
     IF (TOLEM.ED.O.O) TOLER=0.005*(SCALEX*SCALEY)
CALL MELAX(SURF(1.1.K).NX.NY.TOLER)
GO TO 100
320 IF (TABL.NE.SHMAKEF) GO TO 460
     IMAXH=SPEC(1)
     IMAXL=SPEC(2)
     DE CHINGS
     HRITE (50.330) NX.NY.SCALEX.SCALEY.(INDEX(ILAYR).ILAYR=1.25).
                      ((PHOP(1.1HOCK).1=1.6).1ROCK=1.25)
    1
330 FI -MAT (215,2(1PE18.10) .2512. (1PE18.10))
     On 340 I=I+IMAXL
     PERINO 1
 340 CONTINUE
     07 380 J=1+1.Y
37 370 1=1+1.X
     HUFF(I)=I
     bliff (2) = J
```

DO 350 K=3.27

```
BUFF(K)= -10.0 E+50
  350 CONTINUE
       DD 360 K=1.IMAXL
       READ (K+300+END=420) BUFF (K+2)
000
       *****LDC5400
       READ (K.300) BUFF (K.2)
       1F (EDF.K) 420.360
C
  360 CONTINUE
       WRITE (50.300) (BUFF(K).K=1.27)
  370 CONTINUE
  380 CONTINUE
       CALL EPAGE
  PPINT 390
390 FDRMAT (27HIGEOMOD TERMINATED NORMALLY)
  GO TD 45
400 PPINT 410
  410 FORMAT (1H+, 24H***** UNRECOGNIZED *****)

82X,24H***** UNRECOGNIZED *****)
       GO TO 100
  420 CALL EPAGE
430 PRINT 440.K
  440 FORMAT (44HOLOGICAL ERROR - YOU ATTEMPTED TO USE LAYER +11.

1 52H. BUT DID NOT SPECIFY IT BY MEANS OF A LAYER CARD - .
2 30HGEOLOGY FILE BUILDING DELETED.)
   450 IF (K.GE.IMAXL) GO TO 45
       K=K+1
        READ (K+300+END=430) BUFF (K+2)
        GO TO 450
       C
   460 IF (TAGI-NE. SHSCALE) GO TO 490
        ISURFA=SPEC(1)
        ISURFB=SPEC(2)
        SCALE=SPEC(3)
        DO 480 J=1.NY
        DO 470 1=1.NX
SURF(I.J.ISURFB)=SCALE.SURF(I.J.ISURFA)
   470 CONTINUE
   480 CONTINUE
   GO TO 100
490 1F (TAG1.NE.SHSUM ) GO TO 520
         ISUPFA=SPEC(1)
         15URFB=SPEC (2)
         ISURFU=SPEC(3)
        DO 510 J=1.NY
DO 500 1=1.NX
         SHRF (1.J. ISURFC) = SURF (1.J. ISURFA) +SURF (1.J. ISURFB)
   500 CONTINUE
   510 CONTINUE
   GO TO 100
520 1F (TAGI.NE.SHDIFFE) GO TO 400
         ISURFA=SPEC(1)
         1SUPFB=SPEC(2)
         1SURFU=SPEC (3)
         D0 540 J=1.NY
D0 530 1=1.NX
SURF(1.J.ISURFC)=SURF(1.J.ISURFA)-SURF(1.J.ISURFB)
    530 CONTINUE
540 CONTINUE
```

```
50 TO 100
         E110
         SUBROUTINE BENDER (NX+NY+5CALEX+SCALEY+A+B+C+D+E+F+G)
С
        DIMENSION A(30+30)+8(30+30)+C(30+30)+D(30+30)+8x(30+30)+
                       BY (30.30) . CLOSE (50.4) . POINT (3.900) . Q(6)
С
         COMPUTE THE PARTIAL DERIVATIVES FOR SURFACE B. THE NEW MEDIAN.
         DX=G.5/SCALEX
         DY=0.5/SCALEY
         INFLUN=E
        LIMX=NX-1
         LIMY=NY"1
         TOLER=0.005 (SCALEX SCALEY)
C
        THE AUGUMACY TOLERANCE FOR THE BENDER IS SET AT ONE-MUNDREDTH OF THE AVERAGE OF THE SCALEX AND SCALEY VALUES. THIS SEEMS TO BE ACCUMATE ENOUGH - SOME SMOOTHING IS PERFORMED BY SHFIT.
        HX(1+Jb)=DX=(-3.0°B(1+JB)+4.0°B(2+JB)-B(3+JB))
        DO 10 10=2.L14X
         Px (18.72)=DX+(P(18-1.78) -B(18-1.78))
    IO CONTINUE
        4). (tix - Jo) = 0x + (8 (NX-2 - J6) -4 -0 +8 (NX-1 - J6) +3 -0 +8 (NX - J6))
    30 CONTINUE
        SC 40 15=1+8X
        BY (13.1)=0Y*(-3.0*B(18.1)+4.0*B(18.2)-B(18.3))
        57 30 JS=2.LIMY
        8Y([n.Ja)=DY*(H([B.J8+])-B([3.J6-]))
        Ef([0+NY)=DY*(B(1B+NY-2)-4.0*B(1B+NY-1)+3.0*B(1B+NY))
    40 CONTINUE
        COMPUTE THE X AND Y DIRECTION COSINES OF THE VECTORS NORMAL TO
        SURFACE B AT ITS GMID POINTS. ARRAY BX (18.18) IS USED FOR THE X DIRECTION COSINES AND ARRAY BY (18.18) IS USED FOR THE Y
C
Č
        DIRECTION COSINES.
С
        DO 60 10=1+NX
        DO 50 J5=1+1.Y
         Vr CMAG=53RT (Bx (16+JH) *8x (18+JH) +8Y (18+JH) *BY (18+JH) +1.0)
         HK([5+JE)=BX([H+JH)/VECHAG
        BY (IR . Jo) = BY (IB . Jd) / VECMAG
    50 CONTINUE
    60 CENTITUE
        FOR EACH PUINT ON SURFACE A. FIND THE NORMAL VECTORS ON SURFACE B
        SHICH PASS THROUGH THAT POINT. EXTEND EACH OF THESE VECTORS FROM SUPPRACE & TO SUPPRACE C. IN ORDER TO DETERMINE HOW FAR THE MEDIAN PLANE HAS BEEN DISPLACED ALONG THAT VECTOR. ADD ALL OF THESE DISPLACEMENTS TOOR THER AND DIVIDE BY THE NUMBER OF VECTORS FOUND.
        1. GAGER TO COMPUTE THE DISPLACEMENT OF THAT POINT ON SURFACE A.
        A = THE NAME OF THE ARRAY FOR THE OLD SURFACE WHICH IS TO BE BENT.
H = THE NAME OF THE ARRAY FOR THE NEW MEDIAN SURFACE.
C = THE NAME OF THE ARRAY FOR THE OLD MEDIAN SURFACE.
        D = THE NAME OF THE ARRAY FOR THE NEW SURFACE. AFTER BENDING.
        N-TS=0
        DJ 160 IA=1.NA
YM.1=AL 071 DD
0.0=AMCS
        5 . MY = 0 . U
         5'1MZ=0.0
```



```
COUNT=0.0
         IHEG=MAXO(I.(IA-INFLUN))
         IEND=M1N0(LIMX+(IA+INFLUN))
         JREG=MAXO(I.(JA-INFLUN))
         JEND=M1N0(LIMY+(JA+INFLUN))
С
         FOR EACH SCALEX-BY-SCALEY REGION ON SURFACE B. DETERMINE WHETHER
         IT IS PUSSIBLE TO SELECT A NORMAL VECTOR FROM THE REGION WHICH PASSES THROUGH THE POINT CURRENTLY BEING PROCESSED ON SURFACE A.
С
C
         WE START BY GUESSING THAT THE DESIRED NORMAL VECTOR GDES THROUGH THE CORNER OF THE REGION. WE THEN TRY TO REFINE THAT GUESS. IF IN DOING SO WE MOVE THE NORMAL VECTORS STARTING LOCATION OUT OF THE REGION. WE QUIT. DTHERWISE. WE QUIT WHEN WE HAVE EITHER FOUND THE DESIRED VECTOR OR WHEN WE HAVE MOVED IT LESS THAN DRE-HUNDREDTH OF THE GRID SPACINGS. IN ANY ITERATION. THE VECTOR IS (VX.VY.VZ).
C
         DO 140 IB=IBEG. IEND
         DO 130 JH=JHEG.JENO
         Dx=0.0
         DY=0.0
    70 VX=SCALEX#(IA-IB-DX)
         VY=SCALEY+(JA-JB-DY)
         THE FOLLOWING IS THE HARMONIC INTERPOLATION SCHEME.
         VZ=A(IA+JA)-((I-DX)*(1-DY)*B(IB+JB)*DX*(I-DY)*B(IB+I+JB)
               *DY*(I-DX)*B(IB,JB*I)*DX*DY*B(IB*1,JB*1))
         VMAG=SQRT(VX+VX+VY+VY+VZ+VZ)
         IF (VMAG.EQ.0.0) GD TD 72
         VX=VX/VMAG
         VY=VY/VMAG
         VZ=VZ/VMAG
         GO TO 74
    72 Vx=0.0
         VY=0.0
         VZ=0.0
C
         THE FOLLOWING IS THE HARMONIC INTERPOLATION SCHEME.
    74 VECX=(1-DX)*(1-DY)*BX(18+J8)+DX*(1-DY)*BX(18+1+J8)
                 +UY+(1-Dx)*ux(1B,Jo+1)+Ux*DY*Bx(1B+1,JH+1)
         VECY=(1-Dx)*(1-DY)*8Y(I&*JB)*DX*(I-DY)*BY(IB*1*JB)
                  *DY*(1-0x)*BY(IB.JB+1)*DX*DY*BY(IB+1.JB+1)
         VECZ=SURT(1.0-VECX+VECX-VECY+VECY)
         COSANG=VECX+VX+VECY+VY+VECZ+VZ
         SINANG=SORT (1.0-COSANG*CDSANG)
         MAKING THE SIMPLIFYING ASSUMPTION THAT A AND B ARE LEVEL SURFACES.
         DIST=VMAG*SINANG
         OVX=(VX-VECA) +SIGN(I.O.CDSANG)
         DVY=(VY-VECY) *SIGN(1.0.CDSANG)
         DVMAG=SURT (DVX+DVX+OVY+DVY)
         IF (DVMAG.EQ.0.0) DVMAG=10.0E+50
         DVX=DVX/DVMAG
         DVY=DVY/DVMAG
         DX=DX+DIST+DVX/SCALEX
         DY=DY+DIST*DVY/SCALEY
        NOTE THAT NO LOGIC IS INCLUDED FOR STEPPING DVER GRID LINE BOUNDARIES. IN THE GENERAL SENSE. THE PROGRAM IS ALLOWED TO WANDER UNE-QUARTER OF A GRID—LINE SPACING INTO ADJACENT GRID SOUARES. IN ORDER TO ENSUME THAT DESIRED PUBLIS WHICH FALL EXACTLY ON GRID LINES ARE FOUND. HOWEVER. IF THE PROGRAM INTRUDES FARTHER THAN DNE-QUARTER OF THE GRID—LINE SPACING INTO AN ADJACENT GRID
```

```
STUARE . THE SEARCH IS ENDED - THE DESIRED NORMAL VECTOR IS ABSENT.
       IF (0x.LT.-0.25) 60 TO 120
       IF (DX.GT. 1.25) GO TO 120
       IF (UY.LT.-0.25) 60 TO 120
IF (UY.GT. 1.25) 60 TO 120
       IF (GIST.GE.TULER) 60 TO 70
C
       AT THIS POINT. A NUMMAL VECTOR PASSING THROUGH THE DESIRED POINT
      OR SURFACE A HAS BEEN FOUND. IT IS A UNIT VECTOR HAVING THE COMPONENTS (VX.VY.VZ). IT PASSES THROUGH SURFACE & AT THE POINT WHERE X=(IB-1+DX)*SCALEX AND Y=(JB-1+DZ)*SCALEY. NEXT WE WILL FIND
C
       THE POINT AT WHICH IT INTERSECTS SURFACE C. WE WILL FIRST GUESS THAT IT INTERSECTS SURFACE C AT THE SAME COORDINATES AT WHICH IT
C
       INTERSECTS SURFACE 8. WE WILL THEN REFINE OUR GUESS.
       IC=Id
       JC≍Jನ
       UKC=UK
       DYC=UY
       ZA=A(IA+JA)
   80 VFCX=5CALEX+(IA-IC-DXC)
       VECY=SCALEY* (JA-JC-OYC)
       THIS IS THE HARMUNIC INTERPOLATION SCHEME.
       V: CZ=ZA-((1-DAC)*(1-0YC)*C(IC+JC)*UXC*(1-DYC)*C(IC+1+JC)
              +U/C+(1-UXC)+C(1C+JC+1)+DXC+DYC+C(1C+1+JC+1))
       VFCMAG-SURT (VECX+VECX+VECY+VECY+VECZ+VECZ)
       IF (VECHAG.EQ.0.0) GO TO 82
       V. CX = VECX/VECMAG
       VECT=VECY/VECMAG
       V-CZ=VEUZZVECMAG
   60 TO 84
       VF CY = 0 . 0
       VECZ=0.0
   84 COSANG=VECX+VX+VECY+VY+VECZ+VZ
       SINANG=SUPT (1.0-CUSANG+COSANG)
       MAKING THE SIMPLIFYING ASSUMPTION THAT C IS A LEVEL SURFACE.
       DIST=VEUHAG*SINANO
       DVK=(VA-VECX) =513H(1.0.005ANG)
DV/=(VY-VECY) =51GH(1.0.005ANG)
       DVMAG=5GRT (DVX+DVX+DVY+DVY)
       IF (D.MAS, EU. 0.G) DVMAG=10.0E.50
       D.X=UVA/LVM.G
       DVY=DVY/DVMAG
       THE VALUE OF DIST GIVES THE DISTANCE AT WHICH THE NEXT ITERATION
С
       IS TO BECLIVE THE VALUES OF DVX AND DVY GIVE THE DIRECTION.
       DACH=DXC+DIST+DVX/SCALEX
       DYCK-DYC+DIST ODVY/SCALEY
       I'JAUL'I
       JY=LYLN
       DXCH=UKCH-IX
       DYCN=UYLN-JY
       THIS IS THE LUGIC FOR STEPPING BACKWARD OVER GRID SQUARE EDGES.
       IF (DACH-GE.0.0) GO TO 90
       OFCN=DAGN+1.0
       14=14-1
   90 IF (DYCH.CE.U.0) 60 TO 100
```

```
DYCN=DYCN+1.0
         THIS IS THE LOGIC FOR STEPPING FORWARD OVER GRID SQUARE EDGES.
   100 IC=IC+IX
         JC=JC+JY
         DXC=DXCN
         DYC=D"CN
         IF (IC.GT.NA)
                                      GO TO 120
                                      GO TO 120
GO TO 120
          IF (UC.LT.I)
          IF (JC.GT.NY)
                                      GU TU 120
         DIST (= (18+DX-1C-DXC) *SCALEX
DIST(= (JB+DY-JC-DYC) *SCALEX
         DIST != VZ * VMAG-VECZ * VECMAG * SIGN(1.0 + COSANG)
         TEST=DIST/SUPT(DISTX*DISTX*DISTY*DISTY*DISTZ*DISTZ)

IF (TEST-LT.0.01) GO TO 110
         IF (DIST.GE. TOLER) GO TO BO
         STORE DISPLACEMENT FROM SURFACE C TO SURFACE B ALONG (VX.VY.VZ).
   IIO SUMX=SUMX+DISTX
         SUMY=SUMY+DISTY
         SUMZ=SUMZ+DISTZ
         COUNT = COUNT + I . 0
   120 CONTINUE
   130 CONTINUE
   140 CONTINUE
         IF (COUNT.LE.0.0) GO TO 160
         NPTS=NPIS+1
         POINT(1+NPTS) = (IA-I) *SCALEX+SUMX/COUNT
         POINT (2+NPTS) = (JA-1) *SCALEY+SUMY/COUNT
         POINT (3.NPTS) = A (IA.JA) + (SUMZ/COUNT)
         IF (POINT(I.NPTS).LT.-SCALEX) GO TO 150
IF (POINT(Z.NPTS).LT.-SCALEX) GO TO 150
IF (POINT(I.NPTS).GT.(NX*1)*SCALEX) GO TO 150
IF (POINT(Z.NPTS).LE.(NX*1)*SCALEX) GO TO 160
   ISO NPTS=NPTS-I
   160 CONTINUE
   170 CONTINUE
   180 CONTINUE
C
         WE HAVE NOW DISPLACED ALL OF THE GRID POINTS OF SURFACE A. WE HAVE PLACED THE RESULTS IN THE POINT ARRAY. WE HAVE DISCARDED THE RESULTS FOR GRID POINTS WHICH WERE DISPLACED MORE THAN ONE GRID SPACING OFF OF THE SIDE OF THE GRID. WE MUST NOW DETERMINE THE HEIGHT OF THIS DISTORTED SURFACE AT EACH GRID POINT. THE RESULTS
C
         OF THIS COMPUTATION WILL BE PLACED IN THE D ARRAY.
C
   18S N=12
         IF (N.GT.NPTS) N=NPTS
DO 310 I=I+NX
         X=(1-1) SCALEX
         DO 300 J=1+NY
         Y=(J-I) SCALEY
         FIND THE N POINTS WHICH ARE CLOSEST TO THE GRID POINT (1.4). STORE THEM IN ORDER OF CLOSENESS IN THE ARRAY NAMED CLOSE.
         DO 190 K=1.N
         CLOS* (K+4)=10.0E+50.
   190 CONTINUE
         DO 250 K=1+NPTS
         Dx=X-POINT(1.K)
```

DY=Y-POINT(2.K)

```
UISTSU-JAMUX *DIMOY
      1F (DISTSU-GE-CLUSE(N-4)) GO TO 240
  200 IF (01515Q.GT.CLOSE(L.4)) GO TO 210
      17 (L.GT.0) GO TO 200
  210 L=L+1
  177=N
220 IF (NN.LE.L) GO TO 230
      CLOSE (Net-1) - CLOSE (IIII-1-1)
      CLOSE (NH+2) = CLUSE (M+-1+2)
      CLOSE (NN+3) = CLUSE (NN-1+3)
      CLUSE (UN+4) = CLUSE (NN-1+4)
      (v)_{i} = NN - 1
      GO TO 220
  230 CLOSE(L+1)=POIT.T(1+K)
      CLOSE (L.2) = 26111 (2.K)
      CL (SE (L+3) = POINT (3.K)
        OSE (L+4) = 015750
  240 L ITINGE
  250 CONTINUE
      AFTER FITTING A SECOND-DEGREE POLYNOMIAL TO THE CLOSEST POINTS. WE CALCULATE AND STORE THE HEIGHT OF THE SURFACE AT THE GRID POINT.
C
  260 CALL SHFIT (2.NUMBER.CLUSE(1.1).CLUSE(1.2).CLUSE(1.3).Q.IFLAG)
      IF (IFLAG.LE.0) 60 TO 290
      NIWHERA IJYOURS
      IF (NUMBER LE . N) GU TO 260
      PHINT 2/0. I.J.X.Y
  THE NUMBER DA + SHEAST OR X + 4X + 10HNORTH OR Y + 4X + 6HHEIGHT +
              5H .. 2 2.64.6HD15TSU./.27x.12H------44.
              Un 205 L=1+14
  #- HIT 200. L. (CLUSE (L.K) . K=1.4)
200 FURMAY (304.14.94.F10.1.44.F10.1.44.F11.1.44.F10.1)
  205 CHI.T 11.JE
      .(1)= -10.0E+50
  290 D(1.J)=..(1).G(2).X+D(3).Y+G(4).X*X+D(5).X*Y+Q(6).Y*Y
  300 CONTINUE
  316 CALTINUE
      RETURY
С
C
      THIS ENTRY POINT IS USED IN TILTING THE SURFACE (CALLED A). A
      MINNER OF DEGREES (DEC) . IN A RIGHT-HANDED FASHION . AROUND A
      HT 120 VIAL VECTOR THROUGH THE POINT X=PIX+Y=PIY+Z=PIZ+ WHICH
           , IN A DIRECTION PHI WHICH IS MEASURED IN DEGREES. IN A
      COMPASS-LIKE FASHION FROM NORTH (OR EQUIVALENTLY. THE Y AXIS).
      ETTHE TILT (NX.NESCALEX.SCALEY.A.DEG.AXIS.D.PTX.PTY.PTZ)
č
      e .... COL 6400
      ELTAY TIET
L
      ENTRY TILT
      Dir Cars
      AXIS=L
      PTKEE
                           Reproduced from
С
      PTY=F
      217=6
```

```
GAMMA=DEG/57.2957795
        PH1=-AX15/57.2957795
        $1NPH1=51N(PH1)
        COSPHI=COS (PHI)
        NPTS=0
        00 410 1=1+NX
00 400 J=1+NY
Y=(J-1)*SCALEY
        X=(1-1) *SCALEX
        NPTS=NPTS+1
        Z=A(1+J)-PTZ
        P= (X-PTX)*COSPHI+(Y-PTY)*SINPHI
        QQ=(PTX-X)*SINPHI+(Y-PTY)*COSPHI
        THETA=$1GN(1.57079633.2)
        (1.57079633 IS EQUAL TO PI OVER TWO)
        IF (P.NE.O.O) THETA=ATAN(Z/P)
        R=SORT (Z*Z*P*P)
        PPRIME=R*COS(THETA-GAMMA)*SIGN(1.0.P)
        POINT(1*NPTS)=PPRIME*COSPHI-00*SINPHI*PTX
POINT(2*NPTS)=PPRIME*SINPHI*00*COSPHI*PTY
        POINT (3+NPTS)=PPRIME TAN (THETA-GAMMA) +PTZ
  400 CONTINUE
  410 CONTINUE
        GO TO 185
        END
        SUBROUTINE PAGER(N)
C
        COMMON /10COM/ NLINE+NPAGE
C
        OATA MARKER /1/
        IF (N+NLINE.LE.40) RETURN
        NPAGE=NPAGE+1
        IF (MARKER.EQ.1) GO TO 20
        PPINT 10
   10 FORMAT (1H0.25X.80H0
                                             1
                                                   8./.26X.80H12345678901234567890123
                        6
      84567890123456789012345678901234567890123456789012345678901
    20 PPINT 30.NPAGE
30 FORMAT (1H1.50x.30HIMAGES OF CONTROL CARDS FOLLOW.43x.5HPAGE .13)
        PRINT 10
        NL INE =+
        MARKER=0
        RETURN
С
        ENTRY EPAGE
Ç
        IF (MARKER.EO.1) RETURN
        PPINT 10
        MARKER=1
        RETURN
        SUBROUTINE GRAPH (GRIO . M . N. NPLOT)
00000000
       THIS SUBROUTINE PRODUCES X - Y (THAT IS. EAST - NORTH) PLOTS OF GEOLOGICAL SURFACES. IF THE SURFACES ARE MORE THAT TWELVE OATA POINTS WIDE. IT PRINTS THEM OUT IN NORTH-TO-SOUTH STRIPS WHICH ARE EACH NO MORE THAN TWELVE OATA PUINTS WIDE. AND WHICH CAN BE PLACED SIDE BY SIDE SO THAT THE WHOLE SURFACE CAN BE SEEN.
        A SIMPLE FORM OF DATA-CONTROLLED FORMATTING IS USED.
        01MENS10N GR10(30+30)+NLABEL(12)
```

```
resteriorial
    LOWM=1
    L [ MM = M 11.0 (M . 12)
10 LIMI=LIMM-LOW4+1
    1/20 I=1 + 1M1
20 *. LASEL (1) = LUNY+ I-1
    PAINT 300 MALOTOHOTALE
30 FI)RMA1 (22H1Z VALUES FOR SURFACE +11+26H = NORTH IS TOWARD THE TOP
1 55H OF THE PAGE+ EAST IS TOWARD THE RIGHT. (EAST = X OR I+
2 23H NORTH = Y OR J) STRIP +11)
     D.) 280 K=1+N
     Jat, + 1 -K
    #16=0.0
DO 70 I=LOWM+LIMM
     $ [2 + 1] CI = 0 + 10 + 13 (1 + 4) }
     1F ($1/1-816) 60.60.50
 50 810=51/L
 60 CONTINUE
 70 CHATINUL
     IF (816-1.0) 40.100.100
 40 PAINT 90-J-(GRID(1-J)-I=LOWM+LIMM)
90 FARMAT(////-14-14-54-12(F8-6-24))
     60 10 270
100 IF (B16-10.0) 110.150.130
110 FRINT 120.J. (GRID(1.J).1=LOWM.LIMM)
120 FORMAT (////-1x.14.5x.12(F8.5.2X))
     60 10 270
130 18 (316-100.0) 140.160.100
140 PRINT 150.J. (GKIU(1.J).1=LOMM.LIMM)
150 FORMAT (/////+1A+14+5A+12(Fd+4+2A1)
     60 10 210
165 1 (216-1630.6) 170-196-190
1/3 PAIRT 100.J. (ORTU(1.J).1=LOMM.LIMM)
180 FRAMAT (/////.1X.14.5X.12(F8.3.2X))
03 10 5/0
140 15 (PIO-10000:0) 530:550:550
200 PRINT 210-J-(GRID(1-J)-1=LOAM-LIMM)
210 FORMAT (////-1X-14-5X-12(FB-2-2X))
     00 10 270
220 IF (dig-100000.0) 230.250.250
23) PRINT 240.0. (SRID(1.0).I=LG.M.LIMM)
240 F 144AT (////+1x+14+5x+12(Fd+1+2x))
      G1 TO 2/0
250 F -11:7 200. J. (OH 10 (1. J) . 1 = LOWM. LIMM)
200 F -145 (/////-14. 14.5x.12 (FB.0.2X))
270 Cot.T150E
300 LOWALLAMOLE
      NE #M=LU#M+11
      LINVEHIND (MINERM)
      NST41P="STAIP+1
      GO TO 10
```



```
310 RETURN
END
        SUBROUTINE RELAX (GRID . M . N . TOLER)
        THIS SUBROUTINE RELAXES AN M BY N GRID DF DATA POINTS SO THAT LAPLACES EQUATION IS SATISFIED WITH RESPECT TO THE BOUNDARY POINT VALUES GIVEN. M IS THE COLUMN INDEX. N IS THE ROW INDEX.
CC
CC
        DIMENSION GRID(30,30)
С
        FIRST. INITIALIZE THE GRID BY LINEAR APPROXIMATION.
        LIMN=N-I
        00 20 I=2.LIMM
        DIFF=(GRID(I+N)-GRID(I+I))/LIMN
        DO 10 J=2.LIMN
        GRID(I.J)=GRID(I.I)+(J-I)*DIFF
    10 CONTINUE
    20 CONTINUE
        ITER=I
c
c
        FOUR DIFFERENT RELAXATION PATTERNS ARE USED ALTERNATELY. THIS SPEEDS UP ERROR PROPOGATION. AND THEREBY. CONVERGENCE.
C
    30 LOWM = 2
        LOWN = 2
LIMM = M - 1
        LIMN = N - I
        INCRM = I
        INCRN = I
        Gn TO 70
    40 LOWM = M-I
LOWN = 2
        LIMM = 2
        LIMN = N-I
        INCRM = -I
        INCRN = I
        GO TO IIO
    50 LOWM = M-I
LOWN = N-I
        LIMM = 2
        LIMN = 2
        INCRM = -I
        INCRN = -I
        GO TO 70
    60 LOWM = 2
       LOWN = N - 1
LIMM 2 M - I
        LIMN = 2
        INCRM = 1
INCRN = -1
        GO TO IIO
        J WITHIN I RELAXATION (INDICES CAN GO UP OR DOWN)
    70 BIGDIF=0.0
        I=LOWM
    BO J=LOWN
    96 TESTVAL=GRID(1.J)
GPID(1.J)=0.25*(GRID(1.1.J)*GRID(1-1.J)*GRID(1.J*I)*GRID(1.J-1))
        CHANGE=ABS(TESTVAL-GRID(I.J))
BIGDIF=AMAXI(CHANGE,BIGDIF)
        IF (J.EW-LIMN) GD TD 100
```

```
J=J+I1+LKN
       GO TO 90
  100 IF (I.EQ.LIMM) GO TO 150
I=1+INCHM
       CO TO BO
C
       I WITHIN J RELAXATION (INDICES CAN GO UP OR ODWN)
  IIO BIGDIF=0.0
        J=LO#N
   120 I=L0#M
  130 TESTVAL=GRID(I.J)
       GPID(I+J)=0-25*(GMID(I+1+J)+GRID(I+1+J)+GRID(I+J+1)+GRID(I+J+1))
CHANGE=ABS(TES) VAL-GRID(I+J))
       HIGDIF = AMAXI (CHANGE . BIGDIF)
        IF (1.Ed.LIMM) GO TO 140
        I=I+INCHM
  GO TO 130
140 IF (J.EJ.LIMN) GO TO 150
       J=J+INCHN
       GO TO 120
       CHECK FUR CONVERGENCE
   150 IF (BIGUIF-TOLER) 170.170.160
        IF NOT WITHIN TOLERANCE. REPEAT RELAXATION USING NEXT PATTERN.
С
С
   160 ITER=ITER+1
        IF (ITER.GT.4) ITER=1
GO TO (30.40.50.60).ITER
        OTHERWISE . RETURN
   170 RETURN
       END
        SURFOUTINE SEFIT (NORD + M + X + Y + Z + A + IF)
       INTEGER FK+FU
DIMENSION A(50)+B(50)+F(50)+X(50)+Y(50)+

Z(50)+PHI(50+50)+BIN(50+50)
        1F=0
        UMIN=0.0001
        NOP=NORU+1
        N=N02+(NUP+1)/2
       DO 240 JS=I+NOP
DO 240 KS=I+JS
        1=J5+(J5-1)/2+KS
        DO 90 K=1.M
        xx=1.0
        YY=1.0
   1F (1-1) 250.80.10
10 1F (1-3) 20.30.40
20 XX=X(K)
        GO TO 80
    30 YY=Y(K)
        60 10 80
    40 FK=JS-KS
       F J=K5-I
   1F (FK) 60.60.50
50 xx=x(K)**FK
60 1F (FJ) 80.80.70
70 YY=Y(K)**FJ
80 CGNTINUE
    40 F(K)=AA 4YY
        A(1)=0.0
```

IF (1-1) 100.100.120

B. PROGRAM TUNNEL

```
PROGRAM TUNNEL
                                             REAT: GEOLOGY FILE. CREATE TUNNEL FILE
C
С
         COMMON /FPOLE/ XX.YY.ZZ.II.JJ.LL
         COMMON JGEOLFL/ NX.NY.SCALEX.SCALEY.INDEX(25).PROP(6.25)
COMMON JNEWPT/ X1.Y1.Z1.X2.Y2.Z2.XM.YM.ZM.DL.LSEGNO
         COMMON JUPARMY DIAM. AORIG. YORIG. UNIT. DELTA
C
         DIMENSION CARDIN(5)
         DATA CUMBL /0./
DATA ICOUNT /0/
         DATA IFLAG /0/
         DATA INEND /0/
         DATA LEIN /0/
         DATA ESTEE /0/
         DATA SENGTH /0./
DATA CARDIN /5*0./
                                             INITIALIZE
С
         DIAM = 10.
         XORIG = 1.
         YORIG = 1.
         Unit = 1.
         DFLTA = 20.
         LSEGNO = 0
         x_1 = 0.
         Y1 = 0.
          x2 = 0.
          YP = 0.
          12 = 0.
         REWIND 50
         REWIND 40
                                             READ GEOLOGY FILE
C
         CALL HOUSEL
                                             READ PARAMETER CAROS
С
   80 IF (INEND .EQ. 1) GO TO 300

HEAD 100. IKEY. (CARDIN(1).I=1.5)

100 FOHMA! (A6.4x.5(F10.4))

ICOUNT = ICOUNT . 1

IF (IKEY .EO. 6HNEWLEG) GO TO 190

IF (IKEY .EO. 6HSTART ) GO TO 170

IF (IKEY .EU. 6HEND ) GO TO 180

IF (IKEY .EO. 6HOPTION) GO TO 150

PAINT 110. IKEY
          PRINT 110. IKEY
    110 FORMAT (39HOEHROR - INVALID KEYWORD ON INPUT CARD .A6 )
          60 TO 400
                                              OPIION CARD READ
    150 IF (ILCUNT .EQ. 1) 60 TO 160
    PWINT 155
155 FORMAT (47HOERROR - OPTION CARD. IF PRESENT. MUST BE FIRST.)
    GO TO 400
160 IF (CARDIN(I) .GT. 0.) DIAM = CARDIN(I)
          XORIG = CARDIN(2)
YORIG = CARDIN(3)
          IF (CARDIN(4) .GT. 0.) UNIT = CARDIN(4)
IF (CARUIN(5) .GT. 0.) DELTA = CARDIN(5)
          GO TO 60
                                              START CARD READ
    170 PRINT 172. DIAM.XURIG.YORIG.UNIT.DELTA
172 FORMAT (26HITUNNEL OPTIONS - DIAM.9X.5HAORIG.11X.5HYORIG.10X.
4HUNIT.8X.5HDELTA/17X.F10.3.2X.2(F14.3.2X).2(F10.3.2X)//
```

```
PROPERTY 1 PROPERTY 5
                                                                              PROPERTY 2 . PROPERTY 6.
                                        POSITION
            SCHOTUNNEL FILE -
                                        PROPERTY 4
            5X+55HPKOPERTY 3
            3X+4HFLAG /)
        X1 = CARDIN(1)
        Y1 = CARDIN(2)
        71 = CARDIN(3)
        GO TO 80
                                       END CARD FEAD
C
  180 1NEND = 1
C
                                       NEWLEG CARD READ
  190 X2 = CARDIN(1)
        Y2 = CARDIN(2)
Z2 = CARDIN(3)
        LSEGNO = LSEGNO + 1
С
                                       PROCESS TUNNEL LEG BETWEEN (X1.Y1.Z1)
                                             AND (X2.Y2.Z2)
C
        XWRK = (X2-X1)*(X2-X1)*(Y2-Y1)*(Y2-Y1)*(Z2-Z1)*(Z2-Z1)
SLNGTH = SURT (XWRK)
        OL = 0.
        1F (LSEGNO .GT. 1) GO TO 250
                                       FINO LAYER OF BEGINNING POINT
C
        XX = XI
        YY = Y1
ZZ = Z1
        CALL GETLYR
        LSTLL = LL
С
                                       TEST POINTS ALONG TUNNEL HIDLINE IN INCREMENTS OF DELTA FT.
  250 OL = DL + DELTA

IF (DL .GT. SLNGTH) DL = SLNGTH
        CALL NEWPNT
        YY = YM
        27 = ZM
        CALL GETLYR

IF (DL .LT. SLNGTH) GO TO 260

LFIN = LSEGNO
  GO TO 270
260 IF (LSTLL .EQ. LL) GO TO 250
                                       NEW LAYER ENCOUNTERED
С
   270 DOL = UL . CUMOL
  LPROP = INDEX(LSTLL)
PRINT 275+DDL+ (PROP(1+LPROP)+1=1+6)+1FLAG

275 FORMAT (11x+7(F14+4+1x)+2x+14)

277 1ROPTEM=PROP(2+LPROP)
WRITE(40+280) DDL+PROP(1+LPROP)+1ROPTEM+(PROP(1+LPROP)+1=3+6)+1FLA
   280 FORMAT(2E18.10.15.4E18.10.15)

IF (DDL .LT. 0.) GO TO 310

LSTLL = LL
        IF (LFIN .LT. LSEGNO) GO TO 250
                                       ENO OF TUNNEL SEGMENT MAS BEEN REACHED
        XI = X2
        ZI = ZZ
CUMDL = CUMDL + DL
        GO TO 80
                                       END OF JOB
   300 DDL = -100.
   GO TO 277
310 PRINT 320
   320 FORMAT (27HOTUNNEL TERMINATED NORMALLY )
```

```
430 CALL EAST
         SUBROUTINE GETLYR
         PURPOSE - FIND LAYER (LL) IN WHICH THE POINT (xx+yy+22) 13 LOCATED
        COMMON /FPOLE/ XX-YY-ZZ-11-JJ-LL
COMMON /GEULFL/ NX-NY-SCALEX-SCALEY-INDEX(25)-PROP(6-25)
COMMON /UPARM/ DIAM-XORIG-YORIG-UNIT-DELTA
COMMON //SAVE/ ZSTOR (30-30-25)-LFLAG(25)
DIMENSION /HOLD(25)
        DATA LHULD /0/
C
        L \vdash OLD = 0
        00 120 J = 1.25
ZHOLD(J) = -10.0 E51
  120 CONTINUÉ
                                          FIND I INTERVAL FOR XX
         XCDOR = I + (XX-XDRIG) / (SCALEX*UNIT)
         ILCW = ACDOR
         IHI = ILOW + I
         YCOOR = 1 • (YY -YORIG) / (SCALEY * UNIT)
С
         JLOW = YCOUR
JHI = JLOW + 1
                                           SEE IF POINT IS OUTSIDE I J GRID
C
        IF (ILGW .LT. I) GO TO 700
IF (IHI .GT. NX) GO TO 730
IF (JLOW .LT. I) GO TO 750
IF (JHI .GT. NY) GO TO 760
                                          EXAMINE THE 4 (1.J) POLES SURROUNDING (XX.YY.ZZ) FOR LAYER(S) INVOLVEO
C
C
         II = ILUA
        JJ = JLOW
CALL FINDL
        LHOLD = LL
С
        JJ = JHI
CALL FINDL
IF (LHOL) - LL) 310+240+310
   240 II = IH1
        CALL FINDL
         IF (LHOLD - LL) 310.280.310
  280 JJ = JLÛW
        CALL FINDL
         IF (LHOLD - LL) 310,950,310
                                          INTERPOLATION REQUIRED
  310 X4 = ILUW
        YA = JLUW
XH = J-1
         YH = JLUW
        xc1 = 1LOW
        XC = XCJOH
YC = JH1
        00 500 J=1.25
         IF (LFLAGIJ) .EO. 0) GJ TO 500
         ZA = ZSTOR (ILOW+JLOW+LYH)
        ZH = ZSIOR([HI+JLOW+LYR)
        ZC1 = ZSTOH(ILOW+JHI+LYR)
ZC2 = ZSTOR (IHI+JHI+LYR)
```

```
FIND POINT ON LINE BETWEEN (ILOW-JHI-ZCI)
C
                                            AND (IHI+JHI+ZC2) WHICH IS AT XX
       ZC = (XCOOR - XC1) • (ZC2 - ZC1) • ZC1
DERIVE EQUATION OF PLANE DEFINED BY
С
                                       (XA.YA.ZA) . (XB.YB.ZB) . (XC.YC.ZC)
       A = YA*ZB*YC*ZA*YB*ZC-YC*ZB-YH*ZA-YA*ZC
B = ZA*AB*ZC*XA*ZB*XC-ZC*XB-ZB*XA-ZA*XC
        C = XA*YB+XC*YA+XH*YC-XC*YB-XH*YA-XA*YC
        D = XA*Y8*ZC+YA*ZB*XC+ZA*XB*YC-ZA*Y8*XC-YA*X8*ZC-XA*ZB*YC
        STORE Z FOR PLANE AT POINT (XX.YY)
ZHOLD(J) = D - B*YCOUR - A*XCOUR / C
C
  500 CUNTINUL
                                     FIND LOWEST ZHOLD(J) S.T. ZHOLD(J) GT ZZ
С
  510 ZLOW = 999999.
       LL = 0
00 550 J=1.25
        IF (LFLAG(J) .EQ. 0) GO TO 550
        TESTZ = ZHOLD(J)
        IF (TESTZ .LT. ZZ) GO TO 550
IF (TESTZ .GT. ZLOW) GO TO 550
        ZLOW = TESTZ
        LL = J
  550 CONTINUE
  IF (LL .GT. 0) GO TO 950
PRINT 570. XX.YY.ZZ

570 FORMAT (34H0ERROR - NO LAYER FOUND FOR POINT .3(FI4.3.IX) )
        GO TO 900
С
        c
č
                                     POINT WEST OF GRID
  700 11 = 1
702 1F (JHI .GT. NY) GO TO 740
1F (JLOW .LT. 1) GO TO 745
        JJ = JLOW
CALL FINDL
        LHOLD = LL
        LHOLD = LL

JJ = JH1

CALL FINOL

IF (LL .EQ. LHOLD) GO TO 950

DO 705 J=1.25

IF (LFLAG(J) .EQ. 0) GO TO 705

ZC1 = ZSTOR(11.JLOW.J)

ZC2 = ZSTOR(11.JHI.J)
        ZHOLD(J) = (YCOOR - JLOW) * (ZC2-ZC1) * ZC1
   705 CONTINUE
        GO TO 510
                                      POINT EAST OF GRID
C
   730 11 = NX
        GO TO 702
                                      POINT NW OR NE OF GRID
  740 JJ = NY
        GO TO 790
                                      POINT SW OR SE OF GRID
   745 JJ = 1
        GO TO 740
                                      POINT SOUTH OF GRID
   750 \text{ JJ} = 1
   752 IF (1H1 .GT. NX) GO TO 770 IF (1LOW .LT. 1) GO TO 775
        II = ILOW
CALL FINDL
        LHOLD = LL
        CALL FINDL
        IF (LL .EQ. LHOLD) GO TO 950
```

```
DO 755 J=1.25
IF (LFLAG(J) .EQ. 0) GO TO 7S5
         7C1 = ZSTOR(ILUW+JJ+J)
          ZHOLD(J) = (XCOOR - ILOW) . (ZC2 - ZCI) + ZC1
    755 CONTINUE
          60 TO 510
                                           POINT NORTH OF GRID
    760 JJ = NY
         GO TO 752
                                           POINT NE OF GRID
    770 II = NX
         GO TO 790
С
                                           POINT NW OF GRID
   775 II = 1
790 CALL FINOL
         GU TO 450
    900 CONTINUE
   CALL EXIT
         RETURN
         E1:0
         SUBROUTINE NEWPAT
         PURPOSE - GIVEN ENDPOINTS (X1.Y1.Z1) AND (X2.Y2.Z2) OF LINE.

FIND (XM.YM.ZM) WHICH IS DL FT. FROM (X1.Y1.Z1) ON LINE
TECHNIQUE-EXPRESS YM AND ZM IN TERMS OF XM. USING 2-POINT FORM
OF STRAIGHT-LINE EUUATION.
SUBSTITUTE IN FORMULA FOR DISTANCE BETWEEN 2 POINTS.
                           (XI+Y1+Z1) AND (XM+YM=F(XM)+ZM=G(XM))+
                       AND SOLVE FOR XM.

RECUNSTRUCT YM ANO ZM FROM XM.

SPECIAL CASES EXIST IF XDIF. YDIF. OR ZDIF ARE ZERO.

THUS REDUCING PROBLEM TO 1 OR 2 DIMENSIONS.
         NOTE
                    - IF UL IS GT LENGTH OF SEGMENT. ROUTINE WILL ABORT.
         COMMON /NEWPT/ X1.Y1.Z1.X2.Y2.Z2.XM.YM.ZM.DL.LSEGNO
         DATA LSTSEG /0/
        DATA MUUUE /0/
         DATA IBRNCH /0/
         OATA XDIF. YDIF. 201F. A.B. T1. T2 /7.0./
C
        NEGOT = 0
        X4 = 0.
Y4 = 0.
        Z4 = 0.
        IF (LSEGNO .EU. LSTSEG) GO TO JO
C
                                         INITIALIZE FOR NEW LINE SEGMENT
        MCODE = 0
        XDIF = X2 - X1
YDIF = Y2 - YI
ZDIF = Z2 - ZI
        IF (XDIF .EQ. 0.) MCODE = 1
IF (YDIF .EQ. 0.) MCODE = MCODE • 10
IF (ZDIF .EQ. 0.) MCODE = MCODE • 100
                                         BHANCH ACCORDING TO CASE INVOLVED
   30 IF (MCOUE .EQ. 0 ) GO TO 80
IF (MCOUE .EQ. 11 ) GO TO 60
IF (MCOUE .EQ. 101) GO TO 625
IF (MCOUE .EQ. 101) GO TO 650
```

(MLOUE . LQ. 1) GC TO 675

```
IF (MCCDE .EO. 10 ) GO TO 700 IF (MCODE .EO. 100) GO TO 725
        PPINT 50
    50 FORMAT (28HOEHROR - ENOPOINTS IDENTICAL)
        GO TD 880
                                             NORMAL CASE (XDIF.YOIF.ZOIF NON-ZERO)
       IF (LSEGNO .EQ. LSTSEG) GO TO 110

SET UP COEFFICIENTS OF QUAORATIC EQUATION

A = 1.* (YD1F * YD1F * Z01F * ZD1F) / (X01F * X01F)

B = -2. * A * X1
   80 18RNCH = 1
       T1 = X1
        15 = X5
       GO TO 100
                                       RECONSTRUCT YM ANO ZM
    90 XM = RT
       XFRAC = (XM - XI) / XOIF
YM = YI + (YDIF + XFRAC)
ZM = ZI + (ZDIF + XFRAC)
       Gr) TO 750
С
        100 IF (A .EQ. U.) GO TO 450
110 ARG = 4. • A • DL • DL
TEST FOR EXISTENCE OF REAL RUOT(S)
  IF (ARG .GE. 0.) GO TO 300

PHINT 200. A.B.ARG

200 FORMAT (36HOERROR - ARG IN NEWPNT NEGATIVE. A= .F14.3.4H B= .

F14.3.6H ARG= .F14.3)
       GO TD 880
                                     FIND ROOTS OF QUADRATIC
  300 ARGP = SQRT (ARG)
  JOO ARGP = SURT(ARG)

DEN = 2. • A

IF (DEN .EQ. 0.) GO TO 450

RT = (-8 + ARGR) / DEN

SELECT ROOT ON GIVEN SEGMENT OF LINE

400 IF (TI .LE. RT .AND. RT .LE. I2) GO TO 500

IF (T2 .LE. RT .AND. RT .LE. TI) GO TO 500

NROOT = NROOT + 1
  NROOT = NROOT + 1
IF (NROOT .EQ. 2) GO TO 450
RT = (-4 ~ ARGR) / DEN
GO TO 400
450 PPINT 4/0, A. B. ARG
470 FORMAT (51H0ERRDR + NEWPNT FOUND NO ROUT ON GIVEN SEGMENT. A= .

F14.3.4H B= .F14.3.6H ARG= .F14.3)
       GO TO 880
  500 GD TO ( 90.680.705.730) . 1 BRNCH
        SPECIAL CASES
             SPECIAL LAGES

XDIF AND YOIF ARE ZERO
  600 YM = YI
       XM = X1
  IF (ZDIF) 610.605.605
605 ZM = Z1 + OL
  GO TO 750
610 ZM = Z1-DL
       50 TO 750
                                      XDIF AND ZOIF ARE ZERO
   625 \times 4 = X1
        Z4 = Z1
        IF (YDIF) 635.630.630
  630 Y4 = Y1 + DL
        GO TO 750
```

```
035 Y' = Y1 - UL
      60 10 750
                                   YDIF AND ZDIF ARE ZERO
C
  650 YM = Y1
       24 = 21
       1: (xD1F) 660+655+655
  655 X4 = X1 + OL
  GO TO 750
660 XM = XI - DL
GO TO 750
                                   ONLY XDIF IS ZERO
  675 IRRNCH = 2
       IF (LSTSEG .EQ. LSEGNO) GO TO 110
       A = 1. (YDIF YOIF)/(ZDIF ZDIF)
  678 8 = -2. A #21
       T1 = 21
T2 = 22
       GO TO 100
  680 XV = X1
       24 = HT
       YH = Y1 + (ZM - ZI) + YDIF / ZDIF
       60 TD 750
                                   ONLY YOIF IS ZERO
  700 14RNCH = 3
       1F (LSTSEG .EQ. LSEGNO) GO TO 110
A = 1.+ (XDJF=XDJF)/(ZDJF=ZDJF)
       GO TO 678
  705 YM = Y1
ZM = RT
        X4 = X1 + (ZM-Z1) * XD1F/Z01F
       GO TO 750
                                   ONLY ZDIF IS ZERO
       T1 = X1
       12 = 12
       GO TO 100
  730 ZM = 21
X4 = RT
        Y'4 = Y1 . (XM-X1) . YOIF/XOIF
   CHECK RANGE DF RESULTING PUINT
750 1F (X1 *LE * XM *ANO * XM *LE * X2) GO TO 760
1F (X2 *LE * XM *AND * XM *LE * XI) GO TO 760
       GO TO 850
   760 1F (Y1 .LE. YM .ANO.YM .LE. Y2) GO 70 770 1F (Y2 .LE. YM .AND.YM .LE. Y1) GO TO 770
        CO TO 850
   770 1F (Z1 .LE. Z4 .AND. ZM .LE. Z2) GO TO 999
1F (Z2 .LE. ZM .AND. ZM .LE. Z1) GO TO 999
   850 PPINT 870. XM.YM.ZM
   870 FORMAT (48HOERHOR - POINT GIVEN BY NEWPNT NOT ON LINE. XM= .
               F14.3.5H YM= .F14.3.5H ZM= .F14.3)
   880 CALL EAST
   999 LSTSEG = LSEGNO
        RE TURN
        SUBROUTINE HOGEOL
        ENTRY RUGEOL READS AND STORES ALL GEOLOGY FILE DATA
        ENTRY FINDL OFTERMINES WHAT LAYER (LL) INCLUDES POSITION ZZ AT POLE (III+JJ)
```

```
C
         COMMON /FPOLE/ XX.YY.ZZ.II.JJ.LL
COMMON /GEOLFL/ NX.NY.SCALEX.SCALEY.INDEX(25).PROP(6.25)
COMMON /ZSAVE/ ZSTOR (30.30.25).LFLAG(25)
          DIMENSION HOLD (27)
C
    DO 30 1 = 1.25
LFLAG(1) = 0
30 CONTINUE
    READ (50.60) NA.NY.SCALEA.SCALEY.(INDEX(ILAYR).ILAYR=1.25).

((PROP([:IKOCK).1=1.6).IROCK=1.25)

GO FORMAT (215.2(E18.10).2512.(E18.10))
     LIM = NA • NY
DO 200 K = 1.LIM
READ (50.80) (HOLD(L).L=1.27)
80 FORMAT ((E18.10))
          I = HOLD(I)
           J = HOLD(2)
          Do 150 1Z = 1.25
          ZSTOR(1+J+1Z) = HOLD(1Z+2)
   150 CONTINUE
          IF (M .OT. 1) GO TO 200
DO 170 IY = 1.25
          IF (HOLU(1Y+2) .GT. -10.0 ES1) LFLAG(1Y) = 1
    170 CONTINUE
   200 CONTINUE
          RETURN
C
          ENTRY FINDL
                                                   FIND LOWEST HOLDZ(K) FOR WHICH
C
                                                            HOLDZ(K) GE ZZ
          ZLOW = 999999.
   ZLOW = 999999.

LL = 0

600 DO 700 K = 1.25

IF (LFLAG(K) .EO. 0) GO TO 700

TESTZ = ZSTOR (11.JJ.K)

IF (TESTZ .LT. ZZ) GO TO 700

IF (TESTZ .GT. ZLOW) GO TO 700

ZLOW = TESTZ
    700 CONTINUE
   IF (LL .GT. 0) GO TO 800
PPINT 720, XX.YY.ZZ
720 FORMAT (14HOERROR - POINT .3(F14.3.2X).12HABOVE GROUND)
    CALL EXIT
BOO LSTII = II
LSTJJ = JJ
           RETURN
           END
```

C. PROGRAM GENTAL

```
PROGRAM GENTAL
С
         THIS PROGRAM GENERATES A TUNNEL FILE USING CARO INPUT ONLY.
BYPASSING GEOLOGY FILE REDUIREMENT
C
C
         DIMENSIUN CD(8)
DATA OPUS /-10./
Ç
         REWIND 40
 PHINT 4005
4005 FORMAT (///-20X-33H GEOLOGY PARAMETERS FOR TUNNEL
 PRINT 4006
4006 FORMATY//-5X+105H THIS GEOLOGY UNCONF
                                                             UNCONF INEO
                                                                                    ABRASIVENESS
                                                                                                              ROC
 1K GUALITY
PRINT 4007
4007 FORMAT(2X-105H CEASES AT(FEET) COMPRESSIVE
LIGNATION TEMPERATURE RATE
                                                                        WATER INFLOW
                                                                                                              OES
 PAINT 4008
4008 FORMAT (5X+105H
                                                        STRENGTH (PSI)
                          (LH/FT++3)
                                                                           (GAL/HIN)
  100 REAO )10. (CO(1).I=1.8)

110 FORMAT (dF10.4)

CD(2)=CD(2)/1000.

IF (CD(1) .LT. 0. .OR. CD(1) .GT. OPOS) GO TO 140

PRINT 120. CO(1)
   120 FORMAT (34HDERROR - CARO SPECIFYING POSITION .F10.4.
  140 IFLAG = CD(8)
  | 1A=CO(3)

OPOS = CO(1)

WPITE(40*210) (CO(1)*I=1*2)*1A*(CD(J)*J=4*7)*IFLAG

210 FORMAT(2E18*10*15*4E18*10*15)

IF (CD(1) *LT. 0*) GO TO 900

PPINT 250* (CO(1)*1=1*7)*IFLAG

250 FORMAT ( 3X*7(F14*4*1X)*2X*14)
         14=CO(3)
         GO TO 100
  900 PPINT 910
  910 FORMAT (43HOTUNNEL FILE GENERATION TERMINATED NORMALLY )
REWIND 40
         CALL EXIT
         END
```

D. PROGRAM CONTROL

GOLETA FOR	TRAN 1.3 . AUTO RFL . (07-12-72)		07/25/72
	PROGRAM CONTPL	CONTRL	2
000003	COMMON /WHFELS/ AF.AF.AMAX.AMAXL.AMINL.BSL.CARCAP.CP.OF.DF.DTAS	WHEELS	2
	I. OTHA-DTU-FL-FC-FR-FT-HPA-HPEA-HPEV-HPFV-HPV-LOCD-MC-ML	WHEELS	3
	2. NCAPS.NPOINT.NTD.NTM.NTMAX.XP.NTMILP.NTMLPP.NTRACK.SL	WHEELS	4
	3. TCURVX (20) .TCURVY (20) .TMAINT .TWE .VD .VS .VE .VF .VMAX .WC .WL .XDS	WHEELS	5
	4. MAXLD.NUMLD.LQUE.QUC.WUC.STATUS(36).WHY(24).MLTYP.WMR.ECONEQ.	WHEELS	6
	5 ECONSS.ELOCO.EMUCKC.ETRACK.ESWITC.EUNLOA.ERMAIN.IIBORE.	WHEELS	7
	6 ISW(25)*NTINIT*TCCV*TMCV COMMON /OLDCOM/ IFILD*KSTOP(25)*KUNLO*LSTOP*LVEHCL*NBYRY*NSWCH	WHEELS	ğ
000003	77	WHEELS	10
	I. NTRDA.NVFHCL.NIMSWT.SWITCH(20).TFC(25).TDP(25).TSTAT(25.4) 2. UTIME(25).LDADR.MUKOT.XGS.IEXCA.MGS(5).MCV.MFLAGC.DUMMY(20)	WHEELS	ii
000003	COMMON /NEWCOM/ LIFILO.LKSTOP(25).LKUNLO.LLSTOP.LLVHCL.LNBYBY	WHEELS	12
000003	1. LNSWCH-LNTRDA-LNVHCL-LNMSWT-FSWTCH(20) +FTFC(25) +FTOP(25)	WHEELS	13
	2. FTSTAT(25.4).FUTIME(25).LLCADR.LMUKOT.FXGS.LTEXCA.LMGS(5)	WHEELS	14
	3. LMCV.LMFLAC.FDUMMY(19)	WHFFLS	15
000003	DIMENSION COMOLO(260).COMNEW(260).LTSTAT(25.4).ITSTAT(25.4)	WHIFELS	16
000003	EQUIVALENCE (NVEHCL .NTRAIN.NTRUCK) . (LVEHCL .LTRAIN.LTRUCK)	WHEELS	17
	1. (COMOLD.IFILD).(COMNEW.LIFILD.IFILLO).(NTDA.LNTROA)	WHEELS	18
	2. (FTSTAT.LTSTAT).(TSTAT.17STAT)	WHEELS	19
	3. (LLVHCL.LLTRAN.LLTRUK). (LNVHCL.LNTRAN.LNTRUK)	WHEELS	20
000003	COMMON /BORING/ CL(3).CPC.OTA.OTC.DTCD.OTC.OTM.KK.PBM.R(100).RC	BORING	2
	A. RPM.TR.XCPC. MASSEM.MBM.MBORE.MCD.MDISAS.LNCHNG.LNCUTR.NCUT(20)	BORING	3
	B. WEAR(100).EBORFQ.ETRANS	BORING	•
000003	COMMON /BLAST / ADB+ADH+AH+CBIT+CBURN+CCAP+CEX+CM+CPL+CSTEEL	BLAST	2
	B. LO.LOB.LRIT.LBURN.LSTEEL. MEN.NO.NOR.NH.NHB.PF.POB.POD.TCHG	BLAST	3
	C. TIN. TOUT . TYPEPF . WPL . JUMIN . JUMOUT . NORILB . NORILL	BLAST	2
000003	COMMON /CONVEY/ ACM+DTRS+OWM+EE+FL+MP+QC+SMIN+WRI	BELTS	č
	1. WO.XLF. NEURGE.OF.OD.SM. NTCR. NTWR. AR. VRI. NEXON. NGEO. XF.LNSURG.		
	2 STIME DAMP THIS DING FLM	ALL	2
000003	LUMMUN ZALL Z XIOSINOTAORONOCSOTAMBOFLOWOIFLAG 10 ATOOSEOSKOTONTOXOPPOXMAXOTMAXONXOVOTPRINTOTPRNTOIMOVEOJMETH	ALL	3
	1. AT-0.E.SK.T.DT-X.PP.XMAX.TMAX.DX.DV.TPRINT-DIPRNT-INDVE-JMETH 2. TSHFT-REPORT-DPPCT-TO-XO-XOISCH-ICHNG-XCHNG-TCHNG	ALL	4
000003	EQUIVALENCE (JMOVE + IMOVE) + (IMETH + JMETH)	ALL	5
000003	COMMON/MONEY JMMHM+OJM+OJMHM+OJMRO+DJMBMM+DMAINT+DJMRM+DJMGS	ALL	6
000003	I. PMGS.JMCV.OJMEC.ROPLAN.HPLANT.GSPLAN	ALL	7
	2. ECPLAN.ROTIME.HTIME(2).GSTIME.ECTIME	ALL	8
000003	COMMON/PERFRM/ ROUTIM.RODTIM.UMHTIM.DMHTIM.GSUTIM.GSOTIM.ECUTIM	ALL	9
00000	1. ECOTIM.GOAY.GADV.GEND.GREG	ALL	10
000003	COMMON/LABOR/ RDMEN(10.2) . HMEN(10.2.2) . GSMEN(10.2) . ECMEN(10.2)	ALL	11
000003	REAL JUMMH.LD.LOB.LBIT.LBURN.LSTEEL.JMCV	ALL	12
000003	DIMENSION G(B)	ALL	13
000003	EQUIVALENCE (G+XT)+(XE+XOE)+(PR+PC)	ALL	14
000003	COMMON /GRNO/ PSST(60+9).MAXPSST. UCS.UCSC.RATERR.RATESC.RATESS	SUPPORT	S
	1. GSLOS.IAS.IST.ERBORI.ESCPLA.GOOM.GSETOO.MAXPSS	SUPPORT	3
000003	COMMON /ENVC/ MAXMEN+TOTHP+QM+QD+VAMIN+VAMAX+QG(10)+	ENVIRON	
	I TA-TD-WA-FKD-FKT-CPA-CKA-REFRAT-AMC(10)-00R-EVENTP-CPUMP	ENVIRON	
. 000003	DIMENSION DETOPICES!	CONTRL	10
000003	EOUTVALENCE (JSTOP+LKSTOP)	CONTRL	11
000003	DATA (STATUS=6HSTOPPE+6HD+ EMP+2HTY+ 6HSTOPPE+6HD+ FUL+1HL+	CONTRL	12
	1 6HACCEL . 6H EMPTY . 1H . 6HACCEL . 5H FULL . 1H . 6HFULL S. 6HPEED .	CONTRL	13
	2 SHEMPTY. 6HFULL S. 6HPEED 4HFULL. 6HDECEL. SHEMPTY. IM .	CONTRL	14
	3 6HOFICEL . SH FULL . IH . 6HIN SWI . 6HTCH . E. 4HMPTY .	CONTRL	15
	4 6HIN SWI-6HTCH. F. 3HULL. 6HIN DIS. 6HCHARGE. 5H AREA. 6HIN MAI.	CONTP	16 17
	6 6HNTENAN 2HCE)	CONTRI	18
	7. (WHY=6HAT FAC+6HE; LOA+4HDING+ 6HTRAIN +5HAHEAO+1H +	CONTRL	10

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                  CONTRL
                                                                                                                            07/25/72
                     6 6HTRAIN .6HCOMING.IM . 6HEXTERN.6HAL REA.4HSONS.
6 6HWAITIN.6HG TO U.5HNLOAD. 6HWAITIN.6HG TO L.3HOAD.
6 6HAT FAC.6HE. IN . 5HQUEUE. 3*6H.....)
DATA (COSTS=30*0.).(DX=0.).(DV=0.).(LOADR=0.).(HBORE=0).(MBM=0)
[. (LNCUTR=0).(RATMAX=0).(IDLE=0).(NOTIDL=0)
                                                                                                                 CONTRL
                                                                                                                                19
                                                                                                                 CONTRL
                                                                                                                 CONTRL
                                                                                                                                21
                                                                                                                                53
                                                                                                                 CONTRL
000003
                                                                                                                 CONTRL
000003
                     DATA INTX/0/
                                                                                                                 CONTRL
                                                                                                                                24
                                                                                                                                25
26
                                                                                                                 CONTRL
                                                                                                                 CONTRL
            CCC
                      INITIALIZATION ONLY
                                                                                                                                27
                                                                                                                 CONTRL
                                                                                                                 CONTRL
                                                                                                                                28
29
                                                                                                                 CONTRL
000003
                                                                                                                                30
                     CALL INPUT
                                                                                                                 CONTRL
000004
                     CALL BOPE CALL CUTTER
                                                                                                                 CONTRL
                                                                                                                                31
32
                                                                                                                 CONTRL
                     CALL REPAIR
                                                                                                                                33
34
35
                                                                                                                 CONTRL
000006
                     CALL CVLOAD
                                                                                                                 CONTRL
000007
                                                                                                                 CONTRL
                     CALL RAILHL
                                                                                                                                36
000011
                                                                                                                 CONTRL
000012
                                                                                                                                37
                     CALL RAILEX
                                                                                                                 CONTPL
000013
                     CALL RATLDS
                                                                                                                 CONTRL
                                                                                                                                38
000014
                     CALL RAILMT
                                                                                                                 CONTRL
                                                                                                                                39
000015
                     CALL GRNSUP
                                                                                                                 CONTRL
                                                                                                                                40
                     CALL GSMAIN
                                                                                                                 CONTRL
000016
000017
                     CALL ENVIR
                                                                                                                 CONTRL
000030
                     CALL REPORT
                                                                                                                                43 44 45
                                                                                                                 CONTRL
                                                                                                                 CONTRL
                     CALL REPORC
000022
                                                                                                                 CONTRL
                     CALL INPUT2
DO 310 II=1.260
COMMEW(II)=COMOLD(II)
000023
000024
                                                                                                                 CONTRL
                                                                                                                                CONTRL
000026
                                                                                                                 CONTRL
               310 CONTINUE
                                                                                                                 CONTRI
000030
            C ...
                                                                                                                 CONTRL
                     PRINT 410
                                                                                                                 CONTRL
000032
               410 FJPMAT (1H1)
TPRINT=T+DTPRNT
000036
                                                                                                                 CONTRL
000036
                                                                                                                 CONTRL
                     CALL OUTPUT
                                                                                                                 CONTRL
000040
                                                                                                                                55
56
000041
               400 CONTINUE
                                                                                                                 CONTRL
                                                                                                                 CONTRL
                                                                                                                                57
58
59
                                                                                                                 CONTPL
                  START LOOP ON DT
                                                                                                                 CONTPL
                                                                                                                 CONTRL
                                                                                                                                60
61
62
                                                                                                                 CONTRL
               401 XTEMP=X-XDISCH
IF (XTEMP .LE. XT) GO TO 405
000041
                                                                                                                 CONTRL
                                                                                                                 CONTRL
                                                                                                                 CONTRL
                                                                                                                                63
            C---
            C
                                                                                                                 CONTRL
                                                                                                                                64
65
66
67
68
                  READ NEW GEOLOGY
                                                                                                                 CONTRL
            C
                                                                                                                 CONTRL
                                                                                                                 CONTRL
000046
                     READ (40+402) G
                                                                                                                                69
70
71
                                                                                                                 CONTRL
                     ICHNG=1
000053
                     TCHNG=(1-T0)/24.
                                                                                                                 CONTRL
000054
000057
                     XCHNG=X-XD1SCH
                                                                                                                 CONTRL
                     IF (EOF. 40) 600.404
                                                                                                                 CONTRL
000061
```

CONTRL

402 FORMAT (2E18.10.15.4E18.10.15)

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                        CONTRL
          404 GO TO 401
                                                                                                    CONTRL
                                                                                                                  74
75
000064
                                                                                                    CONTRL
                                                                                                                  76
                                                                                                    CONTRL
                                                                                                                  77
                ROCK DISINTEGRATION
                                                                                                    CONTRL
                                                                                                    CONTRL
                                                                                                                  79
             405 CONTINUE
420 CALL RORER
000065
                                                                                                    CONTRL
000065
                                                                                                    CONTRL
                                                                                                                  81
000066
                  CALL MAINT
                                                                                                    CONTPL
                                                                                                                  82
000067
                  CALL CUTCHS
CALL RAILTR
                                                                                                    CONTRL
                                                                                                                  83
                                                                                                    CONTRL
                                                                                                                  84
             406 CALL RAILOS
                                                                                                    CONTRL
                                                                                                                  85
000071
                                                                                                    CONTRL
000072
                  CALL RAILXT
000073
                  CALL RAILMT
                                                                                                    CONTRL
                                                                                                                  87
000074
                  CALL LOADCY
                                                                                                    CONTRL
                                                                                                                  88
000075
                  CALL CURPR
                                                                                                    CONTRL
                                                                                                                  89
000076
                  CALL GROUN
                                                                                                    CONTRL
                                                                                                                  90
                                                                                                                  91
                  CALL GSMNT
                                                                                                    CONTRL
000077
                                                                                                                  92
93
                  CALL ENVIRC
                                                                                                    CONTRL
000100
           C..
                                                                                                    CONTRL
                                                                                                    CONTRL
                                                                                                                  94
                                                                                                                  95
                                                                                                    CONTRL
                  UPDATING X.T. AND FLAGS
                                                                                                    CONTRL
                                                                                                                  96
                                                                                                    CONTRL
           C..
000101
000103
000105
000107
000111
009113
                                                                                                    CONTRL
                  T=T+01
                                                                                                    CONTRL
                                                                                                                  99
                  X=X+DX
                                                                                                    CONTRL
                                                                                                                 100
                  00 446 11=1.260
                                                                                                                 101
                  COMOLD (T1) = COMNEW (T1)
                                                                                                    CONTRL
                                                                                                    CONTRL
             446 CONTINUE
                  IF (MBM.EQ.0) GOTO 480
                                                                                                    CONTRL
                                                                                                                 103
000114
                                                                                                    CONTRL
                  MRORF = 1
                                                                                                                 104
                                                                                                                 105
                                                                                                    CONTRL
                  GOTO 492
                                                                                                    CONTRL
                                                                                                                 106
000116
             480 IF (MROPE.FO.1) MRORE=0
                                                                                                                 107
000121
                  IF (LNCUTR.EQ. 0) GOTO 482
                                                                                                    CONTRL
                                                                                                    CONTRL
                  MRORE = 2
                                                                                                                 109
110
111
112
                                                                                                    CONTRL
000123
                  GOTO 492
                                                                                                    CONTRL
000124
             482 IF (MRORE.EQ.2) MRORE=0
IF (NRYRY.EQ.9) GOTO 484
                                                                                                    CONTRL
                                                                                                    CONTRL
000130
                  MRORE=3
             GOTO 492
484 IF (MRORE.EQ.3) MRORE=0
1F (NSWCH-1) 490.488.486
                                                                                                    CONTRL
                                                                                                                 113
000131
                                                                                                    CONTRL
000132
                                                                                                    CONTRL
                                                                                                                 į 15
000135
             486 MADRE = 5
GOTO 492
                                                                                                    CONTRL
                                                                                                                 116
117
000140
                                                                                                                 118
119
120
121
                                                                                                    CONTRL
             488 MBORE=4
000142
             GO TO 492
490 IF (MRORE.EQ.4 .OR. MBORE.EQ.5) MBORE=0
000143
                                                                                                    CONTRL
                                                                                                    CONTRL
                                                                                                    CONTRL
             492 IF (LOADR .EQ. 0) GO TO 494
000154
                                                                                                                 155
                                                                                                    CONTRL
                  NUQUENUQU+1
000155
                                                                                                    CONTRL
000157
                  GO TO 500
                                                                                                                 124
                                                                                                    CONTRL
000157
             494 IF (MBORE .NE. 6) GO TO 496
                                                                                                    CONTRL
                                                                                                                 125
                  MRORE=0
000161
                                                                                                    CONTRL
                                                                                                                 126
000162
                  NURUEO
                                                                                                    CONTRL
                                                                                                                 127
                  G010 530
                                                                                                    CONTRL
000163
             496 NUQU=0
```

GO TO 472

0002.7

183

CONTRL

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                       CONTRL
                                                                                                             07/25/72
             471 INIX=0 472 CONTINUE IF (T.LT.TMAX .AND. X.LT.XMAX) GOTO 400
000327
000330
000330
                                                                                                   CONTRL
                                                                                                               184
185
                                                                                                   CONTRL
                                                                                                                186
          CONTRL
                                                                                                                147
                                                                                                               188
                  FNDING STMULATION
                                                                                                   CONTPL
                                                                                                               189
190
191
                                                                                                   CONTRL
                                                                                                               192
193
194
000341
             473 CALL OUTPUT
                                                                                                   CONTRL
                  CALL WEPONS
                                                                                                   CONTRL
000342
000343
                                                                                                   CONTRL
000344
                  RETURN
                                                                                                               195
             600 PATHT 501 601 FORMAT (24HO GEOLOGY FILE EXHAUSTED)
                                                                                                   CONTRL
                                                                                                               196
000346
000352
                                                                                                               198
199
200
201
                  RETHRY
000352
                                                                                                   CONTRL
000354
             605 PRINT 474
                                                                                                   CONTRL
             474 FORMATI//+1x,40H SIMULATION ENDED-NO ADVANCE FOR 5 DAYS
                                                                                                1 CONTRL
000360
                                                                                                   CONTRL
000360
00036? END **OLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED NTPUCK
                                                                                                   CONTRL
                                                                                                               202
LTRAIN
LTRUCK
IFILD
LIFILD
LNTRDA
LLTRAN
LLTRUK
LNTRAN
LNTRUK
IMOVE
JMETH
XDE
PC
NVEHCL
NTDA
LLVHCL
LNVHCL
JHOVE
IMETH
XΣ
PR
```

E. SUBROUTINE INPUT

GULETA I	FORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/7
	SUBROUTINE INPUT	INPUT	2
	C+++	INPUT	3
200000	COMMON /WHEELS/ AE+AF+AMAX+AMAXL+AMINL+BSL+CARCAP+CP+DE+DF+DTAS	WHEELS	2
	1. DTM4.DTU.FL.FC.FR.FT.HPA.HPFA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHEELS	3
	2. NCAPS.NPOINT.NTD.NTM.NTMAX.XP.NTMILP.NTMLPP.NTRACK.SL	WHFELS	4
	3. TCHRVX(20).TCHRVY(20).TMAINT.TWE.VD.VS.VE.VF.VMAX.WC.WL.XDS	WHFELS	- 5
	4. MAXLD.NUMI,D.LQUE.QUC.WUC.STATUS(36).WHY(24).MLTYP.WMR.ECONEG.	WHEELS	6
	S ECONSS+ELOCO+EMUCKC+ETPACK+ESWITC+EUNLOA+ERMAIN+IIBORE+	WHEELS	7
	6 ISH(25).NTINIT.TCCV.TMCV	WHFELS	8
200000	COMMON /OLDCOM/ IFILD+KSTOP(2S)+KUNLO+LSTOP+LVEHCL+NRYPY+NSWCH	WHFFLS	9
	1. NTPDA.NVFHCL.NUMSWT.SWITCH(20).TFC(25).TOP(25).TSTAT(25.4)	WHFELS	10
	2. UTIME(25).LDADR.MUKOT.XGS.IEXCA.MGS(5).MCV.MFLAGC.DUMMY(20)	WHEELS	11
200000	COMMON /NEWCOM/ LIFILD+LKSTDP(25)+LKUNLO+LLSTOP+LLVHCL+LNRY#Y	WHFELS	12
	1. LNSWCH.LNTRDA.LNVHCL.LNMSWT.FSWTCH(20).FTFC(25).FTOP(25)	WHEELS	13
	2. FTSTAT(25.4).FUTIME(2S).LLOADR.LMUKDT.FXGS.LIEXCA.LMGS(5)	WHEELS	14
	3. LMCV.LMFLAC.FDUMMY(19)	WHEELS	15
200000	OTHERSTON COMOLD (260) . COMNEW (260) .LTSTAT (25.4) .TTSTAT (25.4)	WHEELS	16
200002	EDUIVALENCE (NVEHCL.NTRAIN.NTRUCK). (LVEHCL.LTRAIN.LTRUCK)	WHFFLS	17
	1. (COMOLO.IFILD). (COMNEW.LIFILO.IFILLO). (NTDA.LNTRDA)	WHEELS	18
	2. (FTSTAT.LISTAT).(TSTAT.ITSTAT)	WHEELS	19
	3. (LLYHCL.LLTRAN.LLTRUK).(LNYHCL.LNTRAN.LNTRUK)	WHEELS	20
20000	COMMON /BORING/ CL(3).CPC.DTA.DTC.DTCD.DTD.DTM.KK.PBM.R(100).RC	BORING	2
	A. RPH.TR.XCPC. MASSEM.MRM.MBORE.MCD.MDISAS.LNCHNG.LNCUTR.NCUT(20)	BORING	3
	8. WEAR (100) . EROREG. ETRANS	BORING	4
00002	COMMON /CONVEY/ ACM-DIRS-DHM-FF-FL-HP-QC-SMIN-HRI	BELTS	ž
	1. WO.XLE.MEHRGE.OF.OD.SM.OTCP.DTMR.AR.VRI.MEKON.NGEO.XE.LNSURG.	:-	1
	S CLIME - JUMB - ULMI - ULMO - ELM		2
20000	COHNON /BLAST / ADB+ADH+AH+CRIT+CRURN+CCAP+CEX+CM+CPL+CSTEEL	BLAST	2
	B. LD.LDB.LBIT.LRUPN.LSTEFL. MFN.ND.NDR.NH.NHR.PE.POB.POD.TCHG	BLAST	3
	C+ TIN+TOUT+TYPEPF+WPL+JUMIN+JUMOUT+NDRILB+NORILL	BLAST	4
20000	COMMON /ALL / XT+STR+IA+POD+CS+TAMB+FLOW+IFLAG	ALL	2
	1. AT.D.E.SK.T.DT.X.PR.XMAX.TMAX.DX.DV.TPRINT.DTPRNT.IMDVE.JMETH	ALL	3
	2. TSHFT.RFPORT.OPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	4
00002	EDUIVALENCE (JYONE-HOOM) + (AVOMI-FYOND)	ALL	5
200002	CDMWONYWOMEAN JMMHM+DJMMH-DJMHD+DJMBMM+DMAINT+DJMGS	ALL	6
	1. PMGS+JMCV+DJMEC+RDPLAN+HPLANT+GSPLAN	ALL	7
	2. ECPLAN. ROTIME. HTIME (2). GSTIME. ECTIME	ALL	8
20000	COMMON/PERFRM/ ROUTIM+ROOTIM+UMHTIM+DMHTIM+GSUTIM+GSDTIM+ECUTIM	ALL	9
	1. ECDTIM.GRAY.GADV.GEND.GREG	ALL	10
00002	COMMON/LAROR/ ROMEN(10+2)+HMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
20000	REAL JMMHM.LD.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	12
50000	DIMENSION G(A)	ALL	13
20000	EQUIVALENCE (G+XT)+(XE+XOE)+(PR+PC)	ALL	14
200002	CDMHON /GRND/ PSST(60+9)+MAXPSST+ UCS+UCSC+RATERA-RATESC+RATESS	SUPPORT	2
	1. GSLOS+IAS+IST+FRBORI+ESCPLA+GOOW+GSETDO+MAXPSS	SUPPORT	3
20000	CDMMON /ENVC/ MAXMEN.TOTHP.QM.OO.VAMIN.VAMAX.OG(10).	ENVIRON	2
	1 TA.TO.WA.FKO.FKT.CPA.CKA.REFRAT.AMC(10).QDR.FVFNTP.CPHMP	ENVIRON	3
	C***	INPUT	11
20000	DIMENSION IMAGE()4).METHOD(10).MOVER(10)	INPUT	12
00002	DATA (METHOD(I) •I=1•10)/4HRDRE•SHBLAST•3HJET•6HPELLET•6#SHDUMMY/	INPUT	13
20002	DATA (MOVER(J)+J=1+10)/ SHRAILS+ 6HTRUCKS+ SHBELTS+ 7*SHDUMMY/	INPUT	14
00005	OATA (PI=3.1415926535A98)	INPUT	15
50000	OTHENSION ISTA(25) .TPDS(25) .TSPD(25) .TMAIN(25)	INPUT	16
20000	DIMENSION BOMEN(10) . BOCST (10) . RAMEN(10) . RACST (10) . CVMEN(10) .	INPUT	17
	1 CVCST(10) .GMEN(10) .GCST(10) .VCMEN(10) .VCCST(10)	INPUT	18



```
INPUT
                                                                                                              07/25/72
GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)
                                                                                                    INPUT
                  NAMELIST /ROPE
900002
                                                                                                                 20
                     CL.CPC.DTA.DTC.DTCD.DTD.DTH.KK.PBM.R.RC.RPM.TR.XCPC
                                                                                                    INPUT
                                                                                                    INPUT
                 2.EBOREQ.ETRANS.DJMBMM.BOMEN.BOCST
                                                                                                                 21
                                                                                                    INPUT
                                                                                                                 22
200000
                  NAMELIST /BLAST /
                                                                                                    INPUT
                                                                                                                  24
                  NAMELIST /JET
                                                                                                    INPUT
000002
                                                                                                                 25
                                                                                                    TNDIIT
                                                                                                    INPUT
000002
                  NAMELIST /PELLET/
                                                                                                    INPUT
                                                                                                                  27
                                                                                                    INPUT
                                                                                                                  28
000002
                  NAMELIST /RAILS /
                      AE.AF.AMAX.AMAXL.AMINL.BSL.CARCAP.CP.DE.DF.DTAS.DTMA.DTU
                                                                                                                  29
                                                                                                     TYPUT
                                                                                                    INPUT
                                                                                                                  30
                      NSWCH. NGEO. NEXON. XDE . AR. VRI.SM
                      EL .FC.FR.FT.HPA.HPEV.HPEA.HPEV.HPFA.HPEV.HPV.LOCD.MC.ML
                                                                                                     INPUT
                      NCARS.NPOINT.NTD.NTM.NTMAX.XP.NTM1LP.NTMLPP.NTRACK.SL
                                                                                                    INPUT
                                                                                                                  32
                 3.
                      TCHRVX.TCHRVY.TMAINT.TWE.VD.VS.VE.VF.VMAX.WC.WI .XDS.MAXLD
                                                                                                    INPUT
                                                                                                                  33
                                                                                                                  34
35
                      NVEHCL . NUMSHT . SWITCH . ISTA . TPOS . TSPD . TMAIN . KSTOP . MLTYP . WMR
                                                                                                    TNPILT
                      ELOCO.FHUCKC.FTRACK.ESWITC.EUNLDA.ERMAIN.JMMHM.NUMLD.ISW
                                                                                                    INPUT
                                                                                                    INPUT
                                                                                                                  36
                      RAMEN.RACST
                  NAMELIST /TRUCKS/
AF.AF.AMAX.AMAXL.AMINL.BSL.CARCAP.CP.DE.DF.DTAS.DTMA.DTU
                                                                                                                  37
                                                                                                    INPUT
200000
                                                                                                                  38
                                                                                                    INPUT
                      NSWCH.NGEQ.NEXON.XDE.AR.VBI
                                                                                                    INPUT
                                                                                                                  39
                      EL.FC.FR.FT.HPA.HPFV.HPFR.HPFV.HPFA.HPFV.HPV.LOCO.MC.ML
                                                                                                                  40
                                                                                                     INPUT
                      NCARS *NPOTNT *NTD *NTM *NTM AX *XP *NTM *LP *NTM LPP *NTRACK * $L
TCURVX *TCURVY *TM A INT *TWE *VD *VS *VE *VF *VM AX *WC *WL *XDS *MAXLD
NVEHCL *NUMSWT *SWITCH *ISTA *TPOS *TSPD *TM A IN *KSTDP *MLTYP *WMR
                                                                                                    INPUT
                                                                                                                  41
                                                                                                     INPUT
                                                                                                     INPUT
                                                                                                                 44
                      ELOCO.EMUCKC.ETRACK.ESWITC.EUNLDA.ERMAIN.JMMHM.NUMLD.ISW
                                                                                                     NPILT
                                                                                                     INPUT
                      TRHEN.TROST
                                                                                                                 46
                  NAMELIST /BELTS /
                                                                                                     INPUT
200002
                                                                                                    INPUT
                 1
                                                                                                                  48
                  NAMELIST /GENERL/
                                                                                                    INPUT
000002
                                                                                                                  49
                      D.DT.X.YMAX.T.TMAX.DTPRNT.SK.PR.OPPCT.REPORT.XDISCH.E
                                                                                                    INPUT
                                                                                                                  50
                  NAMELIST/GROUND/
                                                                                                     INPUT
200000
                                                                                                                  51
                                                                                                     INPUT
                 1 UCS.UCSC.RATERB.RATESC.RATESS.MAXPSS.ERBORT.ESCPLA.DJMGS
                                                                                                    INPIRT
                                                                                                                  52
                      GDON . GSETDO . GMEN . GCST
                                                                                                     INPUT
                                                                                                                  53
                  NAMELIST/LOADER/
000002
                                                                                                                  54
                                                                                                     INPUT
                     AR. VRI.SM. TCCV. TMCV. WMR. MLTYP. ECONEQ. ECONSS. JMCV
                                                                                                                  55
                                                                                                     INPUT
                      CVMEN.CVCST
                                                                                                                  56
                                                                                                     INPUT
000002
                  NAMELIST/ENVIRC/
                                                                                                                  57
                      EVENTP. MAYMEN. TOTHP. TA
                                                                                                     INPUT
                      QH.QD.VAMIN.VAMAX.TD.WA.CPA.CKA.REFRAT.AMC.VCMEN.VCGST.CPUMP
                                                                                                    INPUT
                                                                                                                  58
                                                                                                     INPUT
                                                                                                                  59
                                                                                                     INPUT
                                                                                                                  60
                  EQUIVALENCE (ROMEN(1) + ROMEN(1+1))
000002
                                                                                                     INPUT
                                                                                                                  61
                  FOUTVALENCE (ROCST(1) . ROMEN(1.21)
EQUIVALENCE (VCMEN(1) . ECMEN(1.1))
200000
                                                                                                     INPUT
000002
                                                                                                     INPUT
                                                                                                                  63
                  FOUTVALENCE (VCCST (1) . FCMEN (1.21)
000002
                  EQUIVALENCE (RAMEN(1) + HMEN(1-1-1))
EQUIVALENCE (RACST(1) + HMEN(1-2-1))
                                                                                                     INPUT
000002
                                                                                                     INPUT
                                                                                                                  65
000002
                                                                                                     INPUT
                                                                                                                  66
                  EQUIVALENCE (CVMEN(1) + HMEN(1-1-2))
000002
                                                                                                     INPUT
                                                                                                                  67
                  FOUTVALENCE (CVCST (1) +HMEN(1+2+2))
200000
                  EQUIVALENCE (GHEN (1) + GSHEN (1 +1))
                                                                                                     TUPUT
                                                                                                                  68
000002
                                                                                                                  69
                                                                                                     INPUT
                  EQUIVALENCE (GCST (1) + GSMEN (1+2))
000002
                                                                                                                  70
71
                                                                                                     INPUT
           C---
                  EFUNC(X)=1.8*EXP(.084*X)
                                                                                                     INPUT
200000
                                                                                                    INPUT
                                                                                                                  73
                THE FIRST SECTION OF SUBROUTINE INPUT
                                                                                                    INPUT
```

```
07/25/72
                                                                                     INPUT
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                  COPIES CARO-IMAGES FROM FILE4 (CARD READER)
ONTO FILES (INPUT FILE FOR REMAINDER OF PROGRAM)
                                                                                                                      INPUT
                                                                                                                                      74
75
                                                                                                                      INPUT
                                                                                                                      INPUT
                                                                                                                                      76
                  AND FILES (OUTPUT FILE FOR THE PROGRAM)
                                                                                                                      INPUT
                                                                                                                                      77
                                                                                                                      INPUT
            č•••
                                                                                                                      INPUT
                     LINE = 0
000013
                                                                                                                      INPUT
                                                                                                                                      80
                                                                                                                      INPUT
                                                                                                                      INPUT
                                                                                                                                      82
                  COC 6000 FORTRAN
                                                                                                                      INPUT
                                                                                                                      INPUT
                                                                                                                                      84
                  I READ (4.10) IMAGE
IF (EOF.4) 3.2
                                                                                                                      INPUT
                                                                                                                                      85
000014
                                                                                                                                      86
87
                                                                                                                      INPUT
000022
                                                                                                                      INPUT
                                                                                                                      INPUT
                                                                                                                                      88
                                                                                                                                      89
90
                                                                                                                      INPUT
                  85500 FORTRAN
                                                                                                                      INPUT
                                                                                                                      INPUT
                  I READ (4+10+ENO=3) IMAGE
                                                                                                                                      92
93
                                                                                                                      INPUT
                                                                                                                       INPUT
                                                                                                                                      94
95
                                                                                                                       INPUT
000025
                 10 FORMAT (1346.42)
                                                                                                                      INPUT
000025
                  2 WRITE (5.10) IMAGE
                 IF (MOD(LINE-40).eQ.0) WRITE (6.11)

11 FORMAT (1H1. 9X14HCARD-IMAGES.../)

IF (MOD(LINE-10).eQ.0) WRITE (6.12) (K. K=5.80.5)

12 FORMAT (1H0. 19X1615/ 14X6HCARD . 8(10H....................))
                                                                                                                                      96
97
                                                                                                                       INPUT
000033
                                                                                                                      INPUT
000043
                                                                                                                                      98
                                                                                                                      INPUT
000043
                                                                                                                      INPUT
000060
                                                                                                                                     100
                                                                                                                      INPUT
                     LINE = LINE+1
000060
                 WRITE (6.13) LINE. IMAGE
13 FORMAT (118. 2X13A6. A2)
                                                                                                                      INPUT
                                                                                                                                     101
000062
                                                                                                                       INPUT
                                                                                                                                     102
                                                                                                                      INPUT
                                                                                                                                     103
200071
                     GOTO I
                                                                                                                      INPUT
                                                                                                                                     104
000072
                  3 ENDFILE 5
                                                                                                                       INPUT
                                                                                                                                     105
000074
                     REWIND 5
                                                                                                                      INPUT
                                                                                                                      INPUT
                                                                                                                                     107
                                                                                                                       INPUT
                  READ FRAGMENTATION AND REMOVAL METHODS
                                                                                                                       INPUT
                                                                                                                      INPUT
                                                                                                                       INPUT
000076
                      READ (5.21) M.N
                                                                                                                      INPUT
000106
                 21 FORMAT (A6. 4XA6)
                     00 30 I=1.10
IF (M.EQ.METHOO(I)) GOTO 31
                                                                                                                       INPUT
000106
                                                                                                                       INPUT
000110
                                                                                                                       INPUT
060112
                 30 CONTINUE
                 WRITE (6-36) M
36 FORMAT (1H0 + 9X21HFRAGMENTATION METHOD + A6+
1 36H CANNOT BE SIMULATED AT THIS TIME....
2 31HJOB ARORTED BY SURROUTINE INPUT)
                                                                                                                       INPUT
000114
                                                                                                                       INPUT
000121
                                                                                                                                     118
                                                                                                                       INPUT
                                                                                                                       INPUT
                                                                                                                       INPUT
                      I = 0
151000
                                                                                                                       INPUT
                                                                                                                                     121
                 31 00 32 J=1.10
000122
                 IF (N.EO.MOVFR(J)) GOTO 33
32 CONTINUE
                                                                                                                       INPUT
000124
                                                                                                                       INPUT
                                                                                                                                     i 23
000126
                                                                                                                       INPUT
                 37 FORMAT (1HO. 9X16HMUCK REMOVAL 8Y . A6.
I 36H CANNOT RE SIMULATEO AT THIS TIME....
2 31HJO8 AROPTEO 8Y SUBROUTINE INPUT)
000130
                                                                                                                       INPUT
                                                                                                                                     125
                                                                                                                       INPUT
                                                                                                                       INPUT
000130
                                                                                                                       INPUT
                  33 IF (1.EO.O .OR. J.EQ.O) STOP
```

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                           INPUT
                                                                                                                  07/25/72
                   IMETH = I
JMOVE = J
000141
                                                                                                        INPUT
                                                                                                                     129
 000143
000144
                   READ (5.GENERL)
                                                                                                        INPUT
                                                                                                                     131
000147
                   WRITE 16 GENERL)
                                                                                                        INPUT
                                                                                                                     132
000152
                   GOTO (110-120-130-140). IMETH
                                                                                                        INPUT
                                                                                                                     133
              110 READ (5.BORE )
000162
                                                                                                        INPUT
                                                                                                                     134
000165
                   WRITE (6. PORE )
                                                                                                        THPUT
                                                                                                                     135
                   GOTO 205
 000170
                                                                                                        INPUT
                                                                                                                     136
000171
              120 READ (5.BLAST )
                                                                                                        INPUT
                                                                                                                     137
000174
                   WRITE (6.RLAST )
                                                                                                        INPUT
                                                                                                                     138
000177
                   GOTO 205
                                                                                                                     139
                                                                                                        INPUT
                   WRITE (6+JET )
000200
              130 PFAD (5.JET
                                                                                                        INPUT
000203
                                                                                                        INPUT
                                                                                                                     141
000206
                   GOTO 205
                                                                                                        INPUT
                                                                                                                     143
144
145
146
000207
              140 READ (S.PELLET)
                                                                                                        INPUT
000212
                   WRITE (6.PELLET)
                                                                                                        INPUT
              205 GOTO (210.220.230). JHOVE
210 READ (5.RAILS)
000215
                                                                                                        INPUT
455000
                                                                                                        INPUT
             WRITE (6.RAILS)

WRITE (6.RAILS)

GOTO 305

230 READ (5.TRUCKS)

WRITE (6.TRUCKS)

GOTO 305

230 READ (5.RELTS)

WRITE (6.RELTS)
                                                                                                                     147
000227
                                                                                                        INPUT
                                                                                                        INPUT
000233
                                                                                                                     149
150
                                                                                                        INPUT
                                                                                                        INPUT
006241
                                                                                                                    151
152
                                                                                                        INPUT
000242
                                                                                                        INPUT
000245
                                                                                                                    153
154
155
                                                                                                        INPLIT
000250
              305 CONTINUE
                                                                                                        INPUT
000250
                   READ (5.LOADER)
                                                                                                        INPUT
                   WRITE (5.LDADER)
READ (5.GROUND)
000253
                                                                                                        INPUT
                                                                                                                     156
                                                                                                        INPUT
                                                                                                                    157
000261
                   WRITE (6. GROUND)
                                                                                                        INPUT
                                                                                                                    158
                   READ (5.ENVIRC)
WRITE (6.ENVIRC)
000264
                                                                                                        INPUT
                                                                                                                    159
                                                                                                        INPUT
                                                                                                                    160
010272
                   REWIND 40
                                                                                                        INPUT
                                                                                                                    161
000274
                   READ (40 - 402) G
                                                                                                        INPUT
                                                                                                                    162
000702
                   TCHNG=1
                                                                                                        INPUT
                                                                                                                    163
000303
                   TCHNG=T/24.
                                                                                                        INPUT
                                                                                                                    164
                   XCHNG=X-XDISCH
                                                                                                        INPUT
000305
                                                                                                                    165
              402 FORMAT (2E18.10.15.4E18.10.15)
200307
                                                                                                        INPUT
                                                                                                                    166
                   AT = PI+D+0/4.0
                                                                                                                    167
000307
                                                                                                        INPUT
                                                                                                                    168
000312
                   PRINT 403
                                                                                                        INPUT
000316
              403 FORMAT (1H1)
                                                                                                        INPUT
000716
                   PRINT 404. AT
                                                                                                        INPUT
                                                                                                                    170
000324
              404 FORMAT (25HO TUNNEL CROSS SECTION = F 10.4. 6H SQ FT)
                                                                                                        INPUT
                                                                                                                    171
000324
                   LVEHCL=0
                                                                                                        INPUT
000325
                   03 306 I=I+25
                                                                                                        INPUT
                                                                                                                    173
                   174
175
000327
                                                                                                        INPUT
000331
                                                                                                       INPUT
                    TSTAT(1.3)=TSPD(1)
                                                                                                                    176
177
178
000334
                                                                                                       INPUT
                                                                                                        INPUT
                    TSTAT(1.4)=TMAIN(I)
000336
                   IF (ISTA(I).EQ.O .AND. KSTOP(I).EQ.1) LVENCL=I
                                                                                                        INPUT
000340
000350
                                                                                                        INPUT
                                                                                                                    179
              306 CONTINUE
             JO6 CGNTINUE
IF (MAXPSS .EO. 0) GO TO 325
DO 320 I=1.MAXPSS
READ(5.322) (PSST(I.K).K=1.9)
322 FORMAT(9F8.2)
                                                                                                                    180
181
                                                                                                        INPUT
000352
000353
                                                                                                        INPUT
                                                                                                        INPUT
000355
                                                                                                        INPUT
000370
```

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-721
                                                                                          INPUT
                                                                                                                                            184
185
186
187
188
                320 CONTINUE
325 CONTINUE
                                                                                                                              INPUT
000370
                                                                                                                             INPUT
INPUT
000373
                      XO=X
                                                                                                                              INPUT
000375
                      TO=T
                                                                                                                              INPUT
000376
                      NT INIT = NVEHCL
                                                                                                                                            189
190
191
                                                                                                                              INPUT
                      RETURN
                                                                                                                              INPUT
             C
                                                                                                                              INPUT
                      ENTRY INPUT2
PRINT 78
000400
                                                                                                                              INPUT
                                                                                                                                            192
000405
               PRINT 78
78 FORMAT(1HI)
PRINT 77
77 FORMAT (50H0 INPUT OATA AFT
WRITE(6.GENEPL)
GOTO (501.502.503.504).IMETH
501 WRITE (6.BORF)
                                                                                                                              INPUT
                                                                                                                                            193
000411
                                                                                                                              INPUT
                                                                                                                                             194
000411
                                             INPUT DATA AFTER INITIALIZATION BY SUBROUTINES)
                                                                                                                              INPUT
                                                                                                                                            195
000415
                                                                                                                              INPUT
                                                                                                                                            196
000415
                                                                                                                              INPUT
                                                                                                                                             197
000420
                                                                                                                              INPUT
                                                                                                                                            198
000430
                GOTO 505
502 WRITE (6.8LAST)
                                                                                                                              INPUT
                                                                                                                                            199
000433
                                                                                                                              INPUT
                                                                                                                                            200
                502 WRITE (6.0EASI)
503 WRITE (6.JET)
5010 505
504 WRITE (6.PELLET)
505 G010 (511.512.513). JMOVE
000437
                                                                                                                              INPUT
                                                                                                                                            105
                                                                                                                                            202
203
204
205
                                                                                                                              INPUT
000440
300443
                                                                                                                              INPUT
000444
                                                                                                                              INPUT
000447
                511 WRITE (6.RAIL5)
GOTO 520
512 WRITE (6.TRUCK5)
GOTO 520
513 WRITE (6.BELTS)
520 WRITE (6.GROUND)
WRITE (6.LOADER)
                                                                                                                                            206
                                                                                                                             INPUT
000456
                                                                                                                              INPUT
000461
                                                                                                                              INPUT
                                                                                                                                            208
000452
000465
                                                                                                                              INPUT
                                                                                                                                            209
                                                                                                                              INPUT
                                                                                                                                            210
000466
                                                                                                                              INPUT
                                                                                                                                            211
212
213
000471
                                                                                                                              INPUT
                                                                                                                             INPUT
000477
                      WRITE (6.ENVIPC)
                                                                                                                             INPUT
                                                                                                                                            214
000502
                      RETURN
000503
                      END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTRATN
NTRUCK
LTRAIN
ETRUCK
IFILD
LIFILO
IFILLD
ENTPDA
LLTRAN
LETRUK
LNTRUK
INOVE
XT
FC
NTDA
LEVHCL
LNVHCL
```

F. SUBROUTINE OUTPUT

SOLETA	FORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/7
		OUTPUT	2
	SUBROUTINE OUTPUT COMMON /WHEELS/ AF+AF+AMAX+AMAXL+AMINL+BSL+CARCAP+CP+OE+DF+DTAS	WHEELS	ž
20005		WHEELS	3
		WHFELS	- 4
		WHFELS	5
	7	WHEELS	6
		WHEELS	ž
	5 ECONSS.FLOCO.FHUCKC.ETRACK.ESWITC.EUNLOA.ERMAIN.IIBORF.	WHEELS	8
	6 ISW (25) *NTINIT *TCCV *TMCV	WHEFLS	9
20000	COMMON /OLDCOM/ IFILD KSTOP (25) KUNLO LSTOP L VEHCL NAYBY NSWCH	WHEELS	10
	I. NTRDA. NVFHCL . NUMSHT . SWITCH(20) . TFC(25) . TOP (25) . TSTAT (25.4)	WHEELS	11
	2. UTIME (25) . LOADR . MUKOT . XGS . IF XCA . MGS (5) . MCV . MFL AGC . OUMMY (20)		12
20000	COMMON INFWCOMY LIFTLD. LKSTOP (25) . LKUNLO. LLSTOP. LLVHCL. LNBYBY	WHEFLS	13
	I. LNSWCH.LNTROA.LNVHCL.LNMSWT.FSWTCH(20).FTFC(25).FTOP(25)	WHEELS	14
	2. FTSTAT (25.4) . FUTTME (25) . LLOADR . LMUKOT . FXGS . LTFXCA . LMGS (5)	WHFELS	
	3. LMCV.LMFLAC.FOUMMY(19)	WHFELS	15
20000	OTHENSION COMOLD (260) . COMNEW (260) .L TSTAT (25.4) . ITSTAT (25.4)	WHEELS	16
20000	EQUIVALENCE (NVEHCL+NTRAIN+NTRUCK)+ (LVEHCL+LTRAIN+LTRUCK)	WHFELS	17
	I. (COMOLD.IFILD).(COMNEW.LIFILD.IFILLO).(NTDA.LNTRDA)	WHEELS	18
	2. (FTSTAT.LTSTAT).(TSTAT.ITSTAT)	WHEELS	19
	3. (LLVHCL.LLTRAN.LLTRUK). (LNVHCL.LNTRAN.LNTRUK)	WHEELS	20
20000	COMMON /BORING/ CL(3).CPC.DTA.DTC.DTCO.OTD.OTM.KK.PBM.R(100).RC	BORING	2
	A. RPM.TR.XCPC. MASSEM.MBM.MBORF.MCD.MDISAS.LNCHNG.LNCUTR.NCUT(20)	BORING	3
	8. WEAR(100).EBOREG.ETRANS	BCRING	4
00002	COMMON /ALL / XT+STR+IA+ROD+CS+TAMR+FLOW+IFLAG	ALL	2
	1. AT.D.E.SK.T.DT.X.PR.XMAX.TMAX.DX.DV.TPRINT.DTPRNT.IMOVE.JMETH	ALL	3
	Z. TSHFT.REPORT.OPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	4
00002	EQUIVALENCE (JMOVF.IMOVE).(IMETH.JMETH)	ALL	5
20000	SDMCO+MBMCO+TMIAMO+MMBMCO+ORMCO+MMCO+MCO+MPMC \Y3MCM\FCMFO>	ALL	6
	T. PMGS.JMCV.DJMEC.RDPLAN.HPLANT.GSPLAN	ALL	7
	2. ECPLAN. RDTIME . HTIMF (2) . GSTIME . ECTIME	ALL	8
20000	COMMON/PERFRM/ RDUTIM.RODTIM.UMHTIM.OMHTIM.GSUTIM.GSDTIM.ECUTIM	ALL	9
	I. ECDTIM.GDAY.GADV.GENO.GBEG	ALL	10
00002	COMMON/LABOR/ RDMFN(10.2) . HMFN(10.2.2) . GSMEN(10.2) . ECMEN(10.2)	ALL	11
00002	REAL JMMHM.LD.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	12
00002	OTMENSION G(A)	ALL	13
20000	EQUIVALENCE (G.XT) + (XE+XDE) + (PR+PC)	ALL	14
00002	DIMFNSION IVAL (20)	TEST	2
00002	COMMON/TEST/VALUF(30) NAME(30)	TEST	3
00002	1. IHFAD([[0].JHEAD([00)	TEST	4
2000	EQUIVALENCE (IVAL. VALUE)	TEST	5
00005	OATA (NAME=2HT=+ 2HX=+ 3HTA=+ 4HSTR=+ 3HDX=+ 4HMRM=+ 7HLNCUTR=+	OUTPUT	7
40045	I 6HNRYBY=, 6HNSWCH=, 6HMRORE=, 6HLOADR=, 7HNUMSWT=,	OUTPUT	8
	2 6HIEXCA=,4HMCV=,7HMFLAGC=,7HIEXCAV=,7HMGS(2)=	OUTPUT	9
	7 .7HMGS(3) = .7HMGS(4) = .4HXGS= .5HPMGS= .4HQDR= .8+1H) . (NNAME=22)	OUTPUT	10
		OUTPUT	11
	C	OUTPUT	12
	C OUTPUT FOR TEST CASE	OUTPUT	ίΞ
		OUTPUT	14
	C	OUTPUT	15
****	VALUE 411-7	OUTPUT	16
20000	VALUE(I)=T	OUTPUT	17
00004	VALUE (2)=x-xDISCH	OUTPUT	18
00006	[VAL (3) = [A	OUTPUT	19
00007	VALUE (4) = SYR	OUTPUT	20
00011	VALUE (5) =D.4	OUTPUT	21
00012	IVAL (6) = Mf M	WILLER	

```
07/25/72
                                                                             OUTPUT
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                            OUTPUT
                                                                                                                           55
                    IVAL (7) = LNCUTR
000014
                                                                                                            OUTPUT
                                                                                                                           23
000015
                    IVAL (A) =NBYRY
                                                                                                                           24
25
26
27
                                                                                                            OUTPUT
                    IVAL (9) =NSWCH
000017
                                                                                                            OUTPUT
                    IVAL (10)=MBORE
IVAL (11)=LOADR
IVAL (12)=NUMSWT
000020
                                                                                                            OUTPUT
000072
                                                                                                            OUTPUT
000023
                                                                                                                           28
                                                                                                            OUTPUT
                    IVAL (13)=1EXCA
IVAL (14)=MCV
IVAL (15)=MFLAGC
000025
                                                                                                            OUTPUT
                                                                                                            OUTPUT
                                                                                                                           30
000030
                                                                                                            OUTPUT
                    IVAL (16) = NUMLD
000031
                                                                                                            OUTPUT
                                                                                                                           32
                    IVAL (17) =465(2)
000033
                                                                                                            OUTPUT
                                                                                                                           33
                    IVAL (18) =465 (3)
000034
                                                                                                                           34
35
                                                                                                            OUTPUT
                    IVAL (19) = MGS (4)
000036
                                                                                                            OUTPUT
                    VALUE (20) = XGS-XDISCH
003037
                                                                                                            OUTPUT
                                                                                                                           36
                    VALUE (21) =PHG5
000041
                                                                                                                           37
38
                                                                                                            OUTPUT
                    VALUE (22) =QDR
000043
                                                                                                             OUTPUT
000044
                                                                                                                           39
                                                                                                             OUTPUT
                 5 FORMAT (///+1x+16H WORKING STORAGE
000050
              PRINT 411. (NAME(I).VALUE(I).I=I.NNAME)
411 FORMAT (//2(3XA7.E10.3).3XA7.I4./
1 9(3XA7.14). 4(3XA7.I4).3(3XA7.E10.3).
PRINT 412. (WEAR(K).K=1.KK)
                                                                                                                           40
                                                                                                             OUTPUT
000050
                                                                                                             OUTPUT
000065
                                                                                                            OUTPUT
                                                                                                                           42
                                                                                                                           43
                                                                                                            OUTPUT
000055
              412 FORMAT (16HO CUTTER WEAR... / (1(720.3))
IF (LNCUTR.NE.1) GOTO 420
PRINT 413. (NCUT(1):1=1.LNCHNG)
413 FORMAT (26HO CUTTER5 REING CHANGEO... /(10110))
                                                                                                             OUTPUT
                                                                                                                           44 45 47 48
000100
                                                                                                            OUTPUT
                                                                                                            OUTPUT
000102
                                                                                                             OUTPUT
                                                                                                             OUTPUT
              420 CONTINUE
000115
                                                                                                                           49
50
51
52
53
                                                                                                             OUTPUT
               104 DO 108 I=1.NVEHCL
IS=ITSTAT(I+I)
000115
                                                                                                             OUTPUT
000117
                                                                                                             OUTPUT
                    K5=15+3+1
000121
                                                                                                             OUTPUT
                    MS=KS+2
000123
                                                                                                             OUTPUT
                    JS=KSTOP(I)
                                                                                                                           54
55
56
                                                                                                             OUTPUT
000127
                    LS=JS+3-2
                                                                                                             OUTPUT
                    IF (JS.GT.100) L5=19
000130
                                                                                                             OUTPUT
                    IF (JS.EQ.0) LS=22
000133
                                                                                                                           57
                                                                                                             OUTPUT
                    NS =LS+2
000135
                                                                                                                           58
59
               OUTPUT
000137
                                                                                                             OUTPUT
000142
                                                                                                             OUTPUT
                                                                                                                           60
61
62
63
64
65
                                                                                                             OUTPUT
000203
                                                                                                             OUTPUT
                                                                                                             OUTPUT
000203
               ICS CONTINUE
                                                                                                             OUTPUT
                    RETURN
 000206
 000206
 FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTPAIN
NTRUCK
LTPAIN
1 TRUCK
 IFILD.
LIFILD
 IFILLD
 LNTRDA
 LLTRAN
 LLTRUK
```

GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)

OUTPUT

07/25/72

LNTRAN LNTRUK IMOVE JMETH XT XDE PC LVEHCL LVHCL LNVHCL JMOVE IMETH XE PR

G. SUBROUTINE BORE

GOLETA	FORTR	AN I.3 . AUTO RFL . (07-12-72)		07/25/72
		SURROUTINE BORE		
	С	ELEMENT - ROCK DISINTEGRATION	BORE	3
	č	GENERAL PROCESS - BORING MACHINE	BORE	
	č	ACTIVITY - BORE	BORE	4
	č		BORE	5
000002	C	TECHNIQUE - ROLLING DISC CUTTERS	BORE	6
000002		COMMON /RORING/ CL (3) .CPC.OTA.DTC.DTCD.DTD.DTM.KK.PBM.R(100) .RC	BORING	2
		A. RPM.TR.XCPC. MASSEM.MBM.MBORF.MCD.MDISAS.LNCHNG.LNCUTR.NCUT(20)	BORING	3
		B. WEAR(100).EHORFO.ETRANS	BORING	4
000005		COMMON /ALL / XT+STR+IA+ROD+CS+TAMB+FLOW+IFLAG	ALL	2
		1. AT.D.E.SK.T.DT.X.PR.XMAX.THAX.DX.DV.TPRINT.DTPRNT.1HDVE.JMETH	ALL	- 3
		2. TSHFT.REPORT.OPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	4
000002		EQUIVALENCE (JMOVF · IMOVE) · (IMETH · JMETH)	ALL	5
200000		COMMON/MONEY JHMHH . DJM . DJMHH . DJMRD . DJHHHM . DMAINT . DJMHH . DJMG5	ALL	6
		1. PMGS.JMCV.DJMFC.ROPLAN.HPLANT.GSPLAN	ALL	7
		2. ECPLAN.RDTIME.HIIME(2).GSTIME.ECTIME	ALL	8
000005		COMMON/PERFRM/ ROUTIM. PONTIM. UMHTIM. DMHTIM. GSUTIM. GSDTIM. ECUTIM	ALL	9
		I • ECOTIM•GDAY•GADV•GEND•GBEG	ALL	10
200000		COMMON/LAROR/ RDMFN(10+2)+HMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
200000		REAL JMMHM.LD.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	12
200000		DIMENSION G(A)	ALL	iš
000002		EQUIVALENCE (G.XT) + (XE.XOE) + (PR.PC)	ALL	14
000002		DATA (RDUTIME=0.) (RDDTIME=0.)	BORE	. 0
200000		DATA NEEOIN.INIT.IESET/3.0/	BORE	10
	C	OPTION 2 - DIAMETER WITHIN 6-20 FT. AND STRENGTH WITHIN 5-30E3PSI	BORE	ii
200000		1 IF(D .GT. 20.1 .OR. D .LT. 6.0) GO TO 10	BORE	iż
000013		IF (STR .GT. 30.1 .OR. STR .LT. 5.0) GD TO 10	BORE	iš
000023		INIT=I	BORE	14
000024		IF (PAM .EO. 0.) PBM=40.*EXP(.19*0)	BORE	15
000032		IF (PR .EQ. 0.) PR=.02	BORE	16
000034		IF (E .NE. 0.) GO TO 5	BORE	17
000035		IFSET=1	BORE	-
000036		5 IF (NEEDIN .EQ. 0) GO TO 999	BORE	18
000637		NEFOIN=0		19
000040		GO TO 25	BORE	50
000040	1	0 PRINT 20	RORE	21
000044			BORE	55
000044	•			23
300044		I TUNNEL DIAMETER OR ROCK STRENGTH) STOP	HORE	24
300044	C	3100	BORE	25
000046	C	CHICA CARE	BORE	26
		ENTRY AGRER	BORE	27
000053	•	25 IF (INIT .EQ. 1) GO TO 28	BORE	28
000055		NFEDIN=1	BORE	29
090055		60 TO I	BORE	30
000057	-	8 IF (IESET .EO. 0) GO TO 29	BORE	31
000060		E=I.8*EXP(.084*STR)	BORE	32
000066		9 CONTINUE	BORE	33
	C		ACRE	34
	C	COMPUTING LABOR TIME USED FOR THIS ACTIVITY	HORE	35
	С		BORE	36
000066		RDTIME=ROTIME+DT	BORE	37
000070		IF (MAGRE.NE.O) GOTD 40	BORE	38
000071	3	0 DJMRD=DJMRD + PBM + .746 + PR + DT	BORE	39
000076		DX=P84*DT/AT/E*550.*3600./144000.	BORE	40
201000		DV=DX=AT	BORE	41
	C		BORE	42

```
GOLETA FORTRAN 1.3 . AUTD RFL . (07-12-72)
                                                                        HORE
                                                                                                               07/25/72
                                                                                                    HORE
HORE
                   CONPUTING UP TIME FOR ROCK DISINTEGRATION
                                                                                                                  BORE
000103
                  ROUTIM=ROUTIM+OT
                                                                                                     BORE
                   COMPUTING PLANT AND EQUIPMENT COSTS FOR BORING
                                                                                                     BORE
                                                                                                     BORE
              35 ROPLAN=ROPLAN+DX+EBOREQ+DX+ETRANS
RETURN
                                                                                                     BORE
000105
                                                                                                     BORE
000111
                                                                                                     BORE
              40 DX=0.
DV=0.
IF(MBORE .SE. 3) GO TO 35
                                                                                                     BORE
000112
000112
000114
000117
000121
000121
                                                                                                     BORE
                                                                                                     BORE
             RODTIM=FODTIM+OT
999 CONTINUE
RETURN
                                                                                                     BORE
                                                                                                     BORE
                                                                                                     BORE
000122 END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
IMOVE
                                                                                                     BORE
JMETH
XT
XOE
PC
JHOVE
IMETH
XΕ
```

H. SUBROUTINE CUTTER

GOLETA FO	RTR	N 1.3 . AUTO REL . (07-12-72)		07/25/72
			CUTTER	2
		SUBROUTINE CUITER	CUTTER	3
	С	ELEMENT - ROCK DISINTEGRATION	CUTTER	4
	C	GENERAL PROCESS - BORING MACHINE	CUTTER	5
	C	ACTIVITY - CUTTER CHANGE	CUTTER	6
	č	TECHNIQUE - ROLLING DISC CUTTERS	BORING	ž
20000	-	COMMON /BORING/ CL(3) + CPC+DTA+DTC+DTCD+DTD+DTM+KK+PBM+R(100) +RC		3
00000		A. RPM.TR.XCPC. MASSEM.MRM.MBORE.MCD.MDISAS.LNCHNG.LNCUTR.NCUT (20) B. WEAR (100).EROREQ.ETRANS	BORING	4
		COMMON (ALL / XT-STR-1A-RON-CS-TAMB-FLOW-IFLAG	ALL	2
000002		I. AT.D.E.SK.T.DT.X.PR.XHAX.THAX.DX.DV.TPRINT.DTPRNT.IMOVE.JMETH	ALL	3
		2. TSHFT.REPORT.OPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	4
		EQUIVALENCE (JMOVE+THOVE) + (1METH+JMETH)	ALL	5
000002		COMMON/MONEY/ JMMHM . DJM . DJMMH . DJMRD . DJMBMM . DMAINT . DJMBM . DJMGS	ALL	6
000002		The same a sugar open and the table control and	ALL	7
		The same of the sa	ALL	8
		COMMON/PERFRM/ RDUTIM-RDOTIM-UMMTIM-DMMTIM-GSUTIM-GSDTIM-ECUTIM	ALL	9
000002			ALL	10
		T. ECDTIM.GDAY.GADV.GENO.GREG COMMON/LABOR/ RDMEN(10+2).HMEN(10+2+2).GSMEN(10+2).ECMEN(10+2)	ALL	11
000002		COMMONANT OF THE MATTORS SALES TO THE COMMONANT OF THE COMMONANT OF THE COMMONANT OF THE COMMONANT OF THE COMMONANT OF THE COMMONANT OF THE COMMON OF THE CO	ALL	12
000002		REAL JMMHM . LD . LOB . LBIT . LBURN . LSTEEL . JMC1	ALL	13
200002		OTHENSION G(A)	ALL	14
200000		EQUIVALENCE (G.XT) - (XE - XDE) - (PR-PC)	CUTTER	9
000002		OATA (TENP1=31.415926235898)	CUTTER	10
200002		IF (RPM .GT.0.0) GOTO 11	CUTTER	11 .
000005		RPM = 5.0	CUTTER	12
000006		CL(I)=1000000•	CUTTER	13
000007		CL(2)=400000.	CUTTER	14
000010		CL(3)=100000.	CUTTER	15
000012		RC = .75	CUTTER	16
000013		KK=D/.48 +.9	CUTTER	17
000017		R(I)=2.88	CUTTER	18
000021		00 10 K=2.KK	CUTTER	19
250000		R(K)=R(K-1)+2+88	CUTTER	20
000025		10 CONTINUE	CUTTER	21
000027		CPC = 80.	CUTTER	55
000030		XCPC=3.36	CUTTER	23
000032		TR = .5		24
000033		11 00 15 K = 1 • K K	CUTTER	25
000035		15 WEAR(K) = 0.0	CUTTER	
000040		TIME = 0.0	CUTTER	26
000041		LNCUTR=0	CUTTER	27
		RETURN	CUTTER	28
000042	_	AL TOM	CUTTER	29
	С	ENTRY CUTCHG	CUTTER	30
000042	С	Edital Colone	CUTTER	31
000017	C	IF (LNCUTR .NE. 0) GO TO 30	CUTTER	32
000047		INCHACES	CUTTER	33
000050		MK = 0	CUTTER	34
000051		IF (MRORE.NE.D) RETURN	CUTTER	35
000052		DO 21 K=1.KK	CUTTER	36
000053			CUTTER	37
	С	CALCULATE CUTTER WEAR WEAR(K)=WEAR(K)+TENPI=RPM+DT+R(K)/CL(IA)	CUTTER	38
000055		MERKIK JERURANIN POLITICAL PROPERTY OF THE PRO	CUTTER	39
000064		IF (WEAR(K).GE.1.) LNCUTR=1	CUTTER	40
000071		21 CONTINUE	CUTTER	41
000074		IF (LNCUTR.NE.1) RETURN	CUTTER	
000076		DO 22 K=1+KK	30	_

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                            CUTTER
                                                                                                                     07/25/72
                                                                                                          CUTTER
                   IF (WEAR(K) .LT. PC) 60 TO 22 WEAR(K) = 0.
                                                                                                                        43
44
45
000100
060103
000104
                   LNCUTR=1
                                                                                                          CUTTER
                                                                                                                        46
000105
                   LNCHNG = ENCHNG + 1
                                                                                                          CUTTER
000107
                   MK= MK+1
                                                                                                          CUTTER
000110
                   NCUT (MK) =K
                                                                                                          CUTTER
                                                                                                                         48
000111
                                                                                                                         49
               SS CONTINUE
                                                                                                          CUTTER
                   TE (LNCUTR . (0.0) SO TO 40
                                                                                                          CUTTER
                                                                                                                        50
51
52
53
55
55
57
58
60
62
                   TTIME = LNCHUG + TR
000115
                                                                                                          CUTTER
000117
                                                                                                          CUTTER
                   DJMPD=DJMPD+LNCHNG+(1.0+XCPC)+CPC
                   RETURN
               30 TIME = TIME + DT
IF (TIME + GE. TTIME) GOTO 35
LNCUTR=2
000125
                                                                                                          CUTTER
                                                                                                          CUTTER
CUTTER
000127
000131
000132
                   RETURN
                                                                                                          CUTTER
                                                                                                          CUTTER
CUTTER
CUTTER
CUTTER
CUTTER
                   CUTTER CHANGE COMPLETED
               35 TIME = 0.0
LNCUTR = 0
000133
000134
000135
000136
               40 RETURN
                  END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED 1MOVE
JHETH
ХT
XOE,
JMOVE
IMETH
XE
PR
```

I. SUBROUTINE REPAIR

DLETA	ORTRAN 1.3 * AUTD RFL * (07-12-72)		07/25/7
	SUBROUTINE REPAIR	REPAIR	2
	C GENERAL PROCESS - BORING MACHINE	REPAIR	ā
	C ACTIVITY - GENERAL MAINTENANCE AND REPAIR	REPAIR	4
0002	CDMMON /BORING/ CL (3) . CPC. DTA. DTC. DTCD. DTD. DTM. KK. PBM. R (100) . RC	BORING	2
3002	A. RPM.TR.XCPC. MASSEM.MBM.HBDRE.MCD.HDISAS.LNCHNG.LNCUTR.NCJT(20)	BORING	ā
		BORING	4
		ALL	2
2005	THE THE PARTY OF MALE BY BU TOTAL BY BUILDING THOUSE. INCTM	ALL	ž
	1. AT-D-E-SK-T-DT-X-PR-XMAX-IMAX-IX-DV-IPKINI-DIPKNI-I-DVE-J-E-IN	ALL	Ĭ.
	2. TSHFT.REPORT.OPPCT.TD.XD.XDISCH.ICHNG.XCHNG.TCHNG	ALL	5
002	CDMMON/HDNEY/ JMMHM+DJ4+DJMMH+DJMRD+DJMB4M+DMAINT+DJMB4+DJMGS	ALL	6
9002	CDMM3N/MDMEA\ JMMHM*DJ4*DJMMM*DJMPDJADJMADM*TALADQMGJA	ALL	7
	1. PMGS.JMCV.DJMEC.RDPLAN.HPLANT.GSPLAN	ALL	8
	2. ECPLAN.RDTIME.HTIME(2).GSTIME.FCTIME CDMMON/PERFRM/ RDUTIM.RDDTIM.UMHTIM.DMHTIM.GSUTIM.GSDTIM.ECUTIM	ALL	ğ
2005	ARAM ARMA ARMA ARMA	ALL	10
	1. ECDTIM.GDAY.GADV.GEND.GREG	ALL	11
2000	CDMMDN/LABOR/ RDMEN(10.2) . HMEN(10.2.2) . GSMEN(10.2) . ECMEN(10.2)	ALL	iż
2006	REAL JYMHM.LD.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	13
2000	DIMENSION G(8)		14
2000	EQUIVALENCE (G.XT) (XE.XDE) (PR.PC)	ALL REPAIR	17
2000	IF (DTC .GT. 0.0) GO TO 5		8
0005	DTC = 7.	REPAIR	9
0006	DTM = 1.	REPAIR	-
007	DJMBMM=0.	REPAIR	10 11
010	5 TM=0.	REPAIR	12
0011	TIME=DTC	REPAIR	13
0013	MRM=0	REPAIR	
0014	RETURN	REPAIR	14
	C	REPAIR	15
0014	ENTRY MAINT	REPAIR	16
	C 15 MAINTENANCE IN PROGRESS	REPAIR	17
1500	10 IF (MRM.NE.0) GOTO 20	REPAIR	18
2500	TIME=TIME-DT	REPAIR	19
	C IS MAINTENANCE REQUIRED	REPAIR	50
0024	IF (TIME.GT.O.) RETURN	REPAIR	21
0026	MRM=1	REPAIR	52
0027	TM=0 .	REPAIR	53
0030	TIME = DTC	REPAIR	24
0032	рјиви=рјиви+рјивин	REPAIR	25
0034	RETURN	REPAIR	56
0034	C 1F IN PROGRESS. UPDATE PROGRESS	REPAIR	27
0034	20 Th = TM + DT	REPAIR	58
0036	1F (TH.LT.DTH) RETURN	REPAIR	29
0041	MUNEO METANOMIA	REPAIR	30
0042	TIME=DTC	REPAIR	31
0044	RETURN	REPAIR	32
0044	END	REPATR	33
0044	ING VARIABLES EQUIVALENCED BUT NOT REFERENCED		
OVE	THE VARIANCES CONTROL TO SEE THE SEE T		
ETH			
E			
2.45			
DVE			
ETH			

J. SUBROUTINE CVLOAD

GOLETA	FORTRAN 1.3 . AUTO REL . (07-12-72)		07/25/72
	CURNOUT INC. CHI OAD	CVLOAD	2
	SUBROUTINE CYLOAD	CVLOAD	5
	C ELEMENT - MATERIALS HANDLING	CVLOAD	4
	C ELEMENT - MATERIALS HANDLING C GENERAL PROCESS - INTEGRATED CONT. EXCAVATOR-CONVEYOR LOADER	CVLOAD	5
	C ACTIVITY - LOADING	CVLOAD	6
	C	CVLOAD	7
200000	COMMON JUMEELS / AF . AF . AMAX . AMAX L . AM INL . RSL . CARCAP . CP . DE . DF . OTAS	WHEELS	2
000002	1. GTMA.OTH.FL.FC.FR.FT.HPA.HPEA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHEELS	3
	2. NCARS. NPOINT. NTD. NTM. NTMAX. XP. NTHILP. NTMLPP. NTRACK. SL	WHEELS	4
	3. TOURVX '20) . TOURVY (20) . THATHT. THE . VD . VS . VE . VF . VHAX . HC . HL . XDS	WHEELS	5
	4. MAYLD . A INC D. LOUE . OUC. AUC. STATUS (36) . WHY (24) . MLTYP . WHR . ECONEQ.	WHEELS	6
	5 ECONSSIPTION FRUCE CIFTRACK - ESWITC - EUNLDA - ERMAIN - ITBORE -	WHEELS	7
	6 TSW(25) NTINIT TOOV THOV	WHEFLS	6
000002	COMMON VOLOCOMY TEILD+KSTOP (25) +KUNLO+LSTOP+LVFHCL+NRYRY+NSWCH	WHFELS	9
	1. NTPDA.NVF (CL.NUMSAT.SATTCH(20).TFC(25).TOP(25).TSTAT(25.4)	WHEELS	10
	2. UTIME (25) .LOADR . MUMDT . XGS . TEX CA . MGS (5) . MCV . MFL AGC . DUMMY (20)	WHEELS	11
200000	COMMON /NEWCOM/ LIFILD.LMSTDP(25).LKUNLO.LLSTOP.LLVHCL.LNRYBY	WHEELS	12
	1. LNSWCH+LNTROA+LNVHCL+LNMSWT+FSWTCH(20)+FTFC(25)+FTOP(25)	WHEELS	13
	2. FISTAT(25.4).FUTIME(25).LLOADR.LMUKDT.FXGS.LIFXCA.LMGS(5)	WHEELS	14
	3. 1 4C LAFLAC. FOUNHY (19)	WHEELS	15
000005	OTHERISTON COMPLETEROD . COMMEN (260) . LTSTAT (25.4) . TTSTAT (25.4)	WHFELS	16
000005	EQUIVALENCE (NVEHOL+GTRAIN+NTRUCK) + (LVEHOL+LTRAIN+LTRUCK)	WHEELS	17
	I. (COMOLO.IFILD). (COMNEW.LIFILO.IFILLD). (NTDA.LNTROA)	WHEELS	18 19
	2. (FTSTAT.LTSTAT).(TSTAT.TTSTAT)	WHEELS	, 20
000002	3. (LLV**CL*LLTRAN*LLTRUK).(LNVHCL*LNTRAN*LNTRUK) COMMON /ALL / AT*STR*IA*ROD*CS*TAMB*FLOW*1FLAG	ALL	ĘŠ
000002	1. AT.D.F.SK.T.DT.A.PR.XMAX.TMAX.DX.DV.TPRINT.DTPRNT.IMOVE.JMETH	ALL	3
	2. TSHFT. REPORT. OPPCT. TO. XO. XDISCH. TCHNG. XCHNG. TCHNG	ALL	4
200002	EQUITABLESCE (JACTE THOSE) . (THETH . JMETH)	ALL	5
000005	COMMODIZATIVE AND MARK OF WHAT OF MARKEN ALL ALL OF MARKEN	ALL	6
	1. PMCS.JMCV.D PMFC.PDPLAN.HPLANT.GSPLAN	ALL	7
	2. ECPLAN. PDIIMS . HTIME (2) . GSTIME . ECTIME	ALL	8
200000	COMMON/PERFRMY ROUTIM. PODTIM. UMHTIM. DMHT1M. GSUTIM. GSUTIM. ECUTIM	ALL	9
	1. ECDTIM+GDAY+GADV+GFND+GREG	ALL	10
000005	COMMON LARGRY RDMFN(10+2)+HMFN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
000005	REAL JHMWHOLDOLDROLBITOLBURNOLSTEELOJMCV	ALL	12
200000	OIMERSION G(4)	ALL	13
000005	EQUIVALENCE (A.XI) + (XE+XRE) + (PR+PC)	ALL	14
000005	COMMON /CONVEY/ ACM .OTRS .DNM .FE .FL .HP .QC .SMIN .WBI	RELTS	2
	1. WP.XLF.NSTPRE.QE.QP.SM.DTCR.DTMR.AB.VR1.NEXON.NGEO.XE.LNSURG	UPDA7	1 2
	2 STIME + 00MP + 0TMI + DTMO	CVLOAD	11
000002	EQUIVALENCE (VB.VBI)	CVLOAD	12
000005	DATA INIT /0/ OATA NFEDIN /0/	CVLOAD	iŝ
000005	OATA OTLO /O./	CVLOAG	14
000005	OATA GTEY /0,/	CVLOAD	15
000005	DATA QUE /0./	CVLOAD	16
000005	OATA WUF /0./	CVLOAD	17
	CINITIALIZE	CVLOAD	18
000002	100 1F (AB * V9 .FQ. 0.) GD TO 200	CVLOAD	19
	C OPTION 1	CVLOAD	20
000004	XWRK = AR • VR	CVLOAD	21
000005	WHR = ,03 * XWRK * CS / SK	CVLOAD	22
900011	QMR = 60. * XHRK _ '	CVLOAD	23
000-12	PRINT 101. OHR.WMR	CATOVO	24



GOLETA	FORTRAN	1.3 • AUTO RFL • (07-12-72)	CVLOAD	07/25/72
000022	101	FORMAT (IOHO QHR.WMR= 2E14.61	CVLC)AD 25
250000		GO TO 250	CVLO	
-	С	OPTION	_	_
000023	200	QMR = 2000. * WMR * 5K / CS	CVLO	AD 28
	С	BOTH OP	TION5 CVLC	9S (A)
000027	250	INIT = I	CVLO	AD 30
000030		IF (NEEDIN .EQ. 0) GO TO 900	CVLO	AO 31
000031		NEEDIN = 0	CVLO	AD 32
000032		GO TO 370	CVLO	AD 33
	С	NORMAL		
000032	-	ENTRY LOADCY	CVLO	
000037		IF (INIT .EQ. 1) GO TO 370	CVLO	
	С		IZATION REQUIRED CVLC	
000041		NEEOIN = 1	CAFO	
000042		GO TO 100	CVLO	_
	С		LOADING	
000043	370	OTLD = OT	CVLO	
000045	_	OVLD = OV	CVLO	
	C		CVLO	
	C	COMPUTING LABOR TIME USED FOR	· · · · · · · · · · · · · · · · · · ·	
000011	С	WT1MF (3) - WT1WF (3) - AT	CVLO	
000046		HTIME(2) #HTIME(2) +OT	CVLO	_
000050 000051		IF(MCV .NE. 0) GO TO 900 IF((MLTYP .NE. 2) .ANO. (LVEHC)	CVL0 L .EQ. 0)) GO TO 380 CVL0	
000031	С	Trithelir and 27 annua levend	CVL0	
	č	COMPUTING PLANT AND EQUIPMENT		
	č	COM DI INO YEATT AND ESSI MENT	CVLO	
000060	•	HPLANT=HPLANT+ECONEQ+DX+ECONS5		
000064	380	IF (LOAOR .NE. 1) GO TO 390	CVLO	
000056	• • •	0TL0 = 2.0 0T	CVLO	
000070		DVLO = OV . OTEM	CVLO	
000072	390	QDD = DVLD + SK / OTLO	CVLO	AD 56
000075		WOD = DVLD . CS / (DTLO . SK .	2000.) CVL0	AD 57
000100		IF (MLTYP .EQ. 2) GO TO 600	CVLO	
	С	UNITIZE	D MAIN LINE SYSTEM CVLO	AD 59
000102		IF (LLVHCL.LF.0) GOTO 700	CVLO	AD 60
000104		LLOAOR = 0	CVLO	
000105		IF (OTEH .EQ. 0.) GO TO 550	CVLO	
	С		FOR HUCK FROM LAST CYCLE CVLO	
000106		QUF = QUF + QTEM	CVLO	
000107		WUF = WUF + WTEM	CVL.0	
000111		QTEM = 0.	CVLO	
000112	550	WTEM = 0.	CVLO	
000112	220	IF (QDD .GT. QMR .OR. WOO .GT.		F 1
000124		MUF = MUF + WOO + DTLO	CVLO	
000176		IF (QUC .GT. QUF .ANO. WUC .GT.		
000131	С		E UNIT FULL. CAN BE RELFASED CVLO	
000142	C	I=LLVHCL	CVLO	
000143		LKSTOP(I)=5	CVLO	
000145		LT5TAT(1+1)=7	CVLO	
000146		OTEM = OUF + OUC	CVLO	
000150		WTEM = WUF - WUC	CVLO	
000152		QUF = 0.	CVLO	-
0001.5		WUF = 0.	CVLO	
500.55		••	0.00	

```
07/25/72
                                                                         CVLOAD
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                      CVLOAD
                  GO TO 900
000153
                                               CONTINUOUS MAINLINE SYSTEM
                                                                                                                    82
                                                                                                       CVLOAD
             600 IF (QDD .GT. QMR .OR. WDO .GT. WHR) GO TO 700
000154
                                                                                                       CVLOAD
                                                                                                                    83
84
85
86
87
88
89
90
                  FOL = 000
60 TO 900
000166
                                                                                                       CYLOAD
                                               CONVEYOR CAPACITY EXCEEDED - TURN OFF FXCAVATOR NEXT CYCLE TO AVG. EXCESS OUT
                                                                                                       CVLOAD
                                                                                                      CVLOAD
             700 LLOADR = 1
QTEM = DVLD
WTEM = WDD * DTLD
000167
                                                                                                       CVLOAD
000170
                                                                                                       CVLOAD
000172
             900 CONTINUE
000174
                                                                                                                    91
                                                                                                       CVLOAD
                  RETURN
000174
                                                                                                       CVLOAD
000175
                  END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTRAIN
NTRUCK
LTRAIN
LTRUCK
IFILO
LIFILD
IF ILLD
LLTRAN
LLTRUK
LNTRAN
LNTPUK
THOVE
JHETH
XT
XDE
PC
VRI
NVEHCL
NTDA
LNVHCL
JHOVE
IMETH
XE
PR
```

K. SUBROUTINE CVMNT

OLETA FO	RTRAN 1.3 . AUTO RFL . (07-12-72)		07/25/7
	SUBROUTINE CVMNT	CVMNT	2
	C	CVMNT	3
	C ELFMENT MATERIALS MANDLING	CVMNT	4
	C GENERAL PROCESS INTEGRATED CONVEYER EXCAVATOR. CONVEYER LOADER		5
	C ACTIVITY MAINTENANCE	CVMNT	6
	C	CVHNT	7
2000	COMMON /ALL / XT.STR.IA.ROD.CS.TAMB.FLOW.IFLAG	ALL	5
	1. AT.D.E.SK.T.DT.X.PR.XMAX.THAX.DX.DV.TPRINT.DTPRNT.IMOVE.JMETH	ALL	3
	2. TSHFT.REPORT.OPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	4
20000	EQUIVALENCE (JYONE + INTERNATION (AVONE)	ALL	5
20002	SOMFG*MBMFG*LNIWMG*MWBMFG*DNHHHG*MHG*MHG*NTALANG*	ALL	6
	I - PMGS+JMCV+DJMEC+ROPLAN+HPLANT+GSPLAN	ALL	7
	2. ECPLAN.RDTIFE.HTIME(2).GSTIME.ECTIME	ALL	8
20002	COMMON/PERFRM/ ROUTIM+RODTIM+UMHTIM+DMHTIM+GSUTIM+GSDTIM+ECUTIM	ALL	9
	I. ECDTIM.GDAY.GADV.GEND.GREG	ALL	10
20002	COMMON/LAGOR/ RDMEN(10+2)+HMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
2000	REAL JMMHM.LD.LDB.LBIT.LBURN.LSTEFL.JMCV	ALL	12
2000	DIMENSION G(8)	ALL	13
2000	EQUIVALENCE (G+XT)+(XE+XDF)+(PR+PC)	ALL.	14
2000	COMMON /WHEELS/ AF+AF+AMAX+AMAXL+AMINL+BSL+CARCAP+CP+DE+DF+DTAS	WHEELS	2
	I DTMA.DTU.FL.FC.FR.FT.HPA.HPEA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHEELS	3
	2. NCARS.NPOINT.NTD.NTM.NTMAX.XP.NTMILP.NTMLPP.NTRACK.SL	WHEELS	4
	3. TCURVX (20) .TCURVY (20) .TAINT.THE .VO.VS.VE.VF.VMAX.HC.HL.XDS	WHEELS	5
	4. MAXLD.NUMLD.LQUE.QUC.WUC.STATUS(36).WHY(24).MLTYP.WMR.ECONEQ.	WHEELS	6
	5 ECONSS-ELOCO-EMUCKC-ETPACK-FSWITC-EUNLOA-ERMAIN-IIBORE-	WHEELS	7
	6 ISW(25) NTINIT . TCCV . TMCV	WHEELS	8
20002	COMMON /OLDCOM/ IFILD.KSTOP(25).KUNLO.LSTOP.LVEHCL.NBYBY.NSWCH	WHEELS	9
,,,,,	I. NTRDA.NVEHCL.NUMSWT.SWITCH(20).TFC(25).TOP(25).TSTAT(25.4)	WHEELS	10
	2. UTTHE (25) . LOADR . MUKOT . XGS . TEXCA . MGS (5) . MCV . MFL AGC . DUMMY (20)	WHEELS	11
2000	COMMON /NEWCOM/ LIFILO.LKSTOP(25).LKUNLO.LLSTOP.LLVMCL.LNBYBY	WHEELS	12
,,,,,	1. LNSWCH.LNTRDA.LNVHCL.LNMSWT.FSWTCH(20).FTFC(25).FTOP(25)	WHEELS	13
	2. FTSTAT (25.4) .FUTIME (25) .LLOADR .LMUKOT .FXGS .LIEXCA .LMGS (5)	WHEELS	14
	3. LMCV+LMFLAC+FDUMMY(19)	WHEELS	15
0002	DIMENSION COMOLD (260) + COMNEW (260) + LTSTAT (25+4) + ITSTAT (25+4)	WHEELS	16
2000	EQUIVALENCE (NVEHCL.NTRAIN.NTRUCK), (LVEHCL.LTRAIN.LTRUCK)	WHEELS	17
	1. (COMOLD. IFILD). (COMNEW.LIFILD. IFILLD). (NTDA.LNTRDA)	WHEELS	18
	2. (FTSTAT.LTSTAT).(TSTAT.ITSTAT)	WHEELS	19
	3. (LLVHCL.LLTRAN.LLTRUK). (LNVHCL.LNTRAN.LNTRUK)	WHEELS	20
2000	DATA LMCV.MCV/2*0/	CVMNT	10
0002	DATA TRET.THNT /2.0./	CVMNT	ii
00002	DATA INIT NEFDIN /200/	CVMNT	12
10002		CVMNT	13
	C EQUIVALENCE FOR SPECIFIC GENERAL PROCESS EQUIVALENCE (GOUM+JMCV)	CVHNT	14
2000	EQUIVALENCE (MMNT+MCV)	CVHNT	15
2002		CVMNT	16
20000	EQUIVALENCE (GDTC+TCCV)	CVMNT	17
2000	EQUIVALENCE (GDTM+TMCV)	CVHNT	18
2000	EQUIVALENCE (LMMNT.LMCV)		
2000	EQUIVALENCE (MFLAG+MFLAGC)	CVMNT	19
2000	EQUIVALENCE (DJMGP DJMMH)	CVMNT	20
10002	EQUIVALENCE (LMFLAG+LMFLAC)	CVHNT	21
	C	CVMNT	55
	C INITIALIZATION	CVMNT	23
	C	CVMNT	24
20000	IO MMNT=0	CVMNT	25
00003	IF(GDTC .EQ. 0.) GDTC=7.	CVHNT	26

(december)

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                    CVHNT
                                                                                                        07/25/72
 000005
000007
                  IF(GDJM .EO. 0.) GDJM=0.
IF(GDTM .EO. 0.) GOTM=1.
                                                                                              CVMNT
 000011
                  IRET=GOTC
                                                                                              CVMNT
                                                                                                           29
 000012
                  INIT = 1
                                                                                              CVHNT
                                                                                                           30
                   IF (NEEDIN .EO. 0) GO TO 999
 000013
                                                                                              CVMNT
                                                                                                           31
 000014
                  NEEDIN = 0
                                                                                              CVHNT
                                                                                                           32
 000015
                  GO TO 200
                                                                                              CVMNT
                                                                                                           33
           C
                                                                                              CVMNT
                                                                                                           34
                                            NORMAL ENTRY
                                                                                              CVHNT
                                                                                                           35
 000015
                  ENTRY CVRPR
                                                                                              CVHNT
                                                                                                           36
37
 000022
                  IF (INIT .EO. 1) GO TO 200
                                                                                              CVMNT
 000024
                  NEEDIN = 1
                                                                                              CVMNT
                                                                                                           38
 000025
                  GO TO 10
                                                                                              CVMNT
                                                                                                           39
40
           C
                                            IS MAINTENANCE IN PROGRESS
                                                                                              CVMNT
 000026
             200 IF (MMNT.NE.0) GOTO 400
                                                                                              CVHNT
                                                                                                          41
 000027
                  IF (MFLAG .NE. 0) GO TO 999
                                                                                              CVMNT
                                                                                                           42
           С
                                            IS MAINTENANCE REQUIRED
                                                                                              CVHNT
                                                                                                          43
 000030
                  TRET = TRET - OT
                                                                                              CVMNT
                 IF (THET .GT. 0.) GO TO 999

ODES ANY OTHER SITUATION EXIST SUCH THAT MAINTENANCE SHOULD
 000032
                                                                                              CVMNT
                                                                                                          45
           С
                                                                                              CVHNT
                                                                                                          46
                           NOT BE PERMITTED. IF SO. GO TO 999
                                                                                              CVHNT
                                                                                                          47
                                                                                              CVHNT
                                                                                                          48
                   ACCUMULATING DOWN TIME
                                                                                              CVHNT
                                                                                                          49
000034
                 LMMNT=1
                                                                                              CVHNT
                                                                                                          50
000035
                  LMFLAG=1
                                                                                              CVMNT
                                                                                                          51
52
000036
                  GO TO 999
                                                                                              CVHNT
           C
                                           UPDATE PROGRESS OF MAINTENANCE
                                                                                              CVHNT
                                                                                                          53
000036
             400 THAT = THAT + OT
                                                                                                          54
55
                                                                                              CVMNT
000040
                 OMHTIM=OMHTIM+OT
                                                                                              CVMN
          C
                                           IS MAINTENANCE COMPLETED
                                                                                              CVHN"
                                                                                                          56
000042
                 IF (TMNT .LT. GOTM) GO TO 999
DJMGP = DJMGP + GDJM
                                                                                             CVMNT
                                                                                                          57
                                                                                              CVMNT
                                                                                                          58
000046
                 TRET = GDTC
                                                                                             CVMNT
                                                                                                          59
                 THAT = 0.
000047
                                                                                              CVMNT
                                                                                                          60
000047
                 LMMNT=0
                                                                                             CUMNT
                                                                                                          61
000050
                 LMFLAG=0
                                                                                             CVMNT
                                                                                                          62
000051
             999 PETURN
                                                                                             CVHNT
                 NOTE -- CHECK TESTING OF MFLAG IN RELATED SUBROUTINES
                                                                                             CVHNT
                                                                                                         64
000052
                                                                                             CVHNT
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
THOVE
JHETH
XT
XOE
PC
NTRAIN
NTRUCK
LTRAIN
LTRUCK
IFILD
LIFILD
IFILLO
LNTROA
LLTRAN
```

LLTRUK

GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)

CVMNT

07/25/72

LNTRAN
LNTRUK
TCCV
TMCV
MFLAGC
DJMMH
LMFLAC
JMOVE
IMETH
XE
PR
NVEHCL
LVEHCL
LVHCL
LNVHCL

VI-78

L. SUBROUTINE RAILHL

GOLETA I	ORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/72
	SUBROUTINE RAILHL	RATLHL	2
	C	RAILHL	3
	C ELEMENT - MATERIALS HANDLING	RATLHL	4
		RATLHL	5
	C GENERAL PROCESS -CONVENTIONAL RAIL SYSTEM C ACTIVITY - LONG HAUL MUCK TRANSPORT (INCLUDES RETURN AND	RATLHL	6
	c TRAFFIC OELAYS)	RAILHL	7
	C TECHNIQUE - TRACKS-DOUBLE OR SINGLE WITH CALIFORNIA SWITCHES	RATLHL	8
	C TECHNIQUE - TRACKS-DOUBLE OR SINGLE WITH CALIFORNIA SWITCHES C ORIVE - DI_SEL OR FLECTRIC LOCOMOTIVE	RAILHL	9
	Č	RAILHL	10
	C INSERT COMMON	RATLHL	11
000002	COMMON /WHEELS/ AE.AF. / MAX. AMAXL. AMINL. BSL. CARCAP. CP. DE. DF. DTAS	WHEELS	2
	1. DTMA.DTU.FL.FC.FR.FT.HPA.HPEA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHFELS	3
	2. NCARS . MPOINT . NTO . MITH . NTHAX . XP . NTHILP . NTHLPP . NTRACK . SL	WHEELS	4
	3. TCIPVX (20) . TCUPV (20) . TMAINT. TWF. VD. VS. VE. VF. VMAX. WC. WL. VDS	WHFELS	5
	4. HAXLD.NUMED.LOI & QUC.WUC.STATUS (36) .WHY (24) .MLTYP.WMR.ECONEQ.	WHEELS	6
	5 ECONSS.ELOCO.F MICKC.ETRACK.ESWITC.EUNLOA.ERMAIN.IIBORE.	WHEELS	7
	6 ISW(25) NTINI(OFCCV THCV	WHEELS	8
200000	COMMON /DLDCOM/ IF (LD.KSTOP (25) .KUNLO.LSTOP.LVEHCL.NBYRY.NSWCH	WHEELS	9
	1. NTRDA. TVEHCL . NUMSWT . SWITCH(20) . TFC (25) . TOP (25) . TSTAT(25.4)	WHEELS	10
	2. UTIME(25).LOADR.MUKOT.XGS.1EXCA.MGS(5).MCV.MFLAGC.OUMMY(20)	WHEELS	11
200000	COMMON /NEWCOM/ LIFILD.LKSTOP(25).LKUNLO.LLSTOP.LLVMCL.LNBYBY	WHFELS	12
*****	1. LNSWCH.LNTRDA.LNVHCL.LNMSWT.FSWTCH(20).FTFC(25).FTOP(25)	WHEELS	13
	2. FTSTAT (25.4) -FITTIMF (25) -LLOADR -LMUKOT -FXGS -LIEXCA-LMGS(5)	WHEELS	14
	3. IMCV.IMFLAC.FDUMMY(19)	WHEELS	15
200000	OTHENSION COMOLD (260) . COMNEW (260) . LTSTAT (25.4) . ITSTAT (25.4)	WHEELS	16
200000	EQUIVALENCE (NVEHCL+NTRAIN+NTRUCK)+(LVEHCL+LTRAIN+LTRUCK)	WHEELS	17
	1. (COMOLD.IFILD).(COMNEW.LIFILD.IFILLO).(NTOA.LNTROA)	WHEELS	18
	2. (FTSTAT.LTSTAT).(TSTAT.ITSTAT)	WHEELS	19
	3. (LLVHCL.LITPAN.LLTRUK).(LNVHCL.LNTRAN.LNTRUK)	WHEELS	20
200000	COMMON /ALL / XT+STR+IA+RQD+CS+TAMB+FLOW+IFLAG	ALL	2
	1. AT-D-E-SK-T-DT-X-PR-XMAX-TMAX-DX-OV-TPRINT-DTPRNT-1MOVE-JMETH	ALL	3
	2. TSHET.REPORT.OPPCT.TO.FO.FO.SCH.ICHNG.XCHNG.TCHNG	ALL	- 2
200000	EQUIVALENCE (JHOVE+HOVE)+(IMFIH+JMETH)	ALL	5
200000	COMMON/MONEY/ JMMHM.OJM.DJMMH.OJMRO.OJMBMM.OMAINT.OJMBM.OJMGS	ALL	6
	1. PMGS.JMCV.DJMEC.RDPLAN.HPLANT.GSPLAN	ALL	é
	2. ECPLAN. POTIME . HTIME (2) . GSTIME . ECTIME	ALL	9
200000	COMMON/PERERMY ROUTIM. RODTIM. UMHTIM. DMHTIM. GSUTIM. GSOTIM. ECUTIM	ALL ALL	10
•	1. ECOTIN.GDAY.GADV.GENO.GBEG	ALL	ii
200000	COMMON/LAROR/ ROMEN(10.2) + HMEN(10.2.2) + GSMEN(10.2) + ECMEN(10.2)	ALL	12
000002	REAL JUNHHOLDOLDO LBITOLOURNOLSTEEL JACV	ALL	13
200000	OTHERISTON G(A)	ALL	14
200000	EQUIVALENCE (G.XT) + (XE + XOE) + (PR+PC)	RAILHL	14
200000	OATA INITSW. IRETSW /2*0/	RATLHL	15
200000	OAT% TOPTN /1/ OTHENSTON KTEMP(25) *KTRAIN(25) *ISTATE(25+4) *STATE(25+4)	RAILHL	16
000002	A BECALOCI BYON (35)	RAILHL	17
***	OATA (KTEMP=25*0) + (KTRAIN=25*0) + (STATE =100*0+)	RAILHL	18
000002		RATLHL	19
	EQUIVALENCE (STATE+ISTATE)	RATLHL	20
000002		RATLHL	21
	C PARAMETER INITIALIZATION	RATLHL	22
	C FRANCIE MATTHEMATICAL	RAILHL	23
000003	100 INITSW = 1	RATLHL	24
000002	MLFLS = SL/2.	RAILHL	25
	IF (LOCO .EQ. 2) GO TO 110	RAILHL	26



```
07/25/72
                                                                                               RATLHL
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                                                                       27
28
                                                                                                                                     RAILHL
                        IF (FC .EQ.O.) FC = 0.0455
IF (CP .EQ.O.) CP = 0.14
000007
                                                                                                                                     RAILHL
                                                                                                                                                       29
                                                                                                                                     RATLHL
                        GO TO 120
                                                                                                                                                       30
000013
                                                                                                                                     RAILHL
                 110 FC=-746
IF(CP .E0. 0.) CP=-02
120 IF(VE • VF .GT.0.) GO TO 200
                                                                                                                                     RATI.HL
000014
000016
                                                                                                                                                       32
                                                                                                                                     RATINI
                                                                                                                                                       33
000020
                                                                                                                                     RAILHL
                                                              OPTION 2
                                                                                                                                     RAILHL
                        IOPTN = 2
IF (FT .EQ. 0.) FT = 0.25
IF (AMAX .EQ. 0.) AMAX = 9999.
IF(EL .EQ. 0.) EL=0.8
HPFAC = EL * 375.
000024
                                                                                                                                                        35
                                                                                                                                     RATLHL
                                                                                                                                                       36
37
000025
                                                                                                                                     RAILHL
                                                                                                                                      RAILHL
000027
000031
                                                                                                                                      RAILHL
                                                                                                                                                        38
                        MPAFAC = HPFAC * HPA
GE = (NCARS * NC) * NI,
GF = NCARS * (WC * 1.35 * CARCAP) * NL
X1 = NCARS * MC * ML
000033
                                                                                                                                      RAILHL
                                                                                                                                                        39
000035
                                                                                                                                      RAILHL
                                                                                                                                                        40
                                                                                                                                                        41
000037
                                                                                                                                      RAILHL
000042
                                                                                                                                      RAILHL
                        X1 = NCAM5 = NO

WE = GE / X1

WF = GF / X1

TTEA = FT * WL * 2000.

AC = 6.65 * (CARCAP ** 0.39) * .00;

COMPUTE VE RE VF RF
                                                                                                                                                        43
000047
                                                                                                                                      RAILHL
000053
                                                                                                                                      RAILHL
                                                                                                                                                        45
000054
                                                                                                                                      RAILHL
000056
                                                                                                                                      RAILHL
                                                                                                                                                        46
                                                                                                                                                        47
 000060
                                                                                                                                      RATLHL
               C
                                                                                                                                                        48
                                                                                                                                      RAILHL
                         C1 = 1.3 • (29. / WE)
C2 = AC / (WF * MC)
C4 = HPV * HPFAC
 000056
                                                                                                                                      RAILHL
                                                                                                                                                        50
 000071
                                                                                                                                      RAILHL
 000074
                                                                                                                                      RAILHL
                         REF1 = C1
REF2 = C2
 000076
                                                                                                                                       RAILHL
                                                                                                                                                        52
                        REF2 = C2

A = .045 / C2

8 = C1 / C2

C = -C4 / (C2 * GE)

VE = CUBIC (A. B. C)

IF (VE .GT. VMAX) VE = VMAX

RE = GE*(C1 + (C2 * VE * VE) * (.045 * \E) )

C1 = 1.3 * (?9. / WF)

C2 = AC / (WF * MC)

DFF1 = C1
 000077
                                                                                                                                                        53
                                                                                                                                       RAILHL
 000101
                                                                                                                                       RAILHL
                                                                                                                                                        55
 000102
                                                                                                                                       RAILHL
 000103
                                                                                                                                       RATLHL
                                                                                                                                                        56
 000106
                                                                                                                                       RATLHL
                                                                                                                                                        57
 000111
                                                                                                                                       RAILHL
                                                                                                                                                        58
 000114
                                                                                                                                       RAILHL
                                                                                                                                                        59
 000123
                                                                                                                                       RAILHL
                                                                                                                                                        60
 000126
                                                                                                                                       RATLHL
                                                                                                                                                        61
                         RFF1 = C1
RFF2 = C2
 000131
                                                                                                                                       RAILHL
                                                                                                                                                        62
                         RFF2 = C2

A = .045 / C2

B = C1 / C2

C = -C4 / (C7 = GF)

VF = CUBIC (A.B.C)

IF (VF .GT. VMAX) VF = VMAX

RF = GF = (C1 + (C2 = VF = VF) + (.045 = VF) )

COMPUTE HPEV+HPFV
 000132
                                                                                                                                       RAILHL
                                                                                                                                                         63
                                                                                                                                                         64
 000134
                                                                                                                                       RATLHL
 000135
                                                                                                                                                         65
                                                                                                                                       RAILHL
                                                                                                                                                         66
 000136
                                                                                                                                       RAILHL
                                                                                                                                                         67
 000141
                                                                                                                                       RAILHL
 000144
                                                                                                                                       RATLHL
                                                                                                                                                         68
                                                                                                                                                         69
70
71
 000147
                                                                                                                                       RATLHL
                C
                                                                                                                                       PATLH
                          HPEV = (RE-VF) / HPFAC
HPFV = (RF-VF) / HPFAC
 000156
                                                                                                                                       RAILHL
                                                                                                                                                         72
73
  000161
                                                                                                                                       RAILHL
                          GO TO 250
                                                                                                                                       RATIHL
  000163
                                                               OPTION 1
                                                                                                                                                         74
                                                                                                                                       RATLHL
                                                                                                                                                         75
76
                    200 CONTINUE
  000163
                                                                                                                                       RATLHL
                          HPEAH = HPEA
  000163
                                                                                                                                       RAILHL
  000165
                                                                                                                                                         77
                                                                                                                                       RAILHL
                                                                BOTH OPTIONS
                                                                                                                                                         78
79
                                                                                                                                       RATINL
                    250 DINCR=150.
                                                                                                                                       RAILHL
  000166
                          YWRK = VO
                                                                                                                                                         80
  000170
                                                                                                                                       RAILHL
                          IF (VS .GT. VD) YWRK = VS
XWRK = 2640. * (VF * VF - YWRK * YWRK) / DF
  000171
                                                                                                                                       RATLHL
```

000: /4

```
GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)
                                                                        RAILHL
                                                                                                               07/25/72
                  IF (XWRK .LT. DINCR) OINCR = XWRK
XWRK = 2640. * (VE * VE - VS * VS) / OE
1F (XWRK .LT. OINCR) OINCR = XWRK
                                                                                                     RATLHL
000200
                                                                                                     RATLHL
000207
                                                                                                     RAILHL
                  DELMAX = DINCR / (5280. * VE)
IF (NTRACK .FO. 2) NUMSWT = 1
000212
                                                                                                     RAILHL
                                                                                                                   85
000214
                                                                                                     RATLHL
                                                                                                                   86
                  CPFC = CP * FC
                                                                                                     RAILHL
                                                                                                                  87
000217
                  SWHPE = HPEV * VS / VE
SWHPF = HPFV * VS / VF
                                                                                                     RAILHL
                                                                                                                  BB
155000
                                                                                                     RATI HI
                                                                                                                  89
000224
                  PRINT 260. VF.VF.RE.RF.GE.GF.HPEV.HPFV
955000
                                                                                                     RATLHL
                                                                                                                  90
             260 FORMAT (23HORAIL PARAMETERS - VE.7X.2HVF.7X.2HRE.7X.2HRF.7X.
2HGE.7X.2HGF.6X.4HHPEV.5X.4HHPFV/17X.8(F8.3.1X) )
                                                                                                                  91
000252
                                                                                                     RAILHL
                                                                                                     RATLHL
                  QUC=CARCAP=NCARS=27.
                                                                                                                  93
000252
                                                                                                     RATLHE
             WUC=QUC*.05
PRINT 261. QUC. WUC
261 FORMAT (18HO TRAIN CAPACITY = F10.4. 17H CUBIC FEET AND
                                                                                                     RATIME
000255
                                                                                                     RAILHL
                                                                                                     RATLHL
000266
                 1 F10.4+ 5H TONS)
                                              WAS CALL FOR INITIALIZATION ONLY
                                                                                                     RAILHL
                                                                                                                   98
992000
                  IF (IRETSW) 270.999.270
                                                                                                     RATLHL
                                                                                                                  99
000267
             270 IRETSW = 0
                                                                                                     RATLHL
                                                                                                                 100
                                                                                                                 101
                  GO TO 350
                                                                                                     RATLHL
           C
                                                                                                     RAILHL
                                                                                                                 102
                                                                                                     RAILHL
                                                                                                                 103
                                              UPOATE TRAIN STATUS MATRIX
                                                                                                                 104
105
           C
                                                                                                     RATLHL
000271
                  ENTRY RAIL TR
                                                                                                     RAILHL
                                                                                                                 106
                                              HAS INITIALIZATION BEEN PERFORMED
                                                                                                     RATLHL
           C
                                                                                                                  107
000276
                  IF (INITSW) 350.320.350
                                                                                                     RAILHL
000277
             320 TRETSW = 1
                                                                                                                 108
                                                                                                     RATLHL
000300
             GO TO 100
350 NITER=DT/DELMAX
                                                                                                     RAILHL
                                                                                                                 109
                                                                                                     RAILHL
                                                                                                                 110
000304
                  TFRAC=DT-N1TFR*OELMAX
                                                                                                     RATLHL
                                                                                                                 111
                                                                                                     RATLHL
                                                                                                                 113
                   COMPUTING LABOR TIME USED FOR THIS ACTIVITY
                                                                                                     RAILHL
                                                                                                     RAILHL
                                                                                                                 114
                  HTTME (1) =HTTME (1) +OT
000307
                                                                                                     RATLHL
                                                                                                                 115
000310
                  IF (MFLAGC .NE. 0) GO TO 351
                                                                                                     RATLHL
                                                                                                                 116
                  IF (NUMLD .EQ. 0) GO TO 352 IF (11RORE .NE. 0) GO TO 351
000311
                                                                                                     RAILHL
                                                                                                                 117
                                                                                                                 118
21000
                                                                                                     RATLHL
                                                                                                     RATIMI
                                                                                                                 155
151
150
                                                                                                     RATIHL
                   COMPUTING UP TIME
                                                                                                     RAILHL
           C
                  UMHT1M=UMHT1H+OT
                                                                                                     RAILHL
000313
                                                                                                                 123
           C
                                                                                                     RATLHL
                                                                                                                 124
                   COMPUTING PLANT AND EQUIPMENT COSTS
                                                                                                     RAILHL
                                                                                                     RAILHL
             351 CONTINUE
000315
                                                                                                     RATLHL
                                                                                                                 156
000315
                  HPLANT=HPLANT+DT* (NTRAIN*ELOCO+NTRAIN*NCARS*EMUCKC) *
                                                                                                     RAILHL
                                                                                                                 127
                                                                                                                 128
129
130
                 10X* (ETRACK . NS *ESWITC . EUNLOA . ERMAIN)
                                                                                                     RAILHL
                                                                                                     RAILHL
000333
                  GO TO 353
                                                                                                     RATLHL
                                                                                                                 131
                   COMPUTING DOWN TIME
                                                                                                     RAILHL
                                                                                                     RATLHL
000334
             352 OMHTIM=OMHTIM+OT
                                                                                                                 133
134
                                                                                                      RATLHL
              353 CONTINUE
                                                                                                      RAILHL
                                               RETRIEVE /OLDWAK/ VARIABLES
                                                                                                      RATLHL
                                                                                                                  i 35
000336
                  00 355 J=1.NTRAIN
                                                                                                      RAILHL
                                                                                                                  136
```

```
GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)
                                                                            RAILHL
                                                                                                                    07/25/72
                    ISTATE(J+1) = ITSTAT(J+1)
STATE(J+2) = TSTAT(J+2)
STATE(J+3) = TSTAT(J+3)
000340
                                                                                                         RAILHL
RAILHL
000342
                                                                                                                       138
000345
                                                                                                          RAILHL
                                                                                                                       139
                    STATE(J.4) = TSTAT(J.4)
JSTOP(J) = KSTOP(J)
000347
                                                                                                          RAILHI
                                                                                                                       140
000351
                                                                                                          RAILHL
                                                                                                                       141
              TTFC(J) = TFC(J)
TTOP(J) = TOP(J)
355 CONTINUE
000353
                                                                                                          RAILHL
                                                                                                                       142
000355
                                                                                                          RAILHL
                                                                                                                       143
000357
                                                                                                          RAILHL
                                                                                                                       145
000361
                   ISTOP = LSTOP
                                                                                                         RAILHL
              360 LLTRAN = 0
LRETRN = 0
DELTAT = OELMAX
000362
                                                                                                          RAILHL
                                                                                                                       146
000363
                                                                                                                       147
                                                                                                          RATLHL
000364
                                                                                                          RAILHL
                                                                                                                      148
                   IF (NITER.NE.0) GOTO 362
DELTATETERAC
                                                                                                                      149
000365
                                                                                                          RAILHL
000366
                                                                                                          RAILHL
000370
              362 CONTINUE
                                                                                                          RAILHL
                                                                                                                      151
                   LOUE=100
                                                                                                          RAILHL
                                                                                                                      152
                   DO 364 ITR=1.NTRAIN

IF (ISTATE(ITR-1).NE.0) GOTO 364

IF (JSTOP(ITR).GT.100) LQUE=LQUE-1
000371
                                                                                                         RAILHL
                                                                                                                       153
000373
                                                                                                         RAILHL
000375
                                                                                                          RAILHL
                                                                                                                      155
              364 CONTINUE
000401
                                                                                                         RAILHL
                   IRRNCH = ISTOP + 1
000404
                                                                                                         RAILHL
                   GO TO (500.400.450) IBRNCH
000406
                                                                                                         RAILHL
                                                                                                                      158
                                                SYSTEM MUST BE SHUT DOWN
                                                                                                         RAILHL
                                                                                                                      159
000414
              400 DO 420 J=1.NTRAIN
                                                                                                         RATLHL
                                                                                                                      160
                   IF (JSTOP(J) .NE. 0) GO TO 420 INRK = 1STATE(J.1)
000416
                                                                                                         RATIM
                                                                                                                      161
000420
                                                                                                         RATLHL
                   IF ((IWRK-10) . (IWRK-11) .EQ. 0) GO TO 420
000421
                                                                                                         RAILHL
                                                                                                                      163
                   JSTOP(J) = 4
000426
                                                                                                         RAILHL
                   IF ((IWRK-6)*(IWRK-7) .EQ. 0) GO TO 420
000430
                                                                                                         RAILHL
                   JWRK = (IWRK + 1) / 2
IWRK = IWRK / 2
IS = 7
000435
                                                                                                         RAILHL
                                                                                                                      166
000437
                                                                                                         RAILHL
000441
                                                                                                         RAILHL
                                                                                                                      168
                   IF (IWRK .EO. JWRK) IS = 6
ISTATE(J.1) = IS
000442
                                                                                                         RAILHL
                                                                                                                      169
000445
                                                                                                                      170
171
                                                                                                         RAILHL
000447
              420 CONTINUE
                                                                                                         RAILHL
                   GOTO 500
000452
                                                                                                         RAILHL
                                                                                                                      172
           С
                                                SYSTEM MUST BE BROUGHT UP
                                                                                                         RAILHL
                                                                                                                      173
             450 00 470 J=1.NTRAIN
IF (JSTOP(J) .NE. 4) GO TO 470
000452
                                                                                                         RAILHL
                                                                                                                      174
000454
                                                                                                         RAILHL
                                                                                                                      175
000457
                   JSTOP(J) = 0
                                                                                                         RAILHL
                                                                                                                      176
000460
                   JWRK = ISTATE (J.1)
                                                                                                         RAILHL
                                                                                                                      177
                   IF (JWRK .EQ. 0) ISTATE(J.1) = 2
IF (JWRK .EQ. 1) ISTATE(J.1) = 3
000461
                                                                                                         RAILHL
                                                                                                                      178
000464
                                                                                                         RAILHL
                                                                                                                      179
              470 CONTINUE
000470
                                                                                                         RAILHL
                                                                                                                      190
000473
              475 ISTOP = 0
                                                                                                         RAILHL
                                                                                                                      181
                                                                                                                      192
           С
                                                APPLY DELTA-T TO ALL TRAINS
                                                                                                         RAILHL
000474
              500 DO 750 I = 1.NTRAIN
                                                                                                         RAILHL
                   DELTAC = 0.
STATE(I.4) = STATE(I.4) + (DELTAT / 24.)
000476
                                                                                                         RAILHL
                                                                                                                      184
000477
                                                                                                         RAILHL
                                                                                                                      145
000502
                   ISTAT = ISTATE(I.1)
                                                                                                         RAILHL
                                                                                                                      186
                   TPOS = STATE(1.2)
TSPO = STATE(1.3)
IKTEMP = KTEMP(1)
030504
                                                                                                         RAILHL
                                                                                                                      187
000506
                                                                                                         RATLHL
                                                                                                                      188
000507
                                                                                                         RAILHL
                                                                                                                      199
                   IJSTOP = JSTOP(I)
000511
                                                                                                         RATLHL
                                                                                                                      190
000512
                                                                                                         RAILHL
                                                                                                                      191
```

```
07/25/72
GDLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                      RATLHL
                                                                                                  RATLHL
                                                                                                              192
000514
                  SWP05 = 0
                  IF (IISW .GT. 0) SWPOS = SWITCH(IISW)
IBRNCH = ISTAT + 1
                                                                                                  RATLHL
                                                                                                              193
                                                                                                  RATLHL
                                                                                                               194
000520
                  GO TO (510.530.550.570.590.610.630.650.670.690.700.700) IBRNCH
                                                                                                  RATLHL
                                                                                                               195
000522
                                                                                                  RATLHL
           C
                                             TRAIN IS EMPTY. AND HAS STOPPED
                                                                                                              196
                                                                                                              197
             510 IF (1JSTOP.GT.100) GOTO 511
                                                                                                  RATLHL
000541
                 GOTO (514+516+520+1000+1000+600) IJSTDP
TRAIN IS IN LOAD QUEUE
                                                                                                  RATLHL
                                                                                                              198
000545
                                                                                                  RATINE
                                                                                                              200
000556
             511 CONTINUE
                                                                                                              201
                                                                                                  PATINI
000556
                 GDTO 698
                                                                                                  RAILHL
                                             TRAIN IS BEING LDAOED
                                                                                                              202
           C
000557
                                                                                                  RATLHL
                                                                                                              203
             514 LLTRAN=I
                                                                                                               204
             TRAIN IN SWITCH. WITH ANOTHER STOPPED AHEAD RAILHL SIG IF (ISTATE (IKTEMP.1) .EO. 0) GD TO 700
                  GOTO 698
000561
                                                                                                               205
                                                                                                               206
000561
                                                                                                  RATLHL
                                                                                                               207
                  TPOS = SWPOS - HLFLS
000563
000565
                                                                                                  RATLHL
                                                                                                               209
                  IKTEMP = 0
000566
                                                                                                  RAILHL
                                                                                                              210
                  IJSTOP = 0
000567
                  GO TO 698
                                                                                                  RATLHL
                                                                                                              211
000570
             TRAIN IN SWITCH. WITH ANOTHER APPROACHING 520 IF (STATE (IKTEMP.2) .GT. SWPOS-HLFLS) GD TD 700
                                                                                                  RATLHL
                                                                                                              212
           C
                                                                                                  RATLHL
                                                                                                              213
000570
                                                                                                              214
000576
                                                                                                  RATLHL
                  LRETRN = 1
             GD TO 636
522 1STAT = 2
                                                                                                  RAILHL
                                                                                                   RATIHI
                                                                                                               216
000577
                  TPOS = SWPOS . HLFLS
000600
                                                                                                   RATLHL
                                                                                                              218
                  IKTEMP = 0
000602
                  IJSTOP = 0
                                                                                                   RATLHL
                                                                                                               220
000604
                  GO TO 698
                                             TRAIN IN IST SWITCH. AWAITING DISCHARGE
                                                                                                  RAILHL
                                                                                                              155
           C
             524 IF (IFILLD .EQ. 1) GO TO 700
LRETRN = 5
                                                                                                  RATLHL
                                                                                                              222
000604
                                                                                                  RATIHI
000606
                                                                                                  RAILHL
                                                                                                              224
                  GOTO 662
800607
                                                                                                              225
                                             TRAIN IS FULL AND STOPPED
                                                                                                  RA1LHL
           C
             530 IF (IJSTOP.GT.5) GOTO 1000
                                                                                                  RATIHI
                                                                                                               226
000610
                                                                                                              227
                                                                                                  RATLHL
                  GOTO (1000.536.542.1000.524) IJSTOP
000614
             TRAIN IN SWITCH. ANDTHER STOPPED AHEAD 536 IF (ISTATE (IKTEMP.I) .FQ. 1) GO TO 700
                                                                                                   RATLHL
                                                                                                              228
           C
                                                                                                   RATIHL
880624
                                                                                                   RATLHL
                                                                                                               230
                  LRETRN = 3
888627
                                                                                                   PATLHL
                                                                                                               231
                  GO TD 662
888630
                                             TRAIN IN SWITCH. ANOTHER APPROACHING
                                                                                                   RATLHL
                                                                                                               232
           C
                                                                                                   RATLHL
                                                                                                               233
             542 IF (STATE (1KTFMP+2) .1.T. SWPOS-HLFLS) GO TO 700
000630
                                                                                                   RATIM
                                                                                                               234
000635
                  LRETRN = 5
                                                                                                               235
                                                                                                  RATLHL
                                                                                                  RAILHL
                                                                                                               236
                                             TRAIN IS ACCELERATING EMPTY
           C
             550 IF (10PTN - )) 584.553.584

551 RE = GE + (RFF1 + (TSPD+(REF2+TSP0+0.045)))

AFA = TEA - RE
                                                                                                  RATLHL
                                                                                                               237
000637
                                                                                                   RAILHL
000642
                                                                                                   RATLHL
                                                                                                               239
000650
                  1F (AFA .LT. 0.) AFA = 0.
AE = 39.4 = AFA / GE
                                                                                                   RATLHL
000652
                                                                                                   RAILHL
                                                                                                               241
000654
             AE = 39.4 * AFA / GE

IF (AMAX .LT. AE) AE = AMAX

553 Yl = AE * DELTAT

TPOS = TPOS*DELTAT*((2640.*YI)*(5280.*TSPD))

TSPO = TSPO * YI
                                                                                                   RAILHL
                                                                                                               242
000657
                                                                                                   RATLHL
                                                                                                               243
000662
                                                                                                               244
                                                                                                   RATLHL
000664
                                                                                                   RATLHL
                                                                                                               245
000672
                  IF (IOPTN.EQ.2) HPEAH= (AE . GE/39.4 +RE) . (TSPO/HPFAC)
                                                                                                   RATLHL
                                                                                                               246
000673
```

```
07/25/72
GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)
                                                                            RATLHL
                                                                                                         RAILHL
RAILHL
                                                                                                                       247
                   IF (HPA .GT. D. .AND. HPEAH .GT. HPA) HPEAH = HPA
000703
                   OELTAC = HPEAH
000713
                                                                                                                       249
                                                                                                          RATLHL
                   IF (TSPO - VE) 558,554,554
000714
                                                                                                                       250
                                                                                                          RAILHL
              554 ISTAT = 4
000717
                                                                                                                       251
                                                                                                          RATLHL
                   TSPO = VE
000720
                                                                                                                       252
                                                                                                          RATLHL
              558 00 562 J=1.NUMSWT
000722
                   A = SWITCH(J) - HLFLS - TPOS

IF (A .LT. 0.) GO TO 562

B = 2640. * ((TSPO*TSPO)-(VS*V5)) / DE

IF (A .GT. B) GO TO 562

ISTAT = 6
                                                                                                                       253
254
                                                                                                          RAILHL
003724
                                                                                                          RAILHL
000730
                                                                                                                       255
                                                                                                          RATLHL
000731
                                                                                                          RAILHL
000736
                                                                                                                       257
                                                                                                          RATLHL
000741
                                                                                                                       258
                                                                                                          RATLHL
                   IISW = J
000742
                                                                                                                       259
                                                                                                          RATLHL
                   GO TO 698
000743
                                                                                                          RATLHL
                                                                                                                       260
              562 CONTINUE
000744
                                                                                                          RATLHL
                                                                                                                       261
000747
                   IISW = 0
                                                                                                          RATLHL
                                                                                                                       262
                   GO TO 698
000750
                                                 TRAIN IS ACCELERATING FULL
                                                                                                          RATLHL
                                                                                                                       263
              570 IF (IOPTN - 1) 584.572.584
571 RF = GF * (RFF1 * (TSPD * (RFF2*TSPD * 0.045)))
                                                                                                          RAILHL
                                                                                                                       264
000750
                                                                                                                       265
                                                                                                          RAILHL
600753
                                                                                                          RAILHL
                                                                                                                       266
                    AFA = TEA - PF
000761
                                                                                                                       267
268
              IF (AFA .LT. 0.) AFA = 0.

AF = 39.4 * AFA / GF

IF (AMAX .LT. AF) AF = AMAX

572 Y) = AF * DELTAT
                                                                                                          RAILHL
000763
                                                                                                          RAILHL
000765
                                                                                                                       269
                                                                                                          RATLHL
000770
                                                                                                          RATIHI
                                                                                                                       270
000773
                   TPOS = TPOS - OELTAT*((5280.*TSPO)*(2640.*Y1))
                                                                                                          RAILHL
                                                                                                                       271
000775
                   ISPU = ISPO + YI
IF (IOPTN.EQ.2) HPFAH= (AF*GF/39.4 + RF) * (TSPO/HPFAC)
IF (HPA .GT. 0. .AND. HPFAH .GT. HPA) HPFAH = HPA
OELTAC = HPFAH
                                                                                                          RAILHL
001002
                                                                                                                       273
                                                                                                          RAILHL
001004
                                                                                                                       274
                                                                                                          RAILHL
001014
                                                                                                          RAILHL
                                                                                                                       275
001024
                                                                                                          RAILHL
                                                                                                                       276
                    IF (TSPO - VF) 578,574,574
001025
                                                                                                          RAILHL
                                                                                                                       277
              574 ISTAT = 5
TSPD = VF
001030
                                                                                                          RAILHL
 001031
                                                                                                          RATLHL
                                                                                                                       279
              578 IF (NTRACK .EQ. 2) GO TO 583
 001033
                                                                                                                       280
                   DO 582 J=1.NUMSWT
A = TPOS - (SWITCH(J) + HLFLS)
                                                                                                          RAILHL
 001035
                                                                                                          RAILHL
                                                                                                                        281
001037
                   IF (A .LT. 0.) GO. TO 582

IF (A .CT. B) GO TO 582

IF (A .CT. B) GO TO 582

ISTAT = 7
                                                                                                          RAILHL
                                                                                                                       282
001043
                                                                                                          RAILHL
                                                                                                                       283
 001044
                                                                                                          RAILHL
                                                                                                                        284
 001051
                                                                                                                        285
                                                                                                          RAILHL
001054
                                                                                                          RAILHL
                                                                                                                        286
                    IISW = J
 001055
                                                                                                                       287
                                                                                                          RAILHL
                    GO TO 698
 001056
                                                                                                          RAILHL
                                                                                                                        288
               582 CONTINUE
001057
                                                                                                          RATLHL
                                                                                                                        289
               583 IISW = 0
 001062
                    B = 2640. * ((TSPO*TSPD)-(VD*VD)) / DF
                                                                                                          RAILHL
                                                                                                                        290
 001063
                                                                                                                        291
                                                                                                          RAILHL
                    IF (TPOS .GT. B) GD TO 698
 001070
                                                                                                                        292
293
                                                                                                          RAILHL
                    ISTAT = 7
 001073
                                                                                                          RAILHL
                     IISW = 100
 001074
                                                                                                                        294
                                                                                                          RAILHL
                    GO TO 698
 001075
                                                                                                                        295
296
                                                                                                          RATLHL
                                                 FIND TEA
               584 TEA = TTEA
 001075
                                                                                                                        297
                                                                                                          RAILHL
                    IF (HPA .EQ. 0.) GO TO 585
 001077
                                                                                                                        298
299
                                                                                                          RATLHL
                    Y1 = TEA
 001100
                                                                                                          RAILHL
                    IF (TSPO .NE. O.) Y1 = HPAFAC/TSPD
 001101
                                                                                                          RATLHL
                                                                                                                        300
                    GO TO 589
 001103
                                                                                                          RATLHL
                                                                                                                        301
```

585 IF (TSPD .GT. TCURVX(1)) GO TO 586

```
GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)
                                                                    RATLHL
                                                                                                         07/25/72
001110
                 Y1 = TCURVY(1)
                                                                                               RATLHL
                                                                                                           302
             GO TO 589
586 DO 588 K = 2.NPOINT
001111
                                                                                               RATLHL
                                                                                                           303
001111
                                                                                               RATLHL
                                                                                                           304
                 XWRK = TCURVX(K)
001113
                                                                                               RATLHL
                                                                                                           305
                 IF (XWRK .LT. TSPD) GO TO 588
YWRK = TCURVY(K)
001115
                                                                                               RATLHL
                                                                                                           306
001117
                                                                                               RATLHL
                                                                                                           307
                 Y1 = YWRK-((XWRK-TSP0)*(YWRK-TCURVY(K-1))/(XWRK-TCURVX(K-1)))
GO TO 589
151100
                                                                                               RATLHL
                                                                                                           308
001131
                                                                                               RATI HI
                                                                                                           309
             SAB CONTINUE
                                                                                               RATLHL
001131
                                                                                                           310
                 Y1 = TCURVY (NPOINT)
                                                                                                           311
001134
                                                                                               RATLHL
             589 CONTINUE
001135
                                                                                               RATLHL
                 IF (Y) .LT. TEA) TEA = Y)
001135
                 IF (15TAT - 2) 571.551.571
TRAIN EMPTY. GOING AT FULL SPEED
                                                                                               RATLHL
                                                                                                           313
                                                                                               RATLHL
                                                                                                           314
001140
                                                                                               RATIM
            590 TPOS = TPOS . (5280. * VE * DELTAT)
001143
                                                                                               RATIM
                                                                                                           316
001147
                                                                                               RATLHI
                 GOTO 554
                                                                                                           318
001150
                                           TRAIN IN SWITCH. WAITING TO ENTER LOAD AREA RAILHI.
                                                                                                           319
001150
             600 IF (NUMLO.GE, MAXLD) GOTO 700
                 LRETRN=1
001153
                                                                                               RATLHL
                                                                                                           321
001154
                 GOTO 643
                                                                                               RATLHL
                                                                                                           355
                                           TRAIN FULL. GOING AT FULL SPEED
                                                                                               RATLHL
                                                                                                           323
            610 TPOS = TPOS - (5280. • VF • DELTAT)
OELTAC = HPFV
001154
                                                                                               RATLHL
                                                                                                           324
325
001160
                                                                                               RATLHL
                 GOTO 574
                                                                                                           326
001161
                                                                                               RATLHL
                                    TRAIN IS DECELERATING EMPTY
          C
                                                                                               RATI HL
001161
            630 Y1 = OE . OELTAT
                                                                                               RAILHL
                                                                                                           328
                 TPOS = TPOS + DELTAT + ((5280.*TSPD)-(2640.*Y1))
TSPD = TSPO - Y1
001163
                                                                                                           329
330
                                                                                               RATLHL
                                                                                               RATLHL
001172
                 IF (TSPO .GT. 0.) GO TO 634
                                                                                               RATLHL
                                                                                                           331
001174
                 ISTAT = 0
                                                                                               RATLHL
                                                                                                           332
001174
                 TPOS=SWITCH(IISW)
                                                                                               RATLHL
                                                                                                           333
001176
                 TSP0 = 0.
                                                                                               RATLHL
                                                                                                           334
                 IF (1JSTOP.NF.0) GOTO 698
001177
                                                                                               RATLHL
                                                                                                           335
                                                                                               PATLHL
001200
                 LRETRN=1
                                                                                                           336
                 GOTO 6636
001201
                                                                                               RATLHL
                                                                                                           337
            634 IF (ISTOP .EQ. 1) GO TO 698
IF (ITSW .EQ. 0) GO TO 698
IF (TSPO .GT. VS) GO TO 648
636 IF (IJSW-(NUHSWT-1)) 638, 6638,6636
001201
                                                                                               RATLHL
                                                                                                           338
001203
                                                                                               RATLHL
001204
                                                                                               RATLHL
                                                                                                           340
001210
                                                                                               RATLHL
                                                                                                           341
           6636 LQUE=LQUE+1
001213
                                                                                               RATLHL
                                                                                                           342
001215
                 NUML D=LQUE-99
                                                                                               RATLHL
                                                                                                           343
001217
                 IF (NUHLD.LE.MAXLD) GOTO 627
                                                                                               RATLHL
                                                                                                           344
                 PFINT 6637
                                                                                               RATLHL
                                                                                                           345
001221
                                                                                               RAILHL
001225
           6637 FORMAT (30HO TOO MANY TRAINS AT THE FACE )
                                                                                                           346
            CALL EX
001225
                       EXIT
                                                                                               RATLHL
                                                                                                           347
                                                                                                           348
001226
                                                                                               RATLHL
                 IJSTOP=LQUE
                                                                                               RATLHL
                                                                                                           349
001226
                                                                                                           350
                                                                                               RATIHI
001230
                 GOTO 648
                                                                                                           351
001230
             637 IJSTOP=6
                                                                                               RATIHL
                 IKTE 4P=0
                                                                                                           352
001231
                                                                                               RATLHL
001232
                 GOTC 648
                                                                                                           353
                                                                                               RATLHL
           6638 IF (NIMLO-MAXLO) 643+637+637
638 X1 = SWITCH(IISW + 1)
001233
                                                                                                           354
                                                                                               RATLHL
001236
                                                                                               RATLHL
                                                                                                           355
001240
                 RMAX = X1 + HLFLS
                                                                                               RATLHL
```

```
07/25/72
                                                                                  RAILHL
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                                                 357
358
                                                                                                                   RATLHL
                     RMIN = X1 - HLFLS

DO 642 K=1.NTRAIN

IF (1 .EQ. K) GO TO 642

X1 = STATE(K.2)
001242
                                                                                                                   RATLHL
001243
                                                                                                                   RATLHL
                                                                                                                                 359
001245
                                                                                                                   RATLHL
                                                                                                                                 350
001246
                                                                                                                   RATLHL
                                                                                                                                 361
                     I = STAILE(N.2)

IF (YI .GT. RMAX) GO TO 642

IF (XI .LT. RMIN) GO TO 642

IWRK = ISTATE(K.1)

IF (IWRK = (IWRK-6) .NE. 0) GO TO 639
001250
                                                                                                                                 362
                                                                                                                   RAILHL
001253
                                                                                                                                 363
                                                                                                                   RATLHI
001255
                                                                                                                                 364
                                                                                                                   RATLHL
001257
                                                                                                                   RATLHL
                                                                                                                                 365
                     IKTEMP = K
001262
                                                                                                                   RATLHL
                                                                                                                                 366
                     TUSTOP = 2
001263
                                                                                                                   RATLHL
                                                                                                                                 367
                     GO TO 648
001264
                                                                                                                   RATLHL
                                                                                                                                 368
               639 IF (IWRK .NE. 8) GO TO 640
001264
                                                                                                                   RATLHL
                                                                                                                                 369
                                                                                                                                 370
001266
                                                                                                                   RATLHL
                      IJSTOP = 0
                                                                                                                                 371
001267
                                                                                                                   RATLHL
                     GO TO 642
                                                                                                                                 372
373
001270
                                                                                                                   RATLHL
                640 IF(1WRK .NE. 9) GO TO 641 IKTEMP = K
001270
                                                                                                                   RATLHL
001272
                                                                                                                                  374
                                                                                                                   RAILHL
                      IJSTOP = 3
001274
                                                                                                                                  375
                                                                                                                   RATLHL
               | IJSTOP = 3
GO TO 648
641 | F ((IWRK-I) = (IWRK-7) .NE. 0) GO TO 642
| IKTEMP = 0
| IJSTOP = 0
642 CONTINUE
| GAS CONTINUE
| RMAX = SWITCH(IISW + I) = HLFLS
| RMIN = SWITCH(IISW) + HLFLS
| OO 646 K=1.NTRAIN
                                                                                                                                  376
                                                                                                                   RATI HI
001275
                                                                                                                                  377
378
 001275
                                                                                                                   RATLHL
RATLHL
 001302
 001303
                                                                                                                    RATLHL
                                                                                                                                  379
 001304
                                                                                                                    RATLHL
                                                                                                                                  380
                                                                                                                                  18E
 001307
                                                                                                                    RATLHL
                                                                                                                    RATLHL
 001307
                                                                                                                                  383
                                                                                                                    RATLHL
 001312
                      00 646 K=1.NTRAIN
                                                                                                                                  384
 001314
                      UG 446 K=1.NIMAIN
IF (I .EO. K) GO TO 646
X1 = STATE(K.2)
IF (X1 .GT. RMAX) GO TO 646
IF (X1 .LT. RMIN) GO TO 646
IWK = ISTATE(K.1)
                                                                                                                    RATLHL
 001316
                                                                                                                    RATLHL
                                                                                                                    RATLHL
                                                                                                                                  386
 001321
                                                                                                                                  3A7
                                                                                                                    RATIHI
                                                                                                                                   388
                                                                                                                    RATLHL
 001324
 001326
                                                                                                                                  389
                      IF ((IWRK-I)*(IWRK-3)*(IWRK-5)*(IWRK-7) .NE. 0) GO TO 644
                                                                                                                    RATLHL
                                                                                                                                   390
 001330
                                                                                                                    RATLHL
                       IKTEMP = K
                                                                                                                    RATLHL
                                                                                                                                   391
 001344
                      IJSTOP = 3
 001345
                                                                                                                    RATLHL
                                                                                                                                   392
                 GO TO 648
644 IF (IWRK + (IWRK -6) .NE. 0) GO TO 646
                                                                                                                    RATLHL
                                                                                                                                   393
 001346
                                                                                                                    RATLHL
                                                                                                                                   394
 001346
                       IKTEMP = K
                                                                                                                                   395
  001351
                                                                                                                    RATLHL
                       TUSTOP = 2
                                                                                                                                  396
397
  001353
                                                                                                                    RAILHL
                 GO TO 648
  001354
                                                                                                                    RAILHL
                                                                                                                                   398
  001354
                                                                                                                    RATLHL
                       IF (LRETRN .FQ. I) 60 TO 522
                                                                                                                                   399
  001357
                                                                                                                    RATLHL
                       ISTAT = B
                                                                                                                                   400
  001361
                                                                                                                     RATCHL
                       TSPD = VS
                                                                                                                                   401
  001362
                                                                                                                     RATLHL
                       IKTEMP = 0
                                                                                                                                   402
  001363
                                                                                                                     RATLHL
                       IJSTOP = 0
                                                                                                                     RATLHL
                                                                                                                                   403
  001364
                 GO TO 698
648 IF (LRETRN .FQ. 1) GO TO 649
                                                                                                                                   404
  001365
                                                                                                                     RATLHL
                                                                                                                                   405
                                                                                                                     RATLHL
  001365
                 ISTAT = 6
GO TO 698
649 ISTAT = 0
                                                                                                                     RATLHL
                                                                                                                                   406
  001357
                                                                                                                                   407
                                                                                                                     RATLHL
  001371
                                                                                                                     RATLHL
                                                                                                                                   408
                       GO TO 698
                                                                                                                     RATLHL
                                                                                                                                   409
  001372
                                                       TRAIN IS DECELERATING FULL
                                                                                                                                   410
                                                                                                                     RAILHL
                 650 IF(JSTOP(I) .NE. 5) GO TO 65?
  001373
                                                                                                                     RATLHL
                                                                                                                                   411
```

LRETRN=5

```
RATLHL
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                                    07/25/72
001377
              GO TO 656
652 Y1=DF+DEL TAT
                                                                                                         RATLHL
                                                                                                         RAILHL
                                                                                                                      413
                    TPOS = TPOS . DELTAT . ((2640. - Y11 - (5280. - TSPO1)
001401
                                                                                                         RATLHL
                                                                                                                      414
                   ISPO = TSPO - Y1
IF (ISTOP .EQ. 1) GO TO 698
IF (ISTO .EQ. 10) GO TO 653
IF (TSPO .GT. 0.)GO TO 651
ISTAT = 1
                                                                                                                      415
416
417
001407
                                                                                                         RAILHL
001410
                                                                                                         RATIME
001412
                                                                                                         RATLHL
001414
                                                                                                         RATIMI
                                                                                                                      418
001416
                                                                                                         RATLHL
001417
                    TSPD = 0
                                                                                                         RATLHL
                                                                                                                      420
              GO TO 698
651 IF (IISW .EO. 0) GO TO 698
                                                                                                                      421
001417
                                                                                                         RATI HI
001420
                                                                                                         RATLHL
001421
                   IF (TSPD .GT. VS1 GO TO 666
                                                                                                                      423
                                                                                                         RATLHL
001425
                   GO TO 656
                                                                                                         RAILHL
                                                                                                                      424
001425
              653 IF (TSPD .LE. 0.1 TPOS=0.
                                                                                                         RAILHL
                                                                                                                      425
001430
                    IF (TPOS .GT. 0.1 GO TO 666
                                                                                                         RAILHL
                                                                                                                      426
001433
                    ISTAT = 10
                                                                                                         RATLHL
                                                                                                                      427
                   TPOS = 0
001434
                                                                                                         RAILHL
                                                                                                                      428
                   TSPO = VO
001434
                                                                                                         RAILHL
                                                                                                                      429
                   NTDA = NTDA + 1
001436
                                                                                                         RATLHL
                                                                                                                      430
                   IF (NTDA .GE. NTOL IFILLO = I
001437
                                                                                                         RAILHL
                                                                                                                      431
                   GO TO 698
                                                                                                                      432
433
001442
                                                                                                         RAILHL
              656 IF (115W .NE. 1) GO TO 658
001443
                                                                                                         RAILHL
                   TF(IFILLO .NF. 11 GO TO 658
IJSTOP = 5
IKTEMP = 0
                                                                                                                      434
435
436
437
001445
                                                                                                         RAILHL
001447
                                                                                                         RATLHL
001450
                                                                                                         RAILHL
001451
                   GO TO 666
                                                                                                         RATLHL
              658 IF (IISW .LE. 1) GO TO 662

X1 = SWITCH(IISW - 1)

RMAX = X1 + HLFLS
001451
                                                                                                         RATLHL
                                                                                                                      438
001454
                                                                                                         RATLHL
                                                                                                                      439
001455
                                                                                                         RAILHL
                                                                                                                      440
                   RMIN = X1 - HLFLS
001457
                                                                                                         RATLHL
                                                                                                                      441
                   00 660 K=1.NTRAIN
IF (I .EO. K) GO TO 660
XI = STATF(K.2)
001460
                                                                                                         RATLHL
                                                                                                                      442
                                                                                                         RATLHL
001462
                                                                                                                      443
001463
                                                                                                         RAILHL
                                                                                                                      444
445
446
                   IF (X1 .GT. RMAX) GO TO 660
IF (X1 .LT. PMIN) GO TO 660
IWRK = ISTATE(K-1)
                                                                                                         RATLHL
001465
001470
                                                                                                         RATLHL
                                                                                                                      447
001472
                                                                                                         RATLHL
                   IF (([WRK-])+([WRK-7) .NE. 0) GO TO 6584
001474
                                                                                                         RAILHL
                                                                                                                      448
001501
                   INTEMP = K
                                                                                                                      449
                                                                                                         RAILHL
                                                                                                                      450
001502
                   IJSTOP = 2
                                                                                                         RAILHL
             GO TO 666
6584 IFILMER .NE. 91 GO TO 6586
                                                                                                                      451
452
001503
                                                                                                         RAILHL
001504
001506
                   TKTEMP = 0
                                                                                                                      453
                                                                                                         RATLHL
                    IJSTOP = 0
                                                                                                                      454
001507
                                                                                                         RATLHL
001510
                                                                                                                      455
                   60 TO 660
                                                                                                         RATLHL
            6586 IF (IWRK .NE. 81 GO TO 6588 INTEMP = K
001510
                                                                                                         RAILHL
                                                                                                                      456
001512
                                                                                                                      457
                                                                                                         RATLHL
                   IJSTOP = 3
001514
                                                                                                         RATLHL
                                                                                                                      458
001515
                   SO TO 666
                                                                                                         RATLHL
                                                                                                                      459
             6588 IF ((IWRK-6)*IWRK .NE. 0) GO TO 660
IKTEM= 0
IJSTOP = 0
001515
                                                                                                         RATLHL
                                                                                                                      460
001520
                                                                                                         RATLHL
                                                                                                                      461
001521
                                                                                                         RATLHL
                                                                                                                      462
              660 CONTINUE
662 RMAX = SWITCH(IISW) - HLFLS
001522
                                                                                                         RATLHL
                                                                                                                      463
                                                                                                                     464
                                                                                                         RAILHL
                   RMIN=0.
001530
                                                                                                         RATLHE
                   IF (IISW.NE.11 RMIN=SWITCH(IISW-I)+HLFL5
                                                                                                         RAILHL
                                                                                                                      466
001,31
```

```
07/25/72
                                                                    RATLHL
GOLFTA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                               RAILHL
                                                                                                           467
                 DO 664 K=1.NTRAIN
IF (I .EQ. K) GO TO 664
                                                                                                           468
001535
001537
                                                                                               RAILHL
                                                                                                           469
                 Y1 = STATF(K.2)
001540
                                                                                               RATLHL
                                                                                                           470
                 IF (Y1 .GT. PMAX) GO TO 664
IF(Y1 .LT. RHIN) GO TO 664
IWRK = (STATE(K+1)
001542
                                                                                               RATLHL
                                                                                                           471
001545
                                                                                                           472
                                                                                               RATLHL
001547
                                                                                                           473
                 IF (IWRK . (IWRK-2) . (IWRK-4) . (IWRK-6) .NE. 0) GO TO 663
                                                                                               RATLHL
001551
                                                                                               RATLHL
                                                                                                           474
                 TKTEMP = K
                                                                                                           475
001561
                                                                                               RATLHL
                 TUSTOP = 3
001562
                                                                                               RATLHL
                                                                                                           476
                 GO TO 666
001563
                                                                                                           477
                                                                                               RATLHL
             663 IF (([WRK-1) . ([WRK-7) .NE. 0) GO TO 664
001563
                                                                                               RATLHL
                                                                                                           478
                 TKTEMP = K
001570
                                                                                               RATLHL
                                                                                                           479
                 IJSTOP = 2
001572
                                                                                                           480
                                                                                               RATLHL
001573
                 GO TO 666
                                                                                                           481
                                                                                               RATLHL
             664 CONTINUE
001573
                                                                                                           482
                                                                                                RATLHL
                  IF ((LRETRN-3) . (LRETRN-5) .EQ. 0) GO TO 6662
001576
                                                                                                           483
                                                                                                RAILHL
                  ISTAT = 9
                                                                                                           484
001603
                                                                                                RATIMI
                  TSPD = VS
                                                                                                           485
001604
                                                                                                RATLHL
                  IKTEMP = 0
001606
                                                                                                           486
                                                                                                RATLHL
001507
                  TUSTOP = 0
                                                                                                            487
                                                                                                RATLHL
             GO TO 698
666 IF ((LRETRN-4)*(LRETRN-5) .EQ. 0) GO TO 6666
ISTAT = 7
                                                                                                            488
001610
                                                                                                RATLHL
                                                                                                RATLHL
                                                                                                            489
001615
                                                                                                            490
                                                                                                RAILHL
            GO TO 698
6662 ISTAT = 3
TPOS = SWITCH(IISW) - HLFLS
                                                                                                RATLHL
                                                                                                            491
001616
                                                                                                            492
001617
                                                                                                RAILHL
                                                                                                            493
001620
                                                                                                RATLHL
                  IKTEMP = 0
                                                                                                            494
001623
                                                                                                RATLHL
                  IJSTOP = 0
                                                                                                            495
001624
                                                                                                RATLHL
                  LRETRN=0
                                                                                                            496
001625
                                                                                                RATLHL
            GO TO 698
6666 ISTAT = 1
                                                                                                            497
001626
                                                                                                RATLHL
                                                                                                            498
001626
                                                                                                RATIHL
                  GO TO 698
                                                                                                            499
                                            TRAIN EMPTY. TRAVELING IN SWITCH AT VS
                                                                                                RATLHL
           C
                                                                                                            500
                                                                                                RATLHL
             670 TPOS = TPOS + (5280. * VS * DELTAT)
001630
                                                                                                RATLHL
                                                                                                            501
                  TSPD = VS
DELTAC = SWHPE
IF (TPOS - SWPOS - HLFLS .LT. 0.)GO TO 698
                                                                                                            502
                                                                                                RATIHL
                                                                                                            503
 001634
                                                                                                RATLHL
 001636
                                                                                                RAILHL
                                                                                                            504
                  ISTAT = 2
 001641
                                                                                                            505
                                                                                                RATLHL
                  IISW = 0
 001642
                                                                                                RAILHL
                  GO TO 698
 001443
                                                                                                            507
                                                                                                RATLHL
                                             TRAIN FULL. TRAVELING IN SWITCH AT VS
                                                                                                            508
                                                                                                RATLHL
             690 TPOS = TPOS - (5280. * VS * DELTAT)
                                                                                                            509
 001644
                                                                                                RATLHL
                  DELTAC = SWHOF
 001650
                                                                                                            510
                   IF (SWPOS - HLFLS - TPOS .LT. 0.) GO TO 698
 001651
                                                                                                            511
                                                                                                RAILHL
                   ISTAT = 3
 001654
                                                                                                RATLHL
                                                                                                            512
                   IISW = 0
 001655
                                                                                                 RAILHL
                                                                                                            513
              698 ISTATE(I.1) = ISTAT
 001656
                                                                                                 RATLHL
                                                                                                            514
                   STATE (1.2) = TPOS
 001660
                                                                                                 RATLHL
                                                                                                            515
                   STATE (1.3) = TSPD
 001662
                                                                                                            516
                                                                                                 RATLHL
                   ISW(I) = IISW
 001664
                                                                                                 RATLHL
                                                                                                            517
                   KTEMP(I) = IKTEMP
JSTOP(I) = IJSTOP
 001666
                                                                                                 RATLHL
                                                                                                            518
519
 001570
                   DELTAC = DELTAC + CPFC + DELTAT
                                                                                                 RAILHL
                                                                                                            520
521
 001671
                                                                                                 RATLHL
 001674
                                                                                                 RATLHL
```

TTFC(1) = TTFC(1) + DELTAC

001475

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                 RAILHL
               700 TTOP(I) = TTOP(I) + DELTAT 750 CONTINUE
                                                                                                                              522
523
524
                                                                                                                RATLHL
001677
                                                                                                                 RATLHL
001702
                                                                                                                 RATLHL
            ¢
                                                                                                                              525
525
                                                    IS ANOTHER ITERATION REQUIRED FOR THIS DT
                                                                                                                 RATLHL
            Č
                                                                                                                 RATLHL
                                                                                                                 RAILHL
                                                                                                                               527
001704
                     NITER = NITER + 1
                    NITER = NITER - :
1F (NITER.GE.O) GOTO 360

UPDATE /NEWWRK/
                                                                                                                               528
                                                                                                                 RATLHL
001706
                                                                                                                               529
                                                                                                                 RATLHL
               900 DO 920 J= 1.NTPAIN
LTSTAT(J.1) = ISTATE(J.1)
FTSTAT(J.2) = STATE(J.2)
                                                                                                                 RATLHL
                                                                                                                               530
001707
001711
001713
001716
001720
001722
                                                                                                                 RATLHL
                                                                                                                 RATLHL
                                                                                                                               532
                    FTSTAT(J+3) = STATE(J+3)
FTSTAT(J+4) = STATE(J+4)
LKSTOP(J) = JSTOP(J)
                                                                                                                 RAILHL
                                                                                                                               533
                                                                                                                               534
535
                                                                                                                 RATLHL
                                                                                                                 RATLHL
                    FTFC(J) = TTFC(J)
FTOP(J) = TTOP(J)
                                                                                                                 RATLHL
                                                                                                                               536
001724
                                                                                                                               537
538
539
001726
                                                                                                                 RATLHL
                                                                                                                 RATLHL
               920 CONTINUE
                                                                                                                 RAILHL
RAILHL
001732
                    LLSTOP = ISTOP
                                                                                                                               540
541
001733
001734
              999 RETURN
1000 PRINT 1010
1010 FORMAT (ZOHOIMPOSSIBLE PATHS
                                                                                                                 RAILHL
                                                                                                                 RATLHL
                                                                                                                               542
001740
                                                                                                                 RATLHL
                                                                                                                               543
001740
                     CALL EXIT
                                                                                                                 RATLHL
001741 END FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTRUCK
LTRAIN
LTRUCK
IF ILD
LIFILD
LISTRDA
LLTRUK
LNTRAN
LNTRUK
IMOVE
JMETH
XΤ
XDE,
PC
NVEHCL
LVEHCL
LLVHCL
LNVHCL
JMOVE
IMETH
XE
PR
```

M. FUNCTION CUBIC

GOLETA FORTRAN	1.3 • AUTO RFL • (07-12-72)	07/25/72
	FUNCTION CUBIC (A+B+C)	2
С	CUBIC	3
Ç	THIS FUNCTION FINDS THE FIRST REAL ROOT OF A CUBIC CUBIC	<u> </u>
C	EQUATION OF FORM X++3 + AX++2 + BX + C = 0 CUBIC	5
С	USING CARDAN'S SOLUTION CUBIC	6
. C	CUBIC	7
000006	P = 8 - ((A+A) / 3.) CUBIC	8 9
000010	Q = (2. + (A/3)++3) + (A+B/3.) + C CURIC	
000017	T = P/3. CURIC	10
000021	U = Q/2.	11
000023	QL = T+T+T + U+U CURIC	12
000026	T = SORT(OL) CURIC	13
000030	U = →U CUBIC	14
000032	EX = 1./3. CUBIC	15
000033	BAS = U + T CUBIC	16
000034	AL = (ABS(BAS)) ** EX CUBIC	17
000041	IF (BAS .LT. 0.) AL = -AL CUBIC	18
000046	BAS = U - T CUBIC	19
000050	BL = (ABS(BAS)) ** EX CUBIC	20
000054	IF (BAS .LT. 0.) BL = -BL CUBIC	21
000057	CUBIC = AL + BL - (A/3.)	22
000063	RETURN	23
000063	END	24

N. SUBROUTINE ADDTRN(1)

GOLETA	FORTRAN 1.3 * AUTO RFL * (07-12-72)	07/25/72
	SUBROUTINE ADDITH (I)	DOTEN 2
		IDDTRN 3
		IDDTRN 4
	C GENERAL PROCESS - CONVENTIONAL RAIL SYSTEM	IDDTRN 5
		IDDTRN 6
		IDDTRN 7
	Č	IDDTRN 8
	C INSERT COMMON A	IDDTRN 9
000003		HEELS 2
	1. DIMA-OTU-EL-FC-FR-FT-HPA-HPEA-HPEV-HPFA-HPFV-HPV-LOCO-MC-ML	HEELS 3
	2. NCARS.NPOINT.NTD.NTM.NTMAX.XP.NTMILP.NTMLPP.NTRACK.SL	HEELS 4
	3. TCURVX(20).TCURVY(20).TMAINT.TWF.VD.VS.VE.VF.VMAX.WC.WL.XDS W	IHEELS 5
	A MAYERING DAEGOEAGOSTANGARINA ARTICLES AND	IHFELS 6
	2 CAMPAGE CONTENTS OF A STANDARD CONTENTS OF	HEELS 7
	1) BOATE NEATT AND THE TELEVISION OF THE TELEVIS	IHFELS 8
000003	CO while the second of the sec	HEFLS 9
	The state of the s	HEELS 10
	EA OIL WELL MACHINE CONTRACTOR CO	IHFELS II
900003	Charles Alfraction Fit Ichard Nine Islands and an arrangement	HEELS 12
	A Fighter Arter of Ferning and Control of the Contr	HEFLS 13
	St. 1 12 1 4 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	HEELS 14
	34 Città A A Città	HEELS 15
000003	Discussion Contents of the Content o	HEELS 16
000003	FOOTAMEETE CALLETTE CONTACT CO	INEELS 17
	is the second of	HEELS 18
	CA (I I I I I I I I I I I I I I I I I I I	MEELS 19
	TEL VICIALITY TO THE TOTAL TO THE TELEVICION OF	ILL 2
000003	Chamble And A windless to the contract of the	ill 3
	Totale	ILL 4
	24 1 111 1411 1111 1111 1111 1111 1111	ill 5
000003		ill 6
000003		ILL 7
		ILL 8
000003	SA CONTRIBATION OF ALCOHOLISM	ILL 9
000003	I. ECDTIM.GDAY.GADV.GEND.GBEG	ALL 10
000003		ALL 11
000003		ALL 12
200003		N.L 13
000003		ALI. 14
000003	DATA LEND /0/	ADDTRN 12
000003	DIMENSION TOLIFUE (25)	ADDTRN 13
000003	DATA TQUEUE /25.0/	ADDTRN 14
000003	HLFLS = St / ?.	IDDTRN 15
000005	IF (I.LE.LNTRAN) GOTO 100	ADDTRN 16
000007	PRINT SO. T. NTRAN	ADDTRN 17
000017	SO FORMAT (25H REQUEST TO ADD TRAIN . 13.19H 16NORED. NTRAIN 12)	ADDTRN 18
000017	GD TO 900	ADDIEN 19
120000	100 th (Fe40 *FE* 0) 00 10 300	ADDTRN 20
000023	1, (190606(1) - 1) 00013001000	ADDTRN 21
	C The first is a feet of the f	SS NATCOA
000024	JUU CONTINUE	ADDTRN 23 ADDTRN 24
	to their a three or server.	ADDTRN 24 ADDTRN 25
000024	IN CASH SALEGISTS GOID STO	ADDTRN 26
000630	IF (NUMLD-MAXLD) 410+600+600	TOUTAN EU



```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                             ACCTRN
                                                                                                           ADDTRN
                                                                                                                         27
28
000033
              310 CONTINUE
                                                                                                           ADDTAN
                   RMAX= SWITCH(1) + HLFLS
RHIN= SWITCH(1) - HLFLS
                                                                                                                          29
                                                                                                           ADDTRN
                   RMIN= SWITCH(1) = HEFES
DO 400 K=1*NTRAIN
XWRK = TSTAT(K*2)
IF (XWRK *GT*, RMAX) GO TD 400
IF (XWRK *LT*, RMIN) GO TD 400
TRAIN K IS IN SWITCH 1
000035
                                                                                                                          30
31
                                                                                                           ADDTRN
000037
                                                                                                           ADDTAN
000040
                                                                                                           AODTRN
                                                                                                                          32
000042
                                                                                                                          33
34
35
                                                                                                           AODTRN
000045
                                                                                                           ADDTAN
           ¢
                                                                                                           ADDTRN
                    IWRK = ITSTAT(K+1)
000047
                                                                                                                          36
37
38
                                                                                                           ADDTRN
                    IF (IWRK . (IWRK-6) . (IWRK-9) .EQ. 0 ) GO TO 600
000051
                                                                                                           ADDTRN
              400 CONTINUE
000055
                                                                                                           AODTRN
                                                                                                                          39
003060
                                                  IS THERE A TRAIN IN 1ST SEGMENT OF TRACK
                                                                                                           AODTRN
            C
                                                                                                           ADDTRN
                    RMAX = SWITCH(1) - HLFLS
000060
                                                                                                                          41
                                                                                                           ADDTRN
                    DO 500 K=1.NTRAIN
                                                                                                                          42
000062
                                                                                                           ADDTRN
                    IF (TSTAT(K+2) .GT. RMAX) GO TO 500
IWRK = ITSTAT(K+1)
000064
                                                                                                           ADDTAN
000070
                                                                                                                          44
                    IF (IWRK * (IWRK-6) * (IWRK-1) * (IWRK-3) * (IWRK-5) * (IWRK-7)
                                                                                                           ADDTRN
000071
                                                                                                            ADDTRN
                                      .EQ. 0 ) GO TO 600
                                                                                                           ADDTRN
                                                                                                                          46
              500 CONTINUE
000107
                                                                                                                          47
                                                                                                            ADDTRN
                                                  NEW TRAIN MAY PROCEED
            С
                                                                                                                          48
                                                                                                           ADDTRN
                    LTSTAT(I+1) = 2
000112
                                                                                                                          49
50
51
52
53
54
55
56
57
58
                                                                                                           ADDTRN
                    FTSTAT(1.2) = 0.
FTSTAT(1.3) = VD
000114
                                                                                                            ADDTAN
                                                                                                            ADDTRN
                    LKSTOP(1) = 0
IF (10UEUE(1) .NE. 1) GO TO 900
000117
                                                                                                            ADDTRN
000120
                                                                                                            ADDTRN
                    FISTAT(1.3) = 0.
000122
                                                                                                            ADDTRN
                    LEND = LEND -
 000123
                                                                                                            ADDTRN
                    DD 550 J=1.LEND
 000124
                                                                                                            ADDTRN
                    IQUEUE(J) = IQUEUE(J+1)
000126
                                                                                                            ADDTRN
               550 CONTINUE
000130
                                                                                                            ADDTRN
                    IQUEUE (LEND . 1) = 0
                                                                                                            ADDTRN
                                                                                                                          59
 000133
                    GD TD 900
                                                                                                                          60
61
                                                                                                            ADDTRN
                                                  NEW TRAIN CANST PROCEED
                                                                                                            ADDTRN
               600 LTSTAT(I+1) = 10

FUTIME(I) = 0.

IF (LEND .LE.0) GO TO 670

DD 650 J=1.LEN0

IF (IQUEUE(J) .EQ. I) GD TO 900
 000134
                                                                                                                          62
                                                                                                            ADDTRN
 000136
                                                                                                            ADDTRN
                                                                                                                          63
64
65
66
67
68
69
70
 000137
                                                                                                            ADDTRN
 000141
                                                                                                            ADDTRN
 000142
                                                                                                            ADDTRN
               650 CONTINUE
670 LEND = LEND . 1
 000144
                                                                                                            ADDTAN
 000146
                                                                                                            AOOTRN
                    TOUEUF (LEND) = 1
 000150
                                                                                                            ADDTRN
               900 CONTINUE
RETURN
 000152
                                                                                                            ACDTRN
 000152
                                                                                                                           71
                                                                                                            ADOTRN
                    END
 000153
 *FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
 NTRUCK
 LIRAIN
 LTRUCK
 1FILD
 LIFILD
 IF ILLD
 LNTRDA
 LLTRAN
 LLTRUK
```

GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)

ADDTRN

07/25/72

LNTRUK IMOVE JMETH XT XDE PC NVEHCL LVEHCL NTOHCL LNVHCL JMOVE IMETH XE PR

O. SUBROUTINE RAILDS

GOLETA	FORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/72
	SUBROUTINE RAILDS	RAILDS	2
	C	RATLDS	3
	C ELFMENT - MATERIALS HANDLING	RAILDS	4
	C GENERAL PROCESS - CONVENTIONAL RAIL SYSTEM	RAILDS	5
	C ACTIVITY - UNLOAD MUCK AT DISCHARGE POINT	RAILDS	6
	C TECHNIQUE - SEVERAL. DEPENDING ON NTD AND DTU	RAILDS	7
	C INSERT COMMON	RAILDS	8
200000	COMMON /WHEELS/ AF.AF.AMAX.AMAXL.AMINL.BSL.CARCAP.CP.DE.DF.DTAS	WHFELS	2
	1. OTMA.DTU.FL.FC.FR.FT.HPA.HPEA.HPEV.HPFA.HPFV.HPV.LDCD.MC.ML	WHFELS	3
	2. NCARS.NPDINT.NTD.NTM.NTMAX.XP.NTMILP.NTMLPP.NTRACK.SL	WHFELS	4
	3. TCURVX(20).TCURVY(20).TMAINT.TWE.VD.VS.VE.VF.VMAX.WC.WL.XDS	WHFELS	\$
	4. MAXLD.NUMLD.LDUE.QUC.WUC.STATUS(36).WHY(24).MLTYP.WMR.ECONEQ.	WHEELS	6
	S ECONSS-ELOCD-EMUCKG-ETRACK-ESWITC-EUNLDA-ERMAIN-118DRE-	WHEELS	7
	6 ISW(25).NTINIT.TCGV.TMCV	MHEELS	8
200000	CDMMON /OLDCOM/ 1F1LD+KSTOP(2S)+KUNLD+LSTDP+LVEHCL+NBYRY+NSWCH	WHEELS	9
	1. NTRDA.NVEHCL.NUMSWT.SWITCH(20).TFC(25).TOP(25).TSTAT(25.4)	WHEELS	10
	2. UTIME (25) .LDADR.MUKOT.XGS.1FXCA.MGS(5).MCV.MFLAGC.DUMMY(20)	WHEELS	11
200000	COMMON /NEWCOM/ LIFILD+LKSTOP(25)+LKUNLO+LLSTOP+LLVHCL+LNBYBY	WHEELS	12
	1. LNSWCH.LNTRDA.LNVHCL.LNMSWT.FSWTCH(20).FTFC(25).FTDP(25)	WHEELS	13
	2. FTSTAT(25.4)*FUTIME(2S)*LLDADR*LMUKDT*FXGS*LTEXCA*LMGS(\$)	WHEELS	14
	3. LMCV.LMFLAC.FDUMMY(19)	MHEELS	15
000002	DIMENSION COMOLD(260).COMNEW(260).LTSTAT(25.4).ITSTAT(25.4)	WHEELS	16
200000	EQUIVALENCE (NVEHCL.NTRAIN.NTRUCK).(LVEHCL.LTRAIN.LTRUCK)	WHEELS	17
	1. (COMDED.IFIED).(COMNEW.LIFIED.IFIED).(NTOA.LNTROA)	WHEELS	18
	2. (FTSTAT.LTSTAT).(TSTAT.1TSTAT)	WHEELS	19
	3. (LLVHCL.LTRAN.LLTRUK). (LNVHCL.LNTRAN.LNTRUK)	WHEELS	50
000105	COMMON /ALL / XT.STR.IA.RQD.CS.TAMB.FLOW.IFLAG	ALL	2
	1. AT.D.E.SK.T.DT.X.PR.XMAX.TMAX.DX.DV.TPRINT.DTPRNT.IHOVE.JMETH	ALL	3
	2. TSHFT.REPORT.DPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	5
000002	EQUIVALENCE (JMOVF+1MDVE) + (1METH+JMETH)	ALL	6
000002	COMMON/MONEY/ JAMMH-DJM-DJMHH-DJMRD-DJHBMM-DMAINT-DJMRM-DJMGS	ALL	7
	1. PMGS.JMCV.DJMEC.RDPLAN.HPLANT.GSPLAN	ALL	á
	2. ECPLAN.RDT1ME.HTIME(2).GSTIME.ECTIME		9
000002	COMMON/PERFRM/ ROUTIM-ROOTIM-UMHTIM-DMHTIM-GSUTIM-GSOTIM-ECUTIM	ALL ALL	10
	1. ECOTIM.GOAY.GANV.GEND.GREG	ALL	ii
000002	CD440N/LABOR/ RDMEN(10.2).HMEN(10.2.2).GSMEN(10.2).ECMEN(10.2)	ALL	12
000005	REAL JMMHM.LO.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	15
000002	D1MEMS1DN G(A) EGUIVALENCE (G.XT) • (XE.XDE) • (PR.PC)	ALL	14
000002		RAILDS	ii
200000	EQUIVALENCE (LNTRDA.NCOUNT)	RAILDS	iż
200000	DATA INITOS /0/	RAILDS	13
000002	ENTRY TRUKOS 1F (THITOS .FG. 1) GD TD 100	RAILDS	14
000007	IF (INITOS .EQ. I) GD TO 100 C INITIALIZE	RAILDS	is
000011	INITOS = 1	RAILDS	16
	00 S0 I=1•25	RAILOS	17
000012	UTINE(I) = DTU	RAILOS	18
000014	SO CONTINUE	RAILDS	19
000017	100 IF (KUNLO .Eg. 1) GO TO 800	RAILDS	20
000017	C UPDATE TIMES FOR TRAINS UNLOADING	RAILDS	ŽĬ
000021	NCOUNT = 0	RAILDS	55
000021	00 500 I=1.NTRAIN	RAILDS	23
000022	IF (1TSTAT(I.1) .NE. 10) GO TO SOO	RAILDS	24
000025	FUTTVECTS = UTSMECTS = OT	RATLOS	25
000031	NCOUNT = NCDUNT + 1	RAILOS	26

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                   RAILDS
                                                                                                                               07/25/72
                     IF (FUTIME(I) .GT. 0.) GO TO 500 IF (NTRACK .EQ. I) GO TO 300 LTSTAT(I.1) = 2
                                                                                                                   RAILDS
RAILDS
000032
                                                                                                                                   27
28
29
30
31
000040
000041
000042
000044
                                                                                                                    RAILDS
               GO TO 400
300 CALL ADDTRN(I)
IF (LTSTAT(I.) - IO) 400.500.400
TRAIN HAS E
                                                                                                                    RAILDS
                                                                                                                    RAILDS
                                                                                                                    RAILDS
                                                                                                                                   32
                                                                                                                                   33
34
35
                                                    TRAIN HAS BEEN ADDED
                                                                                                                    RAILDS
000047
               400 NCOUNT = NCOUNT - I
                                                                                                                   RAILDS
                     FUTINE(I) = DTU
000051
                                                                                                                    RAILDS
               500 CONTINUE

IF (NCOUNT - NTD) 600.620.640

600 LIFILD = 0
                                                                                                                                   36
37
000053
                                                                                                                    RAILDS
000056
                                                                                                                    RAILDS
000060
                                                                                                                    RAILDS
                                                                                                                                   38
               GO TO 800
620 LIFILD = 1
                                                                                                                                   39
40
41
                                                                                                                    RAILDS
000061
000062
                                                                                                                    RAILDS
               GO TO 800
640 PRINT 645 , NCOUNT
645 FORMAT (45HOTOO MANY TRAINS IN DISCHARGE AREA. NCOUNT = .IS)
000063
                                                                                                                   RAILDS
                                                                                                                                   42
43
44
45
000064
000072
                                                                                                                   RATLDS
RAILDS
                     CALL FXIT
                                                                                                                   RAILDS
000072
000073
                800 RETURN
                                                                                                                   RAILDS
                                                                                                                   RAILDS
                                                                                                                                   46
000074
                    END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTRUCK
LTRAIN
LTRUCK
IFILD
IFILLD
LNTRDA
LLTRAN
LLTRUK
LNTRAN
LNTRUK
IMOVE
JHETH
XT
KDE
PC
NVEHCL
LVEHCL
NTDA
LLVHCL
LNVHCL
JHOVE
INETH
```

P. SUBROUTINE RAILEX

GOLETA F	FORTRAN 1.3 * AUTO RFL * 107-12-72)		07/25/72
	SUBROUTINE RAILEX	RAILEX	2
	c	RATLEX	3
	C ELEMENT - MATERIALS HANOLING	RATLEX	4
	C GENERAL PROCESS - CONVENTIONAL RAIL SYSTEM	RATLEX	5
	C ACTIVITY - SYSTEM EXTENSION	RATLEX	6
	C TECHNIQUE - SINGLE TRACK PLACED AHEAD OF CALIF. SWITCH	RATLEX	7
	C	RATLEX	8
	C INSERT COMMON	RATLEX	9
200000	COMMON /WHEELS/ AF.AF.AMAX.AMAXL.AMINL.BSL.CAPCAP.CP.DF.DTAS	WHFELS	2
	1. OTMA.DTU.FL.FC.FR.FT.HPA.HPFA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHFELS	3
	2. NCARS.NPOINT.NTD.NTH.NTHAX.XP.NTHILP.NTHLPP.NTRACK.SL	WHEELS	4
	3. TCURVX (20) .TCURVY (20) .THAINT.TWE .VI) .VS.VE .VF.VMAX.WC.WL.XDS	WHEELS	5
	4. MAXLD.NUMLD.LQUE.QUC.WIJC.STATUS (36).WHY (24).MLTYP.WMR.ECONEG.	WHEELS	6
	S ECONSS.ELOCO.FMUCKC.ETRACK.ESWITC.EUNLOA.EPMAIN.IIBORE.	WHEELS	7
	1 1 1 This is a second and a second and a second and a second and a second and a second and a second and a	WHEELS	8
	6 ISW(25)*NTIMIT*TCCV*TMCV COMMON /OLDCOM/ IFILO*KSTOP(25)*KUNLO*LSTOP*LVEHCL*NBYBY*NSWCH	WHEELS	ğ
20000	I. NTPDA.NVEHCL.NUMSWT.SWITCH(20).TFC(25).TOP(25).TSTAT(25.4)	WHEELS	10
		WHEELS	ii
		WHEELS	iż
200000	COMMON /MEMCOM/ LIFILO.LKSTOP(25).LKUNLO.LLSTOP.LLVHCL.LNRYBY	WHEELS	13
	1. LNSWCH-LNTRDA-LNVHCL-LNMSWT-FSWTCH(20)-FTFC(25)-FTOP(25)		14
	2. FTSTAT(25.4).FIJTIMF(25).LLOADR.LMUKOT.FXGS.LTEXCA.LMGS(5)	WHEELS	-
	3. LHCV.LMFLAC.FOIJMMY()9)	WHEELS	15
200002	DIMENSION COMOLD (260) + COMNEW (260) + LTSTAT (25+4) + ITSTAT (25+4)	WHEELS	16
000002	EOUTVALENCE (NVEHCL+NTRAIN+NTRUCK) + (LVEHCL+LTRAIN+LTRUCK)	WHEELS	17
	1. (COMOLO.IFILD). (COMNEW.LIFILD.IFILLD). (NTDA.LNTRDA)	WHEELS	18
	2. (FISTAT.LISTAT) . (TSTAT.ITSTAT)	WHEFLS	19
	3. (LLVHCLLI,TPAN.LLTRUK).(LNVHCL.LNTRAN.LNTRUK)	WHEELS	20
000002	COMMON /ALL / XT+STR+IA+RQD+CS+TAMB+FLOW+IFLAG	ALL	2
	1. AT.D.F.SK.T.DT.X.PR.XMAX.TMAX.DX.DV.TPRINT.DTPRNT.IMDVE.JMETH	ALL	3
	2. TSHFT.REPORT.OPPCT.TO.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	4
200000	EQUIVALENCE (JMOVE.IMOVE).(IMETH.JMETH)	ALL	5
200000	COMMON/MDNEY/ JMMHM+OJM+OJMH+OJMRD+DJMBMM+DMAINT+DJMBM+DJMGS	ALL	6
	I. PHGS.JMCV.OJMEC.RDPLAN.HPLANT.GSPLAN	ALL	7
	2. ECPLAN.ROTIME.HTIME (2).GSTIME.ECTIME	ALL	8
200000	COMMON/PERFRM/ ROUTIM+ROOTIM+UMHTIM+DMHTIM+GSUTIM+ECUTIM	ALL	9
	I. ECDTIM.GDAY.GADV.GFND.GREG	ALL	10
200000	COMMON/LAROR/ RDMFN()0+2)+HMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
20000	REAL JMMHM+LD+LDB+LBIT+LBURN+LSTEEL+JMCV	ALL	12
000002	DIMENSION G(A)	ALL	13
000002	EDITIVALENCE (G.XT) + (XE+XDE) + (PR+PC)	ALL	14
200002	COMMON /CONVEY/ ACM.DTRS.DWM.FE.FL.MP.QC.SMIN.WRI	BELTS	2
	1. WP.XLF.NSURGE.GE.QP.SM.DTCB.DTMR.AB.VRI.NEXDN.NGEO.XE.LNSURG.	UPDA7	1
	2 STIME OOMP OTHI OTHO	UPDA7	2
200000	DATA ALA /0./	RAILEX	13
000002	DATA DIE /0./	RAILEX	14
200002	DATA DTS /0./	RATLEX	15
200002	DATA NEEDIN /0/	RAILEX	16
000002	DATA S /0./	RAILEX	17
200002	DATA INITEX /0/	RATLEX	18
30002	C INITIALIZE	RAILEX	19
000002	ENTRY TRUKEX	RAILEX	20
		RAILEX	21
000007	100 INITEX = I		55
000010	IF (XDE * XDS * BSL .GT.O.) GDTO 200	RAILEX	
	C OPTION 2 (TEMPORARY VALUES)	RATLEX	23
000014	XDE = 5.	RATLEX	24

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                         RAILEX
                                                                                                                07/25/72
                   XDS = 3.
BSL = 5280.
000015
                                                                                                      RAILEX
000016
                                                                                                      RAILEX
                                                                                                                    26
                                              BOTH OPTIONS HERE
                                                                                                      RATLEX
                                                                                                                    27
000017
              200 IF (NTRACK .FQ. 2) BSL = 0
                                                                                                      RATLEX
000022
                   IF (AMINL .EQ. AMAXL) ALA=AMINL
                                                                                                      RAILEX
                                                                                                                    29
000025
                   NDUMMY = 0
                                                                                                      RATLEX
000026
                   NRYBY = 0
                                                                                                      RATLEX
                                                                                                                    31
000027
                   PRINT 205+ XDE+XDS+RSL
                                                                                                      RATIFX
                                                                                                                    35
              205 FORMAT (30H0PAIL FXTENSION - EXT. RATE = F8.2.
U 20H SWIICH MOVE RATE = F8.2.
2 29H DISTANCE RETWEEN SWITCHES = F8.21
000040
                                                                                                      RAILEX
                                                                                                                   33
                                                                                                      RATLEX
                                                                                                                    34
                                                                                                      RAILFX
                                                                                                                    35
                                              WAS CALL FOR INITIALIZATION ONLY
                                                                                                      RAILEX
                                                                                                                   36
000040
                   IF (NFFDIN) 900.900.210
                                                                                                      RAILEX
                                                                                                                   37
38
              210 NFEOIN = 0
                                                                                                      RAILEX
000043
                  GQ TO 270
                                                                                                      RAILEX
                                                                                                                   39
           C
                                               NORMAL ENTRY AFTER FIRST CALL
                                                                                                      RAILEX
                                                                                                                   40
000044
                  ENTRY RATLET
                                                                                                      RAILEX
                  ENTRY TRUKAT
000051
                                                                                                                   42
                                                                                                      RAILEX
           ٠
                                               HAS INITIALIZATION BEEN DONE
                                                                                                      RAILEX
                                                                                                                   43
000056
                   IF (INITEX) 250.250.270
                                                                                                                   44
                                                                                                      RAILFX
000060
              250 NEEDIN = 1
                                                                                                      RAILEX
                                                                                                                   45
             GO TO 100
270 IF (NEXON .EQ. I) GO TO 950
000061
                                                                                                                   46
                                                                                                      RATLEX
000062
                                                                                                      RAILEX
000064
                   NSWTCH = NSWCH
                                                                                                      RAILEX
                                                                                                                   48
             IF (NSWICH) 300-300-530
300 IF (NGEO .EQ. I) GO TO 350
000066
                                                                                                                   49
50
                                                                                                      RAILEX
000067
                                                                                                      RATLEX
                                             CYCLIC OPERATIONS GEOMETRY
                                                                                                      RAILEX
                                                                                                                   51
                   IF (DIE .EQ. O.) OTE = OX / XDE
000071
                                                                                                                   52
                                                                                                      RATLEX
             DTE = DTE - DT
ALA = ALA + DX
IF (DTE) 310,310,320
310 LNRYRY = 0
000074
                                                                                                      RAILEX
                                                                                                                   53
000076
                                                                                                      RAILEX
066100
                                                                                                      RAILEX
900101
                                                                                                     RAILEX
                  DTE = 0
201000
                                                                                                     RAILEX
                                                                                                                   57
             GO TO 330
320 LNBYRY = 1
000103
                                                                                                     RAILEX
000103
                                                                                                      RAILEX
000104
             330 GO TO 450
                                                                                                      RAILEX
           C
                                               CONTINUOUS OPERATION
                                                                                                     RATLEX
                                                                                                                   61
             350 ALA = ALA + (XDE * 01)
S = S + 0X - (XDF * 01)
000105
                                                                                                      RATLEX
000110
                                                                                                     RAILEX
                                                                                                                   63
                  IF (5 .GT. 0) GO TO 400
000113
                                                                                                     RAILEX
                                             EXTENSION HAS CAUGHT EXCAVATOR
                                                                                                     RAILEX
                                                                                                                   65
000115
                  XWRK = XOF . DT
                                                                                                     RAILEX
                  ALA = ALA + XWRK + 0%

S = S - 0% + XWRK
000116
                                                                                                     RATLEX
                                                                                                                   67
121000
                                                                                                     RATIFY
                                                                                                                   68
000123
                  GO TO 450
                                                                                                     RAILEX
                                                                                                                   69
000124
             400 LNRYBY = 0
                                                                                                                   70
71
                                                                                                     RATLEX
                  IF (S .GE. SM) LNBYRY = I
000125
                                                                                                     RATIFX
             420 CONTINUE
000131
                                                                                                                   72
                                                                                                     RAILFX
             450 IF (NSWTCH .GT. 0) GO TO 530 IF (ALA .LT. AMAXL) GO TO 750
000131
                                                                                                                   73
74
                                                                                                     RAILEX
000134
                                                                                                     RAILEX
                   IS SWITCH TO BE ADDED
           C
                                                                                                                   75
                                                                                                     RAILEX
                  IF (851.60. 0) 60 TO 510
IF (NUMSWT .FQ. I) 60 TO 470
XWRK = SWITCH(NUMSWT) - SWITCH(NUMSWT - 1)
000136
                                                                                                     RAILEX
000137
                                                                                                     RAILEX
000141
                                                                                                     RAILEX
                                                                                                                   78
```

RAILEX

IF (XWRK-BSL-SL1 510.490.490

000144

```
07/25/72
GOLETA FORTPAN 1.3 * AUTO RFL * (07-12-72)
                                                                   RAILEX
                                                                                                         80
                                                                                             RAILEX
            470 IF (SWITCH(NUMSWT) -BSL-SL-XDISCH) 510+490+490
000147
                                                                                             PAILEX
000155
            490 NSWTCH = 1
                                                                                                          82
                                                                                             RATLEX
            GO TO 530
510 NSWTCH = 2
000156
                                                                                                          83
                                                                                             PATIFY
000157
                                                                                             RAILEX
            530 CONTINUE
000160
                                                                                                          85
                                                                                             RAILEX
            550 IF (NSWTCH .EQ. 1) 60 TO 650
000160
                                                                                             RATLEX
                                          PUSH SWITCH FORWARD
          C
                                                                                             RATLEX
                                                                                                          87
                 IF (DTS .NE. 0.) GO TO 600
000162
                                                                                             RAILEX
                                                                                                          88
                 DTS = (AMAXL - AMINL) / XDS
000163
                                                                                             RAILEX
                                                                                                          89
                 LNAYRY = 0
000166
                                                                                                          90
                                                                                             RAILEX
000167
            600 DTS = DTS - DT
                                                                                             RAILEX
                                                                                                          91
                 IF (DTS .GT. 0.) GO TO 750
000171
                                                                                             RAILEX
                                                                                                          92
                 DTS = 0.
NSWTCH = 0
000173
                                                                                                          93
                                                                                             RATIFX
000173
                                                                                                          94
                                                                                             RAILEX
                 LNRYBY = 0
000174
                                                                                                          95
                                                                                             RAILEX
                 ALA = AMINL
IF(AMAXL .NE. AMINL) GO TO 620
FSWTCH(NUMSWT) = SWITCH(NUMSWT)+DX
000175
000176
                                                                                             RAILEX
000200
                                                                                             RAILEX
                 DO 605 K=1.NTRAIN
000203
                 IF ((KSTOP(K) .GE. 100) .OR. (KSTOP(K) .EQ. 1)) FTSTAT(K.2) =TSTAT(K RAILEX
                                                                                                          99
000204
                                                                                             RAILEX
                                                                                                         100
                1.21.nx
                                                                                             RAILEX
                                                                                                         101
            605 CONTINUE
155000
                                                                                             RATLEX
            GO TO 750
620 FSWTCH(NUMSWT)=SWITCH(NUMSWT)+AMAXL-AMINL
000224
                                                                                                         103
                                                                                             RAILEX
                                                                                                         104
165000
                 DO 610 K=1+NTRAIN
                 IF ( (KSTOP (K) .GE. 100) .OR. (KSTOP (K) .EQ. 1)) FISTAT (K:2) TSTAT (K RAILEX
                                                                                                         105
000232
                                                                                             RAILEX
                                                                                                         106
                1.2) +AMAXL -AMINL
                                                                                             RATLEX
                                                                                                         107
000250
            610 CONTINUE
                                                                                                         108
                                                                                             RATLEX
000253
                 GO TO 750
                                                                                                         109
                                                                                             RATLEX
                                           ADD NEW SWITCH
            650 1F( DTS) 700.672.700
672 DTS=DTAS
                                                                                             RAILEX
                                                                                                         110
000253
                                                                                             RAILEX
                                                                                                         iii
000254
                                                                                             RAILEX
                                                                                                         112
000256
                 NSWTCH=1
                                                                                             RATLEX
                                                                                                         113
000257
                 LNRYBY = 0
                                                                                             RAILEX
000260
            700 DTS = DTS - DT
                                                                                             RA1.EX
                                                                                                         115
                 IF (DTS) 710.710.750
000262
                                                                                             RAILEX
                                                                                                         116
                                           NEW SWITCH HAS BEEN ADDED
          C
                                                                                                         117
                                                                                             RAILEX
            710 DTS = 0.
000263
                                                                                                         118
                                                                                             RAILEX
                 NSWTCH = 0
000264
                                                                                                         119
                                                                                             RAILEX
                 LNRYRY = 0
000265
                                                                                                         120
                                                                                              RAILEX
                 LNMSWT = NUMSWT . I
000266
                                                                                             RAILEX
                                                                                                         121
                 FSWTCH(LNMSWT) = SWITCH(NUMSWT)
000270
                                                                                              RATLEX
                 FSWTCH(NUMSWT)=SWITCH(NUMSWT)=SL
000272
                                                                                             RAILEX
                                           MUST NEW TRAIN BE ADDED
          C
                                                                                             RAILEX
                                                                                                         124
            750 XWRK=(X-XDISCH)/5280.
000275
                                                                                                         125
                                                                                             RAILEX
                 YWRK = 0.
IF (XWPK .LE. XP) GO TO 770
000300
                                                                                             RAILEX
                                                                                                         126
000301
                                                                                             RAILEX
                                                                                                         127
                 x1 = xP/5280.
000303
                                                                                             RAILEX
                                                                                                         128
                 YWRK = XWRK - XI
000305
                                                                                              RAILEX
                                                                                                         129
                 XWRK = X1
                                                                                              RAILEX
                                                                                                         130
             770 NTFIT=NTINIT+NTMILP+XWPK+NTMLPP+YWRK
000307
                                                                                                         131
132
133
                                                                                              RAILEX
                 IF (NTFIT .GT. NTMAX) NTFIT = NTMAX IF (NTFIT - NTRAIN) 900.900.820
000317
                                                                                             RAILEX
255 000
                                           NEW TRAIN HUST BE ADDED
                                                                                             RAILEX
                                                                                                         134
            820 IF (1FILLD .EQ. 1) GD TO 900
                                                                                             RATIFX
000325
```

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                  RATLEX
                                                                                                                                                     07/25/72
000327
000331
000332
000333
000335
                          LNTRAN = NTRAIN . 1
                                                                                                                                       RATLEX
RATLEX
RAILEX
                                                                                                                                                        135
136
                          L = LNTRAN
FTSTAT(L+4) = 0.
                  FISTATIL.4) = 0.

CALL ADDTRN(L)

IF (LTSTAT(L.1) - 10) 900.870.900

870 NTDA = NTDA - 1

IF (NTDA .GE. NTD) IFILLD = 1

900 LNSWCH = NSWTCH

950 RETURN
                                                                                                                                                        137
                                                                                                                                       RATLEX
RAILEX
                                                                                                                                                        138
139
140
141
142
143
 000340
                                                                                                                                       RATLEX
RATLEX
RATLEX
 000342
 000347
                                                                                                                                       RATLEX
 000350
                         END
                                                                                                                                       RAILEX
 *FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
 NTRUCK
 LTRAIN
 LTRUCK
 TEILD
LIFILD
LNTRDA
LLTRAN
LLTRUK
LNTRUK
IMOVE
JHETH
X T
PC
NVEHCL
LLVHCL
LNVHCL
JHOVE
IHETH
XE
PR
```

Q. SUBROUTINE RAILMT

OLETA	FORTRAN 1.3 . AUTO RFL . (07-12-72)		07/25/7
		RATLMT	2
	SUBROUTINE RAILMT	RATLMT	3
	C	RATLMT	4
	C ELFMENT - MATERIALS HANDLING	RATLMT	5
	C GENERAL PROCESS - CONVENTIONAL RAIL SYSTEM		
	C ACTIVITY - GENERAL MAINTENANCE AND REPAIR OF LOCOMOTIVES . CAR	RAILMI	6
	c	RATLMT	7
	C INSERT COMMON	RATLMT	8
2000	COMMON /WHEFLS/ AF+AF+AMAX+AMAXL+AMINL+BSL+CARCAP+CP+DE+DF+DTAS	WHEELS	2
	T. DIMA.DIU.FL.FC.FR.FT.HPA.HPFA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHEELS	3
	2. NCARS.NPOINT.NTO.NTM.NTMAX.XP.NTMILP.NTMLPP.NTRACK.SL	WHEELS	4
	3. TCURVX(20).TCURVY(20).TMAINT.TWF.VN.VS.VE.VF.VMAX.WC.WL.XDS	WHEELS	5
	4. MAXLD.NUMLD.LQUE.OUC.WUC.STATUS (36) .WHY (24) .MLTYP.WMR.ECONEQ.	WHFELS	6
	5 ECONSS.FLOCD.EMUCKC.ETPACK.FSWITC.EUNLOA.ERMAIN.IIBORE.	WHFELS	7
	6 ISW(25) NTINIT TCCV THCV	WHFELS	8
	COMMON /OLDCCM/ IFILD+KSTOP(25)+KUNLO+LSTOP+LVFHCL+NBYRY+NSWCH	WHEELS	9
2000		WHEELS	10
		WHFELS	11
	COMMON NEWCOMY LIFTLO.LKSTOP(25).LKUNLO.LLSTOP.LLVHCL.LNBYBY	WHEELS	12
20002	COMMON TREACTION OF THE CONTRACT FOR THE CONTRACT OF THE CONTR	WHEELS	13
	I. LNSWCH.LNTRDA.LNVHCL.LNMSWT.FSWTCH(20).FTFC(25).FTOP(25)	WHEELS	14
	2. FISTAT (25.4) .FIJTIME (25) .LLOADR .LMUKOT .FXGS .LTEXCA .LMGS (5)	WHEELS	15
	3. LMCV.LMFLAC.FDUMMY(19)	WHEELS	16
2000	OIMENSION COMOLD (260) . COMNEW (260) . LISTAT (25.4) . ITSTAT (25.4)		
2000	EQUIVALENCE (NYFHCL ONTRAIN ONTRUCK) OLVEHCL OLTRAIN OLTRUCK)	WHFELS	17
	1. (COGOLD.IFILD).(COMNEW.LIFILO.IFILLO).(NTOA.LNTROA)	WHEELS	18
	2. (FISTAT-LYSTAT) - (TSTAT-LISTAT)	WHEELS	19
	3. (LLVHCL+LLTRAN+LLTRUK) - (LNVHCL+LNTRAN+LNTRUK)	WHEELS	20
20000	COMMON /ALL / XT+STR+TA+RQO+CS+TAMB+FLOW+TFLAG	ALL	2
	I. AT.O.E.SK.T.DT.X.PR.XMAX.THAX.DX.DV.TPRINT.DTPRNT.1MOVE.JMETH	ALL	3
	2. TSHFT.REPORT.OPPCT.TO.XO.XOISCH.ICHNG.XCHNG.TCHNG	ALL	4
20000	EQUIVALENCE (UMOVE+IMOVE)+(IMETH+UMETH)	ALL	5
20000	SOMMOOFITA O-MMAPHO-DARCO-DARCO-HMOO-HMOO-MHANL VAJMOW/NUMROD	ALL	6
	T+ PMGS+JMCV+DJMEC+RDPLAN+HPLANT+GSPLAN	ALL	7
	2. ECPLAN.POTIME.HTIME(2).GSTIME.ECTIME	ALL	8
20000	COMMON/PERFRM/ ROUTIM-ROOTIM-UMHTIM-OMHTIM-GSUTIM-GSOTIM-ECUTIM	ALL	9
	T. ECDTIM.GDAY.GANV.GENO.GBEG	ALL	10
2000	COMMODILLARDR / ROMEN(10+2)+MMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
00002	REAL JMMHH.LD.LOB.LBIT.LBURN.LSTEEL.JMCV	ALL	12
00002	DIMENSION G(A)	ALL	13
00002	EQUIVALENCE (G+XT)+(XE+XDE)+(PR+PC)	ALL	14
	EQUIVALENCE (DTH.OTHA)	RAILHT	11
20000	DATA NTMA /O/	RATLMT	1.5
20000		RATLMT	13
20000	DATA MTINIT /0/	RATLMT	14
20000	OLYENSION RTIME(25)	RATLAT	is
00002	ENTRY TRUKHT	RAILMT	16
00007	IF (MTINIT) 100+100+200	RAILMT	17
	C FIRST CALL TO SUBROUTINE		
11000	100 IF (THAINT + JMMHM + OTH ,GT. 0.) GO TO 150	RAILMT	18
	C HERE FOR OPTION 2 (VALUES TEMPORARY)	RAILMI	19
00015	TMAINT = 1.5	RAILMT	20
00016	JMHM = 100.	RAILMT	15
00017	OTM = 20.	RAILMT	22
00020	150 CONTINUE	RAILMT	53
00020	MTINIT = I	RAILMT	24
	00 170 1=1+25	RAILMT	25
150001			26

```
GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)
                                                                         RAILMT
                                                                                                               07/25/72
000025
              170 CONTINUE
                                                                                                                   27
28
 000026
                   NTYA = 0
                                                                                                     RAILMT
000027
                  PRINT 180. THAINT. JMMHM. DTM
                                                                                                     RATIMT
                                                                                                                   29
              180 FORMAT (43HOPAIL MAINT. PARAMETERS - TIME TO REPAIR # .F8.2.
000041
                                                                                                     RAILMT
                                                                                                                   30
                          21H COST OF MATERIALS # +F8.2.23H DAYS BETWEEN MAINT. # .
                                                                                                     RAILMT
                                                                                                                   31
                                                                                                     RAILMT
                                                                                                                   32
                                              IS IT TIME FOR MAINTENANCE
                                                                                                     RAILMT
000041
             200 NCDUNT = 0
                                                                                                     RATIMT
                                                                                                                   34
000042
                  DD 400 I=1.NTRAIN
                                                                                                     RAILMT
                                                                                                                   35
                  IWRK = ITSTAT(1:1)
IF (IWPK .FQ. II) GO TD 300
IF (IWRK .NE. IO) GO TO 400
000044
                                                                                                     RAILMT
                                                                                                                   36
000046
                                                                                                     RAILMT
                                                                                                                   37
000050
                                                                                                     RATLMT
                                                                                                                   38
           ¢
                                              TRAIN IS IN DISCHARGE AREA
                                                                                                     RATIME
                                                                                                                   39
                  IF (TSTAT(1+4) .LT. DTM) GO TO 400
IF (NTMA .GE. NTM) GD TO 400
000052
                                                                                                     RAILMT
                                                                                                                   40
000055
                                                                                                     RAILMT
                                                                                                                   41
           C
                                              TRAIN I NEEDS MAINTENANCE
                                                                                                     RAILMT
                                                                                                                   42
000060
                  LTSTAT(I+1) = II
                                                                                                     RAILMT
                  NTMA = NTMA + I
NTDA = NTDA - I
000061
                                                                                                     RAILMT
                                                                                                                   44
000062
                                                                                                                   45
                                                                                                     RAILMT
             IF (NTDA .LT. NTD) LIFILD = 0

300 RTIME(I) = RTIME(I) + DT

NCOUNT = NCOUNT + 1

IF (RTIME(I).GT. 0.) GD TO 400
000063
                                                                                                     RAILMT
                                                                                                                   46
000066
                                                                                                                   47
                                                                                                     RAILHT
000071
000072
                                                                                                     RAILHT
                                                                                                                  49
                                              MAINTENANCE FINISHED
           C
                                                                                                     RAILMT
000075
                  IF (LIFILD .FO. 1) GO TO 400
                                                                                                                  51
52
                                                                                                     RAILMT
000076
                  LTSTAT(I+1) = 10
                                                                                                     RATIMT
000077
                  FTSTAT (1.4) = 0.
                                                                                                     RAILMT
                                                                                                                  53
00100
                  MHMML + HMMLD = HMMLD
                                                                                                     RAILMT
                                                                                                                  54
201000
                  RTIME(I) = TMAINT
                                                                                                                  55
                                                                                                     RAILMT
000104
                  NTMA = NTMA - 1
                                                                                                     RAILMT
                                                                                                                  56
000105
                  NTDA = NTDA + 1
                                                                                                    RAILMT
                                                                                                                  57
58
                  IF (NTDA .GE. NTD) LIFILO = I
NCOUNT = NCOUNT - I
000106
000111
                                                                                                     RATIMT
                                                                                                                  59
000113
             400 CONTINUE
                                                                                                     RATIMT
                                                                                                                  60
                  NTMA = NCOUNT
1F (NTMA .GT. NTM) GO TO 500
                                                                                                     RAILMT
000117
                                                                                                     RAILHT
                                                                                                                  62
551000
                  RETURN
                                                                                                     RAILMT
                                                                                                                  63
             500 PRINT 550. NTMA.NTM
550 FORMAT (11.4.40H TRAINS IN MAINTENANCE AREA. CAPACITY = .14)
251000
                                                                                                     RAILHT
                                                                                                                  64
000132
                                                                                                     RAILMT
                                                                                                                  65
000132
                  CALL EXTT
                                                                                                     RAILMT
                                                                                                                  66
67
000133
                  END
                                                                                                     RAILMY
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTRUCK
LTRAIN
LTPUCK
1FILD
IFILLD
LNTPDA
LLTRAN
LLTRUK
LNTRAN
LNTRUK
IMOVE
JMETH
```

XT

GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)

RATLHT

07/25/72

XDE PC DTMA NVEHCL LVEHCL LLVHCL LNVHCL JNOVE IMETH XE PR

R. SUBROUTINE GRNSUP

GOLETA	FORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/72
	SUBPOUTINE GRASUP	GRNSU*	2
	c	GRNSUP	3
	C ELFMENT-PPTMARY GROUND SUPPORT	GRNSUP	4
	GENERAL PROCESS-POCKBOLTS+STFEL RIB SETS+SHOTCRETE+COMBINATION	GRNSUP	5
	CS OF THOSE	GRNSUP	6
	C ACTIVITY-INSTALLATION	GRNSUP	7
	c	GRNSUP	8
200900	COMMON /GPND/ PSST(60+9)+MAXPSST+ UCS+UCSC+RATERR+RATESC+RATESS	SUPPORT	2
	1. GSLOS.TAS.TST.FRADRI.ESCPLA.GDOW.GSETDO.MAXPSS	SUPPORT	3
200000	COMMON /WHEELS/ AF.AF.AMAX.AMAXL.AMINL.RSL.CAPCAP.CP.DE.DF.DTAS	WHEELS	5
	1. OTMA.DTU.FL.FC.FR.FT.HPA.HPEA.HPEV.HPFA.HPFV.HPV.LOCO.MC.ML	WHEELS	3
	2. NCARS.NPOINT.NTO.NITM.NTMAX.XP.NTMILP.NTMLPP.NIRACK.SL	WHEELS	4
	3. TCHRVX(20).TCURVY(20).TMAINT.TWE.VO.VS.VE.VF.VMAX.WC.WL.XDS	WHEELS	5
	4. MAYED.NUMED.EQUE.QUE.QUE.STATUS(36).WHY(24).METYP.WMR.ECONEQ.	WHEELS	6
	5 ECONSSIFLACO:FMUCKC:FTPACK:ESWITC:FUNLOA:FRMAIN:11BORF:	WHEFLS	7
	6 15W(25) .NITHIT . TCCV . TMCV	WHEELS	8
000002	COMMON JOLOCOMY IFILO.KSTOP (25).KUNLO.LSTOP.LVEHCL.NBYRY.NSWCH	WHEELS	9
	1. NTPDA.4VEHCL.4NUHSWT.SW1TCH(20).TFC(25).TOP(25).TSTAT(25.4)	WHEFLS	10
_	2. UTTHE (25) .LOADP .MUKOT .XGS . 1EXCA .MGS (5) .MCV .MFLAGC .OUMMY (20)	WHEELS	11
200000	COMMON NIEWCOMY LIFTLO + LKSTOP (25) + LKUNLO + LLSTOP + LLVHCL + LNBYBY	WHEELS	12
	I. LNSWCH.LNTRDA.LNYHCL.LNMSWT.FSWTCH(20).FTFC(2S).FTOP(25)	WHEFLS	13
	2. FTSTAT(2S,4).FUTIME(2S).LLOADR.LMUKOT.FXGS.LIFXCA.LMGS(5)	WHEELS	14
	3. LMCV+LMFLAC+FOUMMY(19)	WHEELS	15
000002	OTMENSTON COMPLD (260) + COMNEW (260) + LTSTAT (25+4) + LTSTAT (25+4)	WHEELS	16
000002	EQUIVALENCE (NVEHCL+NTRATN+NTRUCK)+(LVEHCL+LTRAIN+LTRUCK)	WHEELS	17
	1. (COMOLD.1FILD). (COMNEW.LIFILD.1FILLD). (NTDA.LNTRDA)	WHEELS	18
	2. (FTSTAT.LTSTAT).(TSTAT.1TSTAT)	WHEFLS	19
	3. (LLVHCL+LLTRAN+LLTRUK) . (LNVHCL+LNTRAN+LNTRUK)	WHEELS	20
000005	OATA PSST / 95909075757550505025252500	GRNSUP	11
	1 045.0	GRNSUP	12 13
	2 2*5.,7.,5.,1.,2.,5.,1.,7.,5.,1.,2.,5.,1.,2.,45*0.,	GRNSUP	14
	3 999999999999108856645552245.0	GRNSUP	15
	4 4*5 - 4 - 15*0 - 14 - 12*0 - 14 - 14 - 14 - 14	GRNSUP	16
	6 1133377435.445.0	GRNSUP	17
	7 5 0 5 0 4 0 3 3 . 2 45 . 0	GRNSUP	18
	8 00	GRNSUP	19
	9 0	GRNSUP	20
	A 1.+1.+1.+1.+1.+1.+1.+1.+2.+2.+1.+1.+1.+1.+45*0./	GRNSUP	21
000002	OATA MAXPS/15/	ALL	5 1
000002	COMMON /ALL / XT+STP+TA+RQD+CS+TAMR+FLOW+1FLAG 1. AT+O+F+SK+T+DT+X+PR+XMAX+TMAX+OX+DV+TPR1NT+DTPRNT+IMOVE+JMETH	ALL	3
		ALL	4
00000	2. TSHFT-REPORT-OPECT-TO-XD-XDTSCH-TCHNG-XCHNG-TCHNG EQUIVALENCE (JMOVE-1MOVE)-(IMETH-JMETH)	ALL	5
000002	CDMMJANNGTEACE TOMONTALANA DOM * DOMMH * DOMB ON DOMB ON BOMB * DOMB ON BOMB O	ALL	6
000002	1. PMGS.JMCV.DJMEC.RDPLAN.HPLANT.GSPLAN	ALL	7
	2. ECPLAN-ROTTME-HTIME (2) - GSTIME - ECTIME	ALL	ė
200002	COMMON/PERFRM/ ROUTIM.ROOTIM.UMHTIM.OMHTIM.GSUTIM.GSOTIM.ECUTIM	ALL	9
000002	1. ECDTIM.GDAY.GANV.GEND.GREG	ALL	10
000002	COMMON/LARGR/ RDMFN(10.2).HMFN(10.2.2).GSMEN(10.2).ECMEN(10.2)	ALL	ii
000002	REAL JMMHM.LD.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	iż
000002	DIMENSION G(R)	ALL	13
000002	EQUIVALENCE (G.XT) • (XE • XDF) • (PR • PC)	ALL	14
000002	OTMENSION SSCOEF (9.3) . WEIGSS1(11) . WEIGSS2(11)	GRNSUP	23
	C	GRNSUP	24
	C PRE SETTING TARLES FOR STEEL RIB INSTALLATION	GRNSUP	25



000104

PMGLDS=0.

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                  GRNSUP
                                                                                             GRNSUP
                 LAR=0
000065
                                                                                                         82
                                                                                             GRNSUP
000066
                 WR18=0.
                                                                                             GRNSUP
                                                                                                         83
000067
                 Irst=0.
                                                                                             GRNSUP
                 HRR=0.
000070
                                                                                             GRNSUP
                                                                                                         85
                 SPF= 0
000071
                                                                                             GRNSUP
                                                                                                         86
                 SP=0
000072
                                                                                                         87
                                                                                             GRNSUP
000073
                 VSC=0
                                                                                             GRNSUP
                                                                                                         88
                 DO 25 I=1.MAXPS
000074
                                                                                             GPNSUP
                                                                                                         89
                  IF (PSST(I+1) .LE. RQD) GO TO 30
000075
                                                                                                         90
             25 CONTINUE
30 IP=I
                                                                                             GRNSUP
C00100
                                                                                             GRNSUP
                                                                                                         91
000103
                                                                                             GRNSUP
                                                                                                         92
                 DO 35 I=1P.MAXPS
000105
                                                                                             GRNSUP
                                                                                                         93
                  TF(PSST(1+1) .NE. PSST(1P+1)) GO TO 36
000106
                                                                                             GRNSUP
                                                                                                         94
                 IPPST=PSST(1.2)
000111
                                                                                             GRNSUP
                                                                                                         95
                 1F (1PPST.EQ.JMETH) GG/0 40
000114
                                                                                                         96
97
                                                                                             GRNSUP
             35 CONTINUE
000116
                                                                                             GRNSUP
             36 IQ=I
000120
                                                                                                         98
                                                                                             GRNSUP
                 00 37 J=IP+IQ
000122
                                                                                                         99
                                                                                             GRNSUP
                                              GO TO 39
                  IF (PSST (J+2)
                                 .EQ. 5)
000124
                                                                                                         100
                                                                                             GRNSUP
000127
              37 CONTINUE
                                                                                             GRNSUP
                                                                                                         101
                 GO TO 1800
000132
                                                                                             GRNSUP
                                                                                                         102
             39 IP=J
000132
                                                                                                         103
                                                                                             GRNSUP
000134
                  GO TO 42
                                                                                                         104
                                                                                             GRNSUP
000134
             40 IP=1
                                                                                             GRNSUP
                                                                                                         105
             42 LMETH=PSST (IP+2)
TMETH=JMETH
000136
                                                                                             GPNSUP
                                                                                                         106
000141
                                                                                                         107
                                                                                             GRNSUP
                 AL=PSST(TP+3)
000143
                                                                                             GRNSUP
                                                                                                         108
                  TL=PSST(IP+4)
000144
                                                                                             GRNSUP
                 15T=PSST(1P+5)
000146
                                                                                                         110
                                                                                             GRNSUP
                 SP=PSST(1P+6)
000150
                                                                                             GRNSUP
                                                                                                         111
                 TH=PSST(IP+7)
000152
                                                                                                         112
                                                                                             GRNSUP
000153
                 ICS=PSST(IP+8)
                                                                                             GRNSUP
                                                                                                         113
                 IAS=PSST(IP+9)
000156
                                                                                             GRNSUP
                                                                                                         114
115
000160
                                                                                             GRNSUP
          C
                                                                                                         116
                                                                                             GRNSUP
                  STATUS CHECK FOR GROUND SUPPORT
                                                                                             GRNSUP
                                                                                                         117
                                                                                             GRNSUP
                                                                                                         118
                 DIST=X-XGS
000162
                                                                                                         119
                                                                                             GRNSUP
                 IF (1EXCA .FQ. 0) GO TO 43
000164
                                                                                                         120
                                                                                             GRNSUP
              IF(01ST .LE. TL) LIEXCA=0
43 1F(01ST .GT. AL) LIEXCA=1
000165
                                                                                             GRNSUP
                                                                                                         121
000171
                                                                                             GRNSUP
                                                                                                         122
                 IF (DIST .LT. TL) MAINT=1
000175
                                                                                                         123
                                                                                             GRNSUP
                                                                                             GRNSUP
                                                                                                         125
                   COMPUTING LABOR TIME USED FOR THIS ACTIVITY
                                                                                             GRNSUP
                                                                                             GRNSUP
                                                                                                         126
           C
                                                                                             GRNSUP
                                                                                                         127
                 GSTIME=GSTIME+OT
000201
                                                                                             GRNSUP
                                                                                                         128
                   COMPUTING MATERIALS FOR GROUND SUPPORT
           C
                                                                                                         129
                                                                                             GRNSUP
                  GO TO(1000+200+300+400+500)+15T
000203
                                                                                                         130
                                                                                              GRNSUP
           C
                                                                                                         131
                                                                                              GRNSUP
                   COMPUTING GROUND SUPPORT USING ROCK BOLTS
                                                                                              GRNSUP
                                                                                                         132
             200 IF(MG .EO. 1) MAINT=1
8PF=3.1415=D/(2*.866*(SP)**2)
                                                                                              GRNSUP
                                                                                                         133
000214
                                                                                              GRNSUP
                                                                                                         į 34
 000217
                                                                                              GRNSUP
                                                                                                         135
                  WRB=.284*3.1415*D
 000224
```

```
07/25/72
                                                                     GRN5UP
GOLFTA FORTRAN 1.3 # AUTO RFL # (07-12-72)
                                                                                                GPNSUP
                                                                                                            136
137
                  GO TO 1000
000226
                                                                                                 GRNSUP
          C
                                                                                                 GPNSUP
                                                                                                             138
                  COMPUTING GROUND SUPPORT USING SHOTCRETE
                                                                                                 GRNSUP
                                                                                                             139
                                                                                                 GRNSUP
                                                                                                             140
             300 IF (MG .EQ. 1) MAINT=1
925000
                                                                                                 GPNSUP
                                                                                                             141
                  IF (ROD .LE. 25.) GO TO 1900
IF (1C5 .EQ. 1) GO TO 306
000231
                                                                                                 GPNSUP
                                                                                                             142
000234
             IF (1C5 .E0. I) 60 TO 306
VSC=3.14)5*0*TH/(324.*2.)
GO TO 310
306 VSC=3.*3.1415*0*TH/(324.*4.)
310 60 TO 1000
                                                                                                             143
                                                                                                 GPNSUP
000236
                                                                                                             144
145
146
                                                                                                 GPNSUP
000241
                                                                                                 GRNSUP
000242
                                                                                                 GRNSUP
000246
                                                                                                 GRNSUP
                                                                                                             147
          C
                                                                                                             148
                                                                                                 GRNSUP
                   COMPUTING GROUND SUPPORT USE OF STEEL RIBS
                                                                                                 GRNSUP
                                                                                                             150
                                                                                                 GDNSI!P
             400 IF(HG .EQ. 1) MAINT=1
000247
                                                                                                             151
152
                                                                                                 GPNSUP
                  DO 410 1=1.9
IF (SSCOEF(I-1) .LE. ROO) GO TO 415
000252
                                                                                                 GPNSUP
000254
                                                                                                             153
                                                                                                 GRNSUP
             410 CONTINUE
000257
                                                                                                             154
155
                                                                                                 GPNSUP
             415 IP=I
192000
                                                                                                 GPNSUP
                  IF (SSCOEF (IP+1+2) .EQ. THETH) 1P#1P+1
000263
                                                                                                             156
157
                                                                                                 GRNSUP
                  PLOAD=SSCOEF(1P+3) *0*SP*CS
000270
                                                                                                 GRNSUP
030275
                  00 420 1=1.1)
                                                                                                             158
                                                                                                 GRNSUP
                  PK=(1+6) *2+1
000276
                                                                                                             159
                                                                                                 GRNSUP
                  IF (0 .LE. PK) GO TO 422
000301
                                                                                                 GRNSUP
                                                                                                             160
             420 CONTINUE
GO TO 1950
000304
                                                                                                 GRNSUP
                                                                                                             161
000306
                                                                                                 GRNSUP
                                                                                                             162
             422 SSWEIG=WEIGSS2(I)*(10.**-3)*PLOAO*WEIG551(I)
000306
                                                                                                 GRNSUP
                                                                                                             163
             430 WPI8=3.1415*D*55WE1G
000315
                                                                                                 GPNSUP
                                                                                                             164
             500 GO TO 1000
000320
                                                                                                 GPNSUP
                                                                                                             165
           C
                                                                                                 GPNSUP
                                                                                                             166
                   DETERMINING WHICH COST CALCULATION TO USE
                                                                                                 GRNSUP
                                                                                                             168
                                                                                                 GRNSUP
                                                                                                             169
170
                                                                                                 GRNSUP
                   DETERMINING ADDITIONAL SUPPORT COMPUTATIONS
                                                                                                 GRNSUP
                                                                                                             171
                                                                                                 GPNSUP
            1000 IF(IFST .EO. 1) GO TO 1050
000321
                                                                                                 GRNSUP
                                                                                                             172
                  1FST=1
000323
                                                                                                 GRNSUP
                   SPIZSP
                                                                                                 GRNSUP
                   MG=MGS(IAS)
 000326
                                                                                                 GRNSUP
                  GO TO(1050+1020+1030+1040+1050) +TAS
 000330
                                                                                                  GRNSUP
                                                                                                              176
                    WITH ADDITIONAL SUPPORT . ROCK BOLTS SET UP BOCKBOLT COMPUTATIONS GPNSUP
                                                                                                              177
                                                                                                 GRNSUP
                                                                                                              178
                                                                                                  GRNSUP
                                                                                                              179
            1020 IF(IST .NE. 3) GO TO 1025
IF(ROD .GT. 50.) GO TO 1050
 000340
                                                                                                              180
                                                                                                  GRNSUP
 000342
                                                                                                             181
                                                                                                 GRNSUP
                   SP=5
 000346
                   GO TO 200
 000347
                                                                                                              183
                                                                                                 GRNSUP
             1025 IF (IST .NE. 4) GO TO 1028
 000347
                                                                                                              184
                                                                                                 GPNSUP
                   SP=5.
 000351
                                                                                                  GRNSUP
                                                                                                              185
                   GO TO 200
 000353
                                                                                                              186
                                                                                                 GRNSUP
             1028 IF (SP .EO. 0.) 5P=5.
 000353
                                                                                                              187
                                                                                                  GRNSUP
                   GO TO 200
 000355
                                                                                                  GRNSUP
                                                                                                              188
                    AGOITIONAL SUPPORT . SHOTCRETE SET UP FOR SHOTCRETE COMPUTATIONS
                                                                                                  GRN5UP
                                                                                                              189
            Ċ
                                                                                                  GRN5UP
                                                                                                              190
```

C

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                    GRNSUP
                                                                                               GRNSUP
           1030 1F(TH . EQ. 0.) TH=.5*D
60 TO 300
000356
                                                                                                          192
193
194
195
                                                                                               GRNSUP
000361
                                                                                               GRNSUP
          C
                  ADDITIONAL SUPPORTESTEEL RIBS SET UP STEEL RIBS COMPUTATION
                                                                                               CONCHO
                                                                                               GRNSUP
                                                                                                          196
                                                                                               GRNSUP
000362
           1040 IF (15T .NE. 2) 50 TO 1045
                                                                                                          197
                                                                                               GRNSUP
000364
                 SP=4.
                                                                                               GRNSUP
                 GO TO 400
                                                                                               GPNSUP
                                                                                                          199
           1045 IF (SP .EQ. 0.) SP=4.
000366
                                                                                                          200
                                                                                               GRNSUP
000370
                 GO TO 400
                                                                                                          201
                                                                                               GRNSUP
                                                                                               GRNSUP
                                                                                                          202
                  DETERMINING WHICH COST CATEGORY TO USE
                                                                                               GRNSUP
                                                                                                           203
                                                                                               GRNSUP
                                                                                                           204
           1050 1F((1AS .NE. 5) .AND. (IAS .NE. 1)) GO TO 1060
000371
                                                                                               GRNSUP
                                                                                                           205
                 GO TO (1100+1200+1300+1400 ) . IST
000401
                                                                                               GRNSUP
                                                                                                           206
           1060 [F(1AS .NE. 2) GO TO 1070
GO TO (1200-1200-1500-1600-1200)-15T
000411
                                                                                               GRNSUP
                                                                                                           207
000413
                                                                                               GRNSUP
                                                                                                           208
000424
           1070 IF(1AS .NE. 3) GO TO 1080
           GO TO (1300+1500+1700+1300) *IST

1080 1F(IAS *NE* 4) GO TO 1090

GO TO (1400+1600+1700+1400+1400) *IST

1090 GO TO 1825
                                                                                               GRNSUP
                                                                                                          209
000426
                                                                                               GRNSUP
000437
                                                                                               GRNSUP
                                                                                                          211
000441
                                                                                               GRNSUP
                                                                                                           212
000452
                                                                                               GRNSUP
                                                                                                          213
                                                                                                          214
                                                                                               GRNSUP
                  COMPUTING ADVANCE AND COST WITH NO SUPPORT
                                                                                               GRNSUP
                                                                                               GRNSUP
                                                                                                           216
000453
           1100 FXGS=X-TL
                                                                                               GRNSUP
000455
                 GO TO 2000
                                                                                               GRNSUP
                                                                                                           218
                  COMPUTING ADVANCE AND COST WITH ROCK BOLTS
                                                                                               GRNSUP
                                                                                                           219
                                                                                               GRNSUP
                                                                                                           220
                                                                                               GRNSUP
                                                                                                           155
           1200 ANV=RATERR+DT/9PF
000456
                                                                                               GRNSUP
                                                                                                           555
                 FXGS=ADV+XGS
C00451
                                                                                               GRNSHP
                                                                                                           553
                 RRLBS=ADV+RPF+WRB
000463
                                                                                               GRNSUP
                                                                                                          224
225
226
                 DP4GS=RRLAS*UCS
000465
                                                                                               GRNSHP
                 PMGS=PMGS+DPMGS
000467
                                                                                               GRNSUP
000470
                 GO TO 2000
                                                                                                           227
                                                                                               GRNSUP
          c
                                                                                                           228
                                                                                               GRNSUP
                  COMPUTING ADVANCE AND COST USING SHOTCRETE
                                                                                                           229
                                                                                               GRNSUP
          C
                                                                                                           230
                                                                                               GRNSUP
           1300 ADV=RATESC+DT/VSC
000471
                                                                                                           231
                                                                                               GRNSUP
000474
                 FXGS=XGS+ADV
                                                                                               GRNSUP
                                                                                                           232
000476
                 CUYD=ADV*VSC
                                                                                                          233
                                                                                               GRNSUP
                  DPMGS=CUYD*UCSC
000477
                                                                                               GRNSUP
000501
                 PMGS=PMGS+DPMGS
                                                                                               GRNSUP
                                                                                                           235
                 GO TO 2000
000502
                                                                                               GRNSUP
                                                                                                           236
                                                                                               GRNSUP
                                                                                                           237
                  COMPUTING ADVANCE AND COST USING STEEL RIBS
                                                                                               GRNSUP
                                                                                                           238
                                                                                               GRNSUP
                                                                                                           239
           1400 ADV=RATESS*DT*SP
000503
                                                                                               GRNSUP
                                                                                                           240
000506
                 FXGS=XGS+ADV
                                                                                               GRNSUP
                                                                                                           241
                 SRLBS= (ADV/SP) . WRTB
000510
                                                                                                           242
243
                                                                                               GRNSUP
                 DPMGS=SRLAS*UCS
000512
                                                                                               GRNSUP
000514
                 PMGS=PMGS+DPMGS
                                                                                               GRNSUP
                                                                                                           244
000515
                 GO TO 2000
                                                                                               GRNSUP
                                                                                                           245
```

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                   GRNSUP
                                                                                                         246
247
                                                                                              GRNSUP
                  COMPUTING ADVANCE AND COST USING SHOTCRETE AND ROCK BOLTS
                                                                                              GRNSUP
                                                                                                          248
                                                                                              GRNSUP
           1500 ADV= (RATERR/RPF+RATESC/VSC) *DT/2
000516
                                                                                                          249
250
                                                                                              GRNSUP
                 FXGT=XGS+AOV
000524
                                                                                              GRNSUP
                 CUYD=ADV=V5C
000526
                                                                                                          251
                                                                                              GRNSUP
                 RALAS=AOV+BPF+WRB
000527
                                                                                              GRNSUP
                                                                                                          252
253
                                      .RBLBS.UCS
                 OPMGS=CUYO-UCSC
000531
                                                                                              GRNSUP
                 PMGS=PMGS+OPMGS
000535
                                                                                                          254
                                                                                              GRNSUP
                 GO TO 2000
000536
                                                                                                          255
256
                                                                                              GRNSUP
                                                                                              GRNSUP
                  COMPUTING COST AND ADVANCE USING STEEL RIBS AND ROCK BOLTS
                                                                                              GRNSUP
                                                                                                          257
                                                                                                          258
259
           1600 1F(15T .EO. 4) SP=SP1
ADV=(RATES5*SP*RATER8/8PF)*OT/2.
                                                                                              GRNSUP
000537
                                                                                              GRNSUP
                                                                                              GRNSUP
                                                                                                          260
                 FXGS=XGS+ADV
000551
                                                                                              GRNSUP
                                                                                                          261
                 SRLRS=(AOV/SP)*WRIB
RRLBS=AOV*RPF*WRB
000553
                                                                                              GRNSUP
                                                                                                          262
000556
                                                                                              GRNSUP
                                                                                                          263
                 OPMGS=(SRLRS+RBLBS)+UCS
000560
                                                                                              GRNSUP
                                                                                                          264
                 PMGS=PMGS+OPMGS
000563
                                                                                                          265
                                                                                              GRNSUP
000564
                 GO TO 2000
                                                                                              GRNSUP
                                                                                                          266
                  COMPUTING ADVANCE AND COST USING SHOTCRETE AND STEEL RIBS
                                                                                              GRNSUP
                                                                                                          267
                                                                                              GRNSUP
                                                                                                          268
                                                                                              GRNSUP
                                                                                                          269
            1700 ADV=(RATESC/VSC+RATESS*SP)*OT/2.
000565
                                                                                                          270
271
                                                                                              GRNSUP
                 FXGS=XGS+ADV
000573
                                                                                              GRNSUP
                 CUYD=AOV+V5C
                                                                                              GRNSUP
                                                                                                          272
                 SRLAS=(AOV/SP) *WRIB
000577
                                                                                              GRNSUP
                                                                                                          273
                 DP4GS=CUYD=UCSC+SRLBS=UCS
000601
                                                                                              GRNSIJP
                                                                                                          274
                 PMGS=PMGS+OPMGS
000604
                                                                                              GRNSUP
                                                                                                          275
000606
                 GO TO 2000
                                                                                              GRNSIJP
                                                                                                          276
                                                                                               GRNSUP
                                                                                                          277
                   ERROR MESSAGES
                                                                                              GRNSUP
                                                                                                          278
                                                                                              GRNSUP
                                                                                                          279
            1800 PRINT 1801
000606
            1801 FORMATI/1X.* UNARLE TO PERFORM GROUND SUPPORT. CANNOT FIND EXCAVATI
                                                                                              GRNSUP
                                                                                                          280
000612
                10N METHOD IN PSST TABLE AND NOOTHER METHOD IS IN TABLE*)
                                                                                              GRNSUP
                                                                                                          281
                                                                                              GRNSUP
                                                                                                          282
            GO TO 1975
1825 PRINT 1826.145
000612
                                                                                              GRNSUP
                                                                                                          283
000613
           1826 FORMAT(//IX.* AOOITIONAL SUPPORT *.15.* IS NONEXISTANTIN PROGRAM*) GRNSUP
GO TO 1975
1900 PRINT 1901
GRNSUP
                                                                                                          284
000621
                                                                                                          285
286
000621
            1901 FORMAT(1X+75H UNABLE TO PERFORM SUPPORT+SHOTCRETE CANNOT RE USED 1
                                                                                              GRNSUP
                                                                                                          287
000626
                                                                                              GRNSUP
                                                                                                          288
                1F POD IS LESS THAN 25
                                                                                                          289
                                                                                              GRNSUP
000626
                                                                                              GRNSUP
            1950 PPINT 1951
000627
            1951 FORMATIASHUNABLE TO PERFORM SUPPORT STEEL RIB WEIGHT INCETERMINATE GRASUP 1 FOR DIAMETER GREATER THAN 34
                                                                                                          291
 000633
                                                                                                          292
                                                                                              GRNSUP
                                                                                                          293
 000633
            1975 FXG5=XGS
                                                                                                          294
295
                                                                                              GRNSUP
 000535
                 FRACT=0.
                                                                                               GRNSUP
                                                                                               GRNSUP
                                                                                                          296
                   COMPUTING ACTUAL GROUND SUPPORT IF TOO CLOSE TO FACE OR REYONO
                                                                                              GRNSUP
                                                                                                          297
                                                                                                          298
                                                                                              GRNSUP
                                                                                                          299
  000440
             2000 DISTIEX-TL
                                                                                              GRNSUP
```

GRNSUP

300

FRACTUL.

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                             GRNSUP
                   IF(MAINT .EQ. 1) GO TO 2500
IF (FXGS .LE. 01511) GO TO 2005
FRACT=(01511-XGS)/AOV
                                                                                                             GRNSUP
                                                                                                                         301
000644
                                                                                                                         302
                                                                                                             GRNSUP
000646
                                                                                                                         303
                                                                                                             GRNSUP
000650
                                                                                                             GRNSUP
                                                                                                                          304
                   AOV=DISTI-XGS
AOVLOS=FXGS-(X-TL)
000653
                                                                                                                          305
                                                                                                             GRNSUP
000654
                                                                                                             GRNSUP
                                                                                                                          306
                   GSLOS=GSLOS · ADVLOS
000657
                                                                                                             GRHSUP
                                                                                                                          307
                   FXGS=XGS+ADV
000660
                                                                                                             GRNSUP
                                                                                                                          308
                    PMGLOS=DPMGS*(1.-FRACT)
000662
                                                                                                                          309
                                                                                                             GRNSUP
                   PHGS=PHGS-PHGLOS
000665
                                                                                                                          310
                                                                                                             GRNSUP
            2005 GO TO 3000
000667
                                                                                                                          311
                     COMPUTING FEET LOST FOR GROUND SUPPORT IF IN MAINTENANCE OR IF ID
                                                                                                            GRNSUP
                                                                                                                          312
           č
                                                                                                             GRNSUP
                                                                                                                          313
                   LE FOR ALL OT
                                                                                                             GRNSUP
                                                                                                                          314
                                                                                                             GRNSUP
                                                                                                                          315
000670
             2500 PHGS=PHGS-DPMGS
                                                                                                             GRNSUP
                                                                                                                          316
000672
                   GSLOS=GSLOS+(FXGS-XGS)
                                                                                                                         317
                                                                                                             GRNSUP
000675
                   FXGS=XGS
                                                                                                                         318
                                                                                                             GRNSUP
000676
                   FRACT =0
                                                                                                                         319
320
                                                                                                             GRNSUP
000676
             3000 CONTINUE
                                                                                                             GRNSUP
                                                                                                             GRNSUP
                                                                                                                         321
                     COMPUTING UP TIME OF GROUND SUPPORT
                                                                                                                          322
                                                                                                             GRNSUP
            C
                                                                                                             GRNSUP
                                                                                                                          323
                   GSUTIH=GSUTIM+FRACT*OT
000676
                                                                                                                         324
325
                                                                                                             GRNSUP
            CCC
                                                                                                             GRNSUP
                     COMPUTING PLANT AND EQUIPMENT COSTS
                                                                                                                         326
                                                                                                             CONSUP
                   IF((IST .EQ. 2) .OR. (IAS .EQ. 2)) GO TO 3025
IF((IST .NE. 3) .AND. (IAS .NE. 3)) GO TO 3050
IF((IST .EQ. S) .OR. (IAS .EQ. 5)) GO TO 3015
IF((IST .EQ. 1) .OR. (IAS .EQ. 1)) GO TO 3015
                                                                                                             GRNSUP
000701
                                                                                                                         328
329
330
331
332
                                                                                                             GRNSUP
900711
                                                                                                             GRNSUP
000717
                                                                                                             GRNSUP
000725
                                                                                                             GRNSUP
000733
000735
000735
             077=07/2.
GO TO 3020
3015 OTT=0T
                                                                                                             GRNSUP
                                                                                                             GRNSUP
                                                                                                                          333
                                                                                                                          334
335
                                                                                                             GRNSUP
             3020 GSPLAN=GSPLAN+DTT+FRACT+ESCPLA
000737
                                                                                                             GRNSUP
                    GO TO 3050
             3025 IF((IST .EQ. 5) .OR. (IAS .EQ. 5)) GO TO 3027 IF((IST .EQ. 1) .OR. (IAS .EQ. 1)) GO TO 3027
                                                                                                                         336
337
338
                                                                                                             GRNSUP
000744
                                                                                                             GRNSUP
000754
                                                                                                             GRNSUP
000762
                    DTT=01/2
                                                                                                                          339
                                                                                                             GRNSUP
                    GO TO 3030
000764
                                                                                                             GRNSUP
                                                                                                                          340
341
000764
             3027 DTT=01
             3030 GSPLAN=GSPLAN+OTT=FRACT=ERBORI
IF((IST .EQ. 3) .OR. (IAS .EQ. 3)) GO TO 3015
                                                                                                             GRNSUP
000766
                                                                                                                          342
                                                                                                             GRNSUP
000772
                                                                                                             GRNSUP
                                                                                                                          343
              3050 CONTINUE
001002
                                                                                                             GRNSUP
                                                                                                                          344
                    RETURN
001002
                                                                                                             GRNSUP
                                                                                                                          345
                    ENO
001003
 FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
NTRAIN
NTRUCK
LTRAIN
 IFILO
 LIFILD
 IF ILLD
LNTROA
```

LLTRAN

07/25/72 GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72) GRNSUP LLTRUK LNTRAN LNTRUK IMOVE XT XDE PC NVEYCL LVEHCL LVHCL LNVHCL LNVHCL JMOVE IMETH XE PR

VI-110

S. SUBROUTINE GSMAIN

GOLETA F	ORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/72
		GSMAIN	2
	SUBROUTINE GSMAIN	GSMATN	3
	C CONTRACTOR COUNTRY C	GSMAIN	4
	C FLEMENT-PRIMARY GROUND SUPPORT C GENERAL PROCESS-ROCKBOLTS-STEEL RIB SETS-SHOTCRETE-COMBINATION	GSMAIN	5
		GSMAIN	6
	CS OF THOSE	GSMAIN	7
	C ACTIVITY-MAINTENANCE	GSMAIN	8
	COMMON /GRND/ PSST(60.9) . MAXPSST. UCS. UCS. PATERB. PATESC. PATESS	SUPPORT	2
000002	COMMON ACADO DEST (POPPL) SECTION WANDER	SUPPORT	3
	1. GSLOS.TAS.TST.ERBDRI.ESCPLA.GDOW.GSETOO.MAXPSS COMMON /WHEELS/ AF.AF.AMAX.AMAXL.AMINL.BSL.CARCAP.CP.DF.DF.DTAS	WHEELS	2
000002	T. DIMA.DIU.FL.FC.FR.FT.HPA.HPEA.HPEV.HPV.HPV.HPV.LOCO.MC.ML	WHEELS	3
	T. DIMA-DIU-FL -FC-FR-FI-HPA-A-RC A-HPE-NTMLPP-NTMLPP-NTRACK-SL	WHEELS	4
	3. TCURYX (20) . TCURYY (20) . THAINT . TWE . VO. VS . VE . VF . VMAX . WC. WL . XOS	WHEELS	5
	4. MAXLD.NUMLD.LQHE.QUC.WHC.STATUS(36).WHY(24).MLTYP.WMR.ECONEQ.	WHEELS	6
	4. MAXED. NUMED. EQUIC. HUIC. STATE STATE STATE AND ALERMATE ALTROPE.	WHEELS	7
	5 ECONSS.FLOCD.EMUCKC.ETRACK.ESWITC.EUNLOA.ERMAIN.1180RE.	WHEELS	8
	6 ISW(25) *NTINIT * TCCV * TMCV COMMON /OLDCOM/ IFILD ** STOP (25) *KUNLO *LSTOP *LVEHCL ** NRYRY ** NSWCH	WHEELS	9
000002	1. NTRDA.NVEHCL.NUMSWT.SWITCH(20).TFC(2S).TOP(2S).TSTAT(2S.4)	WHEELS	10
	1. NTRDA.NVEHCL.NDMSWI.SWITCHTCOTTTCTCS).MCV.MELAGC.OUMMY(20)	WHEELS	11
	COMMON /NEWCOM/ LIFILO-LKSTOP(2S) -LKUNLO-LLSTOP-LLVHCL-LMBYBY	WHEELS	12
000002	- LUGUAL LUGDA LUULCI I NIMENT EESTIMIZUI OF ITUUCO ITUULO I	WHEELS	13
		WHEELS	14
		WHEELS	15
	3. LMCV.LMFLAC.FDUMMY(19) OIMENSION COMOLO(260).COMNEW(260).		
000002	OTHERSTON COMPLETED !- CONNETTED !-		
• •		WEST S	16
	LTSTAT(25.4).ITSTAT(25.4)	WHEELS	17
200000	EQUIVALENCE (NVEHCL .NTRAIN .NTRUCK) . (LVEHCL .LTRAIN .LTRUCK)	WHEELS	iė
00000	1. (COMOLD.IFILO), (COMNEW.LIFILD.IFILD) + INICATENTAGE	WHEELS	19
	a. (FICTATALICIAT) (ISTATALISTAT)	WHEELS	20
	5. (LEVECT ALL TRANALL TRUK) • (LNVHCL • LNTRAN•LNTKUR)	ALL	5
200002	ADDITION (ALL) YT.CTD.TA.BOD.CS.TAMROPLUWOILLAU	ALL	3
******	AT DEFECK TEDT AND PROMANOTHAN ON OF TRAIN OF THE PRINT O	ALL	4
	TSHET.REPORT.OPPCT.TO.XO.XO.ISCH.ICHNG.XCHNG.TCHNG	ALL	5
200000	EQUIVALENCE (JMOVE . IMOVE) . (1METH . JMETH)	ALL	6
000002	COMMON-TALE ACE TO THE HEAD OF THE ONE OF THE MENT OF	ALL	7
	1. PMGS. MCV.DJMFC.RDPLAN.HPLANT.GSPLAN	ALL	ė
	2. ECPLAN. ROTIME . HTIME (2) . GSTIME . ECTIME	ALL	9
000002	COMMON/PERFRMY ROUTIM . RODTIM . UNHTIM . DMHTIM . GSUTIM . GSOTIM . ECUTIM	ALL	10
	1. ECDTIM.GD4Y.GADV.GEND.GBEG	ALL	11
500000	CONHUNTER OF THE PROPERTY OF T	ALL	12
200000	REAL JHHHM.LD.LOB.LBIT.LBURN.LSTEEL.JMCV	ALL	13
200000	OIMENSION G(A)	ALL	14
000002	EQUIVALENCE (G.XT) - (XE - XOE) - (PR - PC)	GSHATH	12
000002	OTHERSTON GSHT (S) + DOWNT (S) + GOOWN (S) + SETDOW (S)	GSMAIN	13
000002	DATA GSMT/ 5+0./	GSMAIN	
000002	OATA DOWNT/5.0./	GSMAIN	15
000005	DATA GROWN/5.5/	GSMAIN	
000002	DATA SETDOW/50.S/	GSMAIN	
000002	OATA INC/I/	GSMAIN	
000002	OATA INIT+NEFDIN/0+0/	GSMAIN	
	C NOTE- GROUND SUPPORT TYPE =IST-A00ITIONAL SUPPORT =IAS	GSHAIN	
		GSMAIN	
	C IST.IAS ARE C 1 IF NO SUPPORT REQUIRED	GSMAIN	
	THE PERSON AND THE PE	GSMAIN	
		GSMAIN	
		GSHAIN	25
	C 4 IF STEEL RIB SETS ARE BEING INSTALLED		



GOLETA	FORTRAN	1.3 • AUTO RFL • (07-12-72) GSMAIN		07/25/72
	С	S IF LAGGING IS SUPPORT(ONLY IAS MAY =5)	GSMAIN	26
	Č		GSMAIN	27
200000	1	[N[T=]	GSMAIN	28
000003		00 4 J=1+5	GSMAIN	29
000005		IF (GDOW .NE. O.) GOOWN (J)=GOOW	GSMAIN	30
000007		IF (GSFTDO .NE. O.) SETOOW(J)=GSETOO	GSMAIN	31
000012	4	CONTINUE	GSMAIN	32
000014		IF (NFEOIN .EQ. 0) GO TO 150	GSMAIN	33
000015		NEEDIN=0	GSMAIN	34
000016		GO TO 5	GSMAIN	35
	С	NORMAL ENTRY	GSMAIN	36
000016		ENTRY GSMNT	GSMAIN	37
000023		IF(INIT .EQ. 1) GO TO 5	GSMAIN GSMAIN	38 39
000025		NEEOIN=I	GSMAIN	40
920000		GO TO 1	GSMAIN	41
000027	>	IF((IAS .NE. 1) .ANO. (IAS .NE. 5)) INC=2	GSMAIN	42
000040		00 110 1-274 00WN=00WNT(I)	GSMAIN	43
000042		GS4=GSHT(I)	GSMAIN	44
000045		MG=MGS(I)	GSMAIN	45
000043	С	40-103187	GSMAIN	46
	č	DETERMINING IF GROUND SUPPORT TYPE I IS IN USE OURING OT	GSMAIN	47
	č		GSHAIN	48
000047	•	IF((I .EQ. IST) .OR. (I .EQ. IAS)) GO TO SO	GSMAIN	49
000041	С	The second state of the second	GSMAIN	50
	č	DETERMINING IF GROUND SUPPORT TYPE I IS IN MAINTENANCE	GSMATH	51
	č	AND THE RESERVE OF THE PERSON	GSMA IN	52
000056	_	IF(MG .EQ. 0) GO TO 100	GSMAIN	53
	С		GSMAIN	54
	С	REDUCING MAINTENANCE TIME BY OT FOR GROUND SUPPORT TYPE I	GSMAIN	55
	С		GSMAIN	56
000057	25	DOWN =DOWN-DT	GSMAIN	57
000061		IF (DOWN .GT. 0.) GO TO 100	GSMAIN	58
	C		GSHAIN	59
	C	REMOVING GROUND SUPPORT TYPE I FROM MAINTENANCE	GSMAIN	60
	C		GSMAIN	61
000063		DOWN=0.	GSMAIN	62
000063		LMG=0	GSMAIN	63
000064		GO TO 100	GSMAIN	64
000064	50	IF (MG .EQ. 1) GO TO 25	GSMAIN	6S 66
000066		GSM=GSM+DT/INC	GSMAIN	67
	C	ARTERIAL SE ARAUNA AURRARE SMRP & TO BUR FAR MASNIFFILMER	GSMAIN GSMAIN	68
	C	DETERMINING IF GROUND SUPPORT TYPE I IS DUE FOR MAINTENANCE	GSMAIN	69
	С	TELECH LE COMMITTAL CO TO 188	GSMAIN	70
000072		IF(GSM .LE. GDOWN(I)) GO TO 100	GSMA IN	71
	C	PUTTING GROUND SUPPORT TYPE I INTO MAINTENANCE	GSMAIN	72
	č	- Attian author Sacraul tire ! tale unfutfunger	GSMAIN	73
000075	·	LMG=1	GSMAIN	74
000076		DOWN=SETOOW(I)	GSHA IN	75
000078		PMGS=PMGS=0JMGS	GSMAIN	76
000101		GSM=0.	GSMAIN	77
000101		GSOTIM=GSOTIM+00WN	GSHAIN	76
	100	DOWNT (I) = OOWN	GSMA IN	79
000104				

T. SUBROUTINE ENVIR

	FORT	PAN 1.3 • AUTO RFL • (07-12-72)		07/25/72
		SUBROUTINE ENVIR	ENVIR	2
	С		ENVIR	2
	С	ELEMENT - ENVIRONMENTAL CONTROL	ENVIR	4
	C	GENERAL PROCESS - VENTILATION . COOLING	ENVIR	5
	C	*** * HEAT # HUST BE RETRIEVED FROM ROCK DISINTEGRATION ROUTINE	ENVIR	6
	С	**************************************	ENVIR	7
	C		ENVIR	8
000002	_	COMMON /ALL / XT.STR.IA.ROD.CS.TAMB.FLOW.IFLAG	ALL	ž
		1. AT.D.E.SK.T.OT.X.PR.XMAX.TMAX.DX.DV.TPRINT.DTPRNT.1MDVE.JMETH	ALL	3
		2. TSHFT.REPORT.DPPCT.TD.XO.XDISCH.ICHNG.XCHNG.TCHNG	ALL	- 4
200000		EQUIVALENCE (JHOVE . 1MDVE) . (IMETH . JMETH)	ALL	5
200000		COMMON/MONEY/ JMMHM . DJM . DJMMH . DJMRD . DJMBHM . DMAINT . DJMBM . DJMGS	ALL	
		1. PMGS+JMCV+DJMEC+RDPLAN+HPLANT+GSPLAN	ALL	6
		2. ECPLAN. ROTIME. HTIME (2) . GSTIME. ECTIME	ALL	6
200000		COMMON/PERFRM/ ROUTIM-RODITM-UMMTIM-DMHTIM-GSUTIM-GSDTIM-ECUTIM		
000002		1. ECDTIM.GDAY.GANV.GEND.GBEG	ALL	9
200000			ALL	10
000002		CDMMDN/LARDR/ RDMEN(10.2) . HMEN(10.2.2) . GSMEN(10.2) . TCMEN(10.2)	ALL	11
		RFAL JMMHH.LO.LDB.LBIT.LBURN.LSTEEL.JMCV	ALL	12
200000		DIMENSION G(A)	ALL	13
000302		EQUIVALENCE (G+XT) + (XE+XDE) + (PR+PC)	ALL	14
000002		COMMON /ENVC/ MAXMEN+TOTHP+OM+QD+VAMIN+VAMAX+QG(10)+	ENVIRON	2
• • • • •		1 TA+TO+WA+FKD+FKT+CPA+CKA+REFRAT+AMC(10)+ODR+EVFNTP+CPUMP	ENVIRDN	3
200000		EQUITVALENCE (TROCK+TAMB)+(HEAT+HEAT+)	ENVIR	11
200000		DIMENSION ROG(10)	ENVIR	12
200000		DATA INIT /O/	ENVIR	13
000005		DATA NEEGIN /O/	ENVIR	14
000005		DATA PI /3.1415927/	ENVIR	15
000002		DATA DFACT.VFACT.QMP.QDMP.QAV.QDR /4=0./	ENVIR	16
000002		DATA FACT1.FACT2.FACT3.FACT4.TAVELH /5*0./	ENVIR	17
200000		DATA FACTZA /0./	ENVIR	18
000002		DATA QDS /10+0./	ENVIR	19
	С	INITIALIZATION	ENVIR	20
	С		ENVIR	21
200000		10 DJMEC = 0.	ENVIR	22
000003		ECDT1ME=0.	ENVIR	23
000004		ECUTIME=0.	ENVIR	24
000005		IF (QM .EQ. 0.) 9M = 200.	ENVIR	25
00007		1F (9D .EQ. 0.) OD = 106. • 0.334 • TOTHP	ENVIR	26
00013		IF (VAMIN .EO. O.) VAMIN = 50.	ENVIR	27
00015		IF (VAMAX .EQ. 0.) VAMAX = 1000.	ENVIR	28
000017		IF (TO .EQ. 0.) TO = 80.	ENVIR	29
12000		IF (WA .EQ. 0.) WA = 0.075	ENVIR	30
000023		TE IPUS PA A MUS A SE	ENVIR	31
000025		8F 1FUT PA A 1 PMT - 1 PM A	ENVIR	32
000027		## (CD)	ENVIR	33
000031		VP IAVA PA A LAWA - A ALIM	FNVIR	34
00033			ENVIR	35
00035		12 480 PA A 1 80 - A A16	ENVIR	36
000037		AFLAT - A M AL 4	ENVIR	37
00042		WEART - A A AFLAT	ENVIR	38
	С		ENVIR	39
100047	Ī		ENVIR	
/UUU-9-3		AAUG 180 180 180		40
/ U U U = 3	-			
000043	С	4848 - 44 5 5454B	ENVIR Envir	42

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                          ENVIR
000050
                  DAV = VAMIN . VFACT
                                               QDG(N) = AIR VOL. RATE REQUIRED BY OILUTION ENVIR
                                                                                                                     45
           C
           C
                  DD 50 I = I.10
IF (AMC(I) .EO. 0.) GD TO 50
QOG(I) = 1.0E6 * OG(I) / AMC(I)
000052
                                                                                                       ENVIR
                                                                                                       ENVIR
000055
                                                                                                       ENVIR
                                                                                                                     49
                                                                                                       ENVIR
                  CONTINUE
000060
                                                                                                       ENVIR
                                                                                                                     51
                                               ODR = DESIGN REQUIREMENT AIR VOLUME RATE
                                                                                                                     52
000062
                  QNQ = QMP
                                                                                                      ENVIR
                  IF (DDMP .GT. ODR) QDR = DDMP
IF (DAV .GT. ODR) QDR = GAV
DD 70 I = I+10
                                                                                                                    53
54
55
                                                                                                      ENVIR
000064
000067
                                                                                                      ENVIR
000672
                                                                                                      ENVIR
                                                                                                                    56
57
                   IF (QDG(I) .GT. QDR) QDR = ODG(I)
                                                                                                       ENVIR
000074
000101
               70 CONTINUE
                                                                                                      FNVIR
                                                                                                                     58
                                               CHECK DESIGN REQUIREMENT VS ALLOWABLE AIR V ENVIR
           C
                                                                                                                     59
60
                  TAVEL = QDR / VFACT
IF (TAVEL .LE. VAMAX) GO TO 95
PRINT 90. TAVEL.VAMAX
000103
                                                                                                       ENVIR
000105
                                                                                                      FNVIR
                                                                                                                     61
                                                                                                       ENVIR
000107
               90 FORMAT (33HOVENTILATION DESIGN REQUIREMENT. .FI4.3.43H.EXCEEDS ALL ENVIR **OWABLE AIR VELOCITY IN TUNNEL. .FI4.3.17H. RUN TERMINATEO. )
000117
                                                                                                                     63
                  CALL EXIT
                                                                                                      ENVIR
000117
                                               COMPLETE INITIALIZATION
                                                                                                       ENVIR
           C
                                                                                                                     66
67
              95 FACTI = CMA / D
FACT2 = PI + 0
FACT2A = FACT2 + (TA + 80.) / 2.
                                                                                                      ENVIR
000120
                                                                                                      ENVIR
                                                                                                       ENVIR
000124
                  FACT3 = WA + CPA + 60.
FACT4 = 1.3 + 0
                                                                                                                     69
                                                                                                       ENVIR
000127
                                                                                                                     70
                                                                                                       ENVIR
000132
                                                                                                                    71
72
73
74
75
76
77
78
                   TAVELH = TAVFL
                                                                                                       ENVIR
000134
000135
                   INIT = I
                                                                                                       ENVIR
                  IF (NEEDIN .EO. 0) GO TO 999
                                                                                                       ENVIR
000136
                                                                                                       ENVIR
                  NFEOIN = 0
                                                                                                      FNVIR
           C
                                               NORMAL ENTRY
                                                                                                      FNVIR
                  ENTRY ENVIRC
TAVEL = TAVELH
                                                                                                      ENVIR
000140
                                                                                                       ENVIR
000145
                                                                                                                     79
                                                                                                       ENVIR
000147
                  IF (INIT .EQ. I) GD TO 97
                                                                                                                     80
                                                                                                       ENVIR
000151
                   NEEDIN = I
                                                                                                       ENVIR
000152
                  GD TO IO
                                                                                                       ENVIR
           C
                                                                                                       ENVIR
                                                                                                                     83
                    COMPUTING LABOR TIME USED FOR THIS ACTIVITY
           Č
                                                                                                                     85
                                                                                                       ENVIR
               97 ECTIME = ECTIME + OT
000152
                    NOTE ENVIR NEVER STOPS AT PRESENT THIS MAY BE CHANGED IN THE FUTU
                                                                                                      ENVIR
           C
                                                                                                       ENVIR
                                                                                                                     87
                    COMPUTING UP TIME
                                                                                                      ENVIR
                                                                                                                     86
           C
                                                                                                       ENVIR
                                                                                                                     89
                  ECUTIM=ECUTIM+OT
                                                                                                       ENVIR
                                                                                                                     90
000154
                                                                                                       ENVIR
                                                                                                                     91
           C
                                                                                                       ENVIR
                                                                                                                     92
                    COMPUTING PLANT AND EQUIPMENT COSTS
                                                                                                       ENVIR
                                                                                                                     93
                                                                                                                    94
95
96
                  ECPLAN=ECPLAN+DX*EVENTP
                                                                                                       ENVIR
000156
                    CALCULATE COST OF PUMPING WATER OUT OF TUNNEL
                                                                                                      ENVIR
                  OJMEC=DJMEC+CPUMP+DT+60. * (FLOW+QWATR)
                                                                                                      ENVIR
000161
                                                                                                                     97
                    CALCULATE REYNOLOS NUMBER FOR TUNNEL AIL FLOW CONDITIONS
                                                                                                      ENVIR
                                                                                                      FNVIR
                                                                                                                     98
```

100 REYND=TAVEL-0/0.165

```
07/25/72
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                 ENVIR
                                                                                          ENVIR
                QDR = TAVEL . OFACT
000170
         c
                                         DERIVE NUSSELT NO.
                                                                                          ENVIR
                                                                                                     100
                                                                                          ENVIR
                                                                                                     101
                IF (REYNO .GF. 10000.) GO TO 120
000172
                IF (REYNO .LE. 2100.) GO TO 130
                                                                                          ENVIR
                                                                                                     102
000174
                RNUSS=5.0 . (26.7 (REYNO-2100.)/7900.)
000177
                                                                                          FNVIR
                                                                                                     103
                                                                                          ENVIR
                                                                                                     104
000203
                GO TO 150
000203
            120 RNUSS = 0.02 . REYNO .. 0.8
                                                                                          ENVIR
                                                                                                     105
000210
                GO TO 150
                                                                                          ENVIR
                                                                                                     106
000210
           130 RNUSS = 0.5 . REYNO .. 0.3
                                                                                          ENVIR
                                                                                                     107
                                         CALC HEAT TRANSFER COEFFICIENT
                                                                                          ENVIR
                                                                                                     108
         C
            150 HEATC = RNUSS - FACTI
                                                                                          FNVTR
                                                                                                     109
000215
         c
                                         CALC HEAT ADDED TO AIR FROM WALL SURFACE
                                                                                          FNVIR
                                                                                                     110
                                                                                                     111
000217
                XWRK=HEATC - (X-XDISCH)
                                                                                          FNVIR
                QRFAC = (FACT2*XWRK*TROCK) - (XWRK*FACT2A)
000222
                                                                                          FNVIR
                                                                                                     112
                                         CALC HEAT ADDED TO AIR FROM MACHINERY
                                                                                          ENVIR
                                                                                                     113
         C
                                                                                          FNVIR
000226
                OMFAC = HEAT / OT
                                         CALC TEMPERATURE AT TUNNEL FACE
                                                                                          ENVIR
                                                                                                     115
         C
                                                                                          ENVIR
                TOF= (QRFAC + QMFAC) / (FACT3 + QOR) + TA
                                                                                                     116
000230
                IF (TOF .LE. TD) GO TO 500
IF (TAVEL . 100. .GT. VAMAX) GO TO 400
                                                                                          ENVIR
000235
                                                                                          ENVIR
000237
                                         HAX VELOCITY NOT YET ACHIEVED
                                                                                          ENVIR
         C
                                                                                          ENVIR
                                                                                                      20
000244
                TAVEL = TAVEL + 100.
000245
                GO TO 100
                                                                                          FNVIR
                                                                                                     151
                                         CALC MECHANICAL REFRIGERATION LOAD
                                                                                          FNVIR
                                                                                                     122
         C
                                         (TDF - TD)
CALC OPERATING COST OF REFRIGERATION IN DT
                                                                                                     123
000245
           400 QREFRG = QOR * FACT3 *
                                                                                          ENVIR
                                                                                          ENVIR
                                                                                                     124
         C
                                         . REFRAT . DT
                                                                                          ENVIR
000251
                DJMEC = DJMEC + GREFRG
                                         SELECT SUITABLE VENT DUCT VELOCITY
                                                                                          ENVIR
                                                                                                     126
            500 VDUCT = 2380. + 0.0483 * OOR
                                                                                          ENVIR
000254
                                         CALC FRICTION LOSS OF AIR FLOWING IN TUNNEL ENVIR
                                                                                                     128
         C
                HTUN = (FKT * X * TAVEL * TAVEL) / FACT4

CALC VENT DUCT DIAMETER
                                                                                          ENVIR
000257
                                                                                          ENVIR
                                                                                                     130
         c
                XWRK = QDR / (PI * VOUCI)
                                                                                          ENVER
                                                                                                     131
000263
                DOUCT = 2. . SORT (XWRK)
                                                                                          ENVIR
000266
                                          CALC FRICTION LOSS OF AIR IN VENT DUCT
                                                                                          ENVIR
                                                                                                      133
         C
000271
                HOUCT = ( FKO+ (X-XDISCH) + VDUCT + VDUCT I/( 1.3 + ODUCT )
                                                                                          ENVIR
                                                                                                     134
                                          CALC AIR HORSEPOWER
                                                                                          ENVIR
                                                                                                     135
         C
                PAIR = QDR . (HTUN . HOUCT) / 6350.
                                                                                          ENVIR
                                                                                                     136
000277
         C
                                         CALC FAN HORSEPOWER
                                                                                          ENVIR
                                                                                                     137
                PFAN = PAIR / 0.75
                                                                                          ENVIR
                                                                                                     138
000302
                                         CALC VENTILATION POWER COST DJPING DT
          C
                                                                                          ENVIR
                                                                                                     139
                FKWHR = PFAN . 0.7452 . DT
600304
                                                                                          ENVIR
                                                                                                     140
                DJMEC = DJMEC + PR + FKWHR
XI = QREFRG + REFRAT + DT
                                                                                          ENVIR
000306
                                                                                          ENVIR
000311
                X2 = PP . FKWHR
                                                                                          ENVIR
                                                                                                     143
000313
000314
            999 CONTINUE
                                                                                          FNVIR
                                                                                                     144
                RETURN
                                                                                          ENVIR
000314
                                                                                          ENVIR
                ENO
000315
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
IMOVE
JMETH
XT
XDE
```

PC TAMB GOLETA FORTRAN 1.3 " AUTO RFL . (07-12-72)

ENVIR

07/25/72

JMOVE IMETH XE

SUBROUTINE MAXADV

U.

PC JMOVE IMETH XE

07/25/72 GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72) REPORT SUBROUTINE MAXADY REPORT COMPUTING ADVANCE EACH DAY IN FEET. STORING HAXIMUM C REPORT COMMON /ALL / XI-STR-1A-ROD-CS-TAMB-FLOW-IFLAG

1. AT-D-F-SK-T-OT-X-PR-XMAX-TMAX-DX-DV-TPRINT-DTPRNT-IHOVE-JHETH

2. TSUFT-PEROPY-COROT TO THE PEROPY-COROT. ALL 200000 ALL ALL TSHFT.REPORT.OPPCT.TD.XO.XOISCH.1CHNG.XCHNG.TCHNG ALL 000002 000002 ALL ECPLAN.RDT1PE.HT1ME(2).GST1PE.ECTIME
COMMON/PEREMY POUTIM.RDDT1M.UMHTIM.DMHTIM.GSUTIM.GSOTIM.ECUTIM ALL 200000 ALL 1. ECDTIM.GDAY.GADV.GENO.GBEG CDMMDN/LABOR/ RDMEN(10+2)+MMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)
REAL JMMHM+LD+LDH+LBIT+LBURN+LSTEEL+JMCV ALL 200000 ALL 000002 ALL 13 DIMENSION G(8) 000002 EQUIVALENCE (G.XT) (XE.XOE) (PR.PC)
OATA 1N1T-NEFOIN/2*0/
OATA DLOX-ROUT/2*0-/ AI.L 000002 DEPORT 000002 REPORT 000002 REPORT INITIAL 1ZATION C REPORT I INIT=1 200000 REPORT 10 IF (TSHFT .ED. O.) TSHFT=24. 000003 REPORT 000005 REPORT 000007 IF (NFEDIN .EQ. 0) GO TO 999 iā REPORT NEEDIN=0 REPORT GO TO 15 NORMAL ENTRY ENTRY MAXADW 000010 REPORT C REPORT 16 000011 REPORT 10 IF (1N1T .FQ. 1) GO TO 15 000016 REPORT 050020 REPORT GO TO I 150000 15 ROUT=POUTIM-ROUT 1F(ROUT .EQ. 0.) GO TO 999 ADVV=(X-OLDX)/ROUT PEPART 20 21 000022 REPORT 000024 22 23 24 REPORT 000025 REPORT IF (ADVV .LE. GAOV) GO TO 999 GDAY=(T-TO)/24. 000027 REPORT 000031 25 REPORT GEND=X-XOISCH 000034 26 27 REPORT GREG=OLDX-XD1SCH 000036 REPORT GADV=ADVV 000040 28 29 30 REPORT 999 CONTINUE 000041 REPORT OLDX=X 000041 REPORT ROUT=ROUTIM 000043 REPORT RETURN 000044 REPORT END 000045 END *FOLLDWING VARIABLES EQUIVALENCED BUT NOT REFERENCED IMOVE JMETH ΧT XDE

V. SUBROUTINE REPORR

GOLETA	FORTRAN 1.3 * AUTO RFL * (07-12-72)		07/25/72
	SUBROUTINE REPORR	REPORT	33
	c	REPORT	34
	C PRINTING INTERIM PERFORMANCE PEPORT	REPORT	35
	c	REPORT	36
200000	CO-MON /ALL / XT+STR+IA+PQD+CS+TAMB+FLOW+IFLAG	ALL	2
	1. AT.D.E.SK.T.DT.X.PR.XMAX.TMAX.DX.OV.TPRINT.OTPRNT.IMOVE.JMETH	ALL	3
	Z. TSHET.REPORT.GPPCT.TD.XD.XD.XD.ISCH.ICHNG.XCHNG.ICHNG	ALL	4
200000	EDUIVALENCE (JMOVE+IMOVE)+(IMFTH+JMETH)	ALL	5
000005	SDMLO+MBMLO+THIAMG+MMBMLO+GRMLO+HPMLG+MHMML VYRMOMVNOMMOD	ALL	6
	1. PMG5.JMCV.DJMFC.RDPLAN.HPLANT.GSPLAN	ALL	7
	2. ECPLAN.POTIME.HIIMF(2).GSTIMF.ECTIME	ALL	8
000002	COMMON/PERFRY/ RDITIM-RDOTIM-UMHTIM-OMHTIM-GSUTIM-GSUTIM-ECUTIM	ALL	9
	1. ECNTIM.GDAY.GADV.GENO.GBEG	ALL	10
000005	COMMON/LAROR/ ROMEN(10+2)+HMEN(10+2+2)+GSMEN(10+2)+ECMEN(10+2)	ALL	11
000002	REAL JAMHHALDALDBALBITALBURNALSTEEL JMCV	ALL	12
200002	DIMENSION G(R)	ALL	13
000002	EQUIVALENCE (G.XT) + (XE.XDE) + (PR.PC) OATA INIT-NFFDIN/2*0/	ALL	14
200005	DIMENSION IVAL (20)	REPORT	38
000002	COMMONITESTIVALUE (30) NAME (36)	TEST TEST	2
***************************************	1.THEAD(110).JHEAD(100)	TEST	4
000002	EQUIVALENCE (IVAL.VALUE)	TEST	5
000002	DATA IHEAD/THINTERIM. TH PERFOR. THMANCE R. THEPORTS .	REPORT	40
V U V U U L	17HDAYS SI - THUCE CON - THENCED - THEXCAVAT - THING - 28TH	REPORT	41
	27HHEADING.7H POSITI.7HON (FFET.7H) .207H .	REPORT	42
	37HAVERAGE.7H ADVANC.7HE RATE (.7HFFET/OP.7HERATING.7H HOUR) .	REPORT	43
	47HMAXIMUM+7H DAILY +7HADVANCE+7HDAYS SI+7HNCE COM+7HMENCED +	REPORT	44
	57HEXCAVAT+7HING +7H +4H +7HHEAOING+7H POSITI+	REPORT	45
	67HON-REGI+7HWNING 0+7HF THAT +7HDAY (FEE+4HT) +7HHEADING+	REPORT	46
	77H POSITI+7HON-END +7HOF THAT+7H DAY(FE+7HET) +4H +7HAVERAGE	REPORT	47
	8.7H RATE F. THOR THAT. TH DAY (FE. THET/OPER. THATING H. 4HOUR).	REPORT	48
	974CUMULAT - 7HIVE SUB- 7H5YSTEM - 7HPERFORM - 6HANCE 7HELEMENT -	REPORT	49
	ATH/MEASUR + THE +TH OPE + THRATIONA + THL +TH S+	REPORT	50
	B7HUBSYSTE+7H4 +7HAVAILAB+7HILITY+ +7H +7H UTILI+	REPORT	51
	C7HZATION . 2H. ,947H,2H,7H.OPERAT,7HIONAL A.7HVAILANI,	REPORT	52
	D7HLITY=(T+7HOTAL SH+7MIFT TIM+7HE-DOWN +7HTIME)/T+7HOTAL SH+ E7HIFT TIM+1HF+7H++SURSY+7HSTEM UT+7HILIZATI+7HON=(TOT+7HAL SHIF+	REPORT	53
	F7HT TIME-, THOOWN TI. THE-IDLE, TH TIME) /. THTOTAL S. THHIFT TI.	REPORT	54 55
	GSHWEY	REPORT	56
200000	OATA JHEAO/7HINTERIH.7H COST R.7HEPORT .7HOAYS SI.7HNCF COM.	REPORT	57
******	17HMENCEO .THEXCAVAT.THING .TH .TH .THAVERAGE .TH COST P.		58
	2 THER IN S. THITU CUB. THIC YARD, TH EXCAVA. SHTED. THAVERAGE.	REPORT	59
	47H COST P. THER FOOT TH OF TUN. THILL . TH . 3H . THOUNULAT.		60
	STHIVE COS+THT SUMMA+THRY TO 0+THATE++(0+THOLLARS)+THELEMENT+	REPORT	61
	67H/CATEGO.7HRY .7HOIRECT .7H PL.7HANT .7H JO.	REPORT	62
	67H8 •7H PERM•7HANENT •7H OVE•7HR •7H ELEMEN•1HT•	REPORT	63
	77HLABOR •	REPORT	64
	7 7H EQU-THIPMENT -TH MAT-THERIALS -TH MAT-	REPORT	65
	87HFR14LS +7H HE+7HAO +7H TOTAL+14-7H3H	REPORT	66
	914•7H, 3H,	REPORT	67
	ATHGEOLOGY . TH CHANGE . 4HO AT . 5H DAYS . TH FEET F . THROM POR . 4HTAL	REPORT	68
	ATHNEW CHA.	REPORT	69
	BTHRACTERI+THSTICS A+THRE. UN+THCONFINE+THD COMPR+THESSIVE +	REPORT	70
	C7HSTRENGT • 6HH (KSI)/	REPORT	71
		REPORT	72



		REPORR		07/25/72
GOLETA F	ORTRAN	1.3 * AUTO RFL * (07-12-72) REPORR		
		INITIALIZATION	REPORT	73
	C	INTITACTOR	REPORT	74
344443		(NIT=)	REPORT	75
000003		IF (REPORT .EQ. 0.) REPORT=24.	REPORT	76 77
000005		IF(TSHFT .EQ. 0.) TSHFT=24.	REPORT	78
000007		1F (NEEDIN .EQ. 0) GO TO 999	REPORT	79
030010		NFFOIN=0	REPORT	80
000011		60 10 3	REPORT	81
000011	С		REPORT	82
	Č	NORMAL ENTRY	REPORT	83
	č		REPORT	84
000011	-	ENTRY REPORS	REPORT	85
000016		IF (INIT .EQ. 1) 60 TO 3	REPORT	86
000020		NEFOIN =1	REPORT	87
000021		GO TO 1	REPORT	88
• • • • • • • • • • • • • • • • • • • •	С	COMPUTING DAY OF REPORT AND AVERAGE ADVANCE	REPORT	89
000022	3	OAYS=(T-TO)/24.	REPORT	90
000025		TSHET=T-TO	REPORT	91
000026		ADV=X-X0ISCH	REPORT	92
	C	TO DE COOK DECEMPEDATION UP TIME	REPORT	93
	С	OPERATING TIME IS ASSUMED TO BE ROCK DISINTEGRATION UP TIME	REPORT	94
000030		AVGADY= (X-XO) / RDUT 1M	REPORT	95
		THE STATE OF THE S	REPORT	96
	С	PRINTING INTERIM PERFORMANCE REPORTS	REPORT	97
000033		PRINT 4	REPORT	98
000036	4	FORMAT(1H1) PRINT 5-(IMFAD(1)-I=1-10)-DAYS-(IHEAD(1)-I=12-17)-ADV-(IHEAD(1)-	REPORT	99
000036			REPORT	100
		11=18.731.AVGADV FORMAT (////.46x.4AT.///.26x.6AT.F10.3.//.26x.6AT.F10.3.//.26x.	REPORT	101
000072	3		REPORT	102
		16A7+F10+3) PRINT 40+(1HFAD(1)+1=24+33)+GOAY+(1HEAD(1)+I=34+40)+GBEG+(1HEAD(1)	REPORT	103
000072		• •= 43 471-CEND-11NFA0(11-1848-54)-GADV	11 E. O. 1	104
	, ,	FORMAT (/ . 26x . 3A7 . / / . 34x . 6A7 . A4 . F10 . 3 . / / . 34x . 6A7 . A4 . F10 . 3 . / / . 34x .	REPORT	105
000136	40	16A7.A4.F10.3.//.34X.6A7.A4.F10.3)	REPORT	106
		OBINT 80-(THEAD(T)+1=55+84)	REPORT	107
000136	0.4	FORMAT (/+26x+4A7+A6+//+26x+9A7+//+51x+5A7+A2+//+26x+9A7+A21	REPORT	108
000150	01	OPTIM=(TSHFT-RODTIM)/TSHFT	REPORT	109
000150		USETIMERDUTIMITSHET	REPORT	110
000153		DOTALY 120-DOTTM-ISEFTTM	REPORT	111
000154	120	FORMAT (//-25x+19H ROCK FRAGMENTATION +F13.3+10x+F13.3)	REPORT	112
000164	161	OPTIM= (TSHFT-DMHTIM)/TSHFT	REPORT	113
000167		USETIM=UMHTIM/TSHFT	REPORT	114
000170		DRINT 130.0PTIM-USETIM	REPORT	
000700	130	FORMATIZ-25x-19H MATERIALS MANDLING +F13-3-10x+F13-3)	REPORT	_
000200		OPTIM=(TSHFT-GSOTIM)/TSHFT	REPORT	
000203		USFT:M=GSUTIM/TSHFT	REPORT	
000204		PRINT 140.0PTIM.USETIM	REPORT	-
000714	14	B FORMATE + 25x-19H GROUND SUPPORT +F13-3+10X+F13-31	REPORT	
000214		OPTIM=(TSHFT-ECOTIM)/TSHFT	REPORT	
000717		USET IM=ECUTIM/TSHFT	REPORT	
000220		PRINT 150-0PTIM-USETIM	REPORT	*
000230	15	FORMAT (/-25x-22H ENVIRONMENTAL CONTROL .F10.3.10x.F13.3)	REPORT	
000230		PRINT 160.(1HEAD(I).I=85.107)	REPORT	7 -
000242		O FORMAT (//+25x+10A7+A1+///+24x+11A7+A2)	REPORT	
000242	99	9 CONTINUE		

GOLETA FORTRAN 1.3 * AUTO RFL * (07-12-72)

O00242 RETURN
000243 END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCEO
IMOVE
JHETH
XT
XOE
PC
JHOVE
IMETH
XE
PR

W. SUBROUTINE REPORC

DI FTA F	FORTR	AN 1.3 . AUTO REL . (07-12-72)		07/25/7
				130
		SUBROUTINE REPORC	REPORT	131
	С	Source Co.	REPORT	132
	č	PRINTING INTERIM COST REPORT	REPORT	133
	č			133
2000	•	COMMON /ALL / XT.STR.1A.ROO.CS.TAMB.FLON.IFLAG	ALL	3
000		AT-D-F-SK-T-OT-X-PR-XMAX-TMAX-DX-OV-TPRINT-DTPRNT-140VE-JMEIN	ALL	4
		2. TSHET.REPORT.OPPCT.TO.XO.XOISCH.ICHNG.XCHNG.ICHNG	ALL	Š
0002		COUTUM FACE / INOVE-IMOVE) - (IMFTH-JMETH)	ALL	
0002		COMMON/MOREO MEMBER OF THE PROPERTY OF THE COMPANT AND THE COMPAND COM	ALL	6
0002		1. PHGS.JMCV.OJMFC.ROPLAN.HPLANT.GSPLAN	ALL	7
		TO BOOK AND DOTTHE ANTIME (2) A GSTIME OF CTIME	ALL	8
0002		COMMON/PERFRM/ ROUTIM . ROOTIM . UMMTIM . OMMTIM . GSUTIM . GSDTIM . ECUTIM	ALL	-
10002		CAN CAN CAN GENO-GREG	ALL	10
		COMMON/LARORY ROMEN(10.2) . HMEN(10.2.2) . GSMEN(10.2) . ECMEN(10.2)	ALL	11
2000		REAL JMMHM.LD.LOB.LBIT.LBURN.LSTEEL.JMCV	ALL	15
2000		OTHENSION G(R)	ALL	13
2000		EQUIVALENCE (G.XT) + (XE.XDE) + (PR.PC)	ALL	14
2000		OIMENSION IVAL (20)	TEST	5
2000		COMMONITESTIVALUE (301 + NAME (30)	TEST	3
0002		I. IHEAD(1)0) . JHEAD(100)	TEST	4
		EQUIVALENCE (TVAL. VALUE)	TEST	5
0005	С	INITIALYZATION	REPORT	136
	·	OTHENSION ELEMEN(4.6).TOTAL(6)	REPORT	137
2000		1 INIT=1	REPORT	138
2000		1F(OPPCT .EQ. 0.) OPPCT=.20	REPORT	139
0003		IF (REPORT .EQ. O.) REPORT#4.	REPORT	140
00005		00 2 1=1.2	REPORT	141
00007		HTIMF(1) = 0	REPORT	142
00011		2 CONTINUE	REPORT	143
21000		GSTIMF=0.	REPORT	144
0014		ROTIMF=0.	REPORT	145
00015		ECTIME=0.	REPORT	146
00016		IF (NEEOIN .EQ. 0) GO TO 999	REPORT	147
00017		NFEDIN=0	REPORT	148
0020		GO TO 3	REPORT	149
00020	_	NORMAL ENTRY	REPORT	150
	С	ENTRY REPORTO	REPORT	151
12000		IF (INIT .EQ. 1) GO TO 3	REPORT	152
00026		NFEOIN=I	REPORT	153
00030		GO TO 1	REPORT	154
00031		3 00 5 [=1.4	REPORT	155
00032		00 4 J=1.6	REPORT	156
		ELEMEN(I.J) *0.	REPORT	157
00035		TOTAL (J)=0.	REPORT	158
00040		4 CONTINUE	REPORT	159
00041		5 CONTINUE	REPORT	160
00042	С		REPORT	161
	c	COMPUTE JOB MATERIAL .PLANT AND EQUIPMENT COSTS FOR EACH PROCESS	REPORT	162
	C	ELEMEN (1.4)*0.	REPORT	163
00044		ELEMEN(2.4)=0.	REPORT	164
00045		ELEMEN(4.4)=0.	REPORT	165
00046			REPORT	166
00047		ELEMEN(3.3)=0. ELEMEN(1.2)=ROPLAN	REPORT	167
100050		ELEMEN(1.27=HDLANT	REPORT	168
000051		PLEMENIC CONTRACT	REPORT	169

```
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                    REPORC
                                                                                                        07/25/72
                                                                                               REPORT
                                                                                                          170
000054
                 ELEMEN (4.2) =FCPLAN
                                                                                               REPORT
                                                                                                          171
000056
                 ELEMEN(1+3)=DJMRO+DJMRM
                                                                                               REPORT
000060
                 ELEMEN(2+3)=DJMHH
                                                                                               REPORT
                                                                                                          173
000061
                 ELEMEN (3+4) =PMGS
                                                                                               REPORT
000063
                 ELEMEN (4+3) = DJMEC
                                                                                                          175
                                                                                               REPORT
                  COMPUTING LABOR COSTS FOR EACH GENERAL PROCESS
                                                                                               REPORT
                                                                                                          176
                                                                                               REPORT
                                                                                               REPORT
                                                                                                           178
000064
                 00 6 1=1-10
                                                                                                           179
                 ELEMFN(1+1)=FLFMEN(1+1) . ROMEN(1+1) . ROMEN(1+2) . ROTIME
                                                                                               REPORT
000066
                 ELEMEN(3.1)=ELEMEN(3.1) .GSMEN(1.1) .GSMEN(1.2) .GSTIME
                                                                                               REPORT
                                                                                                           180
                                                                                               REPORT
                 ELEMEN(4.1) = ELEMEN(4.1) + ECHEN(1.1) + ECHEN(1.2) + ECTIME
                                                                                                           181
000076
                                                                                               REPORT
               6 CONTINUE
                                                                                                           182
000102
                 00 70 J=1.2
00 7 1=1.10
000104
                                                                                               REPORT
                                                                                                           183
                                                                                               REPORT
                                                                                                           184
000105
000106
                 ELEMEN(2.1) = ELEMEN(2.1) . HMEN(1.1.J) . HMEN(1.2.J) . HTIME(J)
                                                                                               REPORT
                                                                                                           185
                                                                                               REPORT
                                                                                                           186
000117
                                                                                               REPORT
                                                                                                           187
000121
              70 CONTINUE
                 00 9 1=1.4
                                                                                               REPORT
                                                                                                           188
000123
                                                                                               REPORT
                                                                                                          IA9
000124
                 00 B J=1.4
                                                                                                          190
                 ELEMEN(I.5) = ELEMEN(I.5) + OPPCT * ELEMEN(I.J)
                                                                                               REPORT
000125
                                                                                                           191
                                                                                               REPORT
000133
                 CONTINUE
                                                                                               REPORT
                                                                                                           192
000135
               9 CONTINUE
                 00 II 1=1.4
00 10 J=1.5
ELEMEN(1.6)=ELEMEN(I.6)+ELEMEN(I.J)
                                                                                               REPORT
                                                                                                           193
000137
                                                                                                          194
                                                                                               REPORT
000140
                                                                                               REPORT
200141
                                                                                               REPORT
                                                                                                           196
              10 CONTINUE
000146
                                                                                               REPORT
                                                                                                          197
              11 CONTINUE
000150
                 00 13 1=1+4
00 12 J=1+6
                                                                                               REPORT
                                                                                                           198
000152
000153
                                                                                               REPORT
                                                                                                           199
                                                                                               REPORT
                                                                                                           200
                 TOTAL (J) = TOTAL (J) + ELEMEN (I+J)
000154
                                                                                               REPORT
                                                                                                          201
000162
              12 CONTINUE
000163
              13 CONTINUE
                                                                                               REPORT
                                                                                                          202
                                                                                               REPORT
                                                                                                           203
000165
                 DAYS= (T-TO) /24.
                 ACYARD=TOTAL (6)*108./(3.1415*(D**2)*(X-X0))
                                                                                               REPORT
                                                                                                          204
000170
                                                                                                          205
000176
                 ACFOOT=TOTAL (6)/(X-X0)
                                                                                               REPORT
                 PRINT 14
                                                                                               REPORT
                                                                                                          206
207
000200
                                                                                               REPORT
              14 FORHAT (1H1)
                                                                                               REPORT
000204
                 PRINT 15. (JHEAD(1).I=1.10).DAYS.(JHEAD(1).I=11.17).ACYARO.
                                                                                                          208
                                                                                                          209
                                                                                               REPORT
                I(JHEAD(I)+T=18+24)+ACFOOT
              15 FORMAT (///+49x+3A7+///84+6A7+A3+F14.3+//+8X+6A7+A3+F13.2+//+8X+
                                                                                               REPORT
000240
                                                                                               REPORT
                                                                                                          211
                26A7+A3+F13-21
000240
                 PRINT 50 . (JHFAD (1) .1=25.69)
                                                                                               REPORT
                                                                                                          212
              50 FOPMAT(//.8x.647.//.8x.1347.41./.29X.104/.//.8X.1447.43)
                                                                                               REPORT
000252
                                                                                                          214
215
216
                                                                                               REPORT
000252
                 PRINT 90. (ELFYEN(1.J).J=1.6)
             90 FORMAT(/ .7x+ 22H ROCK FRAGMENTATION 111.2+F10.2+F)2-2)
                                                                                               REPORT
                                                                +F9.2+F11.2+3X+F11.2+3X+F
000264
                                                                                               REPORT
            PRINT 100. (ELEMEN (2-J).J=1-6)
100 FORMAT( /-7x-22H MATERIALS HANDLING
1 3x-F11-2-F10-2-F12-2)
                                                                                               REPORT
000264
                                                                                               REPORT
                                                                +F9.2.F11.2.3X.F11.2.
000276
                                                                                               HEPORT
                                                                                                          220
                 PRINT 110 . (ELEMEN (3.J) . J=1.6)
                                                                                               REPORT
000276
            110 FORMAT (/ 7x - 22H GR
                                                                                                          221
000310
                            7X.22H GROUND SUPPORT
                                                               .F9.2.F11.2.3x.F11.2.3x.
                                                                                               REPORT
                                                                                               REPORT
                                                                                               REPORT
                                                                                                          223
000310
                 PRINT 120 + (ELEMEN(4+J)+J=1+6)
```

+F9.2+F11.2+3X+F11.2+3X REPORT

274

120 FORMAT (/ .7x.22H ENVIRONMENTAL CONTROL

000322

```
07/25/72
                                                                              REPORC
GOLETA FORTRAN 1.3 . AUTO RFL . (07-12-72)
                                                                                                                           225
226
227
                                                                                                             REPORT
REPORT
              1.F11.2.F10.2.F12.2)
PRINT 130.(JHEAD(1).T=70.84)
130 FORNAT(/.8X.14A7.A3)
000322
000334
000334
000346
                                                                                                             REPORT
                                                                                                                           228
229
                                                                                                             REPORT
              PPINT 140. (TOTAL (J) .J=1.6)
140 FORMAT (// 7x.22H CATEGORY TOTAL
                                                                           ·F9.2.F11.2.F14.2.F14.2.
                                                                                                             REPORT
                                                                                                             RFPORT
                                                                                                                           230
                   1F10.2.F12.2)
                                                                                                                           231
                                                                                                             REPORT
                    IF (1CHNG .EQ. 0) GO TO 999
                                                                                                             REPORT
000346
                    1CHNG=0
                                                                                                             REPORT
                                                                                                                           233
000347
                    PRINT 150. (JHEAO(1) . 1=85.87) .TCHNG. (JHEAD(1) . 1 . 88.88) .XCHNG.
               1(JHEAD(I).I=R9.100).STR
150 FORMAT(//:8X.2A7.A4.F10.3.A5.F10.3.2A7.A4.///.26X.8A7.A6.F12.4)
                                                                                                                           234
235
000350
                                                                                                             REPORT
                                                                                                             REPORT
                                                                                                             REPORT
                                                                                                                           236
000403
                                                                                                                           237
                    PRINT 165.1A
                                                                                                             REPORT
000403
               165 FORMATISIX.37H ARRASIVENESS
                                                                                                              REPORT
000411
                    PRINT 170.ROD
                                                                                                              REPORT
                                                                                                                           239
 000411
                                                                                                 .F12.41
               170 FORMAT (51x+37H ROCK QUALITY DESIGNATION
                                                                                                                           240
241
                                                                                                              REPORT
 000417
               PPINT 180.CS

180 FORMAT(51X.37H IN SITU DENSITY(LBS/FT.3)
PRINT 190.TAMB

190 FORMAT(51X.37H AMBIENT TENPERATURE(DEG F)
PRINT 200.FLOW
                                                                                                              REPORT
000417
                                                                                                 18.12.41
                                                                                                                            242
                                                                                                              REPORT
                                                                                                              REPORT
REPORT
                                                                                                                           243
244
245
 000425
                                                                                                 .F12.4)
 000433
 000433
                                                                                                 .F12.4)
                                                                                                              REPORT
               200 FORMAT (SIX+37H WATER INFLOW(GAL/MIN)
                                                                                                                           246
 000441
                                                                                                              REPORT
               999 CONTINUE
                                                                                                              REPORT
                                                                                                                           247
 000441
                    RETURN
ENO
 000441
 000442
 FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
 IMOVE
 JMETH
 XT
 XOE
 PC
 JHOVE
 IMETH
 XE
```

X. SUBROUTINE HOLBRN (ICYCLE)

000220

122000

70 RETURN

```
SURRDUTINE HOLBRN(ICYCLE)
                    CDMMON/ALL/ XT.STR.IA.RQD.CS.TAMR.FLDW.IFLAG.AT.D.E.SK.T.DT.X.PR
000003
                        XMAX.TMAX.TD.XD.XDISCH
                   2.0X.DV
                    COMMON/MONEY/ DJMRO
000003
                    COMMON/BLAST/ ADR+ADH+ CRIT+CRURN+CCAP+CEX+CM+CPL+CSTEFL+LRIT
- LBURN+LD+LDR+LSTEEL+MEN+ND+NH+NHB+PF+POB+PDD+TCHG+TIN+TOUT
000003
                   2.TYPEPF . WPL
000003
                    CDMMON/OLOCDM/ JUMIN.JUMOUT.NCHRG.NDRILB.NDRILI
000003
                    CDMMON/NEWCDM/LJUMIN+LJUMDT+LNCHRG+LNDRLB+LNDRIL
                    ELEMENT - ROCK DISINTEGRATION
                    GENERAL PROCESS - DRILL AND BLAST
ACTIVITY - DRILL HOLES DE BURN PATERN
            C
                    TECHNIQUE - PURCUSSION DRIFTSR AND BURN CUT DRILLS
                    DATA TIMED.TIMER.PHI.SE.RD.TD.RDB.TDR /840./
000003
000003
                    IF (ICYCLE .NF. I ) GD TO 50
000005
000005
                    NORILA=0
                    ICYCLF = 50
IF (NH .NF. 0 .AND. NO .NE. 0 .AND. LD .NE. 0) GO TO IO
OPTIDN 2
000006
            C
                    PHI = 1.0

NH = INT (( D .0.I*D*D)*PHI + .5)

ND = INT (NH/8.0 + .5)
000017
000025
                    IF (D.GT.15.) NHB =3
IF (D.LE.15.) NHB =2
000030
000034
                    NDR=I
000037
                    LD = DX + I.0
000040
                    LDB=DX+1.0
000043
                10 IF(STP .GT. 50.0) SE=60.
IF (STR .LT. 50.0) SE=15.*EXP(0.031*STR)
RD=1.9RE3*POD/(ADH*SE)
000046
000052
000063
                    TIME TO DRILL HOLFS
TD = LD/RD * NH/ND
RDR=1.98E3*POB/(ADB*SF)
000066
000073
000076
                    TOR=LOB/RDB . NHB/NDB
000103
                    TIMED=TD
000107
                    PRINT 20.TD.TDR.NH
                 ) FDRMAT (* TIME TO DRILL HDLES - TD=**F10.5** TDB=**F10.5/
* * ND. OF HOLES =**IIO)
KEFP TRACK OF TIME AND CDSTS
000120
000120
                50 TIMED=TIMED=OT
TIMER=TIMER=D?
000123
                    LNDRIL=0
000124
                    LNDRLR=0
000124
                    IF (TIMED.GT. 0.0) GD TD 60
000130
                    IF (NDRILL .EQ. I) GD TD 57
000132
                    IF (LAIT .LE.0.0 .OR. LSTEEL .LF. 0.0) GD TO 55
DJMRD= CBIT/LBIT * NH* LD * CSTFEL * LD * NH/LSTEEL *DJMRD
000132
000143
000154
                    GD TO 60
000154
                55 DJMRD= .I*NH*LD + 0.25 * .I*NH*LD + DJMRD
000162
                    GO TO 60
000163
                57 LNDRIL=I
000164
                60 IF (TIMEB .GT. 0.0) RETURN IF (NOPILB .EO. I) GO TD 67
000170
                   LNDRLB=I
000171
                   IF (LAURN .LF. 0.0 .DR. LSTEEL .LE. 0.0) GO TO 65
DJMRD=CBURN/LAURN+NHB+LDB+CSTEEL+LOB+NHB/LSTEEL+DJMRD
000201
000212
                    GD TO 70
                65 DJMRD=.25*.1*NHB*LDB*DJMRD
60 TO 70
000212
000217
000217
                67 LNDRLR=1
```

Y. SUBROUTINE MOVEIN (ICYCLE)

```
CHAROUTINE MOVEIN (ICYCLE)
         C
         C
               ELEMENT - ROCK FRAGMENTATION
               GENERAL PROCESS - DRILL AND BLAST
         C
               ACTIVITY - REPOSITION AND ALIGN DRILLING EQUIPMENT
         C
               TECHNIQUE - DRILL JUMBO (FULL FACE)
         Č
               COMMON /GRND/ PSST (60.9)
000003
               COMMON/ALL/ XT.STR.IA.RQD.CS.TAMB.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
000003
                   XMAX, TMAX, TO, XO, XDISCH
              2.DX.DV
                COMMON/MONEY/ DJMRD
000003
                                          CBIT+CBURN+CCAP+CEX+CM+CPL+CSTFFL+LBIT
                COMMON/BLAST/ ADR. ADH.
000003
                  LBURN+LD+LDB+LSTEEL+MEN+ND+NH+NHB+PF+POB+POD+TCHG+TTN+TOUT
              2. TYPEPF . WPL
                COMMON/OLDCOM/ JUMIN.JUMOUT.NCHPG.NDRILB.NDRILL
000003
                COMMON/NEWCOM/LJUMIN,LJUMOT,LNCHRG,LNDRLB,LNDRIL
000003
                DATA TT/0./
000003
                IF (ICYCLE .GT. 1)GO TO 10
000003
                JUMIN=0
000006
                ICYCLE = 50
000006
                IF (TIN .LE. 0.0) TIN=.25
000007
                TT=TIN
000012
                DO 5 I=1,15
000013
                IF(PSST(I+1) .LE. RQD) GO TO 6
000015
              5 CONTINUE
000020
              6 IF (PSST(I+3) .GT. 10.) GO TO 7
000021
                DX=PSST(I.3)
000025
                GO TO 8
000026
              7 DX = 10.
000026
              8 DV=AT*DX
000030
             10 TT=TT-DT
000032
                LJUMIN=0
000034
                IF (TT .LE. 0.0) LJUMIN=1
000035
                RETURN
000037
                END
000040
```

Z. SUBROUTINE MOVOUT (ICYCLE)

```
SURROUTINE MOVOUT (ICYCLE)
         C
                ELEMENT - ROCK FRAGMENTATION
         C
         C
                GENERAL PROCESS - DRILL AND BLAST
          C
                ACTIVITY - MOVE OUT DRILLING EQUIPMENT AND BLAST
         C
                TECHNIQUE - DRILL JUMBO (FULL FACE)
          C
                COMMON/ALL/ XT.STR.IA.RQD.CS.TAMB.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
000003
                  XMAX.TMAX.TO.XO.XDISCH
               2.DX.DV
                COMMON/MONEY/ DJMRD
000003
                COMMON/BLAST/ ADB+ADH+ CBIT+CBURN+CCAP+CEX+CM+CPL+CSTEFL+LBIT
000003
               1. LBURN.LD.LDB.LSTEEL.MEN.ND.NH.NHB.PF.POB.POD.TCHG.TIN.TOUT
               2. TYPEPF. WPL
                COMMON/OLDCOM/ JUMIN.JUMOUT.NCHRG.NDRILB.NDRILL
COMMON/NEWCOM/LJUMIN.LJUMOT.LNCHRG.LNDRLB.LNDRIL
000003
000003
000003
                DATA TT/0./
                IF (ICYCLE .GT. 1) GO TO 10
000003
                ICYCLE = 50
000006
                JUMOUT=0
000006
                IF (TOUT .LE. 0.0) TOUT=.25
000007
                SET INITIAL CONDITIONS
000012
                TT=TOUT
000013
             10 TT=TT-DT
000015
                LJUMOT=0
000015
                IF(TT .LE. 0.0) LJUMOT=1
000020
                RETURN
000021
                END
```

```
SUBROUTINE SETCHG (ICYCLE)
        AA.
                 SUBROUTINE SETCHG (ICYCLE)
 000003
                 COMMON/ALL/ XT,STR+IA+RQD+CS+TAMR+FLOW+IFLAG+AT+D+F+SK+T+DT+X+PR
                   XMAX+TMAX+TO+XO+XDISCH
               2.DX.DV
000003
                COMMON/MONEY/ DJMRD
000003
                 COMMON/BLAST/ ADB, ADH,
                                           CRIT.CBURN.CCAP.CEX.CM.CPL.CSTEFL.LBIT
               1. LBURN.LD.LDR.LSTEEL.MEN.ND.NH.NHB.PF.POB.POD.TCHG.TIN.TOUT
               2. TYPEPF. WPL
000003
                COMMON/OLDCOM/ JUMIN.JUMOUT.NCHRG.NDRILB.NDRILL
000003
                COMMON/NEWCOM/LJUMIN.LJUMOT.LNCHRG.LNDRLR.LNDRIL
          C
          C
                ELEMENT - ROCK DISINTEGRATION
          C
                GENERAL PROCESS - DRILL AND BLAST
          C
                ACTIVITY - SET CHARGE
          C
                TECHNIQUE = INDIVIDUAL HAND METHOD OR AUTOMATED
000003
                DATA CE+WEX+DTS+TT /4+0./
                IF (ICYCLE .NE. 1) GO TO 30
000003
000005
                ICYCLE = 50
000005
                NCHRG=0
000006
                IF (PF .NE. 0.0) GO TO 20
000007
             10 IF (TYPEPF .NE. 3.) GO TO 15
000011
                CF = 50.
000012
                WPL=0.5
000014
                CCAP=0.3
000015
                CPL=0.2
                CEX = 0.06
000017
000020
                CM=1.
000022
                GO TO 18
000023
             15 CF = 70.
000024
                WPL=0.
000025
                CPL=0.
000026
                 CCAP = 0.3
000030
                 CEX = 0.3
000031
                CM=1.
         C
                COMPUTE POWDER REQUIRED
000033
             18 PF=(27./144)*(ADH*CE/AT)*NH
000041
             20 WEX = PF/27.0 * AT * DX
         C
                COMPUTE TIME TO SET CHARGES
000044
                IF (TCHG.LE. 0.0) TCHG = 4./60.
000047
                IF (MEN .GT. 0) GO TO 21
000052
                TMFN=NH/8.+.5
000055
                MEN=INT (TMEN)
000056
            21 DTS=TCHG*NH/MEN
000061
                TT=DTS
000063
                PRINT 25.PF.DTS
000073
            30 TT=TT-DT
000075
               LNCHRG=0
000075
               IF (TT .GT. 0.0) RETURN
000100
               LNCHRG = 1
000101
               DJMRD=DJMRD+NH*(WPL*CPL)+NH*CCAP+WEX*CEX+DX*CM
            25 FORMAT (* POWDER FACTOR=*+F10.5+5X+*TIME TO SET CHARGES=*+F10.5)
000113
000113
               RETURN
000113
               END
                                      VI-128
```

BB. SUBROUTINE JETIMP

```
SHARDUTINE JETTMP
        FLEMENT - ROCK DISTUTEGRATION
GENERAL PROCESS - WATER JET IMPACT. CONTINUOUS OR INTERMITTANT PULSES
C
c
        ACTIVITY - JET IMPACT
        COMMONIALL / KT+STP+IA+PQD+CS+TAMP+FLOW+IFLAG+AT+D:F+SK+T+DT+F+PR
       1. XMAX.TMAX.TO.>O.XDISCH
        COMMON/MONEY/ DUMPO
        COMMON/NUET / RET-CPBRE-CSTPRU-DUMMUM-DNOZZ-DTCUFT-DTMUFT-DTMUFT
       1. ENERGJ. FTAGM. FTAJ. FTAJMP. ETAJPT. FOREJ. NGUNS. N IETS. PNO77. PDM
       2. PRJPM.PHI.SEN.TPHRL.VOLPRJ.VFLPRJ.VPRJ.XRJFT.VFLJET
        COMMUNICACOMY LARAPL.LMWJ.LMWJM.LMWJM.
                                                                        FHEATJ.FOWATP.FOX
       1. FOV
        COMMON/OLDCOMY NEARL . MAJ . MAJM . MAJR .
                                                                 VI.XG.STAWO.LTABH
        FOUTVALENCE (SIGC . STR)
        EQUIVALENCE (MROCK - ROD)
        EQUIVALENCE (MPI.MWJ)
EQUIVALENCE (LMPI.LMWJ)
        DATA PI /3.1415927/
        DATA INIT /0/
DATA NECEDIN /0/
        DATA FACTA-FACTR-FACTC-XFACT-QFACT /5+0./
                                        INITIALIZE VARIABLES
    10 IF (PR .EQ. 0.) PR = 0.015
IF (FTAJ .EQ. 0.) ETAJ = 0.3
IF (ETAIMP .EQ. 0.) ETAIMP = 0.2
IF (EMERGJ .ME. 0.) GO TO 100
IF (MODEJ .EQ. 1) GO TO 70
        ENERGY NOT INPUT. MODEY = CONTINUOUS

IF (SIGC .LT. 5.0 .OR. SIGC .GT. 25.0) GO TO BO
ENERGY = 47.0 & EXP (.09 * SIGC)
         GO TO 100
                                        ENERGU NOT INPUT. MODEU . INTERMITTENT
    70 IF (SIGC .LT. 15.0 .OR. SIGC .GT. 35.0) GO TO 80 ENERGJ = 100. * FXP (.072 * SIGC)
         SO TO 100
    55 FORMAT (105HOURT ENERGY MER VOLUME OF ROCK BROKEN MUST PE SPECIFIE OD FOR THE ROCK STRENGTH ENCOUNTERED. RUN TEMMINATED. )
CALL EXIT
                                        GENERATE FACTORS PEDUTRED FOR CALCS
   100 MFACT = PI + 0 + 0 / 4.

YFACT = PI + 04027 + 08027 / 4.
         7FACT = PHLSEN * PPM / 60.
         XW9K = PV077 + 193.2 / 1.3
         VFLUFT = SORT (YWPK)
         OFACT = VFL FT * NUFTS * YFACT * 25.
POWREA = 0.0174 * 0N077 * DN0ZZ * PN07Z ** 1.5
IF (MODEJ .FO. 0) GO TO IIO
SFACT = OFACT * 7FACT
         POWREA = POWEA + ZEACT
    110 CONTINUE
         TOTE R = NUFTS + POMPFA
PWRIN = TOTEWR / ETAU
         FACTA = PWRIN + PR + 0.7452
         FACTS = (1. - STAJ . ETAIMP) . PHRIN . 2545.2
         FACTC = 13.75 * TOTPWR / (XFACT * ENERGY)
IS CALL FOR INITIALIZATION ONLY
          INIT = 1
         IF (NEEDIN .EO. 0) GO TO 999
NEEDIN = 0
         GO TO 300
```



CC. SUBROUTINE JETAGN

```
SUPPOUTINE JETAGN
C
       FLEMENT - ROCK DISINTEGRATION GENERAL PROCESS - WATER JET ACTIVITY - REPOSITION . ALIGN
CCC
                                    OR PROJECTILE FRAGMENTATION
       COMMON/ALL/ XT-STR-IA-ROD-CS-TAMB-FLOW-IFLAG-AT-D-F-SK-T-DT-K-PR
      I. XMAX.TMAX.TO.XO.XDISCH
COMMON/MONEY/ DJMRD
COMMON/NJET / PLT.CPAPL.CSTPRJ.DJMWJM.DNOZZ.DTCJFT.DTMJET.DTRJET
      I. ENERGI-FTAGN-ETAJ-FTAIMP-FTAIPT-NONEJ-NGUNS-NJETS-PNO77-PPM
           PRJPM.PULSED.TRBPL.VOLPRJ.VFLPRJ.WPPJ.XRJET.VFLJET
                                                                 FHFATJ.FOWATR.FOX
       COMMON/NEWCOM/ LNRARL . LMWJ . LMWJM . LMWJR .
       COMMON/OFUCOMY MATER - MATER MATER
                                                           HEATJ-QWATR-DX-DV
       FOUTVALENCE (SIGC.STR)
       EQUIVALENCE (WROCK - ROD)
       EQUIVALENCE (MPI+MWJ)
EQUIVALENCE (LMPI+LMWJ)
       DATA DISTJ /0./
       DATA ELPSO /0./
DATA OLDPOS /0./
       DATA INIT /0/
        ON MICESA ATAC
       ENTRY PRIJAGN
                                    INITIALIZE
C
   IF (STRUET .FQ. 0.) STRUET = 0.25
        OLDPOS=X
        INIT = I
           ('IFEDIN .FQ. 0) GO TO 999
        NEEDIN = 0
       GO TO 50
                                    NORMAL ENTRIES
        ENTRY JETPOS
        ENTRY PRUPOS
        IF (INIT .EQ. 1) GO TO 50
        MEEDIN = I
        60 TO 10
    50 IF (MWJ .EQ. 0) GO TO 100
                                    WATER JET (OR PROJECTILE GUN) STOPPED
C
        IF (MWJR .EQ. 1) GO TO 999

REPOSITIONING NOT YET COMPLETED
C
        ELPSO = FLPSO + DT
        IF (ELPSD .LT. DTRJET) GO TO 999
        LMWJR = I
        LMWJ = LMWJ - I
        OLDPOS = X
        ELP50 = 0.
        GO TO 999
                                    WATER JET (OR PROJECTILE GUN) IS OPERATING
C
   100 DISTU = X - OLDPOS + FOX
NOTE +++ FOR A GIVEN CYCLE+ FOX MUST BE CALCULATED REFORE THIS
Ċ
              STATEMENT IS EXECUTED. SINCE. TO HE CONSISTENT WITH OTHER LOGIC. DISTU MUST REFLECT THE DISTANCE AT THE END OF THE CURRENT CYCLE. HENCE. JET OR PRJIMP MUST HE CALLED PEFONE
CCC
              CALLING JETPOS OR PRJPOS.
```

IF (DISTU.LT. XRUET) GO TO 999
LMWU = LMWU • I
LMWUR = 0
999 RFTURN
ENO

DD. SUBROUTINE JETMNT

```
SUPPOUTINE JETMNT
C
                ELEMENT - ROCK DISINTEGRATION
GENERL PROCESS-WATER LET AND PROJECTILE
ACTIVITY - GENERAL MAINTENANCE + REPAIR
cc
Ċ
                 COMMON/ALL/ XT.STR.TA.POD.CS.TAMR.FLOW.TFLAG.AT.D.E.SK.T.DT.X.PR
               1. XMAX.TMAX.TA.XID.XID.XOTSCH
                 COMMON/MONETY DIMAD
COMMON/NUET / RET+CPRRL+CSTPPJ+DJMWJM+DNO7Z+DTCJFT+DTMJET+DTPJFT
               1. ENERGJ.ETAGN.ETAJ.ETAIMP.ETAIPT.MODEJ.NGUNS.NJETS.PN077.PPM
                       ENFAGJETION OF TRIPE TRIPE TRIPE TRIPE TO THE TOTAL TO THE TRIPE TO THE TRIPE TO THE TRIPE TO THE TRIPE TRIPE TO THE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRIPE TRI
                 COMMON/NEWCOM/ LNRARL .LMW.J.LMWJM.LMWJR.
               T. FDV
COMMON/OLDCOM/ NRARL.MWJ.MWJM.MWJR.
                                                                                                                                    HEATJ. QWATR. DX. OV
                 EQUIVALENCE (STAC.STR)
                 EDUTVALENCE (WADCK . KOD)
                 FOUTVALFACE (HAI-MAN)
FOUTVALENCE (TALI-MAN)
                  DATA INIT /0/
                  DATA NEEDIN /0/
                  DATA IPRU /0/
                                                                                  INITIALIZATION
 C
          10 IF (DTCJET .EO. 0.) DTCJET = 6.

IF (DTMJET .EO. 0.) DTMJET = 2.

IF (IPRJ .EQ. 1 .AND. OJMWJM.EO.0.) OJMWJM = 200.
                  THAT = 0.
                   TIMBT = OTCJET
                   D=CHP
                   J=MLWW
                   INIT = 1
                    IF (NFEOIN .FO. 0) GO TO 999
                   NFFDIN = 0
                   SO TO 200
                   ENTRY PRJMNT
                   IPRJ = I
                   GO TO 10
                                                                                   NORMAL ENTRIES
  C
                   ENTRY PRIRPR
                    102J = 1
                    ENTRY JETROR
                    IF (INIT .EQ. T) GO TO 200
                    VEFDIN . I
                    60 TO TO
                                                                                    IS MAINTENANCE IN PROGRESS
  С
        200 IF (MWJM .EQ. 0) GO TO 400
                                                                                    IS MAINTENANCE REQUIRED
   С
                    TO - TAPLE = TAPLE
                    IF (TIMBT .GT. 0.) GO TO 999
                                                                                    IS REPOSITIONING IN PROGRESS
   C
                    1F (4WJR .EQ. 0) GO TO 999
                    LMM74 = 0
                    FMA1 = FAM1 + 1
                    GO TO 999
                                                                                    UPDATE PROGRESS OF MAINTENANCE
   C
         400 THAT = THAT + DT
                    IF (THAT .LT. DIMUET) GO TO 999
   C
                    LUWJM = T
                    LMWJ = LMWJ - T
NOTE ** TO FORCE REPOSITIONING AFTER COMPLETION OF MAINTENANCE.
REPLACE STATEMENT #LMWJ = LMWJ-1# WITH #LMWJR=0# .
                    DUMBD = DUMBUM % DUMBD
TIMAT = OTCUET
                     TMNT = 0.
         999 RETURN
                    END
```

EE. SUBROUTINE PROJTL

```
SURROUTINE PROJEL
       ELFMENT - ROCK DISINTEGRATION
GENERAL PROCESS - PROJECTILE FRAGMENTATION
ACTIVITY - PROJECTILE IMPACT
OR PROJECTILE FRAGMENTATION
CCC
        COMMON/ALL/ XT.STR.IA.PQD.CS.TAMB.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
           XMAX+TMAX+TO+XO+XDISCH
        COMMON/MONEY/ DIMAD COMMON/NUT / PLT.CPRRL.CSTPRJ.DJMWJM.DNGZZ.DTCJFT.DTMJFT.DTPJFT
       I. ENERGJ. ETAGY. ETAJ. ETAIMP. ETAIPT. MODEJ. NGUNS. NJETS. PNO7Z. PPM
2. PRJPM. PULSED. TRARL. VOLPRJ. VFLPRJ. WPRJ. XRJET
        COMMON/NEWCOM/ LNAARL . LMAJ . LMWJM . LMWJR .
                                                                       FHEATJ.FOWATR.FOX
       1. FDV
        COMMON/OLDCOM/ NRARL . MWJ. MWJM . MWJR .
                                                               HEATJ.QWATR.DX.DV
        EDUTVALENCE (WATCK . CS)
        FOUTVALENCE (SIGC. STR)
         FOUTVALENCE (MPI.MWJ)
         ENJIVALENCE ILMPI.LMWJ)
        DATA INIT /0/
DATA NEEDIN /0/
        DATA FACTA . FACTB . FACTC . FACTD . FACTE /5-0 . /
    INITIALIZE

10 IF (ETAGN .EQ. 0.) ETAGN = 0.3

IF (ETAIPT .EQ. 0.) ETAIPT = 0.2
C
                                       PPOJECTILE ENERGY
IS CALL FOR INITIALIZATION ONLY
         INIT = 1
         IF (NFEDIN .FO. 0) GD TO 999
NFEDIN = 0
         GO TO 200
                                        NORMAL ENTRY
C
         ENTRY PRJIMP
         IF (INIT .EQ. 1) GO TO 200 NEEDIN # I
   60 TO 10
200 EPFT = WPRJ + VELPRJ + VELPRJ / 64.4
                                        PROJECTILE DENSITY
C
         RHOP=1728.**PRJ/VOLPRJ
                                        ROCK DENSITY
 C
         RHOR=WROCK
                                        POCK FRAGMENTED PER PROJECTILE
 C
         XHPK = RHOP / PHOR
         RMASS=I.63F-5*(SGRT(XWRK)*EPFT)**1.189
                                        CONSTRUCT FACTORS USED FOR FACH TIME INCREMENT
 C
         IF (IFST .ED. 1) 60 TO 11
         PRINT III. EPFT. RHOP . RHOR
   111 FORMAT(11. SHEPFT=.F14.4.6H RHOP=.F14.4.6H RHOP=.F14.4)

PPINT 112.XMPK.RMASS.RVOLFT

112 FORMAT(1X. 6H XWPK=.E14.4.7H PMASS=.E14.4.8H RVOLFT=.E14.4)
                                       END OF DERUG
     II XWOK = PRJOH . 60.
FACTA = RVOLET . NGUNS . XWRK
         FACTR = 3.1415927 * 0 * 0 / 4.
```

```
FACTC = EPFT * NGUNS * XWRK * 3.766E-7 / ETAGN

FACTD = CSTPRJ * XWRK

FACTE = 3413.0 * (1 - ETAGN * ETAIPT)

FOU = 0.

FOX = 0.

FHEATJ=0.

IF (MPI .GE. 1) GO TO 999

ROCK FRAGMENTED DURING DELTA-T

FOX = FOX / FACTA

C POWER COSTS

TOTKWH = FACTC * DT

PCST = TOTKWH * PR

PROJECTILE COSTS

C DJMRD = DJMRD + PCST * PJCST

FHEATJ=TOTKWH*FACTE

999 RETURN
END
```

FF. SUBROUTINE PRJBR

```
SHENDATING OF IES
      FLENENT - ROCK DIVINTEGRATION
GENERAL PROCESS - PROJECTILE FRAGMENTATION
ACTIVITY - BARREL REPLACEMENT
      COMMONIVALLY XT.STD. FA. POD. CS. TAMR. FLOW. IFLAG. AT. D. F. SK. T. OT. X. PR
     1. XMAX . TMAX . TO . XO . XDISCH
     1. EMPROJETICM ETAJESTATME + FTATMT + MODEJ + NGUNS + NJETS + PNOZZ + PM
         ENERGU-ETICM FETAU-FTAUM-FIRITISHONDUST PROPHISED-TRHRE-VOLPPU-VFLPHJ-WPRU-XRUST PHEATU-FOWATP-FDX
      CUMMUNIAMENCOMY ENDABLARMANALAMANA FAMANA
     I. FOV
                                                      HEATJ. DWATR. DX. DV
      CUMNUMANTWW. LMM- JAVAN ZHUJOJOTOVAL
       FOITVALFNOF (SIGU.STR)
      ECUTVALENCE (VANCK+CS)
      FOUTVALENCE (MPI+MWJ)
FOUTVALENCE (LMBI+MMJ)
      DATA THR /0./
      OATA OPTIM /0./
      DATA MEEDIN 707
      DATA TT.CFACT /200./
                                  INITIAL 17E
   10 TT = TRBPL * NGUNS
      4942L=1
      CFACT = CPAPL + NGUNS
       1417 = I
       IF (MEFDIN .FQ. 0) GO TO 999
       VEEDIN = 0
      00S CT 00
                                  NORMAL ENTRY
C
       ENTRY PRUARE
IF (INIT .FG. I) 60 TO 200
NEEDIN = 1
       60 TO 10
                                 IS BARPFL REPLACEMENT IN PROGRESS
С
  200 IF INSARL .FD. 0) GO TO 400
                                  REPLACEMENT NOT IN PROGRESS. IS IT REDUIRED
C
       OPTIM = OPTIM + DT
       IF (GPTIM .LT. BLT) GO TO 999
IS REPOSITIONING IN PROGRESS
С
       TF (4475 .EQ. 9) 60 TO 999
       [ + 1 = 1 = 1 = 1
       GO TO 999
                                  REPLACEMENT IN PROGRESS. UPDATE PROGRESS
  400 THR = THR + DT
       IF (THR .LT. TT) 50 TO 999
                                  REPLACEMENT COMPLETED
       FAST = FAST - 1
       DIMAD = DUMAD + CFACT
       DOTIM = 0.
   999 PETURN
       540
```



GG. SUBROUTINE MUKLOD

```
SUBROUTINE MUKLOD
      FLEMENT - MATERIALS HANDLING GENERAL PROCESS - MACHINE LOADERS + SHOVELS
       ACTIVITY - LOADING MUCK AT FACE
C
      CDMMON/ALL/ XT.STR.IA.ROD.CS.TAMR.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
     I. XMAX.THAX.TO.XO.XDISCH
      COMMON/WHEELS/ NCARS.MLTYP.QUC.WUC
COMMON/CONVEY/ &CM.OTRS.DWM.FF.FL.HP.OC.SMIN.WRI.
         WP. XLF . NSURGE . OE . OP . SM . DTCB . DTMR . AR . VRI . NEXON . NGEO . XE . LNSURG .
          STIME . ODMY . DTMI . DTMO . FLM
       COMMON/NEWCOM/ LMACON+LMCAPC+LNSPLC+LLOADR+FOL+LMKIN+LMUKDT+LNRYHY
      1.LTSTAT (25.4) .LKSTOP (25) .LLVHCL.FOV
      COMMON/OLOCOM/ MACON.MCAPC.NSPLIC.LOADR.QL.MKIN.MUKOT.NBYRY
        VALENCE (LLOOP .LLOADR)
      DATA NORS-INIT-NEEDIN /3*0/
  IOO IF (COMP .EO. O.) ODMR = 5400.

IF (STIME .EO. O.) STIME = .05

CSPERK = CS / (SK * 2000.)
       INIT = 1
       IF (NFFDIN .FO. 0) GO TO 900
       NEEDIN = 0
       GO TO 120
                                   NORMAL ENTRY
C
       ENTRY LODMUK
       IF (INIT.EQ. 1) GO TO 120
       NEFDIN = I
       GO TO 100
  IZO IF (MLTYP .EQ. 2) GO TO SOO UNITIZED MAIN LINE SYSTEM
C
       IF (LVEHCL .FO. 0) GO TO 900
                                   A UNIT IS AVAILABLE FOR LOADING
C
       FDV=DV
       LLOOR = 0
       IF (TIMEL .GT. 0.) GO TO 300
DO = ODMR + DT
  130 XWRK=FDV#SK
       IF (XWRK - DO .GE. 0.) GO TO 150
DD = XWRK
       LLOOR = 1
       FDV=0.
60 TO 160
  150 FDV=FDV-(DQ/SK)
                                   VOL + WEIGHT CAP OF UNIT NOW BEING FILLED
C
  160 QUF = QUF + DQ
WIF = WUF + (D2 * CSPERK)
       IF (200 .GT. QUF .ANO. WUC .GT. WHF) GO TO 900 UNIT IS FILLED + CAN BE RELEASED
C
       XWRK = OUF - OUC
       FDV=FDV+XW9K/SK
       QUF=0.
       WUF=0.
       TIMEL = XWRK / ODMR
```

```
C

300 TIMEL = TIMEL + DT

320 IF (TIMEL + LT. STIME) GO TO 900
DD = DDMR * (TIMEL + STIME)
TIMEL = 0.
IF (NCARS *FO. 0) GO TO 350
NCRS = NCRS + 1
IF(NCPS *LE. NCARS) GO TO 130
PELEASE VEHICLE

C

4005 = 0
350 I = LYFECL
LISTAT(1:1)=7
LKSTOP(I)=5
DUF = 0.
GO TO 130

C

CONTINUOUS MAIN LINE SYSTEM

C

500 DO = QDMR * DT
**NCPS=0**
LLDDP = 0
XMRK = DV * CK
IF (XWRN - DO *GF. 0.) GO TO 550
DO = XWPK
LLDDP = 1
FDV=0.
GO TO 600
SEO FOV=DUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF=QUFOT
900 DIFF
```



HH. SUBROUTINE MUKIN

```
SUPPOUTINE MIKIN
0000000
        ELEMENT - MATERIALS HANDLING CENERAL PROCESS - MACHINE LOADERS + SHOVELS ACTIVITY - MOVE MUCKERS TO MUCK PILE
        ***CUPRENTLY. THE CONTROL PROGRAM MUST SET MKIN TO 0 TO
                 INITIATE MOVING IN.
        COMMON/ALL/ YT-STP+IA-POD+CS+TAMH+FLOW+IFLAG+AT+D+F+SK+T+DT+X+PR
       I. XMAX.TMAK.TO.XO.XDISCH
      COMMON/CONVEY/ ACM-DIRS-DWM-FE-FL-HP-OC-SMIN-WRI-

I WP-XLF-NSUMGE-DE-GP-SM-DICH-DIMM-AR-VRI-NEXGN-NGFO-XF-LNSUMG-

STIME-ODMM-DIMI-DIMM-FLM
       COMMONZ'S WCONZ LMACONAL MCAPC .LNSZLC.LLOADR.FOL.LMKIN.LMUKOT.LNBYRY
I.LTSTAT (25.4) .LKSTOP (25) .LLVMCL.FDV
        COMMON/OLDCOMY MACON-MCAPC.NSPLIC.LOADR.QL.MKIN.MIKOT.NRYRY
       I.ITSTAT (25.4) .KSTDP (25) .LVEHCL.DV
EQUIVALENCE (LLODR.LLOADR)
        DATA INIT +NEFDIN /200/
DATA TIMIN /0./
                                       INITIALIZATION
  100 IF (DTM1 .EQ. 6.) DTM1 = 1./12.
        IPTO = PIPIT
        1411 = 1
IF (MEEDIN .EQ. 0) GO TO 900
        NEEDIN = 0
                                        NORMAL ENTRY
С
        ENTRY INMIK
        IF (!NIT .EQ. 1) 60 TO 200
NEEDIN = 1
GO TO 100
200 IF (MKIN .NE. 0) GO TO 900
C
                                       MUCKERS REING MOVED TO MUCKPILE
        TIMIN = TIMIN - DT
IF (TIMIN .GT. 0.) GO TO 900
        LMKIN = 1
  TIMIN = DTMI
        END
```

II. SUBROUTINE MUKOUT

```
SUPROUTINE MUKDUT
CCCC
            ELEMENT - MATERIALS HAT DUTTON
GENERAL PROCESS - MACHINE LOADERS + SHOVELS
ACTIVITY - MOVE MICKERS AWAY FROM FACE
            ***CHRRENTLY. THE CONTROL PROGRAM MUST SET MUKOT TO 0 TO
          INITIATE MOVING OUT.

COMMODIZATE VISTERIA SON CS. TAMBRELOW-IFLAG. AT. O.E. SK. T. OT. Y. PR

1. XMAY.TMAK.TO.EO.E. NISCH
            COMMO IZAMETERS ACARS . METYP . DIC . WILC
          COMMO 1/A-FELSY ACARS -METYP-30.C-WHO
COMMON/CONVEYY ACM-NIPS-DAM-EE-FE-HP-00-SMIN-ARI

WP-XLF-NSURGE-0E-1P-SM-DIRB-0TOR-0TH-04-VRI-NEXON-NCED-*F-ENSURGE
STIME-00MA-DIMI-DIMO-FEM
COMMON/NE-COMY EMACON-EMACHOL-NCPEC-ELOADR-FGE-EMAIN-EMUPOT-ENRYRY
1-LTSTAT(25-4)-EKSTOP(25)-EEVENCE-FDV
COMMON/DE0COMY MACON-MCAPC-NSPEEC-ENDAR-DE-MKIN-MUKOT-NRYRY
1-ITSTAT(25-4)-KSTOP(25)-EVENCE-DV
EQUIVALENCE(LECOR-LECAPR)

TATA-NIT-NEEDIM (2007)
            DATA INIT-NEFDIN /200/
DATA TIM /0./
C
                                                             INITIALIZE
    100 IF (DTMO .EQ. 0.) DTMO = 1./17.
            TIM = DTMO
TMIT = 1
IF (MEEDIN .FQ. 0) GO TO 900
            NEFOTH = 0
            60 TO 200
Ċ
                                                             NORMAL FUTRY
            ENTRY OUTMUK
IF (1911 .FO. 1) GO TO 200
NEEDIN = I
   50 TO 100
200 IF (MUNOT .N.F. 0) GO TO 900
TIM = TIM - DT
            IF (TIM .GT. 0.) GO TO 900
            TT4 = 0T40
    900 RETURN
```

JJ. SUBROUTINE TRUKHL

```
SUBROUTINE TPUYHL
C
             ELEMENT - MATERI LS HANDLING
GENERAL PROCESS - TRUCK SYSTEM
ACTIVITY - LONG HAUL MUCK TRANSPORT
000
              TECHNIQUE - PUBBER-TIPED INDIVIQUAL DIESEL POWER TRUCK UNITS
                             DUAL ROADHAY)
        COMMONIVALLY XT-STP+14+P30+CS-TAMA+FLOW+1FLAG+AT+0+F+SK+T+OT+X+PP
       1. XMAX.TMAX.TO.XD. CDISCHOX.CV
        COMMON/AMEFLEY AF. AF. AF. AMAY. AMEL. PSL. CARCAP. CP. OF. OF. OTAC. OTMA. DTV
       I. EL.FC.FR.FT.HPA.HPEA.HPEV.HPFV.HPV.TS#(25) .LOCO.MC.ML.MLTYP
            MCARS+NPOTHT+NTD+NTTNT++NTM+NTM+X+HUMLD+XP+NTMILP+NTMLPR+NTMACK
       3. GUC.SL.STATUS (30) .TOUR /X (20) .TOURYY (20) .TMAINT.THE .VO.VS.VE .VE
        . VMAX.WC.WL.JHY (24).W42.WC.XDS.BMAXL
CDWDYVCONVEY/ 15.ACM.DMAINT.DTCH.DTHS.DTHS.DTMI.DTMO.DWY.EF.FL
       1. HP.LNSURG. MEXQUINGED. NSURGE . DC. DE. DDMP. DP. SM. SMIM. STIME . VAI
        COMMON/NEWCOMY LIFTLO.LKSTOP(25).LKUNLD.LLSTOP.LLVHCL.LNHYRY
       T.LNSWCH.LNTROA.LNVHCL.LNMSXT.FSWTCH(20).FTFC(25).FTOP(25)
       3. FISTAT (25.4) . FUTTME (25) .LLOADR
        COMMON/OLDCOMY IF ILD . KSTOP (25) . KUNLO . LSTOP . LVEHCL . NPYRY . MSWCH
       1. NTROBANYEMCL SUMSET . SALTCH(20) . TFC (25) . TOP (25) . TSTAT (25.4)
        DITIMETES).LOADR
DIMENSION LISTAT(25.4).TISTAT(25.4)
EDHIVALENCE (COMPLUS IFILD).COMPLES IFILD).COMPLES INTRAINSNIPPONS
       1. (LVEHCL.LTPATH.LTPUCK).
2. (FTSTAT.LTSTAT).(TSTAT.TSTAT)
3. (LLVHCL.LLTPAM.LLTRUK).(LNVHCL.LNTRAN.LMTRUK)
                                                                         (NTDA. VTRDA) .
        DIMENSION STATE (25.4)
DIMENSION ISTATE (25.4)
         EDUTYALENCE (STATE . ISTATE)
         DATA STATE /1990./
        DATA JSTOP /25=0/
         DIMENSTON TEMS (25)
DIMENSTON TEMT (25)
         DATA INITSH. IPETSH /240/
         DATA IDPTN /1/
EQUIVALENCE (THE+HE)
         04TA TEMS /25*0./
         DATA TEMT /25+0./
DATA AFMAX.TLIM-TLIMF.WECT.#FCZ.WFFACT.WFFACZ.HPEVP /8+0./
DATA HPFAC.HPAFAC.HPVFAC.WEFAC.FRFAC.FRWF.AEMAX /7+0./
         DATA HPFVP.HPEAH.HPFAH.DINCP.CPFC.VFFT.VFFT.VDSO.DELMAX /940./
                                        PARAMETER INITIALIZATION
   100 THITS# = 1
         IF INTRUCK .EQ. 0) NTRUCK = 1
         ITSTAT(1.1) = 2
TSTAT(1.2) = 0.
TSTAT(1.3) = 0.
         TSTAT(1.4) = 0.
DD 120 I=1.25
IS4(I) = 0
         TE4T(I) = 0
         TENS(1) = 0.
   120 CONTINUE
         IF INE .EQ. 0.1 GO TO 200
                                        OPTION 2
 C
          IF (FR .EO. 0.) FR = 65.
         IF (EL .ED. 0.) EL = 0.85
IF (FT .ED. 0.) FT = 0.36
IF (AF .FD. 0.) AE = 99999.
         IF (AF .EO. O.) AF = AE
HPFAC = EL * 375.
          HDAFAC = HDFAC . HPA
         HPVF2C = HPFAC + HPV
```

```
WEFAC = HE . (1.35 ° CARCAP)
FPFAC = FR & HFFAC
             FRAF = FR . WE
             AEMAX = AF
             AFHAX = AF
             XWRK = FT + 3000.
            XWRK = FT + 0)00,

TLIM = XWRK = VE

TLIMF = XW'X < VEFAC

WEC1 = WE / 39.4

MFFAC2 = 39.4 / WE

WFFAC2 = JFFAC / 39.4

XWRK = H0/FAC / F0/F

IF (VE = (VF - X/MA) .OE. 0.)VF = XWRX

XWRK = H0/FAC / F0/FAC

IF (VF = (VF - X/MA) .OE. 0.) VF = XWRX

MDEV0 = F0/FAC = VF / H0/FAC

MDFV0 = F0/FAC = VF / H0/FAC
             HPFVP = FREAC P VF / HPFAC
            GD TO 250
                                                       OPTION 1
     SUNTINOS OOS
            HOFAH = HOFA
            HOFAH = HOFA
 250 DINC? = 50.
                                                       BOTH OPTIONS
    250 01NC# = 50.

IF (10P1M .FO. 2) 30 10 255

XMR* = 2640. • VF • VF / DE

IF (XMP* .LT. 01NT*) 01NC# = XMP*

XMPK = 2640. • (VF • VF - VD • VD) / DF

IF (XMP* .LT. 01NC#) 01NC# = XMP*

255 0FLMAX = 01NT# / (5280. • VE)

IF (CP .FO. 0.) CP = 0.14

IF (FC .FO. 0.) CP = 0.06
           IF (FC .E). n.) FC = 0.06
CPFC = CP . FC
VFFT = VF . 5250.
           VFFT = VF * 5280.
VNS1 = V1 * V1
PPINT 260. VF. VF
    260 FORMAT (12HOTRUCK VF = +F10.3-5H VF =+ F10.3)
WAS CALL FOR INITIALIZATION ONLY
            IF (IRETS+) 270,999,270
    270 IRETSW = 0
           SO TO 350
C
C
                                                      NORMAL ENTRY
C
           ENTRY TRUKTA
                                                    HAS INITIALIZATION REEN PERFORMED
           IF (1"1154) 350.320.350
   320 IPETS4 = 1
          GO TO 100
   350 XWOR = (GT / DELMAX) + 1
NITER = XVOR
           AMAK = MILLH
           TERAC = XHRF - YWRK
C
                                                    RETRIEVE /OLDWRK/ VARIABLES
           00 355 J= 1+VTPHCK
          STATE (J+1) = TSTAT (J+1)

STATE (J+2) = TSTAT (J+2)

STATE (J+3) = TSTAT (J+3)
           STATE (J.4) = TSTAT (J.4)
           JSTOP(J) = KSTOP(J)
   355 CONTINUE
         ISTOPT = LSTOP
   360 LLTP IK = 0
          OFLIAT = DELVAY
          IF (MITER .EG. 1) DELTAT = TEPAC . DELMAX
D72640 = DELTAT . 2640.
          DIVERT = DELTAT . VEFT
```

```
DTVFFT = DELTAT • VFFT
DTCPFC = DELTAT • CPFC
OTDAYS = DELTAT / 24.
IMPK = ISTOPT • I
      60 TO (500.400.450) . IWAK
                                      SYSTEM MUST BE SHUT DOWN
 400 DO 420 J=I.NTRUCK
IF (JSTOP(J) .NE. 0) GO TO 420
IMRK = ISTATE(J.1)
       IF ((INRK-10) . (IMRK-II) .EO. 0) 60 TO 420
       JST3P(J) = 4
IF ((IWRK - 6)*(IWRK-7) .FG. 0) 60 TO 420
       IASK = INSK \ 5

TMSK = (INSK + 1) \ 5
       ISTATE (J.1) = 7
       IF (IWPK .FO. JWRK) ISTATE(J.1) = 6
 420 CONTINUE
       GO TO 475
                                      SYSTEM MUST BE BROUGHT UP
 450 00 470 J=I+NTRUCK
       IF (USTOP(U) .NE. 4) GO TO 470
       JSTOP(J) = 0

JWRK = [STATF(J+1)

IF (JWRK +EQ+ 0) ISTATF(J+1) = 2

IF (JWRK +EQ+ 1) ISTATE(J+1) = 3
  470 CONTINUE
  475 ISTOPT = 0
                                      APPLY DELTA-T TO ALL TRUCKS
  500 00 750 I = I.NTRUCK
       OFLTAC = 0.
       STATE (1.4) = STATE (1.4) + DTDAYS
        ISTAT=INT(STATF(1+1))
        TPOS = STATE(1.2)
       TSPO = STATE(1.3)
C
                                                     CRASH CODING
        TATEL = CTATEL
        OTPOS = TPOS
        DISPO = TSPD
                                                     END CRASH CODING
¢
        [JSTOP = JSTOP([)
        TF451 = TF45(1)
        TEMTI = TEMT(I)
        IWAK=ISTAT+1
        50 TO (510.750.550.570.590.610.630.650.750.750.750.750).IWAK
                                       TRUCK IS EMPTY. AND HAS STOPPED
  510 IF (IJSTOP .GT. 1) GO TO 750
                                       TRUCK IS BEING LOADED
       LTRUCK = 1
        GO TO 750
                                       TRUCK IS ACCELERATING EMPTY
  550 IF (IDPTN - 1) 584.753.584
551 AFA = PPA - FRWE
       IF (AFA .LT. O.) AFA = O.
AF = AFA = 4FC?
       AF = AFA = 4-02

IF (AF. GT. AEMAX) AE = AFMAX

IF (DF .GT. 0.) GO TO 553

TENTI = TENTI + DELTAT

TENSI = TENSI + DT2640 + (AE + DELTAT + 2. + TSPD)
  553 YI = AF * CELTAT
TPDS = TPOS * 7T2640 * (YI * 2. * TSPD)
TSPD = TSPD * YI
        IF (IDPTN .En. 2) HPEAH= (AE*WECI*FRVF) * TSPD/HPFAC
IF (HPA .GT. 0. .AND. HPEAH .GT. HPA) HPEAH = HPA
       DELTAC = HPEAH
        IF (TSPO - VF) 559.554.554
  554 ISTAT = 4
```

```
1527 = 15
  IS TRUCK APPROACHING FACE AREA

558 IF (1101% .60. 1) 30 TO 540

IF (07. .7. 0.) 30 TO 540

IF (2. .7 TPOS .67. A) 1514T = 6
                                          CRASH CODING NEEDED WHEN DEZDE = 0 FIFED
        67 TO 544
  560 9 = 1920 + 1920 + 2640. / OF
                                                         CRASH CODING
         *** = [ = 5 + 4
        IF (6.24 .0F. 6) 151AT = 4
IF (6845 .0T. x .450. ISTATO .FG. 2) 50 TO 555
                                                         FND CRASH COSTNO
C
        GO TO 693
                                                        CRASH CODING
                                         PREVENT TRUCK FROM CHASHING EMPTY
   565 Y + 28 = (FE + (X + OT + OS) + (26 + O. C. TS2P + OTSPO)))/(2540. C(DE + AE))
         IF (x 484 .LT. 1.) 50 TO 598
TS90x = $18T(x484)
        TSPOX = STRT(KHRA)

DTRP = (15014 - DTSPO) / AF

TPOSX = OT-OS - (TPRP25640.)*(AF*OTPP + 2.*GTSPO)

IF (TPOSX LI. DTPDS) GO TO 698

OFLITAC = 6854 * TSPOX / TSPO

DTPPP = OFLITAT - OTPP

YI = "E * OTPPP
         TPPS = TPOSX + (2640. + DTPPP) + (2. + TSPDX - Y1)
         TSP0 = TSP04
         S0 TO 632
                                                         END CRASH CODING
C
                                         TRUCK IS ACCELEPATING FULL
C
  570 IF (:0PTN - 1) 584+572+584
   571 AFA = NAA - FREAC

IF (AFA .LT. C.) AFA = 0.

AF = .FFAC1 - AFA
        IF (AF .01. AFMAX) AF = AFMAX

IF (AF .07. 0.) AO IN 572

TEMI = TEMI + DECIAT

TEMSI = TEMSI + DIRAGO * (AF*DELTAT + 2.*TSPD)
   572 Y1 = AF . "FLTST
         TPOS=TPOS-DELT4T+26-0.4 (Y1+2.+TSPD)
         TSP0 = TSP7 . Y1
         IF (IDPTY .FO. 2) HEFAHE (AFRWEFACR*FREAC) * TSROVHPFAC
IF (HPA .GT. 0. .ANC. HPFAH .GT. HPA) HPFAH = HPA
         DELTAC = HPF1H
   IF (TSUN - VE) 578.574.574
574 (STAT = 5
         TSPD = VF
                                          TE TRUCK APPROACHING DISCHARGE POINT
   578 IF (10PTN .ED. 1) GO T
         IF (IDPIN .EV. () 07

IF (OF .GI. 0.) GO IO 07

IF (X - TPOS .LI. TPUS .GO IO 698

CRASH CODING MESDED WHEN DEVDE = 0 FIXED
С
          TENT = TENT + (1500 - VO) / TSPD
         IS#(I) = 100
         50 TO 498
   580 A = 2440. * (TSPD*ISPD - VDSD) / DF
IF (TPDS .GT. A) GO TO 69A
ISTAT = 7
         15.(1) = 100
                                                        CB724 COULTY?
C
         IF (TPOS .LT. # .4%). ISTATO .FO. 7) 60 T) 542
                                                        END CRASH COOTING
C
         60 10 694
                                                        CRASH CODING
С
                                          PREVENT TRUCK FANT CHARACIA FULL
```



```
582 XWPK=(DF*(AF*0TP05*2640.*0TSPD*DTSPD)*2640.*AF*VDS0) /
                         (2640.*(DF+4F1)
       IF (XWPK .LT. 1.) 60 TO 698
        TEPDY = SCRTIXANKI
       TSPDX = SGPT(X4PX)
DTPP = (TSPDX - OTSPD) / AF
TPDSX = OTPOS - (DTPP*2640.)*(AF*DTPP * 2.*OTSPD)
IF (TPDSX .GT. OTPOS) GO TO 698
DFLTAC = HPFA * TSPCX / TSPD
DTPPP = DELTAT - DTPP
YI = OF * DTPPP

**TOTAL **TSPDX - YI
        TPOS = TPOSX - (2640. * DTPPP) * (7. * TSPDX - Y1)
        TSPD = TSPDX
        SO TO 652
C
                      END CPASH CODING
  584 204 = TLIM
        IF (ISTAT .EQ. 3) PPA = TLIMF
        IF (HPA .EQ. 0.) GO TO 585
        Y1 = PPA
IF (TSPO .GT. 0.) YI = HPAFAC / TSPO
GO TO 589
  585 IF (TSPD .GT. TCUPVX(I)) GO TO 586
Y1 = TCURVY(1)
        GO TO 589
  586 DO SAB K=2.NPOINT
        XARK = TCUPVI(K)
IF (XWRK .LT. TSPN) GN TO 588
        YHRK = TCURVY(K)
        YI = YWRK-((XWRK-TSPD)*(YWPK-TCHRVY(K-1)))(XWRK-TCHRVX(K-1)))
        GO TO 549
  SAA CONTINUE
        YI = TOURVY (NPOINT)
   SA9 CONTINUE
        IF (YI .LT. RPA) RPA=YI
        IF (15TAT-2) S71.551.571
TRUCK EMPTY. GOING AT FULL SPEED
  590 TPOS = TPOS + DTVEFT
IF (IDPTN .EQ. 1) HPEVP = HPEV
DELTAC = HPEVP
        60 TO 558
                                       TRUCK FULL. GOING AT FULL SPEFD
   610 TPOS = TPOS - DIVEFT
        IF (INPTN .EO. I) HPFVP = HPFV
        DELTAC = HPEVP
        GO TO 578
                                        TRUCK IS DECELERATING EMPTY
   630 IF (DF .FO. 0.) GO TO 636
Y1 = DE * DELTAT
TPOS = TPOS . DT2640 * (2.*TSPO-YI)
   632 TSPD = TSPD - YI
IF (TSPD .ST. 0.) SO TO 698
ISTAT = 0
         TC=0 = 0.
        TEMTI = 0.
TEMSI = 0.
        TF451 = 0.

IF (IJSTOP-4) 540.698.640

RIMPULL OPTION 2
C
   436 TENTI - TENTI - DELTAT
        IF (TENTI .ST. U.) 60 TO 698
         ISTAT = 0
         TENTI = 0.
        TSPD = 0.
IF (IJSTOP .NE. 4) GO TO 640
TPOS = TPOS * TEMSI
TFMSI = 0.
GO TO 699
                                        TRUCK IN LOADING AREA
С
```

```
640 \text{ TPOS} = X
       IJSTOP = 1
       TEMSI = 0.
       GO TO 698
                                TRUCK IS DECELERATING FULL
   650 IF (DF .FQ. 0.) GO TO 654
       YI = DF * DELTAT
       TPOS = TPOS - DT2640 * (2.*TSPD - Y1)
   652 TSPD = TSPD - Y1
       IF (TSPD .LE. 0.) GO TO 658
       IF (ISW(I) .EO. 100 .AND. TPOS .LE. 0.) GO TO 660
       GO TO 698
                                RIMPULL OPTION 2
  654 TEMTI = TEMTI - DELTAT
       IF (TEMTI .GT. 0.) GO TO 698
       IF (IJSTOP .EQ. 4) TPOS = TPOS + TEMSI
       IF (ISW(I) .EQ. 100) GO TO 660
  658 ISTAT = 1
       TSPD = 0.
       Gn Tn 662
  660 \text{ ISW}(I) = 0
       ISTAT = 10
       TSPN = VN
       TPOS = 0.
  662 TEMTI = 0.
       TEMSI = 0.
  698 STATE (I+1) = ISTAT
      STATE(I.2) = TPOS
      STATE(I+3) = TSPD
      JSTOP(I) = IJSTOP
      TFMS(I) = TEMST
      TEMT(I) = TEMTI
C
                               DEBUG PRINT
      IF (ISTATO .LT. 2 .OR. ISTATO .GT. 3) GO TO 700 FND OF DEBUG PRINT
  700 DJMMH = DJMMH + (DFLTAC * DTCPFC)
  750 CONTINUE
C
C
                               IS ANOTHER ITERATION REQUIRED FOR THIS DT
C
      NITER = NITER - 1
      IF (NITER) 900,900,360
C
                               UPDATE /NEWWRK/
  900 DO 920 J=1.NTRUCK
      FTSTAT(J.1) = STATE(J.1)
      FTSTAT(J+2) = STATE(J+2)
      FTSTAT(J+3) = STATE(J+3)
      FTSTAT(J+4) = STATE(J+4)
      LKSTOP(J) = JSTOP(J)
  920 CONTINUE
      LLSTOP = ISTOPT
 999 RETURN
      END
```

KK. SUBROUTINE TRNPRT(ICYCLE)

```
SUBROUTINE TRAPRT (ICYCLE)
         C
               ELEMENT - MATERIALS HANDLING
         C
         Ċ
               GENERAL PROCESS - CONVEYOR
               ACTIVITY - LONG HAUL MUCK TRANSPORT
         C
               TECHNIQUE - TROUGH BELT CONVEYOR
         C
               COMMON/ALL/ XT.STR.IA.RQD.CS.TAMR.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
000003
              1. XMAX.TMAX.TO.XO.XDISCH.DX
               COMMON/MONEY/ DJMMH
000003
               COMMON/CONVEY/ ACM+DTBS+DWM+EE+FL+HP+QC+SMIN+WBI+
000003
                                        DTCB.DTMB.AB.VBI.NEXON.NGEO.XE.LNSURG.
                  WP.XLF.NSURGE.QE.QP.
                  STIME . QDMR . DTMI . DTMO . FLM . DMAINT
               COMMON/NEWCOM/ LMACON.LMCAPC.LNSPLC.LLOADR.FQL.LMKIN.LMUKOT.LNRYRY
000003
               COMMON/OLDCOM/ MACON+MCAPC+NSPLIC+LOADR+QL+MKIN+MUKOT+NBYRY
000003
               EQUIVALENCE (PR+PC) + (XDE+XE)
000003
               REAL LIR. LRP. LAM
000003
               DIMENSION YKY (3)
000003
               DIMENSION WB(11) + VB(11) + XIIR(11) + XIRR(11) + PLIES (11) + QB(11)
000003
               DATA XIIR/5., 4.5.4.,4.,4.,3.5,3.5,3.5,3.5,3.,3.,3./
000003
               000003
               DATA PLIES/3.,4.,5.,6.,7.,8.,9.,10.,12.,12.,12./
000003
               DATA QR/4., 4.5.5.7, 7.2, 9.6, 11.5, 14.2, 16.9, 19.4, 21.8, 24.3/
000003
               DATA WB/18..20..24..30..36..42..48..54..60..66..72./
000003
               DATA VB/300.,350.,400.,450.,500.,550.,600.,600.,600.,600.,600.
000003
               DATA WPCOMP.AC.LIR.LRR.LAM.WR.X1 /7+0./
000003
               DATA YKY /3*0./
000003
               DATA ARGI.ARG2.ARG3.ARG4.HPS /5*0./
000003
               DATA LIMIT.N.II.I /4*0/
000003
               DETERMINE BELT CAPACITY
         C
               IF (ICYCLE .GT. 1) GO TO 110
000003
               ICYCLE=5
000006
               IF (VBI .LE. 0.0) GO TO 20
000006
               OPTION 1
               WPCOMP = 60./2000. * AB * VBI * CS/SK
000010
               QP = 60. ABAVBI
000014
               DO 10 I=1.11
000015
               IF (WBI .NE. WB(I)) GO TO 10
000017
000021
               I I = I
               GO TO 90
000022
            10 CONTINUE
000023
000025
               PRINT 11.WBI
            11 FORMAT ( 13H BELT WIDTH = .F10.2, 15H IS NOT IN LIST)
000033
               STOP
000033
               DESIGN CONVEYOR OPTION 2
         C
            20 \ 00 \ 30 \ I = 1 \cdot 11
000035
               SOLVE FOR WPCOMP (EST. PEAK TONNAGE COMPUTED) THAT MATCHES OR IS
         C
               GREATER THAN WP (EST. PEAK TONNAGE INPUTTED)
               AB = (1./144.)*(0.1247*WB(I)*WB(I) - 0.8245*WB(I) +1.311)
000040
               WPCOMP=60./2000.*AB*VB(I)*CS/SK
000046
               IF (WPCOMP .LT. WP) GO TO 30
000053
000055
               11=1
               VBI=VB(I)
000057
000060
               WBI=WB(I)
               QP=60. *AB*VBI
000062
               GO TO 50
000064
            30 CONTINUE
000065
```

```
35 PRINT 40
40 FORMAT CLOCK CONVEYOR DESIGN CAN NOT HE FOUND FOR GIVEN PEAK TOWAG
       TE AND MAXIMUM TOTAL CHOSS SECTION OF STRUCTURE!
         CHECK FOR MAX. TOTAL CROSS SECTION OF CONVEYOR STRUCTURE
    50 AC=10.44. .357447! - .0020394719441 . .000414446194819481
         IF (AC .GT. ACM) GO TO 35
SFLEGT INFLEW PULLIF AND POLLER SPACING
II IS THE SUMSCRIPT OF THE PELT WINTH BEING USED
    90 LIP = XII2 (II)
         LAM =.00068*(DR([])+100.*4+)+2.13/LIR+ .035*04([])
        -2.048

IF(XEF .NE. 0.1 SO TO 110

XEF = PELES(11) *55.% ANIX(1.62*LAM) - 500./LAM

COMPARE CONVEYOR CAPACITY WITH THAT REQUIRED FOR GIVEN ADVANCE RATE

COMPUTE REQUIRED CAPACITY
   110 WP=(1./2000.) *TL*CS/SK
PQINT 200.#200#.#K
200 FORMAT(604.2810.2)
         IF (WPCOMP-WR) 130.120.125
   120 LMCAPC= 0
         GO TO 160
   125 LMCAPC = 0
         GO TO 150

CAPACITY OF CONVEYOR EXCERNED

IS THERE A STAGE MIN. TO HOLD EXCESS MICK
  130 IF (NSURGE .FR. 1) 50 TO 140 CASE 1 - NO SURGE 874
         TURN OFF EXCAVATOR ON NEXT CYCLE
         LMCAPC = I
   134 PRINT 135. X.DT. AR. APCOMP. WRI. VRI. AR
   134 PAINT 135: X-01-MA-APC TAP-ANT-VARIABLE
135 FORMAT (33H101-VEYD? CAPADITY EXCEFDED AT #=. F10.2-10H AND TIME#+
1 F10.2/10*... TO./H. - TO./H. - TO./H. - F10.3/10X-13H TO./H. PRO//DED#+
2 F10.2/10*.13* SELT - 10TH=. F10.3/10X-12H RELT SPEFD=-F10.2/
       310x+204 FLO+ CRUSE SECTION=+F10.2/)
        GO TO 150
CASE 2 - SHRIF HIN HAS BEEN PROVIDED
DF= (01 - 02) *)T
         CALL SURSE
         IF (LMSURG .NE. 1) GO TO 160
IF CAPACITY HAS RESURENCED THEM STOP EXCAVATOR IN NEXT CYCLE
C
         L4C4P5 = 1
5) TO 134
         FOR A SYSTEM CONTAINING A SUNGE BIN IT MAY HE NECESSARY TO
         SUBTRACT MUCH FHOM THE SIN WHEN WPCOMP IS GREATER THAN WR
   150 05= (3P-GL190T
         CALL SURCES
         POTOR SHAFT HOUSEPONER
         FOR DALLOW S - 15 WIST BE DESIVED
   160 IF (-2.67.0.1) 65 10 1c0
         N=X/XLF
         THERE ARE THO FOUNTIONS FOR HP. GNE FOR NEG. ONE FOR N GREATER
         THAY J.
         #1 IS THE LAMMON (FT) HAICH IS DESCRIBED IN THE PRITEUR. IT CAN BE X. XLE. OH X-XLE.FOR X1=X. 1 IS SET TO 1. FOR X1=XLE. I IS SET TO 3. YMY IS MY 14 THE
         DOCUMENTATION.
```

Reproduced from best available copy.

```
IF (4.61.0) 60 TO 157
                        I=1
L1411=2
     x1=x
GO TO 159
157 L1*IT=1
                                                                                                                                                                                                                        4.
                          1=2
x1=xLF
                           GO TO 159
     158 LI*17=2
T=3
     | X1=X-XLF | 159 | IF (X1 .6T. A00.) GO TO 161 | YKY(I) = .035 | GO TO 163 | 161 | IF (X1 .6T. 1000.) GO TO 162 | YKY(I) = .032 | GO TO 168 | 162 | IF (X1.6T. 1400.) GO TO 163 | YKY(I) = .030 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO TO 168 | GO T
                            X1=X-XLF
      GO TO 168

163 IF (x1 .6T. 2000.) GO TO 164

YKY(I)= .024

GO TO 168
       164 IF (X1 .GT. 2500.) GO TO 165
YKY(I)= .020
       GO TO 163
165 IF (x1 .GT. 3000.) GO TO 166
YKY(I)= .019
                             GO TO 168
       166 YKY(1) = .018

168 [F (LIMIT .NF. 2) GO TO 158

ARG1 = VAI/37000.

ARG2= .000AA (08(11) +100. *A9) +2.13/LIR

ARG3= .PCOMP/940.
                              ARG4= ARG1*550.

IF (N .GT. 0) 60 TO 170

HPS=X+ARG1*(ARG2+(YKY(1)+.015)*9R(II))+APG3*YKY(1)*X+ARG4
                              GO TO 175
        3 (X-N+XLF) *ARG3+ARG4
OPTION 2 - E MAY RE SPECIFIED
IF (FE .LE. 0.0) FE=0.76
         175 DJ44H=PC+PS+0.746+DT/EE +DJ44H
RETURN
        OPTION 1 - HP AND E MUST RE SPECIFIED

180 IF (FF.LE. 0.) FE=0.76

DUMME PCOMPOXO0.746*DIVEE *DUMMH
C
                                PETURY
                                EN0.
```

LL. SUBROUTINE EXTNSN(ICYCLE)

```
SUBROUTINE EXTNSN(ICYCLE)
         C
         C
                ELEMENT - MATERIALS HANDLING
                GENERAL PROCESS - LONG HAUL CONVEYOR BELT
                ACTIVITY - EXTENSION OF THE BELT
         C
                COMMON/ALL/ XT.STR.IA.RQD.CS.TAMB.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
000003
               1. XMAX.TMAX.TO.XO.XDISCH.DX
000003
                COMMON/MONEY/ DJMMH
                COMMON/CONVEY/ ACM+DTRS+DWM+EF+FL+HP+QC+SMIN+WBI+
000003
                   WP+XLF+NSURGE+QE+QP+ DTCR+DTMB+AB+VBI+NEXON+NGEO+XE+LNSURG+
                   STIME . ODMR . DIMI . DTMO . FLM . DMAINT
000003
               COMMON/NEWCOM/ LMACON+LMCAPC+LNSPLC+LLOADR+FOL+LMKIN+LMUKOT+LNBYBY
                  FSM
               1.
000003
               COMMON/OLDCOM/ MACON+MCAPC+NSPLIC+LOADR+QL+MKIN+MUKOT+NRYBY+SM
000003
               DATA T/0./.DTE2/0./.DTRS2/0./
               DATA DTE /0./
000003
                DATA FLA.FLS.S /3#0./
000003
000003
                IF (ICYCLE .GT.1) GO TO 30
000006
                ICYCLE = 5
000006
                GO TO (1.2.3).NGEO
         C
                GEOMETRY 1 - ASSUME FLA EXTENDS THE FULL LENGTH OF CONVEYOR
000015
              1 FLA = FL
               FLS = 0.
000016
000017
                X = FL
               GO TO 10
000021
                GEOMETRY 2 - ASSUME FEEDER CONVEYOR EXTENSION IS SMALL (FL=0)
         C
                AND EMPTIES INTO SHAFT DIRECTLY
000021
              2 FLA = 0.
000022
                FLS = 0.
000023
                GO TO 10
         C
                GEOMETRY 3
000023
              3 FLS = 0.
                SM = SMIN
000024
         C
                DETERMINE CONVEYOR STRUCTURE EXTENSION PARAMETERS
                OPTION1 - XE, DTBS INPUT
                OPTION 2 - XE = F (WB.LIR)
         C
                OPTION 2 - DTBS =
         C
            10 CONTINUE
000026
         C
                NORMAL ENTRY POINT AFTER FIRST CALL - INCREMENT DT
         C
                IS EXTENSION SHUT DOWN
            30 IF (NEXON .EO. 1) RETURN
000026
                BELT SPLICE OR STRUC. EXTENSION
000031
                PRINT 501.FLA.FLS
000041
           501 FORMAT (96X, 2F10.2)
                IF (NSPLIC .EQ. 0) 60 TO 31
000041
000043
                IF (LNSURG .EQ. 1) GO TO 112
000045
                GO TO 122
         C
               CONVEYOR STRUCTURE ONLY
000046
            31 IF (NGEO .NE. 3) GO TO 40
               GEOMETRY 3 - CYCLIC OPER. IF (DTE .NE. 0.0) GO TO 32
000050
               DTE = DX/XE
000051
000953
            32 DTE = DTE - DT
               UPDATE CONVEYOR STR. COMPLETED
         C
000055
               FLS = FLS + DX
000057
                IF (DTE .GT. 0.)
                                  GO TO 33
```

```
LNRYRY = 0
            DTE = 0.
            GD TO TOO
      33 LNAYAY = 1
            60 TO 100
     GO TO 100
GEMDETRY 1 + 2 - CONTINUOUS OPERATIONS
CONVEYOR STRUCT. COMPLETED IN DT
40 FLS = FLS + XE*DT
AVAILABLE CONVEYOR AFTER DT
IF (NGEO .NE. I) GD TD 45
FLA = FLA - DX
C
C
            60 TD 60
      45 FLA = 0.
FL = FL
            CHECK TO SEE IF CONVEYOR EXTENSION HAS CAUGHT UP TO EXCAVATOR
           FL - FLS - FLA

IF (S .GT. 0.) GO TO 80

CONVEYOR EXTENSION HAS CAUGHT UP. LET ADVANCE DF CONVEYOR

EQUAL EXCAVATOR FOR THIS DT.

FLS = FLS -DT*XE + 0X
C
          GO TD 100

CHECK TO SEE IF FEEDER RUNAWAY TOLERANCE IS EXCEEDED IF ( S .GE. SM) GO TD 90

LNRYGY = 0
            GD TO 100
            EXCEEDED - THEREFORE TURN OFFEXCAVATOR NEXT DT
      90 LNAYRY # 1
   CHECK TO SEE IF RELT SPLICE NEEDED
100 GD TO (105-105-107) * NGED
BFLT SPLICE NDT NEEDED
   101 LNSPLC = 0
    105 IF (FLA .GT. 0.) GD TD 101
   GO TO 109
106 IF(FL .LT. FLM) GO TO 101
GO TO 109
   107 IF (S .LT. SM) GO TO [0]
SPLICE NEEDED
109 LNSPLC = 1
           IF (NSURGE .EO. 1) GO TO 118
IF (NGED .EO. 3) GO TO 111
ARE THERE SURGE BINS TO HOLD MUCK DURING SPLICE
  ARE THERE SURGE BINS TO HOLD MUCK DURING SPLICE

CASE I - NO SURGE BINS (NSURGE = 0)

LET CONVEYOR STRUCTURE CATCH UP TO EXCAVATOR AND SPLICE RELT

110 DTE = (FL - FLA -FLS ) /XE + DTRS

GO TO 112

111 DTE = DTRS

TURN DFF EXCAVATOR UNTIL THIS IS COMPLETED

112 DTE2 = DTE2 + DT

IF(DTE2 - GF- DTE) GO TO 113

LMSPLC = 1
           LNSPLC = 1
           RETURN
            SPLICE COMPLETED - REINITIALIZE
   113 LNSPLC = 0
           GO TO (114-115-116) . NGEO
   114 FLA=0.
           DTE2 = 0.
           RETURN
```

```
115 FL = 0.
    DTE2 = 0.
    AFTURY

116 FW = SMIN
    DTE2 = 0.
    FLS = 0.
    FLS = 0.
    FLS = 0.
    RETURY

C CASE 2 - SURRE BIN MAS BEEN PROVIDED - (NSURGE = 1)

118 OF = (OL - OP) **OT
    CALL SURGE
    IF (LNSURG *F0. 1) GO TO 130
    IF (DIRS2 *NF. 0.) GO TO 122
    DIRS2 = OTBS

122 DIRS2 = OTBS

123 DIRS2 = OTBS

C SPLICE C MPLETED * REINITIALIZE
    GO TO (123*124*125) **NGEO

123 FLS = FLS
    RETURY

124 FL = FL - FLS
    PETURY

125 FSME SMIN
    FLS = 0.
    PETURY

C MELTIN MAS REEN EXCEEDED (LNSURGE = 1) DURING OT* THAN IRFAT

C AS IF THERE IS NO SURGE BIN

130 DIPS = DIRS2
    GO TO (110*110*111) ** NGEO

END
```



```
SURROUTINE SURGE
TWO ENTRY POINTS 14TO THIS SUPROUTINE
ENTRY SURGE - TO PUT MUCK INTO BIN
ENTRY SURGES - TO TAKE MUCKOUT
C
                                      ELEMENT - MATERIALS MANDLING
GENERAL PROCESS - LONG HAND CONVEYOR RELT
ACTIVITY - LONGING EXCESS MUCK INTO SURGE BIN OR UNLOADING FROM RIN
                                       COMMON/ALL/ XT.STR.IA.POD.CS.TAMR.FLOW.IFLAG.AT.D.F.SK.T.DT.X.PR
                                  1. XMAR.THAX.TO.XO.XDISCH.DX
                                  TARTITIANS TO SCHOOL AND SCHOOL STATES TO SAIL STATES TO SCHOOL STATES TO SCHOOL STATES TO SCHOOL STATES TO SCHOOL STATES TO SCHOOL STATES TO SCHOOL SCHOOL STATES TO SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHOOL SCHO
                                         EDUTVALENCE (PR.PC) . (XDE.XE)
                                         DATA 9/0./
                                         ENTRY SURGE
   C
                                          IFILNSURG .ED. 1) RETURN
                      10 LNSUPS = 1
RETURN
10 LNSUPS = 1
RETURN
10 LNSUPS = 1
RETURN
     C
                                           ENTRY SURGES
                                          0=0-0E
IF (0 .GT. 0.) RETURN
0= 0.0
                                           RETURN
```

NN. SUBROUTINE BELT(ICYCLE)

```
SURROUTINE BELT(ICYCLE)
                ELEMENT - MATERIALS HANDLING
         C
                GENERAL PROCESS - LONG HAUL CONVEYOR BELT
         C
                ACTIVITY - MAINTENANCE OF BELT
         C
         C
                COMMON/ALL/ XT.STR.IA.RQD.CS.TAMB.FLOW.IFLAG.AT.D.E.SK.T.DT.X.PR
000003
                  XMAX.TMAX.TO.XO.XDISCH.DX
                COMMON/MONEY/ DJMMH
000003
                COMMON/CONVEY/ ACM.DTBS.DWM.EE.FL.HP.QC.SMIN.WBI.
000003
                   WP + XLF + NSURGE + QE + QP +
                                            DTCB.DTMR.AB.VBI.NEXON.NGEO.XE.LNSURG.
                   STIME + ODMR + DTMI + DTMO + FLM + DMAINT
000003
                COMMON/NEWCOM/ LMACON, LMCAPC, LNSPLC, LLOADR, FQL, LMKIN, LMUKOT, LNBYBY
000003
                COMMON/OLDCOM/ MACON+MCAPC+NSPLIC+LOADR+QL+MKIN+MUKOT+NBYBY
                EQUIVALENCE (PR+PC) + (XDE+XE)
000003
                DATA PI/3.141592/
000003
000003
                DATA W.TM.T /3*0./
                INITIALIZE PARAMETERS
000003
                IF (ICYCLE .NE. 1) GO TO 10
                ICYCLE = 10
000005
                w=0.
000006
                DWM MUST HAVE A DEFAULT VALUE SPECIFIED. SET=1. FOR COMPILATION
000006
                IF (DWM .LE. O.) DWM=1.
000011
                TM=0.
000012
                TT=DTMB
             10 IF (MACON .EQ. 1) GO TO 30
000014
                IF(DTCB .EQ. 0.) GO TO 20
TM = TM + DT
000016
000017
                IF (DTCB .GT. TM) GO TO 15
000021
000024
                LMACON = 1
                TM = 0.
000025
000025
                GO TO 30
000026
             15 LMACON = 0
000027
                RETURN
                TONAGE OF MUCK CRITERIA SPECIFED
             20 W=(PI*D*D/4.)/2000. *CS *DX +W
000030
                IF (W .GE. DWM) GO TO 25
000037
                LMACON = 0
000041
000042
                RETURN
             25 LMACON = 1
000042
000043
                W = 0.
                TIMEKEEPER ON MAINTENANCE
000044
             30 TT=TT-DT
000046
                IF(TT .LE. 0) GO TO 40
                LMACON = 1
000047
000050
                RFTURN
000051
             40 LMACON = 0
         C
                DMAINT NEEDS A VALUE IF IT HAS NOT BEEN SPECIFIED.
                DMAINT SFT =1. FOR COMPILATION
000052
                IF (DMAINT .LE. O.) DMAINT =1.
000055
                DJMMH = DJMMH + DMAINT
000057
                RETURN
000057
                END
*FOLLOWING VARIABLES EQUIVALENCED BUT NOT REFERENCED
PC
XΕ
                                 VI-153
PR
```

OO. SUBROUTINE XXXMNT (General Maintenance Routine to Be Adapted by User for Specific Processes)

```
SUPPOUTINE XXXMNT
С
        ELFMENT -
GENERAL PROCESS -
ACTIVITY - GENERAL MAINTENANCE + REPAIR
0000
        COMMON /
DATA TRFT.TMNT /2*0./
        DATA INIT+NEEDIN /2+0/
C
                                       EQUIVALENCE FOR SPECIFIC GENERAL PROCESS
        EQUIVALENCE (GOTC.
        EDITVALENCE (GDJM+
EDITVALENCE (DJMGP+
EDITVALENCE (MMNT+
        EDUTVALENCE (LMMNT. EDUTVALENCE (MFLAG. EDUTVALENCE (LMFLAG.
C
                                       INITIALIZATION
    10 TRFT = GOTC
        MMNT = 1
IF (GDTC .FQ. 0.) GDTC =
        IF (GDTM .FD. 0.) GDTM = IF (GDJM = 0.) GDJM = INIT = 1
        IF (NEEDIN = 0) GO TO 999
        NFFNIN = 0
GO TO 200
                                       NORMAL ENTRY
        ENTRY XXXRPR
        IF (INIT .EQ. 1) GO TO 200
NEFTIN = 1
        GO TO 10
                                       IS MAINTENANCE IN PROGRESS
C
  200 IF (MMNT .EO. 0) GO TO 400
IS MAINTENANCE REQUIRED
C
        THET = TRET - DT
        IF (TRET .GT. 0.) GO TO 999

DOES ANY OTHER SITUATION EXIST SUCH THAT MAINTENANCE SHOULD

NOT BE PERMITTED. IF 50. GO TO 999
C
        LMMNT = 0
        LMFLAG = LMFLAG + I
        GO TO 999
                                       UPDATE PROGRESS OF MAINTENANCE
C
  400 THAT = THAT + OT
                                       IS MAINTENANCE COMPLETED
        IF (THAT .LT. GOTH) GO TO 999
        TRET = GRTC
THAT = 0.
LWMNT = 1
        LAFLAG = LMFLAG - 1
   999 RETURN
        NOTE -- CHECK TESTING OF MFLAG IN RELATED SUBROUTINES
```